KP-41EXR96
RM-Y112A

SERVICE MANUAL

US Model
Chassis No. SCC-F19H-A

Canadian Model
Chassis No. SCC-F23C-A



AP CHASSIS

MODELS OF THE SAME SERIES	
KP-41EXR96	KPR-46EXR15/53EXR15
KPR-41EXR95	
KPR-46XBR15/53XBR15	

SPECIFICATIONS

Structure	Screen and projector, rear projection type
Projection system	3 picture tubes, 3 lenses, horizontal in-line system
Picture tube	7 inch high-brightness monochrome tubes (5.5 raster size), with optical coupling and liquid cooling system
Projection lenses	High performance, larger-diameter hybrid lens F 1.0
Screen material	Plastic lenticular, Plastic fresnel
Projected picture size	41 inches (measured diagonally)
Screen brightness	2,000 cd/m²
Television system	American TV standards
Channel coverage	VHF: 2-13 UHF: 14-69 CABLE TV: 1-125
Antenna	75 ohm external antenna terminal for VHF/UHF

Input jacks

VIDEO IN 1
- S VIDEO IN (4-pin mini DIN)
  - Y: 1 Vp-p, 75-ohms unbalanced, sync negative
  - C: 0.286 Vp-p (Burst signal) 75-ohms
- Video (phono jacks): 1 Vp-p, 75-ohms unbalanced, sync negative
- Audio (phono jacks):
  - 500 mVrms (100% modulation)
  - Impedance: 47 kilo-ohms

VIDEO IN 2 and 3
- Video (phono jacks): 1 Vp-p, 75-ohms unbalanced, sync negative
- Audio (phono jacks):
  - 500 mVrms (100% modulation)
  - Impedance: 47 kilo-ohms

- Continued on next page -

COLOR REAR VIDEO PROJECTOR

SONY®

MICROFILM

Output jacks	MONITOR OUT S VIDEO MONITOR OUT (4-pin mini DIN) Y : 1 Vp-p, 75-ohms unbalanced, sync negative Video (phono jacks) : 1Vp-p, 75-ohms unbalanced, sync negative Audio (phono jacks) : 500mVrms (100% modulation) Impedance : 10 kilo-ohms AUDIO (VAR) OUT (phono jacks) More than 900mVrms (100% modulation) at the maximum volume setting (variable) Impedance : 5kilo-ohms AUDIO OUT (phono jacks) 900mVrms (100% modulation) Impedance : 5kilo-ohms
Speaker	Two-way coaxial speaker system Woofer 130 mm (5inches) diameter Tweeter 35 mm (1.4inches) diameter
Speaker output	12W×2
CENTER SPEAKER input	16Ω NORM. 30W MAX 50W
Power requirements	120 V AC, 60 Hz
Power consumption	310W (max) 7W (standby mode)
Dimensions (w/h/d)	930×1,185×505 mm ($36_{5/8}$×$46_{3/4}$×20 inches)
Weight	72 kg (138 lb 12 oz)
Supplied accessories	Remote Commander RM-Y112A (1) with 2 size AA (R6) EVEREADY batteries
Optional accessories	U/V mixer EAC-66 Connecting cable RK-74A VMC-810S/820S YC-15V/30V VCR Tray SU-PJT1

Design and specifications are subject to change without notice.

(CAUTION)

SHORT CIRCUIT THE ANODE OF THE PICTURE TUBE AND THE ANODE CAP TO THE METAL CHASSIS, CRT SHIELD, OR CARBON PAINTED ON THE CRT, AFTER REMOVING THE ANODE.

(ATTENTION)

APRES AVOIR DECONNECTE LE CAP DE L'ANODE, COURTCIRCUITER L'ANODE DU TUBE CATHODIQUE ET CELUI DE L'ANODE DU CAP AU CHASSIS METALLIQUE DE L'APPAREIL, OU AU COUCHE DE CARBONE PEINTE SUR LE TUBE CATHODIQUE OU AU BLINDAGE DU TUBE CATHODIQUE.

WARNING!!

AN ISOLATION TRANSFORMER SHOULD BE USED DURING ANY SERVICE TO AVOID POSSIBLE SHOCK HAZARD, BECAUSE OF LIVE CHASSIS.
THE CHASSIS OF THIS RECEIVER IS DIRECTLY CONNECTED TO THE AC POWER LINE.

ATTENTION!!

AFIN D'EVITER TOUT RISQUE D'ELECTROCUTION PROVENANT D'UN CHÁSSIS SOUS TENSION, UN TRANSFORMATEUR D'ISOLEMENT DOIT ETRE UTILISÉ LORS DE TOUT DÉPANNAGE.
LE CHÁSSIS DE CE RÉCEPTEUR EST DIRECTEMENT RACCORDÉ Á L'ALIMENTATION SECTEUR.

SAFETY-RELATED COMPONENT WARNING !!

COMPONENTS IDENTIFIED BY SHADING AND MARK ⚠ ON THE SCHEMATIC DIAGRAMS, EXPLODED VIEWS AND IN THE PARTS LIST ARE CRITICAL TO SAFE OPERATION. REPLACE THESE COMPONENTS WITH SONY PARTS WHOSE PART NUMBERS APPEAR AS SHOWN IN THIS MANUAL OR IN SUPPLEMENTS PUBLISHED BY SONY. CIRCUIT ADJUSTMENTS THAT ARE CRITICAL TO SAFE OPERATION ARE IDENTIFIED IN THIS MANUAL. FOLLOW THESE PROCEDURES WHENEVER CRITICAL COMPONENTS ARE REPLACED OR IMPROPER OPERATION IS SUSPECTED.

ATTENTION AUX COMPOSANTS RELATIFS ÁLA SÉCURITÉ!!

LES COMPOSANTS IDENTIFIÉS PAR UNE TRAME ET PAR UNE MAPQUE ⚠ SUR LES SCHÉMAS DE PRINCIPE, LES VUES EXPLOSÉES ET LES LISTES DE PIECES CONT D'UNE IMPORTANCE CRITIQUE POUR LA SÉCURITÉ DU FONCTIONNEMENT. NE LES REMPLACER QUE PAR DES COMPOSANTS SONY DONT LE NUMÉRO DE PIÉCE EST INDIQUÉ DANS LE PRÉSENT MANUEL OU DANS DES SUPPLÉMENTS PUBLIÉS PAR SONY. LES RÉGLAGES DE CIRCUIT DONT L'IMPORTANCE EST CRITIQUE POUR LA SÉCURITÉ DU FONCTIONNEMENT SONT IDENTIFIES DANS LE PRÉSENT MANUEL. SUIVRE CES PROCÉDURES LORS DE CHAQUE REMPLACEMENT DE COMPOSANTS CRITIQUES, OU LORSQU'UN MAUVAIS FONCTIONNEMENT EST SUSPECTÉ.

SAFETY CHECK-OUT

(US Model only)

After correcting the original service problem, perform the following safety checks before releasing the set to the customer:

1. Check the area of your repair for unsoldered or poorly-soldered connections. Check the entire board surface for solder splashes and bridges.

2. Check the interboard wiring to ensure that no wires are "pinched" or contact high-wattage resistors.

3. Check that all control knobs, shields, covers, ground straps, and mounting hardware have been replaced. Be absolutely certain that you have replaced all the insulators.

4. Look for unauthorized replacement parts, particularly transistors, that were installed during a previous repair Point them out to the customer and recommend their replacement.

5. Look for parts which, though functioning, show obvious signs of deterioration. Point them out to the customer and recommend their replacement.

6. Check the line cord for cracks and abrasion. Recommend the replacement of any such line cord to the customer.

7. Check the condition of the monopole antenna (if any). Make sure the end is not broken off, and has the plastic cap on it. Point out the danger of impalement on a broken antenna to the customer, and recommend the antenna's replacement.

8. Check the B+ and HV to see they are at the values specified. Make sure your instruments are accurate; be suspicious of your HV meter if sets always have low HV.

9. Check the antenna terminals, metal trim, "metallized" knobs, screws, and all other exposed metal parts for AC leakage. Check leakage as described below.

LEAKAGE

The AC leakage from any exposed metal part to earth ground and from all exposed metal parts to any exposed metal part having a return to chassis, must not exceed 0.5 mA (500 microampers). Leakage current can be measured by any one of three methods.

1. A commercial leakage tester, such as the Simpson 229 or RCA WT-540A. Follow the manufacturers' instructions to use these instruments.

2. A battery-operated AC milliammeter. The Data Precision 245 digital multimeter is suitable for this job.

3. Measuring the voltage drop across a resistor by means of a VOM or battery-operated AC voltmeter. The "limit" indication is 0.75 V, so analog meters must have an accurate low-voltage scale. The Simpson 250 and Sanwa SH-63Trd are examples of a passive VOM that is suitable. Nearly all battery operated digital multimeters that have a 2V AC range are suitable. (See Fig. A)

HOW TO FIND A GOOD EARTH GROUND

A cold-water pipe is guaranteed earth ground; the cover-plate retaining screw on most AC outlet boxes is also at earth ground. If the retaining screw is to be used as your earth-ground, verify that it is at ground by measuring the resistance between it and a coldwater pipe with an ohmmeter. The reading should be zero ohms. If a cold-water pipe is not accessible, connect a 60-100 watts trouble light (not a neon lamp) between the hot side of the receptacle and the retaining screw. Try both slots, if necessary, to locate the hot side of the line, the lamp should light at normal brilliance if the screw is at ground potential. (See Fig. B)



Fig. A. Using an AC voltmeter to check AC leakage.



Fig. B. Checking for earth ground.

TABLE OF CONTENTS

SECTION 1
GENERAL

The operating instructions mentioned here are partial abstracts from the Operating Instruction Manual. The page numbers of the Operating Instruction Manual remein as in the manual.

Chapter 1: Setting Up

Unpacking and Viewing Area

1 Carefully follow the instructions on the outside of the packing carton to unpack the projection TV.

Notes
- The supplied accessories are packed in the bottom of the carton. Be sure not to throw them away.
- Keep the original carton and packing materials to safely transport the projection TV in the future.

2 Check to make sure that the following is included:

Universal Remote Commander
RM-Y112A (1)
with 2 size AA (R6) EVEREADY batteries

If the Remote Commander is missing, contact your dealer.

3 Place the projection TV in a cool, dry place where the ventilation openings at the sides are not blocked.

4 Plug the projection TV power cord into an AC 120 volt power outlet.

For further precautions, see p. 2.

Optimum viewing area

For the best picture quality, try to position the projection TV so that you can view the screen from within the areas shown below.

Horizontal viewing area



Optimum viewing position

Vertical viewing area



Optimum viewing position

Locating Controls and Connectors

For details, see the pages indicated by the numbered black circles ●.

Front



* Buttons with the same function are also located on the Remote Commander (p. 10).

Locating Controls and Connectors

Front inner panel



* Buttons with the same function are also located on the Remote Commander (p. 10).

Note
The instructions in this manual are based for the most part on operating the projection TV with the Remote Commander. You can also use the buttons on the projection TV that have the same function.

Rear



Remote Commander RM-Y112A (with the video control cover closed)



* Buttons with the same function are also located on the projection TV (p. 7).

Note
If the TV/CABLE BOX selector is set to CABLE BOX, the Remote Commander is able to control a connected cable box, not the projection TV (p. 70). Set the selector to TV to control the projection TV with the Remote Commander.

Remote Commander (with the video control cover open)

Opening the video control cover

Slide the cover down.





Video operating buttons – STANDARD button

Using the On-Screen Menus

The following flow chart shows the different levels of on-screen menus that you can use to make various adjustments and settings. See the indicated pages for instructions on using each feature.

For picture and sound quality adjustment



For mode adjustment



For time-related settings



Note
Menu items that are shaded are inactive and cannot be selected.

For presetting and other functions



For CONVERGENCE adjustment

Navigating through the menus

Remote Commander

To display the main menu
Press MENU.

To return to the previous menu
Press A/V WINDOW +/– until the cursor points to " ⊃MENU."
Then press RETURN.

To return to the main menu
Repeat the above, until you reach the main menu.

To return to the normal screen
Press MENU.

Note
The menus disappear automatically, if you do not press a button within 90 seconds.



Changing the menu language

The menu language is factory-set to ENGLISH. Follow these instructions to change the menu language to Spanish or French, or back to English.

1 Press POWER to turn on the projection TV.
TIMER/STAND BY indicator blinks until the picture appears.

POWER



2 Press MENU.
The main menu appears.

MENU



3 Press A/V WINDOW +/– until the cursor points to "ENGLISH."
Then press RETURN.
The language display turns red.

A/V WINDOW RETURN



4 Press A/V WINDOW +/– to select the language.
Each time you press A/V WINDOW +/–, the "ESPAÑOL," "FRANÇAIS" and "ENGLISH" menus appear.

A/V WINDOW



Note
Certain parts of the "ESPAÑOL" and "FRANÇAIS" menus remain in English.

5 Press RETURN.
The language is selected.

RETURN

Spanish menu

To return to the normal screen.
Press MENU.

Notes concerning menus

- During PIP (Picture-In-Picture) mode, the on-screen menus may overlap the window picture.
- The menus disappear automatically, if you do not press a button within 90 seconds.

KP-41EXR96
RM-Y112A

SERVICE MANUAL

US Model
Chassis No. SCC-F19H-A

Canadian Model
Chassis No. SCC-F23C-A



AP CHASSIS

MODELS OF THE SAME SERIES	
KP-41EXR96	KPR-46EXR15/53EXR15
KPR-41EXR95	
KPR-46XBR15/53XBR15	

SPECIFICATIONS

Structure	Screen and projector, rear projection type
Projection system	3 picture tubes, 3 lenses, horizontal in-line system
Picture tube	7 inch high-brightness monochrome tubes (5.5 raster size), with optical coupling and liquid cooling system
Projection lenses	High performance, larger-diameter hybrid lens F 1.0
Screen material	Plastic lenticular, Plastic fresnel
Projected picture size	41 inches (measured diagonally)
Screen brightness	2,000 cd/m²
Television system	American TV standards
Channel coverage	VHF: 2-13 UHF: 14-69 CABLE TV: 1-125
Antenna	75 ohm external antenna terminal for VHF/UHF

Input jacks

VIDEO IN 1
- S VIDEO IN (4-pin mini DIN)
  - Y: 1 Vp-p, 75-ohms unbalanced, sync negative
  - C: 0.286 Vp-p (Burst signal) 75-ohms
- Video (phono jacks): 1 Vp-p, 75-ohms unbalanced, sync negative
- Audio (phono jacks):
  - 500 mVrms (100% modulation)
  - Impedance: 47 kilo-ohms

VIDEO IN 2 and 3
- Video (phono jacks): 1 Vp-p, 75-ohms unbalanced, sync negative
- Audio (phono jacks):
  - 500 mVrms (100% modulation)
  - Impedance: 47 kilo-ohms

- Continued on next page -

996493801

MICROFILM

COLOR REAR VIDEO PROJECTOR

SONY®

Adjusting Color Registration (CONVERGENCE)



In a projection TV, the projection tube image appears on the screen in three color layers (red, green and blue). If these layers are not in proper registration, the color is poor and the picture blurs. To correct this, perform the CONVERGENCE adjustment.

1 Press MENU.
The main menu appears.



2 Press A/V WINDOW +/– until the cursor points to "CONVERGENCE."





3 Press RETURN.
The CONVERGENCE screen and the colored adjustment lines appear.



R = Red
G = Green
B = Blue

4 Press A/V WINDOW +/– until the cursor points to the symbol representing the line you want to adjust (see the key below).





Adjustment line symbols key
| (red vertical: left/right adjustment)
— (red horizontal: up/down adjustment)
| (blue vertical: left/right adjustment)
— (blue horizontal: up/down adjustment)

5 Press RETURN.
The adjustment line is selected.



6 Press A/V WINDOW +/– until the line converges with the center green line. Then press RETURN.





To move up To move right	Press A/V WINDOW +.
To move down To move left	Press A/V WINDOW –.

7 Repeat steps 4 – 6 to adjust the other lines, until all the lines have overlapped to form a white cross.



To return to the previous menu
Press A/V WINDOW +/– until the cursor points to " ⊃ MENU."
Then press RETURN.

To return to the main menu
Repeat the above, until you reach the main menu.

To return to the normal screen.
Press MENU.

Setting CABLE ON or OFF



If you have cable connected to the projection TV, follow the steps below to set the cable connection on or off. Set CABLE OFF to preset or watch VHF or UHF channels, and set CABLE ON to preset or watch cable TV channels.

Note
If the projection TV is in video mode, the "CABLE" display is shaded and cannot be selected.
Press TV/VIDEO to change to TV mode.

1 Press MENU.
The main menu appears.



2 Press A/V WINDOW +/– until the cursor points to "SET UP."





3 Press RETURN.
The set up menu appears, and the cursor points to "CABLE."



4 Press RETURN again.
The mode display turns red.



5 Press A/V WINDOW +/– to select "ON" or "OFF."





6 Press RETURN.
The setting is complete.



To return to the previous menu
Press A/V WINDOW +/– until the cursor points to " ⊃ MENU."
Then press RETURN.

To return to the main menu
Repeat the above, until you reach the main menu.

To return to the normal screen.
Press MENU.

Cable TV channel chart•
Cable TV systems use letters or numbers to designate channels. To tune in a channel, refer to the chart below.

Number on this TV	Corresponding CATV channel
1	A-8
5	A-7
6	A-6
14	A
15	B
16	C
17	D
18	E
19	F
20	G
21	H
22	I
23	J
24	K
25	L
26	M
27	N
28	O
29	P
30	Q
31	R
32	S
33	T
34	U
35	V
36	W
37	W+1
38	W+2
39	W+3
•	•
•	•
•	•
•	•
93	W+57
94	W+58
95	A-5
96	A-4
97	A-3
98	A-2
99	A-1
100	W+59
101	W+60
102	W+61
•	•
•	•
•	•
•	•
123	W+82
124	W+83
125	W+84

Check with your local cable TV company for more complete information on the available channels.
• The designation of the cable TV channels conforms to the EIA/NCTA recommendation.

Presetting TV Channels

By presetting TV channels to the projection TV, you can select channels by pressing CH (CHANNEL) +/–.
(You can select VHF channels 2 – 13 without presetting.)



Presetting all receivable channels automatically

Follow these instructions to preset all the receivable VHF, UHF or cable TV channels to the projection TV.

Notes

- If the projection TV is in video mode, the "AUTO PROGRAM" display is shaded and cannot be selected. Press TV/VIDEO to change to TV mode.
- Perform auto programming during the day rather than late at night, when some channels may not be broadcasting.

1 Set the cable connection on or off (pp. 26 – 27) to select the type of channel you want to preset, VHF/UHF or cable TV.



To preset VHF or UHF channels

To preset cable TV channels

2 Press MENU.
The main menu appears.



3 Press A/V WINDOW +/– until the cursor points to "SET UP."





4 Press RETURN.
The set up menu appears.



5 Press A/V WINDOW +/– until the cursor points to "AUTO PROGRAM."





6 Press RETURN.

"AUTO PROGRAM" appears on the screen and receivable channels (other than the channels already preset) are preset in numerical sequence. The channels previously preset will not remain in the projection TV's memory.
When no more channels are found, auto programming stops and the screen returns automatically to the set up menu.

7 Press CH +/– to check or view the preset channels.



Receivable channels for this projection TV
VHF: 2 – 13
UHF: 14 – 69
Cable: 1 – 125

To select TV channels without presetting
Press the 0 – 9 buttons and ENTER.

To return to the previous menu
Press A/V WINDOW +/– until the cursor points to " ↩ MENU."
Then press RETURN.

To return to the main menu
Repeat the above, until you reach the main menu.

To return to the normal screen.
Press MENU.



Erasing TV channels

Follow these instructions to erase unnecessary TV channels, so that when you press CH +/–, the channel(s) are skipped.

1 Press MENU
The main menu appears.



2 Press A/V WINDOW +/– until the cursor points to "SET UP."





3 Press RETURN
The set up menu appears.



4 Press A/V WINDOW +/– until the cursor points to "CH ERASE/ADD."





5 Press RETURN.
The CH ERASE/ADD screen appears, and the cursor points to "ERASE."



6 Press CH +/– to select the channel you want to erase.
The channel display appears.





7 Press RETURN.
A "–" sign appears in front of the channel number display, indicating that the channel is erased; then the CH ERASE/ADD screen automatically reappears.



To erase another channel
Repeat steps 6 – 7.

To return to the previous menu
Press A/V WINDOW +/– until the cursor points to " ⊃ MENU."
Then press RETURN.

To return to the main menu
Repeat the above, until you reach the main menu.

To return to the normal screen
Press MENU.

Note
If you erase a VHF or UHF channel, the same number cable TV channel is also erased (and vice versa).



Adding TV channels

Follow these instructions to add TV channels one by one to the selection memory, or to replace a TV channel you previously erased (pp. 30 – 31).

1 Press MENU
The main menu appears.



2 Press A/V WINDOW +/– until the cursor points to "SET UP."





3 Press RETURN.
The set up menu appears.



4 Press A/V WINDOW +/– until the cursor points to "CH ERASE/ADD."





5 Press RETURN.
The CH ERASE/ADD screen appears.



6 Press A/V WINDOW +/– until the cursor points to "ADD."





7 Press 0 – 9 and ENTER to select the channel you want to add.
The channel display appears.





8 Press RETURN
A "+" sign appears in front of the channel number display, indicating that the channel is added; then the CH ERASE/ADD screen automatically reappears.



To add another channel
Repeat steps 7 – 8.

To return to the previous menu
Press A/V WINDOW +/– until the cursor points to " ⊃ MENU."
Then press RETURN.

To return to the main menu
Repeat the above, until you reach the main menu.

To return to the normal screen
Press MENU.

Note
If you add a VHF or UHF channel, the same number cable TV channel is also added (and vice versa).

Watching TV Programs



Make sure that the TV/CABLE BOX selector on the Remote Commander is set to TV, in order to control the projection TV with the Remote Commander.

1 Press POWER to turn on the projection TV.
TIMER/STAND BY indicator blinks until the picture appears.



2 Set the cable connection on or off (pp. 26 – 27) to select the type of channel you want to watch, VHF/UHF or cable TV.

To watch VHF or UHF channels

To watch cable TV channels

3 Select a channel in one of the following two ways:
To scan the preset channels in numerical sequence, press CH +/–.



To select a channel directly, press 0 – 9 and then ENTER.
For example, to select channel 10, press 1, 0 and ENTER.



4 Press VOL +/– to adjust the volume.



Press + to increase the volume.
Press – to decrease the volume.

If VIDEO 1, VIDEO 2 or VIDEO 3 appears on the screen
Press TV/VIDEO until a TV channel number appears.

To select channels more easily
Set FAVORITE CHANNEL (pp. 64 – 65).

To turn off the projection TV
Press POWER.

Selecting a Picture and Sound Mode

This projection TV features four modes (STANDARD, MOVIE, SPORTS, NEWS) that offer different picture and sound qualities. Choose the one that best suits the type of program that you want to watch.

Example: Select MOVIE mode for picture and sound that gives you the sense of being in a movie theater.



(with video control cover open)

1 Press MENU.
The main menu appears, and the cursor points to "PROG PALETTE."



2 Press RETURN.
The program palette menu appears.



3 Press A/V WINDOW +/– until the cursor points to "MOVIE."





4 Press RETURN.
The "MOVIE" display turns green, indicating that MOVIE mode is selected.



To select a different mode
Repeat steps 3 – 4.

Selecting standard mode (without using the menus)

Follow these instructions to select standard mode without using the on-screen menus.

Press STANDARD.

When you select STANDARD mode
You receive standard picture and sound quality. Any video or audio adjustments you made ("Adjusting the Projection TV," pp. 44 – 52) are cancelled and the original factory settings are restored.

When you select MOVIE mode
You receive a finely detailed picture, and a theatrical audio effect.
To further adjust picture and sound qualities, follow the instructions on pp. 44 – 52.

When you select SPORTS mode
You receive a vivid, bright picture, and sound with a sports stadium effect.
To further adjust picture and sound qualities, follow the instructions on pp. 44 – 52.

When you select NEWS mode
Picture noise is reduced, and you receive clear voice reproduction.
To further adjust picture and sound qualities, follow the instructions on pp. 44 – 52.

To return to the previous menu
Press A/V WINDOW +/– until the cursor points to " ⊃ MENU."
Then press RETURN.

To return to the main menu
Repeat the above, until you reach the main menu.

To return to the normal screen.
Press MENU.

Watching Two Pictures at Once (PIP)

You can watch both the main picture and a window picture simultaneously, using the Picture-in-Picture (PIP) function.

KP-41EXR96 is equipped with one-tuner PIP. To watch two TV channels simultaneously, you must first connect a VCR to the projection TV, which will enable you to watch a second TV channel through the VCR tuner. (See "Connecting Other Equipment," pp. 15 –19.)
Other models are equipped with two-tuner PIP, allowing you to watch two TV channels at once.



Picture-in-Picture special features
When watching the main picture and a window picture, you can:
- Swap the main and window pictures (SWAP).
- Change the position of the window picture (POSITION).
- Display a still picture (FREEZE).
- Choose the sound from the main or window picture (AUDIO).

Notes
- The window picture sound is also output from the AUDIO (VAR) OUT jacks. The AUDIO OUT and MONITOR OUT jacks output the main picture sound only.
- The video label and channel caption will not appear with the window picture even if you have set them.
- If you select a blocked channel in the window picture, the display "BLOCKED" appears with the window picture. (See "Setting CHANNEL BLOCK," pp. 62 – 63.)

Displaying a window picture

Remote Commander



Press PIP to display a window picture



A window picture appears in the last mode you watched. Each time you press PIP, a 1/9 or 1/16 size window picture appears alternately.

To turn PIP function off
Press OFF.
The window picture disappears.

To receive the window picture sound
Press AUDIO.

The ♪ display appears for a few seconds, indicating that the window picture sound is being received.

To restore the main picture sound
Press AUDIO again.

Changing the window picture input mode

Remote Commander



1 Press PIP to display a window picture.



2 Press TV/VIDEO in the Picture-in-Picture control area to select the input mode.
Each time you press TV/VIDEO, "TV," "VIDEO 1," "VIDEO 2" and "VIDEO 3" appear in sequence.



To change TV channels in the window picture
Press CH +/– in the PIP control area.

Displaying CATV input as a window picture

To use Picture-in-Picture with pay cable TV input, make the connections to your cable converter box as shown below.



After making the above connections, turn the cable connection on by following the steps on pp. 26 – 27; then continue with the steps below.

1–2 Follow steps 1 – 2 in "Changing the window picture input mode" on this page to select the video input mode for your connected VCR.

3 Put your VCR on an inactive channel (channel 3 or 4).

4 Change pay cable TV channels with the decoder box.

To control your cable converter box with the supplied Remote Commander
See p. 70.

Watching Two Pictures at Once (PIP)

Changing the position of the window picture

Follow these instructions to change the position of the window picture on the screen.

Remote Commander



1 Press PIP to display a window picture.

2 Press POSITION.
Each time you press POSITION, the window picture moves as illustrated.



Displaying a still picture

Use the FREEZE function to display a still picture. This function is useful when you want to write down a recipe from a cooking program, a displayed address or phone number and so on.

Remote Commander



1 Press PIP to display a window picture.



2 Press FREEZE.
The window picture image remains still on the screen.



To restore the normal picture
Press FREEZE again.

Swapping the main and window pictures

Follow these instructions to swap the input signals of the main and window pictures.

Remote Commander



1 Press PIP to display a window picture.



2 Press SWAP.
Each time you press SWAP, the images from the main and window pictures switch places.

Output jacks	MONITOR OUT S VIDEO MONITOR OUT (4-pin mini DIN) Y : 1 Vp-p, 75-ohms unbalanced, sync negative Video (phono jacks) : 1Vp-p, 75-ohms unbalanced, sync negative Audio (phono jacks) : 500mVrms (100% modulation) Impedance : 10 kilo-ohms AUDIO (VAR) OUT (phono jacks) More than 900mVrms (100% modulation) at the maximum volume setting (variable) Impedance : 5kilo-ohms AUDIO OUT (phono jacks) 900mVrms (100% modulation) Impedance : 5kilo-ohms
Speaker	Two-way coaxial speaker system Woofer 130 mm (5inches) diameter Tweeter 35 mm (1.4inches) diameter
Speaker output	12W×2
CENTER SPEAKER input	16Ω NORM. 30W MAX 50W
Power requirements	120 V AC, 60 Hz
Power consumption	310W (max) 7W (standby mode)
Dimensions (w/h/d)	930×1,185×505 mm ($36_{5/8}$×$46_{3/4}$×20 inches)
Weight	72 kg (138 lb 12 oz)
Supplied accessories	Remote Commander RM-Y112A (1) with 2 size AA (R6) EVEREADY batteries
Optional accessories	U/V mixer EAC-66 Connecting cable RK-74A VMC-810S/820S YC-15V/30V VCR Tray SU-PJT1

Design and specifications are subject to change without notice.

(CAUTION)

SHORT CIRCUIT THE ANODE OF THE PICTURE TUBE AND THE ANODE CAP TO THE METAL CHASSIS, CRT SHIELD, OR CARBON PAINTED ON THE CRT, AFTER REMOVING THE ANODE.

WARNING!!

AN ISOLATION TRANSFORMER SHOULD BE USED DURING ANY SERVICE TO AVOID POSSIBLE SHOCK HAZARD, BECAUSE OF LIVE CHASSIS.
THE CHASSIS OF THIS RECEIVER IS DIRECTLY CONNECTED TO THE AC POWER LINE.

SAFETY-RELATED COMPONENT WARNING !!

COMPONENTS IDENTIFIED BY SHADING AND MARK ⚠ ON THE SCHEMATIC DIAGRAMS, EXPLODED VIEWS AND IN THE PARTS LIST ARE CRITICAL TO SAFE OPERATION. REPLACE THESE COMPONENTS WITH SONY PARTS WHOSE PART NUMBERS APPEAR AS SHOWN IN THIS MANUAL OR IN SUPPLEMENTS PUBLISHED BY SONY. CIRCUIT ADJUSTMENTS THAT ARE CRITICAL TO SAFE OPERATION ARE IDENTIFIED IN THIS MANUAL. FOLLOW THESE PROCEDURES WHENEVER CRITICAL COMPONENTS ARE REPLACED OR IMPROPER OPERATION IS SUSPECTED.

(ATTENTION)

APRES AVOIR DECONNECTE LE CAP DE L'ANODE, COURTCIRCUITER L'ANODE DU TUBE CATHODIQUE ET CELUI DE L'ANODE DU CAP AU CHASSIS METALLIQUE DE L'APPAREIL, OU AU COUCHE DE CARBONE PEINTE SUR LE TUBE CATHODIQUE OU AU BLINDAGE DU TUBE CATHODIQUE.

ATTENTION!!

AFIN D'EVITER TOUT RISQUE D'ELECTROCUTION PROVENANT D'UN CHÁSSIS SOUS TENSION, UN TRANSFORMATEUR D'ISOLEMENT DOIT ETRE UTILISÉ LORS DE TOUT DÉPANNAGE.
LE CHÁSSIS DE CE RÉCEPTEUR EST DIRECTEMENT RACCORDÉ Á L'ALIMENTATION SECTEUR.

ATTENTION AUX COMPOSANTS RELATIFS ÁLA SÉCURITÉ!!

LES COMPOSANTS IDENTIFIÉS PAR UNE TRAME ET PAR UNE MAPQUE ⚠ SUR LES SCHÉMAS DE PRINCIPE, LES VUES EXPLOSÉES ET LES LISTES DE PIECES CONT D'UNE IMPORTANCE CRITIQUE POUR LA SÉCURITÉ DU FONCTIONNEMENT. NE LES REMPLACER QUE PAR DES COMPOSANTS SONY DONT LE NUMÉRO DE PIÉCE EST INDIQUÉ DANS LE PRÉSENT MANUEL OU DANS DES SUPPLÉMENTS PUBLIÉS PAR SONY. LES RÉGLAGES DE CIRCUIT DONT L'IMPORTANCE EST CRITIQUE POUR LA SÉCURITÉ DU FONCTIONNEMENT SONT IDENTIFIES DANS LE PRÉSENT MANUEL. SUIVRE CES PROCÉDURES LORS DE CHAQUE REMPLACEMENT DE COMPOSANTS CRITIQUES, OU LORSQU'UN MAUVAIS FONCTIONNEMENT EST SUSPECTÉ.

Adjusting the Projection TV

You can adjust the picture and sound for each input mode (TV, VIDEO 1, VIDEO 2, VIDEO 3) by pressing TV/VIDEO on the projection TV or on the Remote Commander to select the input mode, before making the adjustments. These adjustments are retained in memory even when you turn off the projection TV, but are cancelled after you change the adjustments, or select a picture and sound mode (pp. 38 – 39).

Adjusting the picture

Follow these instructions to adjust PICTURE, HUE, COLOR, BRIGHT (brightness) and SHARP (sharpness).

Remote Commander (with video control cover open)



1 Press MENU.
The main menu appears, and the cursor points to "PROG PALETTE."



2 Press RETURN.
The program palette menu appears.



3 Press A/V WINDOW +/– until the cursor points to "VIDEO."

4 Press RETURN.
The VIDEO screen appears.



5 Press A/V WINDOW +/– until the cursor points to the item you want to adjust.

6 Press RETURN.
The adjustment screen appears.



7 Press A/V WINDOW +/– to make the adjustment.

Picture quality	Press A/V WINDOW –	Press A/V WINDOW +
PICTURE	For decreased picture contrast with soft color	For increased picture with vivid color
HUE	Skin tones become purplish	Skin tones become greenish
COLOR	For less color intensity	For more color intensity
BRIGHT	For less brightness	For more brightness
SHARP	For less sharpness	For more sharpness

8 Press RETURN.
The adjustment is complete, and the VIDEO screen automatically reappears.



To adjust other items
Repeat steps 5 – 8.

To restore the factory settings for all the items
Select "STANDARD" on the program palette menu, and press RETURN;
or, press STANDARD on the Remote Commander.
All the items, including TRINITONE (p. 46) and NR (p. 47) return to their original factory settings.

To adjust picture contrast
You can also adjust picture contrast with the PICTURE +/– buttons on the Remote Commander.

Press + to increase picture contrast with vivid color.
Press – to decrease picture contrast with soft color.
The picture adjustment screen appears.

To return to the previous menu
Press A/V WINDOW +/– until the cursor points to "MENU."
Then press RETURN.

To return to the main menu
Repeat the above, until you reach the main menu.

To return to the normal screen
Press MENU.

Setting the TRINITONE mode

Color picture tubes are usually manufactured with a fixed color temperature (tint) that determines the "warmth" (red tint) or "coolness" (blue tint) of the picture. Use the Sony Trinitone feature to adjust the picture color to your preference.

Remote Commander



1 Press MENU.
The main menu appears, and the cursor points to "PROG PALETTE."



2 Press RETURN.
The program palette menu appears.



3 Press A/V WINDOW +/– until the cursor points to "VIDEO."

4 Press RETURN.
The VIDEO screen appears.



5 Press A/V WINDOW +/– until the cursor points to "TRINITONE."

6 Press RETURN.
The mode display turns red.

7 Press A/V WINDOW +/– to select "HIGH" or "LOW."

Select "HIGH" to make the picture cool (bluish).
Select "LOW" to make the picture warm (reddish).

8 Press RETURN.
The setting is complete.

To return to the previous menu
Press A/V WINDOW +/– until the cursor points to " ⊃ MENU."
Then press RETURN.

To return to the main menu
Repeat the above, until you reach the main menu.

To return to the normal screen
Press MENU.

Setting NR (picture noise reduction) ON or OFF

Follow these instructions to reduce picture noise.

Remote Commander



1 Press MENU.
The main menu appears, and the cursor points to "PROG PALETTE."



2 Press RETURN.
The program palette menu appears.



3 Press A/V WINDOW +/– until the cursor points to "VIDEO."

4 Press RETURN.
The VIDEO screen appears.

5 Press A/V WINDOW +/– until the cursor points to "NR."



6 Press RETURN.
The mode display turns red.

7 Press A/V WINDOW +/– to select "ON" or "OFF."

Select "ON" to reduce picture noise.
Select "OFF" to restore the normal picture.

8 Press RETURN.
The setting is complete.

To return to the previous menu
Press A/V WINDOW +/– until the cursor points to " ⊃ MENU."
Then press RETURN.

To return to the main menu
Repeat the above, until you reach the main menu.

To return to the normal screen
Press MENU.

Setting S-VIDEO ON or OFF

Follow these instructions to set S-VIDEO on or off, depending on the kind of video equipment you have connected to the projection TV. For instructions on connecting video equipment, see pp. 15 – 18.

Note
If the projection TV is in TV, VIDEO 2 or VIDEO 3 mode, the "S-VIDEO" display is shaded and cannot be selected. Press TV/VIDEO on the projection TV or on the Remote Commander to change to VIDEO 1 mode.

Remote Commander



1 Press MENU.
The main menu appears.



2 Press A/V WINDOW +/– until the cursor points to "MODE SET."

3 Press RETURN.
The mode set menu appears, with the cursor pointing to "S-VIDEO."



4 Press RETURN.
The mode display turns red.

5 Press A/V WINDOW +/– to select "ON" or "OFF."

6 Press RETURN.
The setting is complete.

To return to the previous menu
Press A/V WINDOW +/– until the cursor points to " ↩ MENU."
Then press RETURN.

To return to the main menu
Repeat the above, until you reach the main menu.

To return to the normal screen
Press MENU.

Adjusting the sound

Follow these instructions to adjust the TREBLE, BASS and BALANCE.

Remote Commander (with video control cover open)



1 Press MENU.
The main menu appears, and the cursor points to "PROG PALETTE."

2 Press RETURN.
The program palette menu appears.



3 Press A/V WINDOW +/– until the cursor points to "AUDIO."

4 Press RETURN.
The AUDIO screen appears.

5 Press A/V WINDOW +/– until the cursor points to the item you want to adjust.

6 Press RETURN.
The adjustment screen appears.



7 Press A/V WINDOW +/– to make the adjustment.

Sound quality	Press A/V WINDOW –	Press A/V WINDOW +
TREBLE	To decrease the treble response	To increase the treble response
BASS	To decrease the bass response	To increase the bass response
BALANCE	To emphasize the left speaker's volume	To emphasize the right speaker's volume

8 Press RETURN.
The adjustment is complete, and the AUDIO screen automatically reappears.



To adjust other items
Repeat steps 5 – 9.

To restore the factory settings for all the items
Select "STANDARD" on the program palette menu, and press RETURN; or, press STANDARD on the Remote Commander.
All the items, including SRS mode (p. 50) return to their original factory settings.

To return to the previous menu
Press A/V WINDOW +/– until the cursor points to " ↩ MENU."
Then press RETURN.

To return to the main menu
Repeat the above, until you reach the main menu.

To return to the normal screen
Press MENU.

Selecting an SRS (Sound Retrieval System) mode

For lifelike sound reproduction, follow the instructions below to select the SRS mode you prefer.

In SRS AUTO mode, SRS functions in both monaural and stereo modes.

Monaural sound programs will have a 'simulated stereo' effect.

In SRS STEREO mode, SRS functions only when a stereo program is received.
The STEREO lamp on the TV lights up whenever a stereo broadcast is received.

Select SRS OFF mode to return to normal sound mode.

Remote Commander



1 Press MENU.
The main menu appears, and the cursor points to "PROG PALETTE."



2 Press RETURN.
The program palette menu appears.



3 Press A/V WINDOW +/– until the cursor points to "AUDIO."

4 Press RETURN.
The AUDIO screen appears.

5 Press A/V WINDOW +/– until the cursor points to the SRS mode you want.

6 Press RETURN.
The mode is selected.

To change the SRS mode
Repeat steps 5 – 6.

To return to the previous menu
Press A/V WINDOW +/– until the cursor points to "⊃ MENU."
Then press RETURN.

To return to the main menu
Repeat the above, until you reach the main menu.

To return to the normal screen
Press MENU.

Selecting an MTS (Multichannel TV Sound) mode

Follow these instructions to select an MTS mode.

Select MAIN mode to listen to stereo sound.
The STEREO lamp on the projection TV lights up whenever a stereo broadcast is received.

Select SAP mode to listen to Second Audio Programs.

Select MONO mode to eliminate excessive noise during stereo broadcasts, caused by a weak incoming signal.

Note
If the projection TV is in video mode, the "MTS" display is shaded and cannot be selected.
Press TV/VIDEO on the projection TV or on the Remote Commander to change to TV mode.

Remote Commander



1 Press MENU.
The main menu appears.



2 Press A/V WINDOW +/– until the cursor points to "MODE SET."

3 Press RETURN.
The mode set menu appears.



4 Press A/V WINDOW +/– until the cursor points to "MTS."

5 Press RETURN.
The mode display turns red.

6 Press A/V WINDOW +/– to select the mode you want.
Each time you press A/V WINDOW +/–, "MAIN," "SAP" and "MONO" appear in sequence.

7 Press RETURN.
The mode is selected.

To return to the previous menu
Press A/V WINDOW +/– until the cursor points to "⊃ MENU."
Then press RETURN.

To return to the main menu
Repeat the above, until you reach the main menu.

To return to the normal screen
Press MENU.

Setting SPEAKER — MAIN or CENTER

Follow these instructions to set SPEAKER to "CENTER" when you connect an audio system (p.19), and to "MAIN" when you want to listen to the sound from the projection TV speakers.

Remote Commander



1 Press MENU.
The main menu appears.



2 Press A/V WINDOW +/– until the cursor points to "MODE SET."

3 Press RETURN.
The mode set menu appears.



4 Press A/V WINDOW +/– until the cursor points to "SPEAKER."

5 Press RETURN.
The mode display turns red.

6 Press A/V WINDOW +/– to select "MAIN" or "CENTER."

7 Press RETURN.
The setting is complete.

To return to the previous menu
Press A/V WINDOW +/– until the cursor points to "MENU."
Then press RETURN.

To return to the main menu
Repeat the above, until you reach the main menu.

To return to the normal screen
Press MENU.

Setting channel captions — CH CAPTION

Follow these instructions to caption each channel number display with a name, for instance, the television station call letters. (You can set up to four letters or numbers).

Example: Caption channel 15 as "NBC."

Remote Commander



1 Press MENU.
The main menu appears.



2 Press A/V WINDOW +/– until the cursor points to "SET UP."

3 Press RETURN.
The set up menu appears.



4 Press A/V WINDOW +/– until the cursor points to "CH CAPTION."

5 Press RETURN.
The CH CAPTION screen appears.



6 Press CH +/–, or press 1, 5 and ENTER to set channel "15."



7 Press RETURN.
The first caption space turns red.

8 Press A/V WINDOW +/– to select "N."
Each time you press A/V WINDOW +/–, "0" – "9," "A" – "Z," "&," "/," "-" and "_" (blank space) appear in sequence.



9 Press RETURN.
The second caption space turns red.

(Continued)

Setting channel captions – CH CAPTION
(Cont'd. from prev. page)

Remote Commander



10 Press A/V WINDOW +/– to select "B."



11 Press RETURN.
The third caption space turns red.

12 Press A/V WINDOW +/– to select "C."



13 Press RETURN.
The fourth caption space turns red.

14 Press A/V WINDOW +/– to select a blank space.



15 Press RETURN.
The setting is complete.
When you select or display the channel number, the channel caption also appears.

To caption more channels
Repeat steps 6 – 15.

To erase unnecessary captions
Display the CH CAPTION screen, select the channel with the caption you want to erase, and select blank spaces for the channel caption; then press RETURN.
The caption for that channel is erased.

To return to the previous menu
Press A/V WINDOW +/– until the cursor points to " ⊃ MENU."
Then press RETURN.

To return to the main menu
Repeat the above, until you reach the main menu.

To return to the normal screen
Press MENU.

Note
You can set up to 32 channel captions. If the memory is full, "The memory is full, sorry" appears on the screen. Erase any unnecessary captions, and begin again.

Setting VIDEO LABEL

Follow these instructions to label each input mode, in order to identify the equipment connected to each input terminal.

Example: Label VIDEO 1 IN as "VHS."

Remote Commander



1 Press MENU.
The main menu appears.

2 Press A/V WINDOW +/– until the cursor points to "SET UP."

3 Press RETURN.
The set up menu appears.



4 Press A/V WINDOW +/– until the cursor points to "VIDEO LABEL."

5 Press RETURN.
The VIDEO LABEL screen appears.

6 Press A/V WINDOW +/– until the cursor points to the input mode you want to label. (In this case, the cursor is already pointing to "VIDEO 1.")

7 Press RETURN.
The label display turns red.

8 Press A/V WINDOW +/– to select "VHS."

Each time you press A/V WINDOW +/–, the label changes:

VIDEO 1
VIDEO 1 → BETA → 8mm → VHS → LD → S-VIDEO

VIDEO 2
VIDEO 2 → BETA → 8mm → VHS → LD

VIDEO 3
VIDEO 3 → BETA → 8mm → VHS → LD

9 Press RETURN.
The setting is complete.
When you select or display the video mode, the video label appears.

To label other input modes
Repeat steps 6 – 9.

To change a label
Same as above.

To return to the previous menu
Press A/V WINDOW +/– until the cursor points to " ⊃ MENU."
Then press RETURN.

To return to the main menu
Repeat the above, until you reach the main menu.

To return to the normal screen
Press MENU.

Using Timer-Activated Functions

Setting DAYLIGHT SAVING

If you live in an area that uses daylight savings time, set DAYLIGHT SAVING to "YES" or "NO" depending on the season, before setting the current time. At the next daylight savings date, you will be able to automatically adjust all the time-related settings (CURRENT TIME, ON/OFF TIMER and CHANNEL BLOCK) simply by changing the DAYLIGHT SAVING setting.

When setting DAYLIGHT SAVING:

- **After the first Sunday in April (spring daylight savings)**
  Set to "YES" before setting the current time.
  Then, on the last Sunday in October (fall daylight savings), set to "NO."
  All the time-related settings automatically move one hour back.
- **After the last Sunday in October (fall daylight savings)**
  Set to "NO" before setting the current time.
  Then, on the first Sunday in April (spring daylight savings), set to "YES."
  All the time-related settings automatically move one hour ahead.

Remote Commander



Follow these instructions to set DAYLIGHT SAVING to "YES" or "NO."

1 Press MENU.
The main menu appears.



2 Press A/V WINDOW +/– until the cursor points to "TIME."

3 Press RETURN.
The time menu appears.



4 Press A/V WINDOW +/– until the cursor points to "DAYLIGHT SAVING."

5 Press RETURN.
The mode display turns red.

6 Press A/V WINDOW +/– to select "YES" or "NO."

7 Press RETURN.
The setting is complete.

To return to the previous menu
Press A/V WINDOW +/– until the cursor points to "↩ MENU."
Then press RETURN.

To return to the main menu
Repeat the above, until you reach the main menu.

To return to the normal screen.
Press MENU.

Setting the clock — CURRENT TIME SET

Follow these instructions to set the current time. The correct current time must be set in order to use the other time-related functions (DAYLIGHT SAVING, ON/OFF TIMER, CHANNEL BLOCK).

Example: Set the time to 3:15 PM, Monday.

Remote Commander



1 Press MENU.
The main menu appears.

2 Press A/V WINDOW +/– until the cursor points to "TIME."

3 Press RETURN.
The time menu appears, and the cursor points to "CURRENT TIME SET."



4 Press RETURN again.
The CURRENT TIME SET screen appears, with a reminder to set DAYLIGHT SAVING.

If you do not need to set DAYLIGHT SAVING, press RETURN and continue from step 5.

To set daylight saving

a Press A/V WINDOW +/– until the cursor points to "DAYLIGHT SAVING."

b Press RETURN.
The time menu appears, and the cursor points to "DAYLIGHT SAVING."

c Press RETURN.

d Press A/V WINDOW +/– to select "YES" or "NO."

e Press RETURN.
The setting is complete.

To set the time, press A/V WINDOW +/– until the cursor points to "CURRENT TIME SET"; press RETURN, then continue from step 5.

5 Press RETURN.
The CURRENT TIME SET screen appears, and the "SUN" display appears (red).

6 Press A/V WINDOW +/– to select "MON."
Each time you press A/V WINDOW +/–, the day changes consecutively.



(Continued)

Setting the clock — CURRENT TIME SET
(Cont'd from prev. page)

Remote Commander



7 Press RETURN.
The hour and am/pm displays turn red.

8 Press A/V WINDOW +/– to set "3:00PM."
Each time you press A/V WINDOW +/–, the hour changes in sequence beginning with "12:00AM."



9 Press RETURN.
The minute display turns red.

10 Press A/V WINDOW +/– to select "15" (minutes).
Each time you press A/V WINDOW +/–, the minutes change in sequence.



11 Press RETURN.
The cursor points to "START."

12 Check the actual time, and press RETURN to start the clock.
The setting is complete.

To reset the time
Display the CURRENT TIME SET screen and repeat steps 5 – 12.

To display the current time
Press DISPLAY.

To return to the previous menu
Press A/V WINDOW +/– until the cursor points to " ⊃ MENU."
Then press RETURN.

To return to the main menu
Repeat the above, until you reach the main menu.

To return to the normal screen.
Press MENU.

Setting the ON/OFF TIMER

Follow these instructions to make the program of your choice appear on the screen at a specified time.

Example: Set the timer to turn on the projection TV every Monday through Friday at 1:30 AM for 3 hours, on channel 8, as PROGRAM 1. (You can set up to three programs.)

Remote Commander



1 Press MENU.
The main menu appears.



2 Press A/V WINDOW +/– until the cursor points to "TIME."

3 Press RETURN.
The time menu appears.



4 Press A/V WINDOW +/– until the cursor points to "ON/OFF TIMER."

5 Press RETURN.
The ON/OFF TIMER screen appears, and the cursor points to "1."



6 To set program 1, press RETURN.
(To set program 2 or 3, press A/V WINDOW +/– until the cursor points to that program; then press RETURN.)
The day input space turns red.

7 Press A/V WINDOW +/– to select "EVERY MON-FRI"; then press RETURN.
Each time you press A/V WINDOW +/–, the days of the week change as shown in Fig. 1 (p. 61).



8 Press A/V WINDOW +/– to select "1:00AM"; then press RETURN.
Each time you press A/V WINDOW +/–, the hour changes in sequence.



(Continued)

Setting the ON-OFF TIMER *(Cont'd from prev. page)*

Remote Commander



9 Press A/V WINDOW +/– to select "30" (minutes); then press RETURN.
Each time you press A/V WINDOW +/–, the minutes change in sequence.



10 Press A/V WINDOW +/– to select "3" (hour duration); then press RETURN.
Each time you press A/V WINDOW +/–, the duration changes from "1" – "6" in sequence.



11 Press A/V WINDOW +/– to select "8" (channel); then press RETURN.
The TIMER/STAND BY lamp lights, indicating that the setting is complete.
Each time you press A/V WINDOW +/–, the channel number changes from 1 – 125 in sequence.



The display "TIMER WILL BE OFF" appears on the screen one minute before the timer duration ends.

To set program 2 or 3.
Press RETURN and repeat steps 6 – 11.

To erase an ON/OFF TIMER setting
Display the ON/OFF TIMER screen, select the setting you want to erase, and select a blank space for the day.
The ON/OFF TIMER setting is erased.

To enter a new ON/OFF TIMER setting
Display the ON/OFF TIMER screen and repeat steps 6 – 11.

To return to the previous menu
Press A/V WINDOW +/– until the cursor points to " ⊃ MENU."
Then press RETURN.

To return to the main menu
Repeat the above, until you reach the main menu.

To return to the normal screen.
Press MENU.

Note
If you unplug the projection TV or a power failure occurs, both the clock and timer settings will be erased. Reset the current time; then set the timer.

Fig. 1
Selecting the day(s) of the week
When you press A/V WINDOW +, the days of the week appear in the following order:



Setting CHANNEL BLOCK

Follow these instructions to prevent a channel from appearing on the screen during the time that you specify. You can use this function to prevent children from watching unsuitable programs.

Example: Set CHANNEL BLOCK every Saturday at 4:30 PM for 1 hour, on Channel 12.

Remote Commander



Note
If you have not set the current time, the "CHANNEL BLOCK" display is shaded and cannot be selected.

1 Press MENU.
The main menu appears.



2 Press A/V WINDOW +/– until the cursor points to "TIME."

3 Press RETURN.
The time menu appears.



4 Press A/V WINDOW +/– until the cursor points to "CHANNEL BLOCK."

5 Press RETURN.
The CHANNEL BLOCK screen appears, and the cursor points to the day input space.



6 Press RETURN.
The day input space turns red.



7 Press A/V WINDOW +/– to select "EVERY SAT"; then press RETURN.
Each time you press A/V WINDOW +/–, the days of the week change as shown in Fig. 1 (p. 61).

8 Press A/V WINDOW +/– to select "4:00PM"; then press RETURN.
Each time you press A/V WINDOW +/–, the hour changes in sequence.

9 Press A/V WINDOW +/– to select ":30" (minutes); then press RETURN.
Each time you press A/V WINDOW +/–, the minutes change in sequence.



10 Press A/V WINDOW +/– to select "1" (hour duration); then press RETURN.
Each time you press A/V WINDOW +/–, the duration changes from "1" – "6" in sequence.

11 Press A/V WINDOW +/– to select "12" (channel); then press RETURN.
The setting is complete.
Each time you press A/V WINDOW +/–, the channel number changes from "1" – "125" in sequence.



At the specified time, "BLOCKED" appears in red on the screen, and the picture of the specified channel is blocked and the sound is muted.



To erase a CHANNEL BLOCK setting
Display the CHANNEL BLOCK screen and select a blank space for the day.
The CHANNEL BLOCK setting is erased.

To enter a new CHANNEL BLOCK setting
Display the CHANNEL BLOCK screen and repeat steps 4 – 10. (You can only set one CHANNEL BLOCK at a time.)

To return to the previous menu
Press A/V WINDOW +/– until the cursor points to "⊃ MENU."
Then press RETURN.

To return to the main menu
Repeat the above, until you reach the main menu.

To return to the normal screen.
Press MENU.

Note
If the ON/OFF TIMER is set for an overlapping time (pp. 59 – 61), the later time setting takes precedence. For example, if CHANNEL BLOCK is set for 2:00 PM and ON/OFF TIMER is set for 3:00 PM, ON/OFF TIMER will take effect at 3:00 PM.

SAFETY CHECK-OUT

(US Model only)

After correcting the original service problem, perform the following safety checks before releasing the set to the customer:

1. Check the area of your repair for unsoldered or poorly-soldered connections. Check the entire board surface for solder splashes and bridges.

2. Check the interboard wiring to ensure that no wires are "pinched" or contact high-wattage resistors.

3. Check that all control knobs, shields, covers, ground straps, and mounting hardware have been replaced. Be absolutely certain that you have replaced all the insulators.

4. Look for unauthorized replacement parts, particularly transistors, that were installed during a previous repair Point them out to the customer and recommend their replacement.

5. Look for parts which, though functioning, show obvious signs of deterioration. Point them out to the customer and recommend their replacement.

6. Check the line cord for cracks and abrasion. Recommend the replacement of any such line cord to the customer.

7. Check the condition of the monopole antenna (if any). Make sure the end is not broken off, and has the plastic cap on it. Point out the danger of impalement on a broken antenna to the customer, and recommend the antenna's replacement.

8. Check the B+ and HV to see they are at the values specified. Make sure your instruments are accurate; be suspicious of your HV meter if sets always have low HV.

9. Check the antenna terminals, metal trim, "metallized" knobs, screws, and all other exposed metal parts for AC leakage. Check leakage as described below.

LEAKAGE

The AC leakage from any exposed metal part to earth ground and from all exposed metal parts to any exposed metal part having a return to chassis, must not exceed 0.5 mA (500 microampers). Leakage current can be measured by any one of three methods.

1. A commercial leakage tester, such as the Simpson 229 or RCA WT-540A. Follow the manufacturers' instructions to use these instruments.

2. A battery-operated AC milliammeter. The Data Precision 245 digital multimeter is suitable for this job.

3. Measuring the voltage drop across a resistor by means of a VOM or battery-operated AC voltmeter. The "limit" indication is 0.75 V, so analog meters must have an accurate low-voltage scale. The Simpson 250 and Sanwa SH-63Trd are examples of a passive VOM that is suitable. Nearly all battery operated digital multimeters that have a 2V AC range are suitable. (See Fig. A)

HOW TO FIND A GOOD EARTH GROUND

A cold-water pipe is guaranteed earth ground; the cover-plate retaining screw on most AC outlet boxes is also at earth ground. If the retaining screw is to be used as your earth-ground, verify that it is at ground by measuring the resistance between it and a coldwater pipe with an ohmmeter. The reading should be zero ohms. If a cold-water pipe is not accessible, connect a 60-100 watts trouble light (not a neon lamp) between the hot side of the receptacle and the retaining screw. Try both slots, if necessary, to locate the hot side of the line, the lamp should light at normal brilliance if the screw is at ground potential. (See Fig. B)



Fig. A. Using an AC voltmeter to check AC leakage.



Fig. B. Checking for earth ground.

Setting FAVORITE CHANNEL

By setting FAVORITE CHANNEL, you can select the channels you use most frequently (up to seven channels) simply by pressing RETURN.

Remote Commander



Follow these instructions to set the channels.

1 Press MENU.
The main menu appears.



2 Press A/V WINDOW +/– until the cursor points to "SET UP."

3 Press RETURN.
The set up menu appears.



4 Press A/V WINDOW +/– until the cursor points to "FAVORITE CHANNEL."

5 Press RETURN.
The FAVORITE CHANNEL screen appears, and the cursor points to the first channel position.



6 Press A/V WINDOW +/– to select the channel position; then press RETURN.

7 Press 0 – 9 and ENTER to set the channel number.



8 Press RETURN.
The setting is complete.

To set other channels
Repeat steps 6 – 8.

To erase a favorite channel setting
Press A/V WINDOW +/– until the cursor points to the channel number you want to erase; press RETURN, then press 0 and ENTER.

To reset a favorite channel setting
Display the FAVORITE CHANNEL screen and repeat steps 6 – 8.

To return to the previous menu
Press A/V WINDOW +/– until the cursor points to " ⊃ MENU."
Then press RETURN.

To return to the main menu
Repeat the above, until you reach the main menu.

To return to the normal screen.
Press MENU.

Selecting a favorite channel

After setting the channels, follow these instructions to select the channel you want to watch.

1 Press RETURN.
The FAVORITE CHANNEL display appears.



Note
If you have set channel captions (pp. 53 – 54), the captions appear with the channel numbers.

2 Press A/V WINDOW +/– to select the channel you want to watch; then press RETURN.
The channel is selected.

If you press RETURN on the Remote Commander before setting FAVORITE CHANNEL, this screen appears.



Follow steps 1 – 8 to set your favorite channels, and then make the selection.

Using the Pre-Programmed Remote Commander

You can operate other video equipment (such as VCRs, video disc players and cable boxes) that have an infrared remote detector with this supplied Remote Commander.

Operating Sony video equipment

Follow these instructions to operate Sony video cassette recorders (Beta, 8 mm and VHS) and video disc players (including multi-disc players).

Remote Commander
(with video control cover open)



1 Set the VTR1-2-3 MDP selector according to the video equipment you want to operate.



Fig. 2: Video equipment settings

If you want to operate a:	set to:
Beta, ED Beta VCR	VTR 1
8 mm VCR	VTR 2
VHS VCR	VTR 3
Video disc player	MDP

2 Use the video operating buttons to control the connected equipment.

Fig. 3: Operating a VCR (VTR1, 2, 3)	
To turn on or off	Press POWER.
To change channels (when watching TV programs through the VCR's tuner)	Press CH +/–.
To record	Press ● and REC simultaneously.
To play	Press ▶.
To stop	Press ■.
To fast forward	Press ▶▶.
To rewind the tape	Press ◀◀.
To pause	Press ❚❚. *To resume normal playback, press again.*
To search the picture forward and backward	Keep pressing ▶▶ or ◀◀ during playback. *To resume normal playback, release the button.*
To change input mode	Press TV/VTR.

Fig. 4: Operating a Video Disc Player (MDP)	
To turn on or off	Press POWER.
To play	Press ▶.
To stop	Press ■.
To pause	Press ❚❚. *To resume normal playback, press again.* **Note** This function is effective only for CAV (standard-play disc). With CLV (extended-play disc), the projection TV goes off (standby mode) if you press ❚❚.
To search the picture forward and backward	Keep pressing ▶▶ or ◀◀ during playback. *To resume normal playback, release the button.*

Notes

- If the video equipment does not have a certain function, the corresponding button on this Remote Commander will not operate.
- If you set another manufacturer's code to a VTR1-2-3 MDP selector position (pp. 68 – 69), you must also set the Sony code to operate Sony equipment.

Caution

When you replace the batteries, do so within approximately 30 minutes. Otherwise the settings you made under the Pre-Programmed function (pp. 68 – 70) may be erased.

Operating non-Sony or Sony video equipment

Follow these instructions to set the manufacturer's code, which will enable you to operate non-Sony and Sony video equipment with the pre-programmed Remote Commander.

Example: Operate an RCA video cassette recorder connected to the VIDEO 2 IN jacks.

Remote Commander
(with video control cover open)



1 Set the VTR1-2-3 MDP selector to VTR2.



Note
To use another manufacturer's equipment besides a Sony VCR, set the selector to a position not being used for your Sony video equipment.

2 While pressing CODE SET, press 0, 7 and ENTER to set RCA's code number. (For manufacturer code numbers, see Figs. 5, 6 and 7 on p. 69.)



3 Use the video operating buttons to operate the connected equipment. (see Fig. 3 on p. 66 and Fig. 4 on p. 67.)

Fig. 5: VCR manufacturer code numbers

MANUFACTURER	CODE
SONY	01, 02, 03
CANON	05
EMERSON	22, 30, 33
FISHER	10, 11, 12, 15
FUNAI	29
GENERAL ELECTRIC	05, 08
GOLDSTAR	25
HITACHI	07, 08, 36
JVC	16, 35
MAGNAVOX	05, 06, 09
MITSUBISHI	18, 19, 26, 27
MULTITECH	29
NEC	16, 23, 31
PANASONIC	05, 06
PHILCO	05, 06
PHILIPS	05, 06, 09
QUASAR	05, 06
RCA	07, 08
SAMSUNG	24, 32
SANYO	11, 15
SCOTT	21
SHARP	13, 14
SHINTOM	34
SYLVANIA	05, 06, 09
SYMPHONIC	29
TEKNIKA	28, 29
TOSHIBA	20, 21
TOTE VISION	25
ZENITH	17

Fig. 6: MDP manufacturer code numbers

MANUFACTURER	CODE
SONY	04
KENWOOD	58
MAGNAVOX	52
MARANZ	54
MITSUBISHI	51
PANASONIC	55
PHILIPS	52
PIONEER	51
RCA	51
SANYO	57
SHARP	56
YAMAHA	53

Fig. 7: Sony Equipment and Code Numbers

SONY EQUIPMENT	CODE
Beta, ED Beta VCR	01
8 mm VCR	02
VHS VCR	03
Video disc player	04

Note
In some rare cases, you may not be able to operate your non-Sony video equipment with the supplied Remote Commander. This is because your equipment may use a code that is not provided with this Remote Commander. In this case, please use the equipment's own remote control unit.

Operating a cable converter box

Follow these instructions to set the manufacturer's code, which will enable you to operate a connected cable converter box with the pre-programmed Remote Commander.

Example: Operate a connected Zenith cable converter box.

Remote Commander (with video control cover open)



1 Set the TV/CABLE BOX selector to CABLE BOX.



Notes

- If more than one code number is listed, try entering them one by one, until you come to the correct code for your equipment.
- If you enter a new code number, the code number you previously entered at that setting is erased.
- In some rare cases, your equipment may use a code that is not provided with this Remote Commander and you may not be able to operate your cable converter box with the supplied Remote Commander. In this case, use the equipment's own remote control unit.

2 While pressing CODE SET, press 6 and 8 (Zenith's code number — see Fig. 8) and ENTER.

3 Use the projection TV control buttons (POWER, 0 – 9, ENTER and CH +/–) to operate the cable converter box.



To return to the normal screen
Set the TV/CABLE BOX selector to TV; then use the projection TV control buttons to control the projection TV.

For more details on operating the cable box
Refer to the operating instructions that come with the cable box.

Fig. 8: Cable box manufacturer code numbers

MANUFACTURER	CODE
JERROLD	60, 61, 62, 63, 64, 65
PIONEER	69, 70
SCIENTIFIC ATLANTA	66, 67
TOCOM	71, 72
ZENITH	68

Selecting a VCR mode directly — DIRECT PLAY

Follow these instructions to switch from TV to VCR mode by simply pressing the ▶ (playback) button on the supplied Remote Commander.

Example: Connect your VCR to the VIDEO 2 IN jacks, and set the VTR1-2-3 MDP selector to VTR2. When you press ▶, the input mode changes to the VCR connected to the VIDEO 2 IN jacks.

After completing the steps below, the VTR selector position is retained in the projection TV's memory.

Remote Commander (with video control cover open)



1 Press MENU.
The main menu appears.



2 Press A/V WINDOW +/– until the cursor points to "SET UP."

3 Press RETURN.
The set up menu appears.



4 Press A/V WINDOW +/– until the cursor points to "DIRECT PLAY."

5 Press RETURN.
A message screen appears.

Note
This screen reminds you to set the manufacturer's code, if you have not already done so (pp. 68 – 69).

6 Press RETURN again.
The DIRECT PLAY screen appears.



7 Press A/V WINDOW +/– until the cursor points to the video input mode. (When the video equipment is connected to VIDEO 1 IN, select "VIDEO1.")

8 Press RETURN.
The mode display turns red.

(Continued)

Selecting a VCR mode directly – DIRECT PLAY

(Cont'd. from prev. page)

Remote Commander



9 Press A/V WINDOW +/– to select the VTR selector mode you have set on the Remote Commander. (When the VTR1-2-3 MDP selector is set to VTR2, select "VTR 2.")

Each time you press A/V WINDOW +/–, "VTR 1," "VTR 2," "VTR 3," "MDP" and "OFF" appear in sequence.



10 Press RETURN.

The direct play setting is complete.

To set direct play for other connected video equipment
Repeat steps 7 – 10.

To return to the previous menu
Press A/V WINDOW +/– until the cursor points to " ⊃ MENU."
Then press RETURN.

To return to the main menu
Repeat the above, until you reach the main menu.

To return to the normal screen.
Press MENU.

Appendix

Troubleshooting

Disturbances in picture and sound can often be eliminated by checking the symptoms and following the suggestions listed here. If the problem still cannot be solved, contact your nearest service facility.

Symptom	Possible causes and remedies
No picture (screen not lit), no sound	• Make sure POWER is switched on. • Check the power cord connection. • Check that the TV/VIDEO and VTR1-2-3 MDP controls are set correctly. • Make sure that the TV/CABLE BOX selector is set to TV.
Poor or no picture (screen not lit), good sound	• Adjust the picture using the VIDEO screen (pp. 44 – 47). • Check the antenna/cable connections. • Adjust the color registration (pp. 24 – 25).
Good picture, no sound	• Press VOLUME + on the projection TV or VOL + on the Remote Commander. • Press MUTING on the Remote Commander. • Check the MTS setting (p. 51). • Check that the TV/VIDEO and VTR1-2-3 MDP controls are set correctly. • Make sure SPEAKER is set correctly (p. 52).
No color for color programs	• Check the HUE and COLOR settings (pp. 44 – 45).
Snow and noise only	• Check that it is an active or correct channel. • Check the cable setting. • Check antenna/cable connections.
 Dotted lines or stripes	This is often caused by local interference (for example, cars, neon signs and hairdryers). Adjust the telescopic aerial for minimum interference.
 Double images or ghosts	Reflections from nearby mountains or buildings often cause this problem. Connecting a highly directional outdoor antenna or a CATV cable may improve the picture.
Remote control does not operate	• Check the battery in the Remote Commander.
No picture and/or sound for the connected equipment	• Check that the TV/VIDEO button is set correctly. • Check that the connections are properly made. • Check that the power of the connected equipment is turned on. • Check that the connected equipment is set correctly.
Try another channel. It could be station trouble.	

SECTION 2
DISASSEMBLY

2-1. H2 BOARD REMOVAL



2-2. D BOARD REMOVAL



2-3. H1 BOARD REMOVAL



2-4. REFLECTION MIRROR REMOVAL



2-5. BACK COVER REMOVAL



2-6. MAIN CHASSIS ASSY REMOVAL



2-7. SERVICE POSITION



NOTES INSERTED IN SERVICE POSITION

Service Position Procedure

1)Remove the path locks where the harness comes into.(MAIN bracket, G shield)
2)Remove the following connectors befor removing the main bracket.
※ HV grounding lead, G shield grounding lead, V-2 connector(V board).
3)Remove the main bracket.(Take care as the connector leads linking to the C and Z boards considerably short).
4)Before power ON,be sure to connect the connectors removed.
※ HV grounding lead, G shild grounding lead.
In case that grounding lead(Black) of HV Block is not connected with chassis grounding, it causes arcing of CRT and it is daigerous.
Be sure to connect grounding lead of HV Block with chassis grounding.

CONNECTOR CABLES

※ In order to put the set in the service position, use the extension connector cables below.

Parts No.	Connection
1-941-897-38	CB-4toCN1652(G BOARD)



Parts No.	Connection
1-941-897-39	CG-16toCN1608(A BOARD)



Parts No.	Connection
1-941-897-40	ZG-19toCN1308(DO BOARD)



Parts No.	Connection
1-941-897-41	ZR-18toCN1306(DO BOARD)



Parts No.	Connection
1-941-897-42	ZG-2toD-2



Parts No.	Connection
1-941-897-43	CR-15toCN1609(A BOARD)



Parts No.	Connection
1-941-897-44	ZR-1toD-1



Parts No.	Connection
1-941-897-45	A-21toCRT BRACKET



Parts No.	Connection
1-941-897-46	V-2toZR-3



2-8. SUB CONNECTOR PANEL REMOVAL



TABLE OF CONTENTS

2-9. MAIN CONNECTOR PANEL REMOVAL



2-10. U BRACKET REMOVAL



2-11. V BOARD REMOVAL



2-12. N BRACKET REMOVAL



2-13. G BOARD REMOVAL



2-14. MIRROR COVER REMOVAL

① 2-1 H2 BOARD REMOVAL,
2-3 H1 BOARD REMOVAL,
2-4 REFLECTION MIRROR REMOVAL,



2-15. CHASSIS ASSY REMOVAL



2-16. PICTURE TUBE REMOVAL



2-17. HIGH-VOLTAGE CABLE INSTALLATION AND REMOVAL

(1) Remover



(2) Installation



2-18. CONNECTOR CABLE



SECTION 3
SET-UP ADJUSTMENTS

3-1. FOCUS LENS ADJUSTMENTS

1. Set the D-board registration variable resistors (VR) to mechanical center.
2. Set the centering magnets (for red, green, and blue) to 0 as shown in the figure.



3. Input monoscope signal. Set 50% BRIGHTNESS and minimum PICTURE. Make rough adjustment so that 10IRE of the monoscope signal becomes faintly luminous using the screen VRs.
4. Set PICTURE and BRIGHTNESS maximum. Press the commander menu button. Select CONVERGENCE to display test signal.
5. Enter service mode. Select R OFF of SERVICE MODE to cut off red output.
   Similarly, select B OFF to cut off blue output.
6. Turn the green lens to eliminate flare of the test signal.





(Focus block)



7. Turn the green focus VR in the focus block to adjust green focus to reduce both A and B of the test signal to minimum.



8. Repeat avobe 6 and 7. Couple of times to improve tracking and obtain an optimum focus. Then tighten the green lens screw.
9. Adjust the red and blue focuses similarly.

3-2. DEFLECTION YOKE POSITION ADJUSTMENTS

1. Input monoscope signal.
2. Enter service mode. Select R OFF of SERVICE MODE to cut off red output.
   Similarly, select B OFF to cut off blue output.
3. Loosen the deflection yoke (DY) fitting screws. Tilt the DY to obtain the best horizontal and vertical monoscope patterns.
4. After adjustment, press the DY onto the cathode ray tube (CRT) funnel and tighten the screws.
5. Also adjust DY positions for red and blue outputs in the same way.

3-3. 2-POLE MAGNET ADJUSTMENT

1. Input dot signal.
2. Enter service mode. Select R OFF of SERVICE MODE to cut off red output.
   Similarly, select B OFF to cut off blue output.
3. Set PICTURE to maximum. Turn the green focus variable resistor (VR) in the focus block counterclockwise from the just focus to brighten the point in the dot.
4. Adjust the 2-pole magnet to position the bright point at the center of the dot.
5. Adjust the red and blue dots in the same way.

* Use the center dot:red and green
  Use the vertical center and left end dot : blue



3-4. 4-POLE MAGNET ADJUSTMENT

1. Input dot signal.
2. Enter service mode. Select R OFF of SERVICE MODE to cut off red output.
   Similarly, select B OFF to cut off blue output.
3. Set PICTURE to maximum. Turn the green focus variable resistor (VR) in the focus block clockwise (counter clockwise : blue) from the just focus until the dot diameter becomes as shown below.
4. Adjust the 2-pole magnet to make the dot perfectly round.
5. Turn the green focus variable resistor to the just focus.
6. Adjust the red and blue dot in the same way.

* Use the center dot : red and green
  Use the vertical center and left end dot : blue



3-5. DE-FOCUS ADJUSTMENT (BLUE)

1. Input cross hatch signal.
2. Turn the blue focus variable resistor (VR) in the focus block counter clock wise so that thewidth of the left end vertical line becomes as shown below.



without flare

3-6. GREEN PICTURE ADJUSTMENTS

1. Input monoscope signal.
2. Enter service mode. Select R OFF of SERVICE MODE to cut off red output.
   Similarly, select B OFF to cut off blue output.
3. Turn RV913 and RV960, the vertical green linearity variable resistors (V.G LIN VRs) on the D-board, to obtain an optimum vertical linearity. Then turn RV911, the vertical green amplitube variable resistor (V.G SIZE VR) to set vertical amplitude to 11.7 flames.

   Note: The vertical position indicator of the monoscope signal must be positioned at the center by adjusting RV905, the vertical green center position variable resistor (V.G CENT VR) in advance.



Monoscope signal



RV905 V.G CENT
(vertical position)



RV911 V.G SIZE
(vertical amplitude)



RV913 V.G LIN
(vertical linearity)

5. Verify that the horizontal lines on the top and bottom of cross-hatched area of the monoscope signal are horizontal and linear.



6. Turn RV916, RV964 and RV969, the horizontal green linearity variable resistors (H.G LIN VRs) on the D-board, to obtain an optimum horizontal linearity.
   Then turn RV908, the horizontal green amplitude variable resistor (H.G SIZE VR) to set horizontal amplitude to 15.6 frames.
   Note: The horizontal position indicator of the monoscope signal must be positioned at the center by adjusting RV902, the horizontal green center position variable resistor (V.G CENT VR) in advance.





RV908 H.G SIZE
(horizontal position)



RV916 H.G LIN
(horizontal linearity)

7. Input cross hatch signal.
   Turn vertical green (V.G) and horizontal green (H.G) variable resistors (VRs) and make adjustments according to the following steps :

(Adjustment procedure)

1. [BOW] → [SKEW] → [CENT (center position)]
2. [PIN (pin warp)] → [SUB BOW] → [BOW]
3. [KEYS (trapezoid)] → [SUB SKEW] → [SKEW]
4. [M.WAVE (middle sine wave warp)] →
   [WAVE-A (upper and lower sine wave warp)] →
   [WAVE-U (upper sine wave warp)]
   ※ For vertical (V) only.
5. [V-M.PIN (vertical middle pin warp)] →
   [V/WING (vertical wing warp)]
   ※ For vertical (V) only.
6. [H-M.PIN (horizontal middle pin warp)]
   ※ For horizontal (H) only.

(Dot motion)



RV932 H.G BOW
(horizontal green bow)



RV941 H.G PIN
(horizontal green pin warp)



RV950 H.G SUB BOW
(horizontal green sub bow)



V.G BOW·····RV935
V.G PIN·····RV938
V.G SUB BOW·····RV953



RV920 H.G SKEW
(horizontal green skew)



RV925 H.G KEYS
(horizontal green trapezoid)



RV944 H.G SUB SKEW
(horizontal green sub skew)



V.G SKEW·····RV923
V.G KEYS·····RV929
V.G SUB SKEW·····RV947



RV962 V-M-WAVE
(vertical middle sine wave warp)



RV975 V-WAVE-A
(vertical upper and lower sine wave warp)



RV978 V-WAVE-U
(vertical upper sine wave warp)



RV980 V-M. PIN
(vertical middle pin warp)
※ Common in red, green, and blue



RV957 V/WING
(wing warp)
※ Common in red, green, and blue



RV956 H/M. PIN
(horizontal middle pin warp)

3-7. GREEN AND RED REGISTRATION ADJUSTMENTS

1. Input cross hatch signal.
2. Enter service mode. Select B OFF of SERVICE MODE to cut off blue output.
3. Turn the vertical red (V.R) and horizontal red (H. R) variable resistors (VRs) to adjust red picture convergence in relation to green picture according to the following steps :

(Adjustment procedure)

1. [LIN (linearity)] → [SIZE (amplitude)] → [CENT (center position)]
2. [BOW] → [SKEW] → [CENT (center position)]
3. [PIN (pin warp)] → [SUB BOW] → [BOW] [H/M. PIN (horizontal middle pin warp)]
4. [KEYS (trapezoid)] → [SUB SKEW] → [SKEW]
5. [M.WAVE (middle sine wave warp)] → [WAVE-A (upper and lower sine wave warp)] → [WAVE-U (upper sine wave warp)]

(Dot motion)



RV912 V.B SIZE
(vertical red amplitude)



RV952 V.R SUB BOW
(vertical red sub bow)



RV943 V.R BOW
(vertical red bow)



RV928 V.R KEYS
(vertical red trapezoid)



RV946 V.R SUB SKEW
(vertical red sub skew)



RV904 V.R CENT
(vertical red center position)



RV917 V.R LIN
(vertical red linearity)



RV922 V.R SKEW
(vertical red skew)

H.R LIN·····RV915
H.R SIZE·····RV907
H.R CENT·····RV901
H.R BOW·····RV931
H.R SKEW·····RV919
H.R PIN·····RV940
H.R KEYS·····RV926
H.R SUB BOW·····RV949
H.R SUB SKEW·····RV943
V-M-WAVE·····RV973
V-WAVE-A·····RV976
V-WAVE-U·····RV979
V-M.PIN·····RV980
V/WING·····RV957
H/M.PIN·····RV956

SECTION 1
GENERAL

The operating instructions mentioned here are partial abstracts from the Operating Instruction Manual. The page numbers of the Operating Instruction Manual remein as in the manual.

Chapter 1: Setting Up

Unpacking and Viewing Area

1 Carefully follow the instructions on the outside of the packing carton to unpack the projection TV.

Notes
- The supplied accessories are packed in the bottom of the carton. Be sure not to throw them away.
- Keep the original carton and packing materials to safely transport the projection TV in the future.

2 Check to make sure that the following is included:

Universal Remote Commander
RM-Y112A (1)
with 2 size AA (R6) EVEREADY batteries

If the Remote Commander is missing, contact your dealer.

3 Place the projection TV in a cool, dry place where the ventilation openings at the sides are not blocked.

4 Plug the projection TV power cord into an AC 120 volt power outlet.

For further precautions, see p. 2.

Optimum viewing area

For the best picture quality, try to position the projection TV so that you can view the screen from within the areas shown below.

Horizontal viewing area



Optimum viewing position

Vertical viewing area



Optimum viewing position

Locating Controls and Connectors

For details, see the pages indicated by the numbered black circles ●.

Front



* Buttons with the same function are also located on the Remote Commander (p. 10).

3-8. GREEN AND BLUE REGISTRATION ADJUSTMENTS

1. Input cross hatch signal.
2. Enter service mode. Select R OFF of SERVICE MODE to cut off red output.
3. Turn the vertical blue (V.B) and horizontal blue (H.B) variable resistors (VRs) to adjust blue picture convergence in relation to green picture according to the following steps :

(Adjustment procedure)

1. [LIN (linearity)] → [SIZE (amplitude)] → [CENT (center position)] →
2. [BOW] → [SKEW] → [CENT (center position)]
3. [PIN (pin warp)] → [SUB BOW] → [BOW] [H/M. PIN (horizontal middle pin warp)]
4. [KEYS (trapezoid)] → [SUB SKEW] → [SKEW]
5. [M.WAVE (middle sine wave warp)] → [WAVE-A (upper and lower sine wave warp)] → [WAVE-U (upper sine wave warp)] →

(Dot motion)



RV912 V.B SIZE
(vertical blue amplitude)



RV918 V.B LIN
(vertical blue linearity)



RV954 V.B SUB BOW
(horizontal blue sub bow)



RV936 V.B BOW
(vertical blue bow)



RV930 V.B KEYS
(vertical blue trapezoid)



RV948 V.B SUB SKEW
(vertical blue sub skew)



RV924 V.B SKEW
(vertical blue skew)



RV906 V.B CENT
(vertical blue center position)



RV939 V.B PIN
(vertical blue pin warp)



RV903 H.B CENT
(vertical blue center position)



RV909 H.B SIZE
(horizontal blue amplitude)



RV914 H.B LIN
(horizontal blue linearity)



RV942 H.B PIN
(horizontal blue pin warp)



RV954 H.B SUB SKEW
(horizontal blue sub skew)



RV951 H.B SUB BOW
(horizontal blue sub bow)



RV921 H.B SKEW
(horizontal blue skew)



RV927 H.B KEYS
(horizontal blue trapezoid)



RV933 H.B BOW
(horizontal blue bow)



RV981
※ Common in red, green, and blue



RV982
※ Common in red, green, and blue

H/M PIN·····RV958
M.WAVE·····RV961
WAVE-A·····RV974
WAVE-U·····RV977

3-9. REGISTRATION CHECK

1. Out put red, blue, and green.
2. Out put cross hatch and monoscope signals to check registration. Also check focus.

3-10. WHITE BALANCE ADJUSTMENTS

1) Screen adjustment

1. Input white signal.
2. Remove connectors CR-15, CG-16, and CB-17.
3. Fit jigs between the ground and R707, R737, and R767.



※ Resistors in each jig are connected serial.

4. Turn the RGB (red, green, and blue) screen variable resistors in the focus block to make the flyback line faint. Stop before the line completely disappears.
5. Insert connectors CR-15, CG-16, and CB-17.

2) White balance adjustments (SBRT, GAMP, BAMP, GCUT, BCUT)

1. Input monoscope signal and enter service mode.
2. Select the picture quality adjustment from the menu and set PICTURE minimum.
3. Use the commander to adjust SBRT so that 10 IRE of the monoscope pattern becomes faintly luminous.
4. Input white signal.
5. Set PICTURE minimum. Adjust item GCUT and BCUT to obtain an optimum white balance.
6. Set PICTURE maximum. Adjust GAMP and BAMP to obtain an optimum white balance.
7. Repeat white balance adjustment alternating PICTURE setting at the minimum and maximum.

SECTION 4
SAFETY RELATED ADJUSTMENTS

4-1. SAFETY RELATED ADJUSTMENTS

When replacing the following components, make the HV REGULATOR adjustments (on the N board)

◪·····HV block, IC803, IC805, D805, D807, C817, C818, C821, C836, C837, R824, R825, R827, R828, R834,R835, R836, R864, R865, R866, R902

When replacing the following components, make the HV HOLD DOWN adjustments (on the N board)

◪·····HV block, IC803, IC804, Q804, D806, D808, C809, C819, C820, C822, C823, C850, R807, R826, R829, R832, R833, R837, R838, R839, R840, R841, R892, R893, R900, R901

When replacing the following components, make the BEAM CURRENT PROTECTOR adjustments (on the N board)

◪·····① IC802, Q805, Q807, D811, D812,C810, C824, C825, C826, C827, C831, R810, R843, R844, R847, R848, R849, R850, R851, R852, R853, R854, R881

② IC804, Q804, Q808, D808, D809, C809, C828,C829, C830, C831, R807, R839, R840, R841,R847, R848, R849, R850, R851, R852, R855, R856, R857, R881

When replacing the following components, make the OVP CIRCUIT adjustments (on the G board)

◪·····Q618, Q621, D628, C634, R639, R649, R652, R655, R656

— Checking with static voltmeter —

HV HOLD DOWN ADJUSTMENTS (⊠R900, R901)

1. Verify that the power switch is off.
2. Connect the HV hold down adjustment resistance jig to the N20 connector on the N board.



3. Connect an external variable resistor (RV) to R 902 of the N board.
4. Remove the cap off from the unused terminal of the high voltage block. Connect a static voltmeter to the terminal.



5. Receive 120 VAC power voltage and monoscope pattern signal. Maximize PICTURE and BRIGHTNESS.
6. Use the external variable resistor of the hold down adjustment jig to make the static voltmeter to read 33.50 ± 0.50kVDC.
7. Raise resistances with the jig until the HV hold down circuit is activated. Read the figures then, and mount resistance of the measured figures to R900 and R901.
   R900 : Must be 1kΩ to 12kΩ
   R901 : Must be Jw 100Ω to 820Ω
8. Turn on power again. Vary external variable resistance and confirm that the HV hold down circuit is activated at the reated value, 33.50± 0.50kV.

HV REGULATOR ADJUSTMENTS (⊠R902)

1. Connect the HV adjustment resistance jig to R902 of the N board.



(Adjustment jig)

2. Remove the red anode lead wire for the CRT tube from the high-voltage block and connect the static voltmeter instead.
3. Receive 120 VAC power voltage and monoscope pattern signal. Set PICTURE and BRIGHTNESS to the standard.
4. Turn on power. To adjust the resistance of R902 with the adjustment jig to read the rated value, 31.50±0.50kV.
5. Receive all-white signal. Set BRIGHTNESS to the standard. Maximize PICTURE. Confirm that the rated value, 31.50±0.50kV is read.
6. Cut off RGB by R OFF, G OFF, B OFF of the service commander. Verify that the rated value, 31.50±0.50kV, is read.

+B VOLTAGE CONFIRMATION

1. Receive 120±1 VAC power voltage and monoscope pattern signal. Set BRIGHTNESS to standard and maximize PICTURE.
2. Connect a digital multimeter between the 115V line and the ground on the G board, and confirm that the rated value, 115.0$^{+3.0}_{-3.0}$V is read.

CHECKING AFTER REPLACING IC601

1. When replacing IC601, check the +B voltage.

CHECKING THE OVP (overvoltage protection) CIRCUIT (⊠R652)

1. Receive 120 VAC power voltage and monoscope pattern signal. Maximize PICTURE and BRIGHTNESS.
2. Remove R638 from the G board and connect a variable resistor (4.7 to 10kΩ) instead.
3. Turn the variable resistor of 10kΩ and confirm that the OVP circuit is activated and luster disappears when +B voltage reads the rated value, 125.0±5.0 VDC.

BEAM CURRENT PROTECTOR CHECK (⊠R852)

1. Receive 120 VAC power voltage and monoscope pattern signal. Maximize BRIGHTNESS.
2. Connect pin① and pin② of the N-21 connector. (on the N board)
3. Remove the jumper connector from the N-8 connector on the N board. Then connect an ABL ammeter between pin ① and pin ④ of the N-8 connector.



4. Raise PICTURE current gradually. Confirm that the beam current protector circuit is activated and luster disappears under the rated value, 3400 μA.
5. Connect pin③ and pin② of the N-21 connector. Verify that the protector circuit is activated and luster disappears similarly.


N Board
R900
N-20
R902


G Board
variable resistor
(50kΩ)
R638
R652
digital multi-meter
+
−

— Checking without static voltmeter —

HV HOLD DOWN ADJUSTMENT (⊠R900, ⊠R901)

1. Receive all-white signal. Maximize PICTURE and BRIGHTNESS.
2. Remove R902 from the N board. Connect a variable resistor of 50kΩ on each end, and minimize the resistance.
3. Remove R900 and R901 from the N board. Connect a variable resistor of 50kΩ on each end, and minimize the resistance.
4. Connect a digital voltmeter between the D801 cathode and chassis ground of the N board.
5. Turn on the power switch. Adjust the variable resistors connected to the R902 of the N board to make the digital multimeter to read 145.0VDC.
6. Adjust the variable resistors connected to R900 and R901 on the N board so as to activate the HV hold down circuit and turn off the display.
7. Read the variable resistors connected to R900 and R901 and mount fixed resistors of measured resistance to the terminals.
   Note : Select fixed resistance from the following ranges.
   R900 : 1kΩ to 12kΩ
   R901 : Jw 100Ω to 820Ω
8. Maximize resistance of the variable resistor connected to R902 of the N board and turn on power.
9. Vary variable resistance at R902. Confirm that the HV hold down circuit is activated and the display is turned off when voltage reads 134±1.0V.



HV REGULATOR ADJUSTMENT (⊠R902)

1. Receive all-white signal. Maximize PICTURE and BRIGHTNESS.
2. Connect a variable resistor of 50kΩ on each end of R902 of the N board. Maximize resistance.
3. Connect a digital voltmeter between the D801 cathode and the chassis of the N board.
4. Turn on power. Adjust the variable resistor so that the digital multimeter reads 135.0V±1.0V.
5. Read the variable resistance then.
6. Mount a fixed resistor of the measured resistance to R902.
   Note : R902 : Must be 2.2kΩ to 27kΩ
7. Turn on power again. Confirm that the digital multimeter reads 135.0V±1.0V.



SECTION 5
CIRCUIT ADJUSTMENTS

5-1. ELECTRICAL ADJUSTMENT BY REMOTE COMMANDER

Use of Remote Commander (RM-Y112A)can be performed circuit adjustments about this model.

NOTE : Test Equipment Required.
1. Pattern Generator
2. Frequency counter
3. Digital multimeter
4. Audio OSC

1. METHOD OF SETTING THE SERVICE MODE

1) Press [POWER] button on the Remote Commander while pressing switch on the rear of the set.



2. ADJUST BUTTONS AND INDICATOR



3. AN ITEM OF ADJUSTMENT

ITEM	REFERENCE DATA	NAME REGIST	
AFC	0	VP	AFC 1.0
HFRE	74	VP	H. FREQUENCE
VFRE	16	VP	V. FREQUENCE
HPOS	5	VP	H. PHASE
GAMP	25	VP	GREEN AMP.
BAMP	26	VP	BLUE AMP.
GCUT	9	VP	GREEN CUT OFF.
BCUT	6	VP	BLUE CUT OFF
SPIX	40	VP	PICTURE
SHUE	29	VP	HUE
SCOL	28	VP	COLOR
SBRT	11	VP	BRIGHT
RGBP	28	VP	RGB PICTURE
SHAR	13		SHARPNESS
DISP	24		OUTPUT
VSMO	0	VP	VSMO
REF	1	VP	REF 1.0
ROFF	1	VP	OFF NR
GOFF	1	VP	OFF NG
BOFF	1	VP	OFF NB
ABLM	0	VP	ABLM
DRGB	0	VP	D RGB
TEST	0	AP	T
MPX	7	AP	ATT
FILO	31	AP	I 1
DEEM	7	AP	I 2
STEV	31	AP	OSC 1
SAPV	31	AP	OSC 2
PILO	7	AP	PILOT
SEP	31	AP	WIDE BAND
VD	7	AP	SPECTRAL
LVOL	0	AP	VOLUME-L
RVOL	0	AP	VOLUME-R
BASS	8	AP	BASS
TRE	8	AP	TREBLE
PHPO	32	PI	READ DELAY H
PVPO	8	PI	READ DELAY V
PLEV	6	PI	PICTURE LEVEL
PFCO	7	PI	FRAME COLOR
PPLL	1	PI	PLLOF
PPVS	6	PI	VSPDEL
NRLE	31		NR LEVEL
DSPP	43		
SHAD	1	PJ	SHADON
VMSW	1	PJ	RS HAD
SCUT	16	PJ	SHAD CUT OFF

4. METHOD OF CANCELLATION FROM SERVICE MODE

Set the standby condition (Press POWER button on the commander) in the next place, press POWER button again, hereupon it becomes TV mode.

5. METHOD OF WRITE FOR MEMORY

1) Set to Service Mode.
2) Press 1 (UP) and 4 (DOWN), select an item of adjustments.
3) Press MUTING button indicate WRITE (RED) on screen.
4) Press ENTER button to write for memory.

6. MEMORY WRITE CONFIRMATION METHOD



1) After adjustment, pull out the plug from AC outlet, and next place, plug in AC outlet again.
2) Turn the power switch ON and set to Service Mode.
3) Call the adjusted items again, confirm they were adjusted.

7. PUB PICTURE POSITION ADJUSTMENT (PHPO, PUPO)

Note : Before doing any Service Adjustments on the models above you must make sure that the PIP Screen is in the number 1 position, even if there are no adjustments being made to PIP.



PIP Positions

After making adjustments into the PIP 1 position, write the information into the ROM.
Next, unplug the unit and recheck the other three positions. Adjustments made to the number 1 position will affect the other three positions.

5-2. A BOARD ADJUSTMENTS

RF AGC ADJUSTMENT(IF BLOCK VR)

1) Input a color-bar signal.
2) Adjust AGC VR of TU 101 so that snow noise and cross-modulation disappear from the picture.
3) Confirm them at every channel.

H.FREQUENCY ADJUSTMENT (HFRE)

1) Set to Service Mode.
2) Input a color-bar signal.
3) Connect a frequency counter to pin③ of A-10 connector.
4) Call the item of AFC, set to 3 level (free run).
5) Select HFRE with 1 and 4.
6) Adjust 3 and 6 to the 15735± 60 Hz level.
7) Call the item of AFC again, adjust the level" 01 ".
8) Write into the memory by pressing MUTING → then ENTER.

V.FREQUENCY ADJUSTMENT (VFRE)

1) Set the Service Mode.
2) Input an off-air signal (VIDEO IN → no signal).
3) Connect the frequency counter across connector ⑬pin of E 1-1 connector and ground.
4) Select VFRE with 1 and 4.
5) Adjust 3 and 6 to the ~~55~~ 56 ±0.5 Hz.
6) Write the memory by pressing MUTING → then ENTER .

SUB CONTRAST ADJUSTMENT (SPIX)

1) Set to Service Mode.
2) Input a color-bar signal. (75 IRE)
3) Set the conditions as follows.

PICTURE	····· MAX
COLOR	····· MIN
BRIGHTNESS	····· MIN
TRINITONE	····· LOW
R OFF	····· ON
G OFF	····· OFF
B OFF	····· OFF



4) Connect an oscilloscope to ⑳pin of E1-1 connector on A board and ground.
5) Adjust 3 and 6 to the 2.10 ± 0.05Vp-p level by select-ing SPIX with 1 and 4.
6) Write the memory by pressing MUTING → then ENTER .
7) Return the following back to normal after adjustment.

G OFF	····· ON
B OFF	····· ON
COLOR	····· CENTER
BRIGHTNESS	····· CENTER
TRINITONE	····· HIGH
PICTURE	····· 80%

Front inner panel



* Buttons with the same function are also located on the Remote Commander (p. 10).

Note
The instructions in this manual are based for the most part on operating the projection TV with the Remote Commander. You can also use the buttons on the projection TV that have the same function.

Rear



SUB HUE, SUB COLOR ADJUSTMENT (SHUE, SCOL)

1) Input a color-bar signal.
2) Press STANDARD to normal.
3) Set to Service Mode.
4) Connect an oscilloscope to pin㉒ of E1-1 connector on A board and ground.
5) Adjust 3 and 4 to the V1=V4 and V2=V3 by select to SHUE and SCOL with 1 and 4. Lower the data 4 steps from this point.



4) Make the data "00" by selecting FILO with 1 and 4 And then, send up the data gradually by pressing 6 . Set the data to D1 before SAT3 changing to 1 from 0.
5) Send up the data gradually. Set data D2 when SAT3 changes 0 from 1.
6) Adjust the data of FILO to $\frac{D1+D2}{2}$.
7) Write into the memory by pressing MUTING → then ENTER .



6) Write into the memory by pressing MUTING →then ENTER .

FILTER ADJUSTMENT (MPX, FILO)

1) Set to Service Mode.
2) Select to TEST with 1 and 4, set the data to "1". Then select MPX and change data to "8".
3) Connect an audio oscillator to R224 using a capacitor (10μ F/16V), set frequency to 62.936 kHz±0.1 kHz.
And then, through the 10kΩ resistor, feed 9.0V into the mute of TUVIF TU 101.



V 4 fh : SINE-WAVE 62.936 KHz±0.1 KHz
LEVEL 3.0 Vp-p

ST VCO ADJUSTMENT (MPX, STEV)

1) Set to Service Mode.
2) Select TEST with 1 and 4 , set the data to "1". And then press MTS to MONO.
3) Select MPX, set the data "8" .
4) Connect an audio oscillator to R 224 using electrolytic capacitor (10μ F/16V) and appply the frequency VST. Then, apply DC voltage to mute of TUVIF TU 101 using 10kΩ connect to 9.0 V line.



Vfh : SINE-WAVE 15.734 KHz±0.1 KHz
LEVEL 0.28 Vp-p

5) Select STEV with 1 and 4, set the data to "00" with 6. And then, send up the data gradually. Set the data to D1 before SAT2 changes from 0 to 1.
6) Send up data gradually, set the data to D2 when SAT2 changes 1 from 0.
7) Adjust the data of STEV to (D 1+D 2)/2.
8) Write into the memory by pressing MUTING → then ENTER .



MPX IN LEVEL ADJUSTMENT (MPX)

1) Set to Service Mode.
2) Select TEST with 1 and 4, set the data to "0" with 6. And then press MTS to MONO.
3) Select MPX with 1 and 4, set the data to "8" with 3 and 6.
4) Write into the memory by pressing MUTING → then ENTER .

PILOT CANCEL ADJUSTMENT (PILO)

1) Set to the Service Mode.
2) Select PILO with 1 and 4, set the data to "08" with 3 and 6.
3) Write into the memory by pressing MUTING → then ENTER .

SAP VCO f0 ADJUSTMENT (SAPV)

1) Set to Service Mode.
2) Input a stereo broadcast signal with SAP.
3) Select TEST with 1 and 4, set the data to "0" And then, press MTS to MAIN.
4) Connect a digital multimeter to TP-1(DBX). This voltage reading will equal V 1.
5) Press MTS to SAP and this voltage will equal V 2.
6) Select SAPV with 1 and 4, adjust 3 and 6 so that V 2=V 1±0.03 VDC.
7) Write the memory by MUTING → ENTER .

SEPARATION ADJUSTMENT (SEP)

1) Set to Service Mode.
2) Press MTS to MAIN and receive a monoral broad -cast signal.
In the next step, receive a stereo broadcast signal.
3) Select SEP and VD with 1 and 4, adjust 3 and 6 so that a clear stereo sound is effected.

SUB PICTURE POSITION ADJUSTMENT (PHPO, PVPO)

1) Input a cross hatch signal.
2) Set to service mode.
3) Press PIP to display a sub picture. (RIGHT LOWER Position)
4) Select PHPO, PVPO with 1 and 4.
5) Adjust 3 and 6 to the standard as shown below.
6) Write the memory by pressing MUTING → then ENTER .



PUB PICTURE POSITION ADJUSTMENT (PHPO, PUPO)

Note : Before doing any Service Adjustments on the models above you must make sure that the PIP Screen is in the number 1 position, even if there are no adjustments being made to PIP.



PIP Positions

After making adjustments into the PIP 1 position, write the information into the ROM.
Next, unplug the unit and recheck the other three positions. Adjustments made to the number 1 position will affect the other three positions.

5-3. DS BOARD ADJUSTMENTS

V. 3 WAVE ADJUSTMENT (RV983)

1) Input a color-bar signal.
2) Connect an oscilloscope IC1712 Pin⑦ of DS board ground.
3) Adjust RV983 as shown the following figure.



H. 3 WAVE ADJUSTMENT (RV984)

1) Input a color-bar signal.
2) Connect an oscilloscope IC1712 Pin① of DS board ground.
3) Adjust RV984 as shown the following figure.



5-4. P1 BOARD ADJUSTMENTS



SUB HUE ADJUSTMENT (RV 3001)

1) Set HUE and COLOR to the standard condition.
2) Make adjustment so that B-Y signal as shown to the right is obtained at the crossing point of R 3009 (0 Ω) and C 3033.
3) Supply the color bar signal of 75 IRE (white) at 2 Vpp to Pin ㉑ (SUB V) of P 1-1 and make adjustment by turning RV 3001.



H. FREQUENCY (H OSC) ADJUSTMENT (RV-3002)

1) Connect a frequency counter to Pin ④ (H OUT) of IC 3003.
2) Connect Pin ⑫ of IC 3003 to ground.
3) Adjust RV3002 for a frequency of 15.734 kHz ± 50 Hz at Pin ④ of IC 3003.
(or until the frequency comes to a standstill.)

Remote Commander RM-Y112A (with the video control cover closed)



* Buttons with the same function are also located on the projection TV (p. 7).

Note
If the TV/CABLE BOX selector is set to CABLE BOX, the Remote Commander is able to control a connected cable box, not the projection TV (p. 70). Set the selector to TV to control the projection TV with the Remote Commander.

Remote Commander (with the video control cover open)

Opening the video control cover

Slide the cover down.





Video operating buttons

STANDARD button

• **A BOARD WAVEFORMS**

①  1.2Vp-p (H)	②  1.2Vp-p (H)	③  2.5Vp-p (H)
④  2.0Vp-p (V)	⑤  2.0 Vp-p (V)	⑥  2.0Vp-p(V)
⑦  1.8Vp-p (V)	⑧  1.0Vp-p (H)	⑨  1.2 Vp-p (H)
⑩  1.0Vp-p (H)	⑪  0.8Vp-p (H)	⑫  1.4 Vp-p (H)
⑬  58 Vp-p (H)	⑭  450Vp-p (H)	⑮  0.7Vp-p (V)
⑯  12.0Vp-p (V)	⑰  1.5Vp-p (H)	⑱  1.5Vp-p (H)
⑲  1.4Vp-p (H)	⑳  1.6Vp-p (H)	㉑  1.6Vp-p (H)
㉒  1.4Vp-p (H)	㉓  1.5Vp-p (V)	

Using the On-Screen Menus

The following flow chart shows the different levels of on-screen menus that you can use to make various adjustments and settings. See the indicated pages for instructions on using each feature.

For picture and sound quality adjustment



For mode adjustment



For time-related settings



Note
Menu items that are shaded are inactive and cannot be selected.

For presetting and other functions



For CONVERGENCE adjustment

Navigating through the menus

Remote Commander

To display the main menu
Press MENU.

To return to the previous menu
Press A/V WINDOW +/– until the cursor points to " ⊃MENU."
Then press RETURN.

To return to the main menu
Repeat the above, until you reach the main menu.

To return to the normal screen
Press MENU.

Note
The menus disappear automatically, if you do not press a button within 90 seconds.

U [AUDIO IN/OUT VIDEO IN/OUT] **UT** [IN/OUT TERMINAL, SP. TERMINAL]

– U BOARD –

IC	
IC1002	B-3
IC1011	F-2

TRANSISTOR	
Q1009	D-2
Q1016	E-3
Q1017	B-5
Q1018	E-2
Q1019	E-3
Q1020	B-5
Q1021	B-2
Q1022	E-1
Q1023	C-2
Q1029	B-2
Q1030	D-2
Q1031	E-2
Q1032	C-4
Q1033	E-2
Q1034	G-2

DIODE	
D1005	A-2
D1009	B-4
D1010	A-4
D1011	B-3
D1012	D-3
D1013	E-3
D1015	B-4
D1017	B-2
D1018	G-2
D1019	G-2
D1020	E-2
D1021	E-3
D1022	E-3



– UT BOARD –


UT
SONY
1-643-153-12
CAD
REAR
FRONT
VIDEO 1 IN
VIDEO 2 IN
VIDEO 3 IN
LOOP OUT
MONITOR OUT
AUDIO OUT (VAR)
AUDIO OUT (FIXED)
VAR R IN
MONI Y IN
MONI C IN
MONI Y IN
VIDEO 1 OUT
VIDEO 2 OUT
VIDEO 3 OUT
FRONT L OUT
FRONT R OUT
REAR L OUT
REAR R OUT
UT-11
UT-9
UT-38
UT-35
UT-23
UT-22



Changing the menu language

The menu language is factory-set to ENGLISH. Follow these instructions to change the menu language to Spanish or French, or back to English.

1 Press POWER to turn on the projection TV.
TIMER/STAND BY indicator blinks until the picture appears.

POWER



2 Press MENU.
The main menu appears.

MENU



3 Press A/V WINDOW +/– until the cursor points to "ENGLISH."
Then press RETURN.
The language display turns red.

A/V WINDOW RETURN



4 Press A/V WINDOW +/– to select the language.
Each time you press A/V WINDOW +/–, the "ESPAÑOL," "FRANÇAIS" and "ENGLISH" menus appear.

A/V WINDOW



Note
Certain parts of the "ESPAÑOL" and "FRANÇAIS" menus remain in English.

5 Press RETURN.
The language is selected.

RETURN

Spanish menu

To return to the normal screen.
Press MENU.

Notes concerning menus

- During PIP (Picture-in-Picture) mode, the on-screen menus may overlap the window picture.
- The menus disappear automatically, if you do not press a button within 90 seconds.

Adjusting Color Registration (CONVERGENCE)



In a projection TV, the projection tube image appears on the screen in three color layers (red, green and blue). If these layers are not in proper registration, the color is poor and the picture blurs. To correct this, perform the CONVERGENCE adjustment.

1 Press MENU.
The main menu appears.



2 Press A/V WINDOW +/– until the cursor points to "CONVERGENCE."





3 Press RETURN.
The CONVERGENCE screen and the colored adjustment lines appear.



R = Red
G = Green
B = Blue

4 Press A/V WINDOW +/– until the cursor points to the symbol representing the line you want to adjust (see the key below).





Adjustment line symbols key
- | (red vertical: left/right adjustment)
- — (red horizontal: up/down adjustment)
- | (blue vertical: left/right adjustment)
- — (blue horizontal: up/down adjustment)

5 Press RETURN.
The adjustment line is selected.



6 Press A/V WINDOW +/– until the line converges with the center green line. Then press RETURN.





To move up To move right	Press A/V WINDOW +.
To move down To move left	Press A/V WINDOW –.

7 Repeat steps 4 – 6 to adjust the other lines, until all the lines have overlapped to form a white cross.



To return to the previous menu
Press A/V WINDOW +/– until the cursor points to " ⊃ MENU."
Then press RETURN.

To return to the main menu
Repeat the above, until you reach the main menu.

To return to the normal screen.
Press MENU.

Setting CABLE ON or OFF



If you have cable connected to the projection TV, follow the steps below to set the cable connection on or off. Set CABLE OFF to preset or watch VHF or UHF channels, and set CABLE ON to preset or watch cable TV channels.

Note
If the projection TV is in video mode, the "CABLE" display is shaded and cannot be selected.
Press TV/VIDEO to change to TV mode.

1 Press MENU.
The main menu appears.

MENU



2 Press A/V WINDOW +/– until the cursor points to "SET UP."

A/V WINDOW



3 Press RETURN.
The set up menu appears, and the cursor points to "CABLE."

RETURN



4 Press RETURN again.
The mode display turns red.

RETURN



5 Press A/V WINDOW +/– to select "ON" or "OFF."

A/V WINDOW



6 Press RETURN.
The setting is complete.

RETURN



To return to the previous menu
Press A/V WINDOW +/– until the cursor points to " ⊃ MENU."
Then press RETURN.

To return to the main menu
Repeat the above, until you reach the main menu.

To return to the normal screen.
Press MENU.

Cable TV channel chart*
Cable TV systems use letters or numbers to designate channels. To tune in a channel, refer to the chart below.

Number on this TV	Corresponding CATV channel
1	A-8
5	A-7
6	A-6
14	A
15	B
16	C
17	D
18	E
19	F
20	G
21	H
22	I
23	J
24	K
25	L
26	M
27	N
28	O
29	P
30	Q
31	R
32	S
33	T
34	U
35	V
36	W
37	W+1
38	W+2
39	W+3
⋮	⋮
93	W+57
94	W+58
95	A-5
96	A-4
97	A-3
98	A-2
99	A-1
100	W+59
101	W+60
102	W+61
⋮	⋮
123	W+82
124	W+83
125	W+84

Check with your local cable TV company for more complete information on the available channels.
* The designation of the cable TV channels conforms to the EIA/NCTA recommendation.

Presetting TV Channels

By presetting TV channels to the projection TV, you can select channels by pressing CH (CHANNEL) +/–.
(You can select VHF channels 2 – 13 without presetting.)



Presetting all receivable channels automatically

Follow these instructions to preset all the receivable VHF, UHF or cable TV channels to the projection TV.

Notes

- If the projection TV is in video mode, the "AUTO PROGRAM" display is shaded and cannot be selected. Press TV/VIDEO to change to TV mode.
- Perform auto programming during the day rather than late at night, when some channels may not be broadcasting.

1 Set the cable connection on or off (pp. 26 – 27) to select the type of channel you want to preset, VHF/UHF or cable TV.



To preset VHF or UHF channels

To preset cable TV channels

2 Press MENU.
The main menu appears.

3 Press A/V WINDOW +/– until the cursor points to "SET UP."

4 Press RETURN.
The set up menu appears.



5 Press A/V WINDOW +/– until the cursor points to "AUTO PROGRAM."

6 Press RETURN.

"AUTO PROGRAM" appears on the screen and receivable channels (other than the channels already preset) are preset in numerical sequence. The channels previously preset will not remain in the projection TV's memory.
When no more channels are found, auto programming stops and the screen returns automatically to the set up menu.

7 Press CH +/– to check or view the preset channels.



Receivable channels for this projection TV
VHF: 2 – 13
UHF: 14 – 69
Cable: 1 – 125

To select TV channels without presetting
Press the 0 – 9 buttons and ENTER.

To return to the previous menu
Press A/V WINDOW +/– until the cursor points to " ⊃ MENU."
Then press RETURN.

To return to the main menu
Repeat the above, until you reach the main menu.

To return to the normal screen.
Press MENU.



Erasing TV channels

Follow these instructions to erase unnecessary TV channels, so that when you press CH +/–, the channel(s) are skipped.

1 Press MENU
The main menu appears.



2 Press A/V WINDOW +/– until the cursor points to "SET UP."





3 Press RETURN
The set up menu appears.



4 Press A/V WINDOW +/– until the cursor points to "CH ERASE/ADD."





5 Press RETURN.
The CH ERASE/ADD screen appears, and the cursor points to "ERASE."



6 Press CH +/– to select the channel you want to erase.
The channel display appears.





7 Press RETURN.
A "–" sign appears in front of the channel number display, indicating that the channel is erased; then the CH ERASE/ADD screen automatically reappears.



To erase another channel
Repeat steps 6 – 7.

To return to the previous menu
Press A/V WINDOW +/– until the cursor points to " ⊃ MENU."
Then press RETURN.

To return to the main menu
Repeat the above, until you reach the main menu.

To return to the normal screen
Press MENU.

Note
If you erase a VHF or UHF channel, the same number cable TV channel is also erased (and vice versa).

SECTION 7
EXPLODED VIEWS

NOTE:
- Items with no part number and no description are not stocked because they are seldom required for routine service.
- The construction parts of an assembled part are indicated with a collation number in the remark column.
- Items marked " ★ " are not stocked since they are seldom required for routine service. Some delay should be anticipated when ordering these items.

The components identified by shading and mark ⚠ are critical for safety.
Replace only with part number specified.

Les composants identifies par une trame et une marque ⚠ sont critiques pour la securite.
Ne les remplacer que par une piece portant le numero specifie.

7-1.SCREEN FRAME AND CONTROL PANEL

● : BVTP3×12 7-685-648-79

□ : BVTP4×12 7-685-661-79



REF.NO.	PART NO.	DESCRIPTION	REMARK
1	X-4031-192-1	FRAME ASSY, SCREEN	2~4
2	3-704-179-01	EMBLEM (NO.9), SONY	
3	4-036-087-21	COVER, INDICATOR	
4	4-033-779-11	BUTTON, CONTROL	
5	4-378-522-31	SCREW, TAPPING, HEXAGON HEAD	
6	*1-643-591-11	H1 BOARD	
7	4-034-053-01	PLATE (L), DIFFUSION	
8	4-036-520-01	PLATE (F), DIFFUSION	
9	4-036-091-01	HOLDER (L), SCREEN	
10	4-036-092-01	HOLDER (S), SCREEN	
11	X-4030-346-1	GRILLE (L) ASSY, SPEAKER	
12	X-4030-348-1	GRILLE (R) ASSY, SPEAKER	
13	4-838-438-00	LATCH	
14	*1-643-592-11	H2 BOARD	
15	X-4030-354-4	PANEL ASSY, CONTROL	16~21
16	4-033-794-11	LID, FRONT	
17	4-374-714-01	CATCH, PUSH	
18	3-703-035-11	SHAFT, LID	
19	4-843-806-00	STRIKE	
20	*4-314-320-00	HOLDER, WIRE	
21	3-721-204-01	DAMPER	
22	X-4030-347-1	COVER ASSY, FRONT	19
23	4-304-851-11	SCREW (4X25), (+) PWH TAPPING	
24	4-039-110-01	SPACER (CA)	



Adding TV channels

Follow these instructions to add TV channels one by one to the selection memory, or to replace a TV channel you previously erased (pp. 30 – 31).

1 Press MENU
The main menu appears.


```
▶PROG PALETTE
 MODE SET
 TIME
 SET UP
 ENGLISH
 CONVERGENCE
SELECT RETURN EXIT
```

2 Press A/V WINDOW +/– until the cursor points to "SET UP."




```
 PROG PALETTE
 MODE SET
 TIME
▶SET UP
 ENGLISH
 CONVERGENCE
SELECT RETURN EXIT
```

3 Press RETURN.
The set up menu appears.


```
▶CABLE: ON
 AUTO PROGRAM
 CH ERASE/ADD
 CH CAPTION
 VIDEO LABEL
 DIRECT PLAY
 FAVORITE CHANNEL
 MENU
```

4 Press A/V WINDOW +/– until the cursor points to "CH ERASE/ADD."




```
 CABLE: ON
 AUTO PROGRAM
▶CH ERASE/ADD
 CH CAPTION
 VIDEO LABEL
 DIRECT PLAY
 FAVORITE CHANNEL
 MENU
```

5 Press RETURN.
The CH ERASE/ADD screen appears.


```
CH ERASE/ADD
▶ERASE
 ADD
 
Select the channel.
ERASE:CHANNEL +/-
ADD:  [0-9]+[ENTER]
SELECT RETURN EXIT
```

6 Press A/V WINDOW +/– until the cursor points to "ADD."




```
CH ERASE/ADD
 ERASE
▶ADD
 
Select the channel.
ERASE:CHANNEL +/-
ADD:  [0-9]+[ENTER]
SELECT RETURN EXIT
```

7 Press 0 – 9 and ENTER to select the channel you want to add.
The channel display appears.




```
CH ERASE/ADD
                10
 ERASE
▶ADD
 
Select the channel.
ERASE:CHANNEL +/-
ADD:  [0-9]+[ENTER]
SELECT RETURN EXIT
```

8 Press RETURN
A "+" sign appears in front of the channel number display, indicating that the channel is added; then the CH ERASE/ADD screen automatically reappears.


```
CH ERASE/ADD
              + 10
 ERASE
▶ADD
 
Select the channel.
ERASE:CHANNEL +/-
ADD:  [0-9]+[ENTER]
SELECT RETURN EXIT
```

To add another channel
Repeat steps 7 – 8.

To return to the previous menu
Press A/V WINDOW +/– until the cursor points to " ⊃ MENU."
Then press RETURN.

To return to the main menu
Repeat the above, until you reach the main menu.

To return to the normal screen
Press MENU.

Note
If you add a VHF or UHF channel, the same number cable TV channel is also added (and vice versa).

7-2.CABINET AND BACK COVER

□: BVTP4×12 7-685-661-79



REF.NO.	PART NO.	DESCRIPTION	REMARK
51	*X-4031-104-1	CABINET ASSY	52~54
52	4-040-755-01	CASTER (DIA. 30)	
53	4-378-522-01	SCREW, TAPPING, HEXAGON HEAD	
54	4-378-522-21	SCREW, TAPPING, HEXAGON HEAD	
55	4-378-522-31	SCREW, TAPPING, HEXAGON HEAD	
56	1-544-768-11	SPEAKER (13CM) (COAXIAL)	
57	4-036-136-01	COVER, MIRROR	
58	4-036-527-01	PLATE, REAR	
59	X-4030-402-1	COVER ASSY, BACK	

SECTION 8
ELECTRICAL PARTS LIST

A

NOTE:

The components identified by shading and mark ⚠ are critical for safety.
Replace only with part number specified.

Les composants identifies par une trame et une marque ⚠ sont critiques pour la securite.
Ne les remplacer que par une piece portant le numero specifie.

- Items marked " * " are not stocked since they are seldom required for routine service. Some delay should be anticipated when ordering these items.
- All variable and adjustable resistors have characteristic curve B, unless otherwise noted.

RESISTORS
- All resistors are in ohms
- F : nonflammable

When indicating parts by reference number, please include the board name.

CAPACITORS
- MF : μF, PF : μμF

COILS
- MMH : mH, UH : μH

- The components identified by ⊠ in this manual have been carefully factory-selected for each set in order to satisfy regulations regarding X-ray radiation. Should replacement be required, replace only with the value originally used.

REF.NO.	PART NO.	DESCRIPTION	REMARK
	*A-1297-079-A	A BOARD, COMPLETE	
		**********	
	4-382-854-11	SCREW (M3X10), P, SW (+)	
		<CONNECTOR>	
A1	*1-564-514-11	PLUG, CONNECTOR 11P	
A2	*1-564-512-11	PLUG, CONNECTOR 9P	
A3	*1-564-507-11	PLUG, CONNECTOR 4P	
A4	*1-564-508-11	PLUG, CONNECTOR 5P	
A5	*1-564-511-11	PLUG, CONNECTOR 8P	
A10	*1-564-511-41	PLUG, CONNECTOR 8P	
A11	*1-564-511-31	PLUG, CONNECTOR 8P	
A12	1-573-297-11	CONNECTOR, BOARD TO BOARD 18P	
A13	1-573-297-11	CONNECTOR, BOARD TO BOARD 18P	
A14	*1-564-513-31	PLUG, CONNECTOR 10P	
A15	*1-564-508-11	PLUG, CONNECTOR 5P	
A16	*1-564-508-11	PLUG, CONNECTOR 5P	
A17	*1-564-508-11	PLUG, CONNECTOR 5P	
A18	*1-691-291-11	PIN, CONNECTOR (PC BOARD) 5P	
A19	*1-691-291-11	PIN, CONNECTOR (PC BOARD) 5P	
A20	*1-691-291-11	PIN, CONNECTOR (PC BOARD) 5P	
A21	*1-508-786-00	PIN, CONNECTOR (5MM PITCH) 2P	
A22	1-573-297-11	CONNECTOR, BOARD TO BOARD 18P	
A25	*1-564-506-11	PLUG, CONNECTOR 3P	
A27	*1-573-979-11	CONNECTOR, BOARD TO BOARD 11P	
A56	*1-564-508-11	PLUG, CONNECTOR 5P	
		<CAPACITOR>	
C201	1-124-910-11	ELECT 47MF 20% 50V	
C202	1-124-903-11	ELECT 1MF 20% 50V	
C203	1-130-495-00	MYLAR 0.1MF 5% 50V	
C204	1-124-477-11	ELECT 47MF 20% 16V	
C205	1-124-557-11	ELECT 1000MF 20% 25V	
C206	1-126-101-11	ELECT 100MF 20% 16V	
C207	1-124-242-00	ELECT 33MF 20% 16V	
C210	1-102-121-00	CERAMIC 0.0022MF 10% 50V	
C212	1-126-803-11	ELECT 47MF 20% 16V	
C213	1-126-103-11	ELECT 470MF 20% 16V	
C214	1-126-101-11	ELECT 100MF 20% 16V	
C215	1-126-803-11	ELECT 47MF 20% 50V	
C216	1-126-101-11	ELECT 100MF 20% 16V	
C217	1-126-803-11	ELECT 47MF 20% 25V	
C218	1-126-103-11	ELECT 470MF 20% 16V	
C219	1-124-443-00	ELECT 100MF 20% 10V	
C220	1-126-803-11	ELECT 47MF 20% 25V	
C223	1-126-803-11	ELECT 47MF 20% 25V	
C224	1-124-261-00	ELECT 10MF 20% 50V	
C225	1-124-120-11	ELECT 220MF 20% 16V	
C226	1-124-120-11	ELECT 220MF 20% 16V	
C227	1-124-621-11	ELECT 3300MF 20% 6.3V	
C299	1-126-101-11	ELECT 100MF 20% 16V	
C502	1-126-182-11	ELECT 0.47MF 20% 50V	
C503	1-130-487-00	MYLAR 0.022MF 5% 50V	
C504	1-136-153-00	FILM 0.01MF 5% 50V	
C507	1-106-383-00	MYLAR 0.047MF 200V	
C508	1-102-973-00	CERAMIC 100PF 5% 50V	
C509	1-102-030-00	CERAMIC 330PF 10% 500V	
C510 ⚠	1-136-565-11	FILM 0.015MF 3% 1.4KV	
C512 ⚠	1-136-598-11	FILM 3MF 5% 200V	
C513	1-136-153-00	FILM 0.01MF 5% 50V	
C514	1-124-477-11	ELECT 47MF 20% 16V	
C522	1-123-024-21	ELECT 33MF 160V	
C523	1-106-383-00	MYLAR 0.047MF 200V	
C528	1-124-662-11	ELECT 220MF 20% 50V	
C534	1-124-011-00	ELECT 220MF 20% 16V	
C535	1-124-011-00	ELECT 220MF 20% 16V	
C536	1-124-662-11	ELECT 220MF 20% 50V	
C537	1-124-662-11	ELECT 220MF 20% 50V	
C539	1-124-907-11	ELECT 10MF 20% 50V	
C542	1-136-153-00	FILM 0.01MF 5% 50V	
C543	1-136-153-00	FILM 0.01MF 5% 50V	
C544	1-136-153-00	FILM 0.01MF 5% 50V	
C545	1-136-153-00	FILM 0.01MF 5% 50V	
C569	1-126-355-11	ELECT 33MF 20% 160V	
C1401	1-124-910-11	ELECT 47MF 20% 50V	
C1402	1-126-157-11	ELECT 10MF 20% 16V	
C1403	1-126-157-11	ELECT 10MF 20% 16V	
C1404	1-126-157-11	ELECT 10MF 20% 16V	
C1405	1-124-910-11	ELECT 47MF 20% 50V	
C1406	1-126-101-11	ELECT 100MF 20% 16V	
C1407	1-126-057-11	ELECT 2200MF 20% 50V	
C1408	1-136-165-00	FILM 0.1MF 5% 50V	
C1409	1-136-165-00	FILM 0.1MF 5% 50V	
C1413	1-124-234-00	ELECT 22MF 20% 16V	
C1424	1-126-057-11	ELECT 2200MF 20% 50V	
C1425	1-126-057-11	ELECT 2200MF 20% 50V	
C1426	1-126-157-11	ELECT 10MF 20% 16V	
C1429	1-126-101-11	ELECT 100MF 20% 16V	
C1430	1-126-101-11	ELECT 100MF 20% 16V	
C1431	1-124-916-11	ELECT 22MF 20% 50V	
C1435	1-124-916-11	ELECT 22MF 20% 25V	
C1440	1-126-336-11	ELECT 220MF 20% 25V	
C1601	1-130-483-00	MYLAR 0.01MF 5% 50V	
C1603	1-136-153-00	FILM 0.01MF 5% 50V	
C1607	1-124-907-11	ELECT 10MF 20% 50V	
C1608	1-136-153-00	FILM 0.01MF 5% 50V	
C1609	1-136-153-00	FILM 0.01MF 5% 50V	
C1610	1-124-916-11	ELECT 22MF 20% 50V	

A

Les composants identifies par une trame et une marque ⚠ sont critiques pour la securite. Ne les remplacer que par une piece portant le numero specifie.

The components identified by shading and mark ⚠ are critical for safety. Replace only with part number specified.

REF.NO.	PART NO.	DESCRIPTION	REMARK
		<DIODE>	
D203	8-719-911-19	DIODE 1SS119	
D204	8-719-911-19	DIODE 1SS119	
D205	8-719-110-36	DIODE RD13ES-B2	
D206	8-719-911-19	DIODE 1SS119	
D207	8-719-911-19	DIODE 1SS119	
D208	8-719-911-19	DIODE 1SS119	
D209	8-719-911-19	DIODE 1SS119	
D211	8-719-110-36	DIODE RD13ES-B2	
D213	8-719-110-78	DIODE RD33ES-B2	
D214	8-719-911-19	DIODE 1SS119	
D215	8-719-911-19	DIODE 1SS119	
D216	8-719-911-19	DIODE 1SS119	
D217	8-719-911-19	DIODE 1SS119	
D219	8-719-911-19	DIODE 1SS119	
D220	8-719-510-48	DIODE D1N20R	
D221	8-719-911-19	DIODE 1SS119	
D222	8-719-911-19	DIODE 1SS119	
D223	8-719-911-19	DIODE 1SS119	
D501	8-719-971-20	DIODE ERC38-06	
D502	8-719-971-20	DIODE ERC38-06	
D503	8-719-300-80	DIODE RU-1C	
D504	8-719-109-88	DIODE RD5.6ES-B1	
D505	8-719-900-95	DIODE V09G	
D506	8-719-900-95	DIODE V09G	
D507	8-719-970-89	DIODE DD50R	
D509	8-719-911-19	DIODE 1SS119	
D510	8-719-109-71	DIODE RD3.9ES-B1	
D511	8-719-911-19	DIODE 1SS119	
D512	8-719-911-19	DIODE 1SS119	
D513	8-719-911-19	DIODE 1SS119	
D514	8-719-911-19	DIODE 1SS119	
D515	8-719-911-19	DIODE 1SS119	
D1401	8-719-911-19	DIODE 1SS119	
D1402	8-719-911-19	DIODE 1SS119	
D1403	8-719-911-19	DIODE 1SS119	
D1404	8-719-110-88	DIODE RD39ES-B2	
D1405	8-719-110-88	DIODE RD39ES-B2	
D1406	8-719-911-19	DIODE 1SS119	
D1407	8-719-110-88	DIODE RD39ES-B2	
D1408	8-719-911-19	DIODE 1SS119	
D1409	8-719-110-88	DIODE RD39ES-B2	
D1607	8-719-911-19	DIODE 1SS119	
D1608	8-719-911-19	DIODE 1SS119	
		<IC>	
IC201	8-749-920-58	IC SI-3090CA	
IC204	8-759-171-05	IC UPC7805H	
IC205	8-759-144-82	IC UPC2405HF	
IC206	8-759-231-58	IC TA7812S	
IC207	8-749-920-58	IC SI-3090CA	
IC506	8-752-057-18	IC CXA1315P	
IC1401	8-759-246-70	IC TA8216H	
IC1601	8-752-058-71	IC CXA1656S	
		<COIL>	
L201	1-408-429-00	INDUCTOR 470UH	
L205	1-410-645-31	INDUCTOR 100UH	
L206	1-408-416-00	INDUCTOR 39UH	
L212	1-410-312-11	INDUCTOR 0.22UH	
L501 ⚠	1-460-196-11	COIL, HORIZONTAL LINEARITY	
L502	1-459-313-00	COIL WITH CORE (HWC)	
L515	1-410-645-31	INDUCTOR 100UH	
		<TRANSISTOR>	
Q201	8-729-119-78	TRANSISTOR 2SC2785-HFE	
Q202	8-729-119-78	TRANSISTOR 2SC2785-HFE	
Q203	8-729-119-76	TRANSISTOR 2SA1175-HFE	
Q501	8-729-119-80	TRANSISTOR 2SC2688-LK	
Q502	8-729-014-88	TRANSISTOR 2SC4891-CA	
Q504	8-729-119-78	TRANSISTOR 2SC2785-HFE	
Q505	8-729-201-32	TRANSISTOR 2SA1013-O	
Q506	8-729-201-32	TRANSISTOR 2SA1013-O	
Q507	8-729-304-92	TRANSISTOR 2SB649A-C	
Q508	8-729-204-16	TRANSISTOR 2SA1301-O	
Q509	8-729-119-78	TRANSISTOR 2SC2785-HFE	
Q510	8-729-119-78	TRANSISTOR 2SC2785-HFE	
Q511	8-729-119-76	TRANSISTOR 2SA1175-HFE	
Q512	8-729-119-78	TRANSISTOR 2SC2785-HFE	
Q1401	8-729-119-78	TRANSISTOR 2SC2785-HFE	
Q1402	8-729-900-63	TRANSISTOR DTA124ES	
Q1407	8-729-119-78	TRANSISTOR 2SC2785-HFE	
Q1408	8-729-119-78	TRANSISTOR 2SC2785-HFE	
Q1601	8-729-119-78	TRANSISTOR 2SC2785-HFE	
Q1602	8-729-119-76	TRANSISTOR 2SA1175-HFE	
Q1603	8-729-119-76	TRANSISTOR 2SA1175-HFE	
Q1604	8-729-119-76	TRANSISTOR 2SA1175-HFE	
Q1605	8-729-119-78	TRANSISTOR 2SC2785-HFE	
Q1606	8-729-119-78	TRANSISTOR 2SC2785-HFE	
Q1620	8-729-119-76	TRANSISTOR 2SA1175-HFE	
		<RESISTOR>	
R203	1-249-425-11	CARBON 4.7K 5% 1/4W	
R204	1-249-441-11	CARBON 100K 5% 1/4W	
R214	1-249-429-11	CARBON 10K 5% 1/4W	
R215	1-249-437-11	CARBON 47K 5% 1/4W	
R216	1-249-377-11	CARBON 0.47 5% 1/4W	F
R219	1-249-426-11	CARBON 5.6K 5% 1/4W	
R221	1-249-409-11	CARBON 220 5% 1/4W	
R222	1-249-436-11	CARBON 39K 5% 1/4W	
R223	1-249-434-11	CARBON 27K 5% 1/4W	
R224	1-249-409-11	CARBON 220 5% 1/4W	
R225	1-249-417-11	CARBON 1K 5% 1/4W	
R229	1-216-488-11	METAL OXIDE 18K 5% 3W	F
R231	1-249-409-91	CARBON 220 5% 1/4W	F
R232	1-215-906-11	METAL OXIDE 15 5% 3W	F
R233	1-249-409-11	CARBON 220 5% 1/4W	
R234	1-249-409-11	CARBON 220 5% 1/4W	
R235	1-249-409-11	CARBON 220 5% 1/4W	
R236	1-249-409-11	CARBON 220 5% 1/4W	
R237	1-249-409-11	CARBON 220 5% 1/4W	
R238	1-249-409-11	CARBON 220 5% 1/4W	
R239	1-249-409-11	CARBON 220 5% 1/4W	
R240	1-215-906-11	METAL OXIDE 15 5% 3W	F
R241	1-249-401-11	CARBON 47 5% 1/4W	
R242	1-215-906-11	METAL OXIDE 15 5% 3W	F
R243	1-217-294-00	WIREWOUND 4.7 10% 5W	F
R244	1-207-676-00	WIREWOUND 6.8 10% 5W	F
R296	1-249-417-11	CARBON 1K 5% 1/4W	
R501	1-247-895-00	CARBON 470K 5% 1/4W	
R502	1-249-377-11	CARBON 0.47 5% 1/4W	F
R503	1-249-377-11	CARBON 0.47 5% 1/4W	F
R504	1-249-417-11	CARBON 1K 5% 1/4W	

A P1

The components identified by shading and mark ⚠ are critical for safety.
Replace only with part number specified.

Les composants identifies par une trame et une marque ⚠ sont critiques pour la securite.
Ne les remplacer que par une piece portant le numero specifie.

REF.NO.	PART NO.	DESCRIPTION				REMARK
R505	1-249-423-11	CARBON	3.3K	5%	1/4W	
R506	1-215-922-11	METAL OXIDE	6.8K	5%	3W	F
R507	1-249-429-11	CARBON	10K	5%	1/4W	F
R508	1-216-373-11	METAL OXIDE	2.2	5%	2W	F
R509	1-216-478-11	METAL OXIDE	390	5%	3W	F
R511	1-249-407-11	CARBON	150	5%	1/4W	
R512	1-249-421-11	CARBON	2.2K	5%	1/4W	F
R513	1-249-417-11	CARBON	1K	5%	1/4W	
R514	1-216-441-00	METAL OXIDE	27K	5%	1W	F
R515	1-249-432-11	CARBON	18K	5%	1/4W	F
R516	1-249-417-11	CARBON	1K	5%	1/4W	
R517	1-249-427-11	CARBON	6.8K	5%	1/4W	F
R518	1-249-422-11	CARBON	2.7K	5%	1/4W	F
R519	1-249-417-11	CARBON	1K	5%	1/4W	F
R520	1-215-925-11	METAL OXIDE	22K	5%	3W	F
R521	1-215-925-11	METAL OXIDE	22K	5%	3W	F
R522	1-249-421-11	CARBON	2.2K	5%	1/4W	
R523	1-249-434-11	CARBON	27K	5%	1/4W	
R524	1-249-434-11	CARBON	27K	5%	1/4W	
R525	1-215-922-11	METAL OXIDE	6.8K	5%	3W	F
R526	1-249-417-11	CARBON	1K	5%	1/4W	
R528	1-216-447-00	METAL OXIDE	27	5%	2W	F
R529	1-216-447-00	METAL OXIDE	27	5%	2W	F
R530	1-249-431-11	CARBON	15K	5%	1/4W	
R531	1-249-431-11	CARBON	15K	5%	1/4W	
R532	1-249-385-11	CARBON	2.2	5%	1/4W	F
R533	1-249-405-11	CARBON	100	5%	1/4W	
R534	1-249-405-11	CARBON	100	5%	1/4W	
R535	1-249-405-11	CARBON	100	5%	1/4W	
R536	1-207-687-00	WIREWOUND	150	10%	5W	F
R537	1-207-687-00	WIREWOUND	150	10%	5W	F
R550	1-249-385-11	CARBON	2.2	5%	1/4W	F
R558	1-249-385-11	CARBON	2.2	5%	1/4W	F
R559	1-249-409-11	CARBON	220	5%	1/4W	
R560	1-249-409-11	CARBON	220	5%	1/4W	
R563	1-249-429-11	CARBON	10K	5%	1/4W	
R564	1-249-429-11	CARBON	10K	5%	1/4W	
R565	1-249-427-11	CARBON	6.8K	5%	1/4W	
R566	1-249-427-11	CARBON	6.8K	5%	1/4W	
R567	1-249-427-11	CARBON	6.8K	5%	1/4W	
R568	1-249-427-11	CARBON	6.8K	5%	1/4W	
R569	1-249-426-11	CARBON	5.6K	5%	1/4W	
R570	1-249-441-11	CARBON	100K	5%	1/4W	
R571	1-249-429-11	CARBON	10K	5%	1/4W	
R572	1-249-429-11	CARBON	10K	5%	1/4W	
R574	1-249-417-11	CARBON	1K	5%	1/4W	
R579	1-249-417-11	CARBON	1K	5%	1/4W	
R1401	1-215-445-00	METAL	10K	1%	1/4W	
R1402	1-215-445-00	METAL	10K	1%	1/4W	
R1403	1-215-445-00	METAL	10K	1%	1/4W	
R1404	1-215-445-00	METAL	10K	1%	1/4W	
R1405	1-249-385-11	CARBON	2.2	5%	1/4W	
R1406	1-249-385-11	CARBON	2.2	5%	1/4W	
R1409	1-249-433-11	CARBON	22K	5%	1/4W	
R1410	1-249-433-11	CARBON	22K	5%	1/4W	
R1411	1-249-437-11	CARBON	47K	5%	1/4W	
R1427	1-215-865-11	METAL OXIDE	220	5%	1W	F
R1428	1-215-865-11	METAL OXIDE	220	5%	1W	F
R1431	1-249-405-11	CARBON	100	5%	1/4W	
R1433	1-249-425-11	CARBON	4.7K	5%	1/4W	
R1434	1-249-423-11	CARBON	3.3K	5%	1/4W	
R1439	1-247-883-00	CARBON	150K	5%	1/4W	
R1440	1-249-417-11	CARBON	1K	5%	1/4W	
R1442	1-215-410-00	METAL	360	1%	1/4W	
R1443	1-215-410-00	METAL	360	1%	1/4W	
R1520	1-249-429-11	CARBON	10K	5%	1/4W	
R1601	1-249-423-11	CARBON	3.3K	5%	1/4W	
R1602	1-249-417-11	CARBON	1K	5%	1/4W	
R1603	1-249-423-11	CARBON	3.3K	5%	1/4W	
R1604	1-249-405-11	CARBON	100	5%	1/4W	
R1605	1-249-405-11	CARBON	100	5%	1/4W	
R1606	1-249-405-11	CARBON	100	5%	1/4W	
R1607	1-249-415-11	CARBON	680	5%	1/4W	
R1608	1-249-415-11	CARBON	680	5%	1/4W	
R1609	1-249-415-11	CARBON	680	5%	1/4W	
R1610	1-249-405-11	CARBON	100	5%	1/4W	
R1611	1-249-405-11	CARBON	100	5%	1/4W	
R1612	1-249-405-11	CARBON	100	5%	1/4W	
R1613	1-249-423-11	CARBON	3.3K	5%	1/4W	
R1614	1-249-411-11	CARBON	330	5%	1/4W	
R1622	1-249-423-11	CARBON	3.3K	5%	1/4W	
R1624	1-249-424-11	CARBON	3.9K	5%	1/4W	
R1627	1-249-429-11	CARBON	10K	5%	1/4W	
R1630	1-249-434-11	CARBON	27K	5%	1/4W	
R1631	1-249-433-11	CARBON	22K	5%	1/4W	
R1656	1-249-397-11	CARBON	22	5%	1/4W	
R1657	1-249-397-11	CARBON	22	5%	1/4W	
R1658	1-249-397-11	CARBON	22	5%	1/4W	

<TRANSFORMER>

T501	⚠ 1-439-545-11	TRANSFORMER, FERRITE	
T502	⚠ 1-437-078-11	TRANSFORMER, HORIZONTAL DRIVE	

<TUNER>

TU101	⚠ 1-693-102-21	TUNER (BTF-XA401)	

****

*A-1195-066-A P1 BOARD, COMPLETE
****

<CAPACITOR>

C3001	1-124-589-11	ELECT	47MF	20%	16V
C3002	1-164-346-11	CERAMIC CHIP	1MF		16V
C3003	1-164-232-11	CERAMIC CHIP	0.01MF	10%	50V
C3004	1-163-119-00	CERAMIC CHIP	120PF	5%	50V
C3005	1-163-235-11	CERAMIC CHIP	22PF	5%	50V
C3006	1-164-232-11	CERAMIC CHIP	0.01MF	10%	50V
C3007	1-164-005-11	CERAMIC CHIP	0.47MF		25V
C3008	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C3009	1-124-925-11	ELECT	2.2MF	20%	50V
C3010	1-163-145-00	CERAMIC CHIP	0.0015MF	5%	50V
C3011	1-163-018-00	CERAMIC CHIP	0.0056MF	10%	50V
C3012	1-164-336-11	CERAMIC CHIP	0.33MF		25V
C3013	1-164-222-11	CERAMIC CHIP	0.22MF		25V
C3014	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C3015	1-164-232-11	CERAMIC CHIP	0.01MF	10%	50V
C3016	1-163-107-00	CERAMIC CHIP	39PF	5%	50V
C3017	1-130-495-00	MYLAR	0.1MF	5%	50V
C3018	1-163-115-00	CERAMIC CHIP	82PF	5%	50V
C3019	1-164-232-11	CERAMIC CHIP	0.01MF	10%	50V
C3020	1-163-105-00	CERAMIC CHIP	33PF	5%	50V
C3021	1-163-115-00	CERAMIC CHIP	82PF	5%	50V
C3022	1-126-301-11	ELECT	1MF	20%	50V
C3023	1-124-589-11	ELECT	47MF	20%	16V

P1

REF.NO.	PART NO.	DESCRIPTION			REMARK
C3024	1-163-018-00	CERAMIC CHIP	0.0056MF	10% 50V	
C3025	1-164-343-11	CERAMIC CHIP	0.056MF	10% 25V	
C3026	1-126-163-11	ELECT	4.7MF	20% 50V	
C3027	1-163-275-11	CERAMIC CHIP	0.001MF	5% 50V	
C3028	1-124-589-11	ELECT	47MF	20% 16V	
C3029	1-163-133-00	CERAMIC CHIP	470PF	5% 50V	
C3030	1-163-037-11	CERAMIC CHIP	0.022MF	10% 25V	
C3031	1-126-177-11	ELECT	100MF	20% 6.3V	
C3032	1-164-004-11	CERAMIC CHIP	0.1MF	10% 25V	
C3033	1-164-004-11	CERAMIC CHIP	0.1MF	10% 25V	
C3034	1-164-336-11	CERAMIC CHIP	0.33MF	25V	
C3035	1-163-117-00	CERAMIC CHIP	100PF	5% 50V	
C3036	1-164-004-11	CERAMIC CHIP	0.1MF	10% 25V	
C3037	1-124-589-11	ELECT	47MF	20% 16V	
C3038	1-136-287-11	FILM	0.0047MF	5% 50V	
C3039	1-164-004-11	CERAMIC CHIP	0.1MF	10% 25V	
C3040	1-164-232-11	CERAMIC CHIP	0.01MF	10% 50V	
C3042	1-164-346-11	CERAMIC CHIP	1MF	16V	
C3043	1-124-465-00	ELECT	0.47MF	20% 50V	
C3044	1-126-301-11	ELECT	1MF	20% 50V	
C3045	1-124-589-11	ELECT	47MF	20% 16V	
C3046	1-126-301-11	ELECT	1MF	20% 50V	
C3047	1-126-301-11	ELECT	1MF	20% 50V	
C3048	1-164-161-11	CERAMIC CHIP	0.0022MF	10% 50V	
C3051	1-164-161-11	CERAMIC CHIP	0.0022MF	10% 50V	
C3052	1-126-177-11	ELECT	100MF	20% 6.3V	
C3053	1-164-004-11	CERAMIC CHIP	0.1MF	10% 25V	
C3054	1-126-177-11	ELECT	100MF	20% 6.3V	
C3055	1-163-133-00	CERAMIC CHIP	470PF	5% 50V	
C3057	1-124-589-11	ELECT	47MF	20% 16V	
C3058	1-163-009-11	CERAMIC CHIP	0.001MF	10% 50V	
C3059	1-164-222-11	CERAMIC CHIP	0.22MF	25V	
C3060	1-124-589-11	ELECT	47MF	20% 16V	
C3064	1-163-123-00	CERAMIC CHIP	180PF	5% 50V	
C3065	1-124-589-11	ELECT	47MF	20% 16V	
C3066	1-164-004-11	CERAMIC CHIP	0.1MF	10% 25V	
C3067	1-124-589-11	ELECT	47MF	20% 16V	
C3069	1-164-232-11	CERAMIC CHIP	0.01MF	10% 50V	
C3070	1-126-177-11	ELECT	100MF	20% 6.3V	
C3071	1-124-589-11	ELECT	47MF	20% 16V	
C3072	1-124-589-11	ELECT	47MF	20% 16V	
C3073	1-124-589-11	ELECT	47MF	20% 16V	
C3074	1-163-121-00	CERAMIC CHIP	150PF	5% 50V	
C3076	1-164-004-11	CERAMIC CHIP	0.1MF	10% 25V	
C3077	1-164-005-11	CERAMIC CHIP	0.47MF	25V	
C3081	1-163-095-00	CERAMIC CHIP	12PF	5% 50V	
C3100	1-164-004-11	CERAMIC CHIP	0.1MF	10% 25V	
C3101	1-162-926-11	CERAMIC CHIP	82PF	5% 50V	

<CONNECTOR>

CN151	1-573-965-21	PIN, CONNECTOR (PC BOARD) 50P	

<DIODE>

D3003	8-719-158-15	DIODE RD5.6S-B	
D3004	8-719-404-46	DIODE MA110	
D3009	8-719-404-46	DIODE MA110	

<IC>

IC3001	8-759-046-25	IC TDA3769	
IC3002	8-759-009-46	IC MC14528BF	
IC3003	8-759-513-48	IC TDA2595/V9	
IC3004	8-759-088-90	IC SDA9187X	
IC3005	8-759-088-91	IC SDA9188X	
IC3006	8-759-112-06	IC UPC78N05H	
IC3007	8-759-046-27	IC SDA9086-3	
IC3008	8-759-112-06	IC UPC78N05H	

<COIL>

L3001	1-410-476-11	INDUCTOR	33UH
L3002	1-408-424-00	INDUCTOR	180UH
L3003	1-408-424-00	INDUCTOR	180UH
L3004	1-410-470-11	INDUCTOR	10UH
L3005	1-410-472-41	INDUCTOR	15UH
L3006	1-412-788-41	INDUCTOR	10UH
L3007	1-410-472-41	INDUCTOR	15UH
L3008	1-410-472-41	INDUCTOR	15UH
L3009	1-410-472-41	INDUCTOR	15UH
L3010	1-410-466-41	INDUCTOR	4.7UH
L3011	1-410-470-11	INDUCTOR	10UH
L3012	1-410-676-31	INDUCTOR	150UH
L3013	1-412-911-11	INDUCTOR, FERRITE BEAD	
L3014	1-412-911-11	INDUCTOR, FERRITE BEAD	
L3015	1-412-911-11	INDUCTOR, FERRITE BEAD	
L3100	1-412-799-41	INDUCTOR	82UH

<TRANSISTOR>

Q3003	8-729-216-22	TRANSISTOR	2SA1162-G
Q3004	8-729-422-27	TRANSISTOR	2SD601A-Q
Q3006	8-729-422-27	TRANSISTOR	2SD601A-Q
Q3007	8-729-216-22	TRANSISTOR	2SA1162-G
Q3008	8-729-422-27	TRANSISTOR	2SD601A-Q
Q3009	8-729-216-22	TRANSISTOR	2SA1162-G
Q3010	8-729-422-27	TRANSISTOR	2SD601A-Q
Q3011	8-729-216-22	TRANSISTOR	2SA1162-G
Q3012	8-729-422-27	TRANSISTOR	2SD601A-Q
Q3013	8-729-422-27	TRANSISTOR	2SD601A-Q
Q3014	8-729-422-27	TRANSISTOR	2SD601A-Q
Q3100	8-729-216-22	TRANSISTOR	2SA1162-G

<RESISTOR>

JR3	1-216-295-00	METAL GLAZE	0	5%	1/10W
R3001	1-216-085-00	METAL GLAZE	33K	5%	1/10W
R3002	1-216-089-00	METAL GLAZE	47K	5%	1/10W
R3003	1-216-067-00	METAL GLAZE	5.6K	5%	1/10W
R3004	1-216-091-00	METAL GLAZE	56K	5%	1/10W
R3005	1-216-689-11	METAL GLAZE	39K	5%	1/10W
R3006	1-216-097-00	METAL GLAZE	100K	5%	1/10W
R3007	1-216-079-00	METAL GLAZE	18K	5%	1/10W
R3008	1-216-073-00	METAL GLAZE	10K	5%	1/10W
R3009	1-216-041-00	METAL GLAZE	470	5%	1/10W
R3010	1-216-049-00	METAL GLAZE	1K	5%	1/10W
R3011	1-216-073-00	METAL GLAZE	10K	5%	1/10W
R3012	1-216-053-00	METAL GLAZE	1.5K	5%	1/10W
R3013	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W
R3014	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W
R3015	1-216-049-00	METAL GLAZE	1K	5%	1/10W
R3017	1-216-083-00	METAL GLAZE	27K	5%	1/10W
R3018	1-216-097-00	METAL GLAZE	100K	5%	1/10W
R3019	1-216-077-00	METAL GLAZE	15K	5%	1/10W
R3020	1-216-099-00	METAL GLAZE	120K	5%	1/10W
R3021	1-216-075-00	METAL GLAZE	12K	5%	1/10W

REF.NO.	PART NO.	DESCRIPTION				REMARK
R3023	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R3025	1-216-015-00	METAL GLAZE	39	5%	1/10W	
R3026	1-216-041-00	METAL GLAZE	470	5%	1/10W	
R3027	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R3028	1-216-027-00	METAL GLAZE	120	5%	1/10W	
R3030	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R3031	1-216-047-00	METAL GLAZE	820	5%	1/10W	
R3032	1-216-041-00	METAL GLAZE	470	5%	1/10W	
R3033	1-216-295-00	METAL GLAZE	0	5%	1/10W	
R3034	1-216-041-00	METAL GLAZE	470	5%	1/10W	
R3035	1-216-045-00	METAL GLAZE	680	5%	1/10W	
R3036	1-216-045-00	METAL GLAZE	680	5%	1/10W	
R3037	1-216-083-00	METAL GLAZE	27K	5%	1/10W	
R3038	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R3039	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R3040	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R3041	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R3042	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	
R3043	1-216-099-00	METAL GLAZE	120K	5%	1/10W	
R3044	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R3045	1-216-295-00	METAL GLAZE	0	5%	1/10W	
R3050	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R3052	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R3053	1-216-037-00	METAL GLAZE	330	5%	1/10W	
R3055	1-216-063-00	METAL GLAZE	3.9K	5%	1/10W	
R3056	1-216-059-00	METAL GLAZE	2.7K	5%	1/10W	
R3057	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R3058	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R3059	1-216-079-00	METAL GLAZE	18K	5%	1/10W	
R3060	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R3061	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R3062	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R3063	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R3064	1-216-295-00	METAL GLAZE	0	5%	1/10W	
R3065	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R3066	1-216-053-00	METAL GLAZE	1.5K	5%	1/10W	
R3067	1-216-295-00	METAL GLAZE	0	5%	1/10W	
R3069	1-216-689-11	METAL GLAZE	39K	5%	1/10W	
R3071	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R3073	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R3074	1-216-295-00	METAL GLAZE	0	5%	1/10W	
R3075	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R3076	1-216-043-00	METAL GLAZE	560	5%	1/10W	
R3077	1-216-037-00	METAL GLAZE	330	5%	1/10W	
R3078	1-216-044-00	METAL GLAZE	620	5%	1/10W	
R3079	1-216-040-00	METAL GLAZE	430	5%	1/10W	
R3082	1-216-029-00	METAL GLAZE	150	5%	1/10W	
R3084	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R3085	1-216-119-00	METAL GLAZE	820K	5%	1/10W	
R3086	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R3087	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R3088	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R3089	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R3090	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R3091	1-216-053-00	METAL GLAZE	1.5K	5%	1/10W	
R3092	1-216-053-00	METAL GLAZE	1.5K	5%	1/10W	
R3098	1-216-296-00	METAL GLAZE	0	5%	1/8W	
R3099	1-216-296-00	METAL GLAZE	0	5%	1/8W	
R3100	1-216-296-00	METAL GLAZE	0	5%	1/8W	
R3101	1-216-051-00	METAL GLAZE	1.2K	5%	1/10W	
R3102	1-216-047-00	METAL GLAZE	820	5%	1/10W	
R3103	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	
R3104	1-216-049-00	METAL GLAZE	1K	5%	1/10W	

REF.NO.	PART NO.	DESCRIPTION				REMARK
		<VARIABLE RESISTOR>				
RV3001	1-241-630-11	RES, ADJ, CARBON 10K				
RV3002	1-238-019-11	RES, ADJ, CARBON 47K				
RV3003	1-241-630-11	RES, ADJ, CARBON 10K				
		<CRYSTAL>				
X3001	1-567-505-11	OSCILLATOR, CRYSTAL				
		**********				
	*A-1306-436-A	M BOARD, COMPLETE				
		**********				
		<CAPACITOR>				
C001	1-124-261-00	ELECT	10MF	20%	50V	
C002	1-163-125-00	CERAMIC CHIP	220PF	5%	50V	
C003	1-136-161-00	FILM	0.047MF	5%	50V	
C004	1-126-301-11	ELECT	1MF	20%	50V	
C005	1-163-125-00	CERAMIC CHIP	220PF	5%	50V	
C014	1-124-910-11	ELECT	47MF	20%	50V	
C017	1-124-589-11	ELECT	47MF	20%	16V	
C018	1-163-141-00	CERAMIC CHIP	0.001MF	5%	50V	
C019	1-164-695-11	CERAMIC CHIP	0.0022MF	5%	50V	
C020	1-163-241-11	CERAMIC CHIP	39PF	5%	50V	
C021	1-163-239-11	CERAMIC CHIP	33PF	5%	50V	
C029	1-163-115-00	CERAMIC CHIP	82PF	5%	50V	
C030	1-163-115-00	CERAMIC CHIP	82PF	5%	50V	
C034	1-163-125-00	CERAMIC CHIP	220PF	5%	50V	
C035	1-163-125-00	CERAMIC CHIP	220PF	5%	50V	
C036	1-163-125-00	CERAMIC CHIP	220PF	5%	50V	
C041	1-163-117-00	CERAMIC CHIP	100PF	5%	50V	
C042	1-163-117-00	CERAMIC CHIP	100PF	5%	50V	
C045	1-163-125-00	CERAMIC CHIP	220PF	5%	50V	
C047	1-124-261-00	ELECT	10MF	20%	50V	
C048	1-124-261-00	ELECT	10MF	20%	50V	
C049	1-124-261-00	ELECT	10MF	20%	50V	
C055	1-163-809-11	CERAMIC CHIP	0.047MF	10%	25V	
C064	1-163-121-00	CERAMIC CHIP	150PF	5%	50V	
C065	1-124-257-00	ELECT	2.2MF	20%	50V	
		<DIODE>				
D001	8-719-404-46	DIODE MA110				
D002	8-719-404-46	DIODE MA110				
D009	8-719-404-46	DIODE MA110				
D010	8-713-300-57	DIODE 1T33				
D011	8-719-404-46	DIODE MA110				
D012	8-719-404-46	DIODE MA110				
D014	8-719-404-46	DIODE MA110				
D015	8-719-404-46	DIODE MA110				
		<IC>				
IC001	8-759-169-06	IC TMC73C247-10				
IC002	8-759-403-44	IC MN1280-S				
		<COIL>				
L001	1-408-409-00	INDUCTOR	10UH			
L002	1-410-476-11	INDUCTOR	33UH			

M E2

REF.NO.	PART NO.	DESCRIPTION	REMARK
		<CONNECTOR>	
M001	1-573-965-21	PIN, CONNECTOR (PC BOARD) 50P	
M39	*1-564-521-11	PLUG, CONNECTOR 6P	
M45	*1-564-523-31	PLUG, CONNECTOR 8P	
		<TRANSISTOR>	
Q001	8-729-216-22	TRANSISTOR 2SA1162-G	
Q009	8-729-422-27	TRANSISTOR 2SD601A-Q	
Q010	8-729-422-27	TRANSISTOR 2SD601A-Q	
Q011	8-729-422-27	TRANSISTOR 2SD601A-Q	
Q012	8-729-422-27	TRANSISTOR 2SD601A-Q	
Q013	8-729-216-22	TRANSISTOR 2SA1162-G	
Q014	8-729-422-27	TRANSISTOR 2SD601A-Q	
		<RESISTOR>	
R001	1-216-045-00	METAL GLAZE 680 5% 1/10W	
R002	1-216-097-00	METAL GLAZE 100K 5% 1/10W	
R003	1-216-121-00	METAL GLAZE 1M 5% 1/10W	
R004	1-216-073-00	METAL GLAZE 10K 5% 1/10W	
R005	1-216-073-00	METAL GLAZE 10K 5% 1/10W	
R006	1-216-065-00	METAL GLAZE 4.7K 5% 1/10W	
R007	1-216-027-00	METAL GLAZE 120 5% 1/10W	
R008	1-216-041-00	METAL GLAZE 470 5% 1/10W	
R009	1-216-027-00	METAL GLAZE 120 5% 1/10W	
R011	1-216-033-00	METAL GLAZE 220 5% 1/10W	
R012	1-216-033-00	METAL GLAZE 220 5% 1/10W	
R013	1-216-067-00	METAL GLAZE 5.6K 5% 1/10W	
R014	1-216-057-00	METAL GLAZE 2.2K 5% 1/10W	
R015	1-216-089-00	METAL GLAZE 47K 5% 1/10W	
R016	1-216-067-00	METAL GLAZE 5.6K 5% 1/10W	
R017	1-216-067-00	METAL GLAZE 5.6K 5% 1/10W	
R018	1-216-065-00	METAL GLAZE 4.7K 5% 1/10W	
R019	1-216-073-00	METAL GLAZE 10K 5% 1/10W	
R033	1-216-073-00	METAL GLAZE 10K 5% 1/10W	
R034	1-216-033-00	METAL GLAZE 220 5% 1/10W	
R035	1-216-033-00	METAL GLAZE 220 5% 1/10W	
R036	1-216-033-00	METAL GLAZE 220 5% 1/10W	
R037	1-216-073-00	METAL GLAZE 10K 5% 1/10W	
R038	1-216-033-00	METAL GLAZE 220 5% 1/10W	
R039	1-216-073-00	METAL GLAZE 10K 5% 1/10W	
R040	1-216-089-00	METAL GLAZE 47K 5% 1/10W	
R041	1-216-057-00	METAL GLAZE 2.2K 5% 1/10W	
R042	1-216-065-00	METAL GLAZE 4.7K 5% 1/10W	
R043	1-216-033-00	METAL GLAZE 220 5% 1/10W	
R044	1-216-033-00	METAL GLAZE 220 5% 1/10W	
R045	1-216-025-00	METAL GLAZE 100 5% 1/10W	
R046	1-216-065-00	METAL GLAZE 4.7K 5% 1/10W	
R047	1-216-065-00	METAL GLAZE 4.7K 5% 1/10W	
R048	1-216-033-00	METAL GLAZE 220 5% 1/10W	
R049	1-216-065-00	METAL GLAZE 4.7K 5% 1/10W	
R050	1-216-295-00	METAL GLAZE 0 5% 1/10W	
R051	1-216-033-00	METAL GLAZE 220 5% 1/10W	
R052	1-216-065-00	METAL GLAZE 4.7K 5% 1/10W	
R053	1-216-065-00	METAL GLAZE 4.7K 5% 1/10W	
R054	1-216-073-00	METAL GLAZE 10K 5% 1/10W	
R055	1-216-073-00	METAL GLAZE 10K 5% 1/10W	
R056	1-216-065-00	METAL GLAZE 4.7K 5% 1/10W	
R057	1-216-065-00	METAL GLAZE 4.7K 5% 1/10W	
R058	1-216-065-00	METAL GLAZE 4.7K 5% 1/10W	
R059	1-216-073-00	METAL GLAZE 10K 5% 1/10W	
R060	1-216-065-00	METAL GLAZE 4.7K 5% 1/10W	
R063	1-216-033-00	METAL GLAZE 220 5% 1/10W	
R064	1-216-053-00	METAL GLAZE 1.5K 5% 1/10W	
R065	1-216-033-00	METAL GLAZE 220 5% 1/10W	
R066	1-216-033-00	METAL GLAZE 220 5% 1/10W	
R067	1-216-033-00	METAL GLAZE 220 5% 1/10W	
R068	1-216-033-00	METAL GLAZE 220 5% 1/10W	
R069	1-216-049-00	METAL GLAZE 1K 5% 1/10W	
R070	1-216-033-00	METAL GLAZE 220 5% 1/10W	
R071	1-216-033-00	METAL GLAZE 220 5% 1/10W	
R072	1-216-033-00	METAL GLAZE 220 5% 1/10W	
R073	1-216-057-00	METAL GLAZE 2.2K 5% 1/10W	
R074	1-216-033-00	METAL GLAZE 220 5% 1/10W	
R075	1-216-033-00	METAL GLAZE 220 5% 1/10W	
R076	1-216-089-00	METAL GLAZE 47K 5% 1/10W	
R077	1-216-057-00	METAL GLAZE 2.2K 5% 1/10W	
R078	1-216-033-00	METAL GLAZE 220 5% 1/10W	
R079	1-216-025-00	METAL GLAZE 100 5% 1/10W	
R080	1-216-061-00	METAL GLAZE 3.3K 5% 1/10W	
R081	1-216-033-00	METAL GLAZE 220 5% 1/10W	
R082	1-216-033-00	METAL GLAZE 220 5% 1/10W	
R083	1-216-033-00	METAL GLAZE 220 5% 1/10W	
R084	1-216-097-00	METAL GLAZE 100K 5% 1/10W	
R085	1-216-033-00	METAL GLAZE 220 5% 1/10W	
R086	1-216-033-00	METAL GLAZE 220 5% 1/10W	
R087	1-216-033-00	METAL GLAZE 220 5% 1/10W	
R088	1-216-033-00	METAL GLAZE 220 5% 1/10W	
R089	1-216-089-00	METAL GLAZE 47K 5% 1/10W	
R090	1-216-033-00	METAL GLAZE 220 5% 1/10W	
R091	1-216-065-00	METAL GLAZE 4.7K 5% 1/10W	
R092	1-216-077-00	METAL GLAZE 15K 5% 1/10W	
R093	1-216-065-00	METAL GLAZE 4.7K 5% 1/10W	
R094	1-216-033-00	METAL GLAZE 220 5% 1/10W	
R095	1-216-073-00	METAL GLAZE 10K 5% 1/10W	
R096	1-216-065-00	METAL GLAZE 4.7K 5% 1/10W	
R097	1-216-065-00	METAL GLAZE 4.7K 5% 1/10W	
R098	1-216-065-00	METAL GLAZE 4.7K 5% 1/10W	
R099	1-216-089-00	METAL GLAZE 47K 5% 1/10W	
R100	1-216-025-00	METAL GLAZE 100 5% 1/10W	
R101	1-216-025-00	METAL GLAZE 100 5% 1/10W	
R102	1-216-089-00	METAL GLAZE 47K 5% 1/10W	
R103	1-216-033-00	METAL GLAZE 220 5% 1/10W	
R104	1-216-033-00	METAL GLAZE 220 5% 1/10W	
		<CRYSTAL>	
X001	1-579-743-11	VIBRATOR, CRYSTAL	
		**********	
	*A-1346-137-A	E2 BOARD, COMPLETE	
		**********	
		<CAPACITOR>	
C2302	1-163-009-11	CERAMIC CHIP 0.001MF 10% 50V	
C2303	1-164-232-11	CERAMIC CHIP 0.01MF 10% 50V	
C2310	1-163-105-00	CERAMIC CHIP 33PF 5% 50V	
C2314	1-164-232-11	CERAMIC CHIP 0.01MF 10% 50V	
C2315	1-126-157-11	ELECT 10MF 20% 16V	
C2316	1-126-157-11	ELECT 10MF 20% 16V	
C2317	1-126-157-11	ELECT 10MF 20% 16V	
C2318	1-164-232-11	CERAMIC CHIP 0.01MF 10% 50V	
C2320	1-124-589-11	ELECT 47MF 20% 16V	
C2321	1-163-017-00	CERAMIC CHIP 0.0047MF 10% 50V	

REF.NO.	PART NO.	DESCRIPTION			REMARK
C2322	1-124-234-00	ELECT	22MF	20% 16V	
C2323	1-124-234-00	ELECT	22MF	20% 16V	
C2324	1-124-234-00	ELECT	22MF	20% 16V	
C2325	1-164-232-11	CERAMIC CHIP	0.01MF	10% 50V	
C2326	1-124-589-11	ELECT	47MF	20% 16V	
C2327	1-164-505-11	CERAMIC CHIP	2.2MF	16V	
C2328	1-164-232-11	CERAMIC CHIP	0.01MF	10% 50V	
C2329	1-164-232-11	CERAMIC CHIP	0.01MF	10% 50V	
C2331	1-164-232-11	CERAMIC CHIP	0.01MF	10% 50V	
C2332	1-124-234-00	ELECT	22MF	20% 16V	
C2333	1-124-234-00	ELECT	22MF	20% 16V	
C2334	1-164-232-11	CERAMIC CHIP	0.01MF	10% 50V	
C2335	1-164-232-11	CERAMIC CHIP	0.01MF	10% 50V	
C2336	1-126-163-11	ELECT	4.7MF	20% 16V	
C2337	1-164-232-11	CERAMIC CHIP	0.01MF	10% 50V	
C2338	1-163-038-00	CERAMIC CHIP	0.1MF	25V	
C2340	1-216-133-00	METAL GLAZE	3.3M 5%	1/10W	
C2341	1-135-217-21	TANTAL. CHIP	15MF	20% 6.3V	
C2345	1-164-505-11	CERAMIC CHIP	2.2MF	16V	
C2346	1-164-232-11	CERAMIC CHIP	0.01MF	10% 50V	
C2347	1-163-367-11	CERAMIC CHIP	39PF	5% 50V	
C2349	1-164-505-11	CERAMIC CHIP	2.2MF	16V	
C2350	1-164-232-11	CERAMIC CHIP	0.01MF	10% 50V	
C2351	1-164-505-11	CERAMIC CHIP	2.2MF	16V	
C2352	1-164-505-11	CERAMIC CHIP	2.2MF	16V	
C2353	1-164-232-11	CERAMIC CHIP	0.01MF	10% 50V	
C2354	1-164-232-11	CERAMIC CHIP	0.01MF	10% 50V	
C2357	1-126-301-11	ELECT	1MF	20% 50V	
C2360	1-163-109-00	CERAMIC CHIP	47PF	5% 50V	

<DIODE>

D2306	8-719-404-46	DIODE MA110
D2307	8-719-946-98	DIODE FMN1
D2308	8-719-946-98	DIODE FMN1
D2309	8-719-404-46	DIODE MA110
D2312	8-719-404-46	DIODE MA110
D2313	8-719-404-46	DIODE MA110
D2314	8-713-300-57	DIODE 1T33
D2317	8-719-404-46	DIODE MA110

<CONNECTOR>

E2-002	1-573-965-21	PIN, CONNECTOR (PC BOARD) 50P
E2-25	*1-564-521-31	PLUG, CONNECTOR 6P
E2-26	*1-564-522-11	PLUG, CONNECTOR 7P
E2-46	*1-564-518-11	PLUG, CONNECTOR 3P

<IC>

IC2301	8-759-066-52	IC PCA8510T/012-T
IC2303	8-759-925-75	IC SN74HC05ANS
IC2304	8-752-037-15	IC CXA1387S
IC2306	8-759-011-65	IC MC74HC4053F
IC2307	8-752-058-68	IC CXA1315M

<COIL>

L2304	1-408-414-00	INDUCTOR	27UH

<TRANSISTOR>

Q2301	8-729-903-10	TRANSISTOR FMW1
Q2303	8-729-403-27	TRANSISTOR XN4401
Q2304	8-729-925-79	TRANSISTOR IMX3
Q2305	8-729-903-10	TRANSISTOR FMW1
Q2306	8-729-403-27	TRANSISTOR XN4401
Q2307	8-729-403-27	TRANSISTOR XN4401
Q2308	8-729-403-27	TRANSISTOR XN4401
Q2309	8-729-903-10	TRANSISTOR FMW1
Q2310	8-729-403-27	TRANSISTOR XN4401
Q2311	8-729-903-10	TRANSISTOR FMW1
Q2312	8-729-403-27	TRANSISTOR XN4401
Q2313	8-729-903-10	TRANSISTOR FMW1
Q2314	8-729-403-27	TRANSISTOR XN4401
Q2315	8-729-903-10	TRANSISTOR FMW1
Q2317	8-729-216-22	TRANSISTOR 2SA1162-G
Q2318	8-729-216-22	TRANSISTOR 2SA1162-G
Q2319	8-729-216-22	TRANSISTOR 2SA1162-G
Q2320	8-729-422-27	TRANSISTOR 2SD601A-Q
Q2321	8-729-422-27	TRANSISTOR 2SD601A-Q
Q2322	8-729-422-27	TRANSISTOR 2SD601A-Q
Q2324	8-729-216-22	TRANSISTOR 2SA1162-G
Q2326	8-729-422-27	TRANSISTOR 2SD601A-Q
Q2327	8-729-422-27	TRANSISTOR 2SD601A-Q
Q2328	8-729-925-79	TRANSISTOR IMX3
Q2329	8-729-925-79	TRANSISTOR IMX3
Q2330	8-729-903-10	TRANSISTOR FMW1
Q2336	8-729-925-79	TRANSISTOR IMX3
Q2337	8-729-925-79	TRANSISTOR IMX3
Q2339	8-729-422-27	TRANSISTOR 2SD601A-Q
Q2340	8-729-422-27	TRANSISTOR 2SD601A-Q
Q2341	8-729-422-27	TRANSISTOR 2SD601A-Q

<RESISTOR>

R2302	1-216-049-00	METAL GLAZE	1K	5%	1/10W
R2303	1-216-049-00	METAL GLAZE	1K	5%	1/10W
R2304	1-216-049-00	METAL GLAZE	1K	5%	1/10W
R2305	1-216-033-00	METAL GLAZE	220	5%	1/10W
R2306	1-216-045-00	METAL GLAZE	680	5%	1/10W
R2307	1-216-045-00	METAL GLAZE	680	5%	1/10W
R2308	1-216-045-00	METAL GLAZE	680	5%	1/10W
R2309	1-216-041-00	METAL GLAZE	470	5%	1/10W
R2310	1-216-055-00	METAL GLAZE	1.8K	5%	1/10W
R2311	1-216-025-00	METAL GLAZE	100	5%	1/10W
R2312	1-216-043-00	METAL GLAZE	560	5%	1/10W
R2313	1-216-055-00	METAL GLAZE	1.8K	5%	1/10W
R2314	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W
R2315	1-216-081-00	METAL GLAZE	22K	5%	1/10W
R2317	1-216-041-00	METAL GLAZE	470	5%	1/10W
R2318	1-216-055-00	METAL GLAZE	1.8K	5%	1/10W
R2319	1-216-079-00	METAL GLAZE	18K	5%	1/10W
R2320	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W
R2321	1-216-063-00	METAL GLAZE	3.9K	5%	1/10W
R2322	1-216-049-00	METAL GLAZE	1K	5%	1/10W
R2323	1-216-067-00	METAL GLAZE	5.6K	5%	1/10W
R2324	1-216-049-00	METAL GLAZE	1K	5%	1/10W
R2325	1-216-049-00	METAL GLAZE	1K	5%	1/10W
R2326	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W
R2327	1-216-063-00	METAL GLAZE	3.9K	5%	1/10W
R2328	1-216-025-00	METAL GLAZE	100	5%	1/10W
R2329	1-216-025-00	METAL GLAZE	100	5%	1/10W
R2330	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W
R2331	1-216-063-00	METAL GLAZE	3.9K	5%	1/10W
R2332	1-216-025-00	METAL GLAZE	100	5%	1/10W
R2333	1-216-067-00	METAL GLAZE	5.6K	5%	1/10W
R2334	1-216-295-00	METAL GLAZE	0	5%	1/10W

Watching TV Programs



Make sure that the TV/CABLE BOX selector on the Remote Commander is set to TV, in order to control the projection TV with the Remote Commander.

1 Press POWER to turn on the projection TV.
TIMER/STAND BY indicator blinks until the picture appears.



2 Set the cable connection on or off (pp. 26 – 27) to select the type of channel you want to watch, VHF/UHF or cable TV.

To watch VHF or UHF channels



To watch cable TV channels

3 Select a channel in one of the following two ways:
To scan the preset channels in numerical sequence, press CH +/–.



To select a channel directly, press 0 – 9 and then ENTER.
For example, to select channel 10, press 1, 0 and ENTER.



4 Press VOL +/– to adjust the volume.



Press + to increase the volume.
Press – to decrease the volume.

If VIDEO 1, VIDEO 2 or VIDEO 3 appears on the screen
Press TV/VIDEO until a TV channel number appears.

To select channels more easily
Set FAVORITE CHANNEL (pp. 64 – 65).

To turn off the projection TV
Press POWER.

E2

REF.NO.	PART NO.	DESCRIPTION				REMARK
R2335	1-216-295-00	METAL GLAZE	0	5%	1/10W	
R2336	1-216-295-00	METAL GLAZE	0	5%	1/10W	
R2337	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R2338	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R2340	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R2341	1-216-041-00	METAL GLAZE	470	5%	1/10W	
R2342	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R2343	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R2344	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R2345	1-216-077-00	METAL GLAZE	15K	5%	1/10W	
R2346	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R2347	1-216-083-00	METAL GLAZE	27K	5%	1/10W	
R2348	1-216-655-11	METAL CHIP	1.5K	0.50%	1/10W	
R2349	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R2350	1-216-097-00	METAL GLAZE	100K	5%	1/10W	
R2351	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R2352	1-216-097-00	METAL GLAZE	100K	5%	1/10W	
R2353	1-216-097-00	METAL GLAZE	100K	5%	1/10W	
R2354	1-216-210-00	METAL GLAZE	3.3K	5%	1/8W	
R2355	1-216-178-00	METAL GLAZE	150	5%	1/8W	
R2356	1-216-677-11	METAL CHIP	12K	0.50%	1/10W	
R2357	1-216-670-11	METAL CHIP	6.2K	0.50%	1/10W	
R2359	1-216-053-00	METAL GLAZE	1.5K	5%	1/10W	
R2360	1-216-053-00	METAL GLAZE	1.5K	5%	1/10W	
R2361	1-216-053-00	METAL GLAZE	1.5K	5%	1/10W	
R2362	1-216-053-00	METAL GLAZE	1.5K	5%	1/10W	
R2363	1-216-041-00	METAL GLAZE	470	5%	1/10W	
R2364	1-216-053-00	METAL GLAZE	1.5K	5%	1/10W	
R2365	1-216-053-00	METAL GLAZE	1.5K	5%	1/10W	
R2366	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R2367	1-216-043-00	METAL GLAZE	560	5%	1/10W	
R2368	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R2371	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R2374	1-216-067-00	METAL GLAZE	5.6K	5%	1/10W	
R2375	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R2376	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R2377	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R2378	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R2379	1-216-043-00	METAL GLAZE	560	5%	1/10W	
R2380	1-216-043-00	METAL GLAZE	560	5%	1/10W	
R2381	1-216-043-00	METAL GLAZE	560	5%	1/10W	
R2382	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R2384	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R2385	1-216-075-00	METAL GLAZE	12K	5%	1/10W	
R2386	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R2387	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R2388	1-216-017-00	METAL GLAZE	47	5%	1/10W	
R2389	1-216-206-00	METAL GLAZE	2.2K	5%	1/8W	
R2390	1-216-043-00	METAL GLAZE	560	5%	1/10W	
R2392	1-216-206-00	METAL GLAZE	2.2K	5%	1/8W	
R2393	1-216-017-00	METAL GLAZE	47	5%	1/10W	
R2394	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R2395	1-216-001-00	METAL GLAZE	10	5%	1/10W	
R2396	1-216-206-00	METAL GLAZE	2.2K	5%	1/8W	
R2397	1-216-043-00	METAL GLAZE	560	5%	1/10W	
R2399	1-216-001-00	METAL GLAZE	10	5%	1/10W	
R3301	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R3302	1-216-001-00	METAL GLAZE	10	5%	1/10W	
R3303	1-216-069-00	METAL GLAZE	6.8K	5%	1/10W	
R3304	1-216-091-00	METAL GLAZE	56K	5%	1/10W	
R3306	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R3307	1-216-085-00	METAL GLAZE	33K	5%	1/10W	
R3308	1-216-043-00	METAL GLAZE	560	5%	1/10W	
R3309	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R3310	1-216-001-00	METAL GLAZE	10	5%	1/10W	
R3311	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R3312	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R3313	1-216-083-00	METAL GLAZE	27K	5%	1/10W	
R3314	1-216-689-11	METAL GLAZE	39K	5%	1/10W	
R3315	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R3316	1-216-071-00	METAL GLAZE	8.2K	5%	1/10W	
R3318	1-216-095-00	METAL GLAZE	82K	5%	1/10W	
R3319	1-216-095-00	METAL GLAZE	82K	5%	1/10W	
R3320	1-216-017-00	METAL GLAZE	47	5%	1/10W	
R3321	1-216-069-00	METAL GLAZE	6.8K	5%	1/10W	
R3323	1-216-101-00	METAL GLAZE	150K	5%	1/10W	
R3324	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R3325	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R3328	1-216-001-00	METAL GLAZE	10	5%	1/10W	
R3330	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R3331	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R3332	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R3333	1-216-657-11	METAL CHIP	1.8K	0.50%	1/10W	
R3334	1-216-661-11	METAL CHIP	2.7K	0.50%	1/10W	
R3335	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R3336	1-216-683-11	METAL CHIP	22K	0.50%	1/10W	
R3337	1-216-685-11	METAL CHIP	27K	0.50%	1/10W	
R3339	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R3340	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R3341	1-216-677-11	METAL CHIP	12K	0.50%	1/10W	
R3342	1-216-670-11	METAL CHIP	6.2K	0.50%	1/10W	
R3343	1-216-097-00	METAL GLAZE	100K	5%	1/10W	
R3344	1-216-097-00	METAL GLAZE	100K	5%	1/10W	
R3347	1-216-687-11	METAL CHIP	33K	0.50%	1/10W	
R3348	1-216-681-11	METAL CHIP	18K	0.50%	1/10W	
R3349	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R3350	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R3351	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R3352	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R3353	1-216-059-00	METAL GLAZE	2.7K	5%	1/10W	
R3354	1-216-059-00	METAL GLAZE	2.7K	5%	1/10W	
R3356	1-216-655-11	METAL CHIP	1.5K	0.50%	1/10W	
R3357	1-216-654-11	METAL CHIP	1.3K	0.50%	1/10W	
R3358	1-216-659-11	METAL CHIP	2.2K	0.50%	1/10W	
R3359	1-216-653-11	METAL CHIP	1.2K	0.50%	1/10W	
R3360	1-216-077-00	METAL GLAZE	15K	5%	1/10W	
R3361	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R3362	1-216-097-00	METAL GLAZE	100K	5%	1/10W	
R3364	1-216-295-00	METAL GLAZE	0	5%	1/10W	
R3365	1-216-097-00	METAL GLAZE	100K	5%	1/10W	
R3367	1-216-077-00	METAL GLAZE	15K	5%	1/10W	
R3368	1-216-083-00	METAL GLAZE	27K	5%	1/10W	
R3369	1-216-001-00	METAL GLAZE	10	5%	1/10W	
R3370	1-216-001-00	METAL GLAZE	10	5%	1/10W	
R3371	1-216-001-00	METAL GLAZE	10	5%	1/10W	
R3373	1-216-673-11	METAL CHIP	8.2K	0.50%	1/10W	
R3374	1-216-059-00	METAL GLAZE	2.7K	5%	1/10W	
R3375	1-216-658-11	METAL CHIP	2K	0.50%	1/10W	
R3376	1-216-647-11	METAL CHIP	680	0.50%	1/10W	
R3377	1-216-647-11	METAL CHIP	680	0.50%	1/10W	
R3378	1-216-659-11	METAL CHIP	2.2K	0.50%	1/10W	
R3379	1-216-655-11	METAL CHIP	1.5K	0.50%	1/10W	
R3380	1-216-661-11	METAL CHIP	2.7K	0.50%	1/10W	
R3381	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R3382	1-216-295-00	METAL GLAZE	0	5%	1/10W	
R3392	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R3401	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	

REF.NO.	PART NO.	DESCRIPTION				REMARK
R7312	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R7313	1-216-047-00	METAL GLAZE	820	5%	1/10W	
R7314	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	
		<CRYSTAL>				
X2301	1-577-071-11	VIBRATOR, CERAMIC				
		**********				
	*A-1346-138-A	E1 BOARD, COMPLETE				
		**********				
		<CAPACITOR>				
C301	1-163-010-11	CERAMIC CHIP	0.0012MF	10%	50V	
C303	1-126-157-11	ELECT	10MF	20%	16V	
C304	1-164-232-11	CERAMIC CHIP	0.01MF	10%	50V	
C305	1-163-251-11	CERAMIC CHIP	100PF	5%	50V	
C306	1-163-117-00	CERAMIC CHIP	100PF	5%	50V	
C309	1-164-505-11	CERAMIC CHIP	2.2MF		16V	
C310	1-163-109-00	CERAMIC CHIP	47PF	5%	50V	
C314	1-124-915-11	ELECT	10MF	20%	16V	
C315	1-164-505-11	CERAMIC CHIP	2.2MF		16V	
C319	1-126-157-11	ELECT	10MF	20%	16V	
C320	1-124-465-00	ELECT	0.47MF	20%	50V	
C321	1-163-125-00	CERAMIC CHIP	220PF	5%	50V	
C322	1-163-003-11	CERAMIC CHIP	330PF	10%	50V	
C323	1-163-099-00	CERAMIC CHIP	18PF	5%	50V	
C324	1-124-234-00	ELECT	22MF	20%	16V	
C325	1-104-563-11	FILM CHIP	0.1MF	5%	16V	
C326	1-104-563-11	FILM CHIP	0.1MF	5%	16V	
C327	1-104-563-11	FILM CHIP	0.1MF	5%	16V	
C328	1-126-157-11	ELECT	10MF	20%	16V	
C329	1-126-157-11	ELECT	10MF	20%	16V	
C330	1-126-157-11	ELECT	10MF	20%	16V	
C331	1-126-301-11	ELECT	1MF	20%	50V	
C332	1-124-584-00	ELECT	100MF	20%	10V	
C333	1-163-037-11	CERAMIC CHIP	0.022MF	10%	25V	
C334	1-137-491-11	FILM CHIP	0.1MF	5%	25V	
C335	1-136-169-00	FILM	0.22MF	5%	50V	
C336	1-126-301-11	ELECT	1MF	20%	50V	
C337	1-126-301-11	ELECT	1MF	20%	50V	
C338	1-124-584-00	ELECT	100MF	20%	10V	
C339	1-124-791-11	ELECT	1MF	20%	50V	
C340	1-163-009-11	CERAMIC CHIP	0.001MF	10%	50V	
C341	1-126-157-11	ELECT	10MF	20%	16V	
C342	1-124-465-00	ELECT	0.47MF	20%	50V	
C343	1-124-589-11	ELECT	47MF	20%	16V	
C344	1-164-232-11	CERAMIC CHIP	0.01MF	10%	50V	
C345	1-124-767-00	ELECT	2.2MF	20%	50V	
C346	1-164-232-11	CERAMIC CHIP	0.01MF	10%	50V	
C347	1-136-169-00	FILM	0.22MF	5%	50V	
C348	1-163-117-00	CERAMIC CHIP	100PF	5%	50V	
C349	1-126-301-11	ELECT	1MF	20%	50V	
C350	1-126-301-11	ELECT	1MF	20%	50V	
C351	1-163-002-11	CERAMIC CHIP	270PF	10%	50V	
C352	1-164-489-11	CERAMIC CHIP	0.22MF	10%	16V	
C353	1-126-163-11	ELECT	4.7MF	20%	50V	
C354	1-136-169-00	FILM	0.22MF	5%	50V	
C355	1-124-465-00	ELECT	0.47MF	20%	50V	
C356	1-163-017-00	CERAMIC CHIP	0.0047MF	10%	50V	
C357	1-163-117-00	CERAMIC CHIP	100PF	5%	50V	
C358	1-124-767-00	ELECT	2.2MF	20%	50V	
C360	1-137-491-11	FILM CHIP	0.1MF	5%	25V	
C361	1-126-301-11	ELECT	1MF	20%	50V	
C362	1-164-232-11	CERAMIC CHIP	0.01MF	10%	50V	
C363	1-164-232-11	CERAMIC CHIP	0.01MF	10%	50V	
C364	1-126-301-11	ELECT	1MF	20%	50V	
C365	1-164-343-11	CERAMIC CHIP	0.056MF	10%	25V	
C366	1-124-257-00	ELECT	2.2MF	20%	50V	
C367	1-126-157-11	ELECT	10MF	20%	16V	
C368	1-124-234-00	ELECT	22MF	20%	16V	
C369	1-163-001-11	CERAMIC CHIP	220PF	10%	50V	
C370	1-164-232-11	CERAMIC CHIP	0.01MF	10%	50V	
C371	1-124-126-00	ELECT	47MF	20%	16V	
C372	1-124-589-11	ELECT	47MF	20%	16V	
C373	1-164-232-11	CERAMIC CHIP	0.01MF	10%	50V	
C378	1-163-117-00	CERAMIC CHIP	100PF	5%	50V	
C379	1-164-232-11	CERAMIC CHIP	0.01MF	10%	50V	
C380	1-163-137-00	CERAMIC CHIP	680PF	5%	50V	
C381	1-163-101-00	CERAMIC CHIP	22PF	5%	50V	
C382	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	
C383	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	
C384	1-163-095-00	CERAMIC CHIP	12PF	5%	50V	
		<DIODE>				
D301	8-719-404-46	DIODE MA110				
D302	8-719-404-46	DIODE MA110				
D303	8-719-404-46	DIODE MA110				
D304	8-719-404-46	DIODE MA110				
D305	8-719-404-46	DIODE MA110				
D306	8-719-158-15	DIODE RD5.6S-B				
D307	8-719-404-46	DIODE MA110				
D310	8-719-158-15	DIODE RD5.6S-B				
D312	8-719-404-46	DIODE MA110				
D313	8-719-404-46	DIODE MA110				
D314	8-719-404-46	DIODE MA110				
D315	8-719-404-46	DIODE MA110				
D316	8-719-404-46	DIODE MA110				
D317	8-719-404-46	DIODE MA110				
D318	8-719-404-46	DIODE MA110				
D319	8-719-404-46	DIODE MA110				
D320	8-719-404-46	DIODE MA110				
D321	8-719-400-94	DIODE MA3130				
		<DELAY LINE>				
DL302	1-415-817-11	DELAY LINE				
		<CONNECTOR>				
E1-001	1-573-965-21	PIN, CONNECTOR (PC BOARD) 50P				
E1-24	*1-564-523-11	PLUG, CONNECTOR 8P				
E1-25	*1-564-521-31	PLUG, CONNECTOR 6P				
E1-26	*1-564-522-11	PLUG, CONNECTOR 7P				
		<IC>				
IC301	8-752-058-68	IC CXA1315M				
IC302	8-752-057-68	IC CXA1464AS				
IC303	8-759-106-02	IC UPC4570G2				
		<COIL>				
L301	1-410-064-11	INDUCTOR	2.7MMH			
L307	1-410-944-31	INDUCTOR CHIP	15UH			
L308	1-410-946-31	INDUCTOR CHIP	22UH			

E1

<TRANSISTOR>

REF.NO.	PART NO.	DESCRIPTION	REMARK
Q301	8-729-925-79	TRANSISTOR IMX3	
Q302	8-729-925-79	TRANSISTOR IMX3	
Q303	8-729-422-27	TRANSISTOR 2SD601A-Q	
Q304	8-729-907-46	TRANSISTOR IMZ1	
Q305	8-729-925-79	TRANSISTOR IMX3	
Q306	8-729-422-27	TRANSISTOR 2SD601A-Q	
Q307	8-729-903-10	TRANSISTOR FMW1	
Q309	8-729-422-27	TRANSISTOR 2SD601A-Q	
Q310	8-729-422-27	TRANSISTOR 2SD601A-Q	
Q311	8-729-403-27	TRANSISTOR XN4401	
Q312	8-729-422-27	TRANSISTOR 2SD601A-Q	
Q314	8-729-403-27	TRANSISTOR XN4401	
Q315	8-729-422-27	TRANSISTOR 2SD601A-Q	
Q316	8-729-422-27	TRANSISTOR 2SD601A-Q	
Q317	8-729-216-22	TRANSISTOR 2SA1162-G	
Q321	8-729-925-79	TRANSISTOR IMX3	
Q322	8-729-216-22	TRANSISTOR 2SA1162-G	
Q323	8-729-422-27	TRANSISTOR 2SD601A-Q	
Q324	8-729-216-22	TRANSISTOR 2SA1162-G	
Q325	8-729-216-22	TRANSISTOR 2SA1162-G	
Q326	8-729-422-27	TRANSISTOR 2SD601A-Q	
Q327	8-729-422-27	TRANSISTOR 2SD601A-Q	
Q328	8-729-422-27	TRANSISTOR 2SD601A-Q	
Q329	8-729-925-79	TRANSISTOR IMX3	
Q330	8-729-925-79	TRANSISTOR IMX3	
Q333	8-729-925-79	TRANSISTOR IMX3	
Q334	8-729-422-27	TRANSISTOR 2SD601A-Q	
Q335	8-729-907-46	TRANSISTOR IMZ1	
Q340	8-729-422-27	TRANSISTOR 2SD601A-Q	
Q342	8-729-925-79	TRANSISTOR IMX3	
Q344	8-729-216-22	TRANSISTOR 2SA1162-G	

<RESISTOR>

REF.NO.	PART NO.	DESCRIPTION				REMARK
R301	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R302	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	
R303	1-216-079-00	METAL GLAZE	18K	5%	1/10W	
R304	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R305	1-216-069-00	METAL GLAZE	6.8K	5%	1/10W	
R306	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R307	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R308	1-216-037-00	METAL GLAZE	330	5%	1/10W	
R309	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R310	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R312	1-216-043-00	METAL GLAZE	560	5%	1/10W	
R313	1-216-035-00	METAL GLAZE	270	5%	1/10W	
R314	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R316	1-216-035-00	METAL GLAZE	270	5%	1/10W	
R317	1-216-121-00	METAL GLAZE	1M	5%	1/10W	
R320	1-216-039-00	METAL GLAZE	390	5%	1/10W	
R325	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R326	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	
R331	1-216-017-00	METAL GLAZE	47	5%	1/10W	
R332	1-216-657-11	METAL CHIP	1.8K	0.50%	1/10W	
R333	1-216-051-00	METAL GLAZE	1.2K	5%	1/10W	
R336	1-216-047-00	METAL GLAZE	820	5%	1/10W	
R338	1-216-043-00	METAL GLAZE	560	5%	1/10W	
R339	1-216-047-00	METAL GLAZE	820	5%	1/10W	
R340	1-216-651-11	METAL CHIP	1K	0.50%	1/10W	
R341	1-216-043-00	METAL GLAZE	560	5%	1/10W	
R343	1-216-077-00	METAL GLAZE	15K	5%	1/10W	
R344	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R345	1-216-292-11	METAL GLAZE	8.2M	5%	1/8W	
R346	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R347	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R348	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R349	1-216-295-00	METAL GLAZE	0	5%	1/10W	
R350	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R351	1-216-674-11	METAL CHIP	9.1K	0.50%	1/10W	
R352	1-216-011-00	METAL GLAZE	27	5%	1/10W	
R353	1-216-001-00	METAL GLAZE	10	5%	1/10W	
R354	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R355	1-216-001-00	METAL GLAZE	10	5%	1/10W	
R356	1-216-001-00	METAL GLAZE	10	5%	1/10W	
R357	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R358	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R359	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R360	1-216-119-00	METAL GLAZE	820K	5%	1/10W	
R361	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R362	1-216-079-00	METAL GLAZE	18K	5%	1/10W	
R363	1-216-295-00	METAL GLAZE	0	5%	1/10W	
R364	1-216-045-00	METAL GLAZE	680	5%	1/10W	
R365	1-216-017-00	METAL GLAZE	47	5%	1/10W	
R366	1-216-001-00	METAL GLAZE	10	5%	1/10W	
R367	1-216-045-00	METAL GLAZE	680	5%	1/10W	
R368	1-216-001-00	METAL GLAZE	10	5%	1/10W	
R369	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R370	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R371	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R372	1-216-031-00	METAL GLAZE	180	5%	1/10W	
R373	1-216-671-11	METAL CHIP	6.8K	0.50%	1/10W	
R374	1-216-037-00	METAL GLAZE	330	5%	1/10W	
R375	1-216-037-00	METAL GLAZE	330	5%	1/10W	
R376	1-216-037-00	METAL GLAZE	330	5%	1/10W	
R377	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R378	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R379	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R380	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R381	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R382	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R383	1-216-653-11	METAL CHIP	1.2K	0.50%	1/10W	
R384	1-216-041-00	METAL GLAZE	470	5%	1/10W	
R385	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R386	1-216-687-11	METAL CHIP	33K	0.50%	1/10W	
R387	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R388	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R389	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R390	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R391	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R393	1-216-051-00	METAL GLAZE	1.2K	5%	1/10W	
R394	1-216-109-00	METAL GLAZE	330K	5%	1/10W	
R395	1-216-071-00	METAL GLAZE	8.2K	5%	1/10W	
R396	1-216-105-00	METAL GLAZE	220K	5%	1/10W	
R397	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R398	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R399	1-216-077-00	METAL GLAZE	15K	5%	1/10W	
R1301	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R1302	1-216-045-00	METAL GLAZE	680	5%	1/10W	
R1303	1-216-085-00	METAL GLAZE	33K	5%	1/10W	
R1304	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R1305	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R1306	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	
R1307	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1308	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	

REF.NO.	PART NO.	DESCRIPTION				REMARK
R1309	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R1310	1-216-045-00	METAL GLAZE	680	5%	1/10W	
R1311	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R1312	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1313	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R1314	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R1315	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R1316	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R1317	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1318	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R1319	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R1320	1-216-063-00	METAL GLAZE	3.9K	5%	1/10W	
R1321	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R1322	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R1323	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R1324	1-216-045-00	METAL GLAZE	680	5%	1/10W	
R1325	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R1326	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1327	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R1328	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R1329	1-216-077-00	METAL GLAZE	15K	5%	1/10W	
R1330	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R1331	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R1332	1-216-093-00	METAL GLAZE	68K	5%	1/10W	
R1333	1-216-129-00	METAL GLAZE	2.2M	5%	1/10W	
R1334	1-216-097-00	METAL GLAZE	100K	5%	1/10W	
R1335	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R1336	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R1337	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R1338	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R1339	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R1340	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1342	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R1343	1-216-105-00	METAL GLAZE	220K	5%	1/10W	
R1344	1-216-091-00	METAL GLAZE	56K	5%	1/10W	
R1345	1-216-101-00	METAL GLAZE	150K	5%	1/10W	
R1346	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R1347	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R1348	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R1349	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1350	1-216-091-00	METAL GLAZE	56K	5%	1/10W	
R1351	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R1352	1-216-039-00	METAL GLAZE	390	5%	1/10W	
R1353	1-216-053-00	METAL GLAZE	1.5K	5%	1/10W	
R1354	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R1355	1-216-017-00	METAL GLAZE	47	5%	1/10W	
R1356	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	
R1357	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R1358	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R1362	1-216-105-00	METAL GLAZE	220K	5%	1/10W	
R1363	1-216-041-00	METAL GLAZE	470	5%	1/10W	
R1364	1-216-053-00	METAL GLAZE	1.5K	5%	1/10W	
R1373	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R1374	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R1379	1-216-079-00	METAL GLAZE	18K	5%	1/10W	
R1380	1-216-075-00	METAL GLAZE	12K	5%	1/10W	
R1381	1-216-041-00	METAL GLAZE	470	5%	1/10W	
R1382	1-216-079-00	METAL GLAZE	18K	5%	1/10W	
R1383	1-216-077-00	METAL GLAZE	15K	5%	1/10W	
R1384	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R1385	1-216-037-00	METAL GLAZE	330	5%	1/10W	
R1386	1-216-037-00	METAL GLAZE	330	5%	1/10W	
R1387	1-216-045-00	METAL GLAZE	680	5%	1/10W	
R1388	1-216-001-00	METAL GLAZE	10	5%	1/10W	
R1389	1-216-097-00	METAL GLAZE	100K	5%	1/10W	
R1390	1-216-097-00	METAL GLAZE	100K	5%	1/10W	
R1391	1-216-097-00	METAL GLAZE	100K	5%	1/10W	
R1392	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R1394	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R1395	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R1396	1-216-125-00	METAL GLAZE	1.5M	5%	1/10W	
R1399	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R5301	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	
R5302	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R5303	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R5304	1-216-085-00	METAL GLAZE	33K	5%	1/10W	
R5305	1-216-085-00	METAL GLAZE	33K	5%	1/10W	

<CRYSTAL>

X301	1-567-505-11	OSCILLATOR, CRYSTAL			

****

	*A-1394-443-A	Y2 BOARD, COMPLETE			
		**********			

<CAPACITOR>

C401	1-124-234-00	ELECT	22MF	20%	16V
C424	1-126-301-11	ELECT	1MF	20%	50V
C425	1-126-301-11	ELECT	1MF	20%	50V
C426	1-126-301-11	ELECT	1MF	20%	50V
C427	1-124-465-00	ELECT	0.47MF	20%	50V
C428	1-126-163-11	ELECT	4.7MF	20%	50V
C429	1-124-478-11	ELECT	100MF	20%	25V
C430	1-124-261-00	ELECT	10MF	20%	50V
C431	1-126-301-11	ELECT	1MF	20%	50V
C432	1-126-301-11	ELECT	1MF	20%	50V
C433	1-131-347-00	TANTALUM	1MF	20%	16V
C434	1-126-301-11	ELECT	1MF	20%	50V
C435	1-130-309-00	FILM	0.033MF	5%	100V
C436	1-126-301-11	ELECT	1MF	20%	50V
C437	1-130-487-00	MYLAR	0.022MF	5%	50V
C438	1-126-301-11	ELECT	1MF	20%	50V
C439	1-124-034-51	ELECT	33MF	20%	16V
C440	1-126-301-11	ELECT	1MF	20%	50V
C441	1-126-301-11	ELECT	1MF	20%	50V
C442	1-124-261-00	ELECT	10MF	20%	50V
C443	1-124-589-11	ELECT	47MF	20%	16V
C446	1-124-234-00	ELECT	22MF	20%	16V
C447	1-126-301-11	ELECT	1MF	20%	50V
C448	1-136-170-00	FILM	0.27MF	5%	50V
C449	1-163-009-11	CERAMIC CHIP	0.001MF	10%	50V
C450	1-130-475-00	MYLAR	0.0022MF	5%	50V
C451	1-124-261-00	ELECT	10MF	20%	50V
C452	1-124-261-00	ELECT	10MF	20%	50V
C453	1-130-475-00	MYLAR	0.0022MF	5%	50V
C454	1-131-368-00	TANTALUM	3.3MF	10%	16V
C455	1-131-347-00	TANTALUM	1MF	20%	16V
C456	1-136-171-00	FILM	0.33MF	5%	50V
C457	1-136-175-00	FILM	0.68MF	5%	50V
C458	1-126-101-11	ELECT	100MF	20%	16V
C459	1-126-101-11	ELECT	100MF	20%	16V
C460	1-126-101-11	ELECT	100MF	20%	16V
C461	1-124-499-11	ELECT	1MF	20%	50V
C462	1-124-499-11	ELECT	1MF	20%	50V
C465	1-130-485-00	MYLAR	0.015MF	5%	50V

Y2

REF.NO.	PART NO.	DESCRIPTION				REMARK
C466	1-130-485-00	MYLAR	0.015MF	5%	50V	
C467	1-136-169-00	FILM	0.22MF	5%	50V	
C468	1-136-169-00	FILM	0.22MF	5%	50V	
C469	1-126-157-11	ELECT	10MF	20%	16V	
C470	1-126-157-11	ELECT	10MF	20%	16V	
C471	1-124-589-11	ELECT	47MF	20%	16V	
C472	1-164-232-11	CERAMIC CHIP	0.01MF	10%	50V	
C473	1-164-232-11	CERAMIC CHIP	0.01MF	10%	50V	
C474	1-124-234-00	ELECT	22MF	20%	16V	
C475	1-164-232-11	CERAMIC CHIP	0.01MF	10%	50V	
C476	1-124-234-00	ELECT	22MF	20%	16V	
C477	1-164-232-11	CERAMIC CHIP	0.01MF	10%	50V	
C478	1-124-478-11	ELECT	100MF	20%	25V	
C479	1-126-163-11	ELECT	4.7MF	20%	50V	
C480	1-124-768-11	ELECT	4.7MF	20%	50V	
C481	1-124-768-11	ELECT	4.7MF	20%	50V	
C482	1-126-163-11	ELECT	4.7MF	20%	50V	
C483	1-163-113-00	CERAMIC CHIP	68PF	5%	50V	
C484	1-163-113-00	CERAMIC CHIP	68PF	5%	50V	
C485	1-163-038-00	CERAMIC CHIP	0.1MF		25V	
C487	1-164-232-11	CERAMIC CHIP	0.01MF	10%	50V	
C488	1-164-232-11	CERAMIC CHIP	0.01MF	10%	50V	

<DIODE>

D405	8-719-107-13	DIODE	RD18M-B1
D406	8-719-107-13	DIODE	RD18M-B1
D407	8-719-107-13	DIODE	RD18M-B1
D408	8-719-105-83	DIODE	RD5.1M-B3
D409	8-719-981-50	DIODE	RB-100A
D410	8-719-981-50	DIODE	RB-100A
D413	8-719-158-19	DIODE	RD6.2S-B
D414	8-719-158-55	DIODE	RD15S-B
D415	8-719-158-55	DIODE	RD15S-B

<IC>

IC403	8-759-996-43	IC RC4558PS
IC404	8-759-067-24	IC 24C04AI/P
IC406	8-752-037-24	IC CXA1264AS
IC407	8-759-245-75	IC TA8184P
IC408	8-752-057-18	IC CXA1315P

<TRANSISTOR>

Q404	8-729-216-22	TRANSISTOR 2SA1162-G
Q405	8-729-216-22	TRANSISTOR 2SA1162-G
Q409	8-729-422-27	TRANSISTOR 2SD601A-Q
Q410	8-729-422-27	TRANSISTOR 2SD601A-Q

<RESISTOR>

R447	1-216-033-00	METAL GLAZE	220	5%	1/10W
R453	1-216-033-00	METAL GLAZE	220	5%	1/10W
R464	1-216-081-00	METAL GLAZE	22K	5%	1/10W
R465	1-216-081-00	METAL GLAZE	22K	5%	1/10W
R466	1-216-025-00	METAL GLAZE	100	5%	1/10W
R467	1-216-033-00	METAL GLAZE	220	5%	1/10W
R468	1-216-033-00	METAL GLAZE	220	5%	1/10W
R469	1-216-055-00	METAL GLAZE	1.8K	5%	1/10W
R470	1-216-033-00	METAL GLAZE	220	5%	1/10W
R471	1-216-033-00	METAL GLAZE	220	5%	1/10W
R472	1-216-686-11	METAL CHIP	30K	0.50%	1/10W
R473	1-216-295-00	METAL GLAZE	0	5%	1/10W
R474	1-216-295-00	METAL GLAZE	0	5%	1/10W
R475	1-216-055-00	METAL GLAZE	1.8K	5%	1/10W
R476	1-216-669-11	METAL CHIP	5.6K	0.50%	1/10W
R477	1-216-675-11	METAL CHIP	10K	0.50%	1/10W
R478	1-216-089-00	METAL GLAZE	47K	5%	1/10W
R479	1-216-669-11	METAL CHIP	5.6K	0.50%	1/10W
R480	1-216-675-11	METAL CHIP	10K	0.50%	1/10W
R481	1-216-089-00	METAL GLAZE	47K	5%	1/10W
R482	1-216-089-00	METAL GLAZE	47K	5%	1/10W
R483	1-216-089-00	METAL GLAZE	47K	5%	1/10W
R485	1-216-073-00	METAL GLAZE	10K	5%	1/10W
R486	1-216-073-00	METAL GLAZE	10K	5%	1/10W
R488	1-216-295-00	METAL GLAZE	0	5%	1/10W
R494	1-216-025-00	METAL GLAZE	100	5%	1/10W
R495	1-216-025-00	METAL GLAZE	100	5%	1/10W
R496	1-216-025-00	METAL GLAZE	100	5%	1/10W
R497	1-216-033-00	METAL GLAZE	220	5%	1/10W
R498	1-216-025-00	METAL GLAZE	100	5%	1/10W
R499	1-216-025-00	METAL GLAZE	100	5%	1/10W
R500	1-216-081-00	METAL GLAZE	22K	5%	1/10W
R501	1-216-669-11	METAL CHIP	5.6K	0.50%	1/10W
R502	1-216-033-00	METAL GLAZE	220	5%	1/10W
R503	1-216-663-11	METAL CHIP	3.3K	0.50%	1/10W
R504	1-216-675-11	METAL CHIP	10K	0.50%	1/10W
R507	1-216-295-00	METAL GLAZE	0	5%	1/10W
R509	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W
R510	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W
R512	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W
R513	1-216-667-11	METAL CHIP	4.7K	0.50%	1/10W
R515	1-216-295-00	METAL GLAZE	0	5%	1/10W
R517	1-216-025-00	METAL GLAZE	100	5%	1/10W
R518	1-216-089-00	METAL GLAZE	47K	5%	1/10W
R519	1-216-295-00	METAL GLAZE	0	5%	1/10W
R521	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W
R522	1-216-033-00	METAL GLAZE	220	5%	1/10W
R523	1-216-033-00	METAL GLAZE	220	5%	1/10W
R524	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W
R525	1-216-067-00	METAL GLAZE	5.6K	5%	1/10W
R526	1-216-049-00	METAL GLAZE	1K	5%	1/10W
R527	1-218-754-11	METAL CHIP	120K	0.50%	1/10W
R528	1-216-691-11	METAL CHIP	47K	0.50%	1/10W
R529	1-216-097-00	METAL GLAZE	100K	5%	1/10W
R531	1-216-097-00	METAL GLAZE	100K	5%	1/10W
R532	1-216-097-00	METAL GLAZE	100K	5%	1/10W
R533	1-216-097-00	METAL GLAZE	100K	5%	1/10W
R535	1-216-049-00	METAL GLAZE	1K	5%	1/10W
R536	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W
R537	1-216-067-00	METAL GLAZE	5.6K	5%	1/10W
R538	1-218-754-11	METAL CHIP	120K	0.50%	1/10W
R539	1-216-691-11	METAL CHIP	47K	0.50%	1/10W
R542	1-216-025-00	METAL GLAZE	100	5%	1/10W
R543	1-216-025-00	METAL GLAZE	100	5%	1/10W
R546	1-216-682-11	METAL CHIP	20K	0.50%	1/10W
R547	1-216-681-11	METAL CHIP	18K	0.50%	1/10W

<CONNECTOR>

Y2-401	1-573-966-11	PIN, CONNECTOR (PC BOARD) 36P

****

REF.NO.	PART NO.	DESCRIPTION			REMARK
	*A-1394-444-A	X2 BOARD, COMPLETE **********			
		<CAPACITOR>			
C2501	1-163-020-00	CERAMIC CHIP 0.0082MF	10%	50V	
C2502	1-163-020-00	CERAMIC CHIP 0.0082MF	10%	50V	
C2503	1-163-001-11	CERAMIC CHIP 220PF	10%	50V	
C2504	1-126-163-11	ELECT 4.7MF	20%	50V	
C2505	1-163-020-00	CERAMIC CHIP 0.0082MF	10%	50V	
C2506	1-163-020-00	CERAMIC CHIP 0.0082MF	10%	50V	
C2507	1-163-017-00	CERAMIC CHIP 0.0047MF	10%	50V	
C2508	1-163-020-00	CERAMIC CHIP 0.0082MF	10%	50V	
C2509	1-163-020-00	CERAMIC CHIP 0.0082MF	10%	50V	
C2510	1-163-989-11	CERAMIC CHIP 0.033MF	10%	25V	
C2511	1-164-004-11	CERAMIC CHIP 0.1MF	10%	25V	
C2512	1-164-004-11	CERAMIC CHIP 0.1MF	10%	25V	
C2513	1-164-004-11	CERAMIC CHIP 0.1MF	10%	25V	
C2514	1-164-004-11	CERAMIC CHIP 0.1MF	10%	25V	
C2515	1-164-004-11	CERAMIC CHIP 0.1MF	10%	25V	
C2516	1-164-232-11	CERAMIC CHIP 0.01MF	10%	50V	
C2517	1-126-157-11	ELECT 10MF	20%	16V	
C2518	1-126-163-11	ELECT 4.7MF	20%	50V	
C2519	1-126-301-11	ELECT 1MF	20%	50V	
C2520	1-126-163-11	ELECT 4.7MF	20%	50V	
C2521	1-163-809-11	CERAMIC CHIP 0.047MF	10%	25V	
C2522	1-124-252-00	ELECT 0.33MF	20%	50V	
C2523	1-126-163-11	ELECT 4.7MF	20%	50V	
C2524	1-164-004-11	CERAMIC CHIP 0.1MF	10%	25V	
C2525	1-126-163-11	ELECT 4.7MF	20%	50V	
C2526	1-164-004-11	CERAMIC CHIP 0.1MF	10%	25V	
C2527	1-126-157-11	ELECT 10MF	20%	16V	
C2528	1-124-465-00	ELECT 0.47MF	20%	50V	
C2529	1-163-989-11	CERAMIC CHIP 0.033MF	10%	25V	
C2530	1-164-182-11	CERAMIC CHIP 0.0033MF	10%	50V	
C2531	1-126-301-11	ELECT 1MF	20%	50V	
C2532	1-126-301-11	ELECT 1MF	20%	50V	
C2533	1-124-261-00	ELECT 10MF	20%	50V	
C2534	1-163-257-11	CERAMIC CHIP 180PF	5%	50V	
C2535	1-164-004-11	CERAMIC CHIP 0.1MF	10%	25V	
C2536	1-164-004-11	CERAMIC CHIP 0.1MF	10%	25V	
C2537	1-126-163-11	ELECT 4.7MF	20%	50V	
C2538	1-126-163-11	ELECT 4.7MF	20%	50V	
C2539	1-164-232-11	CERAMIC CHIP 0.01MF	10%	50V	
C2540	1-164-004-11	CERAMIC CHIP 0.1MF	10%	25V	
C2541	1-163-139-00	CERAMIC CHIP 820PF	5%	50V	
C2542	1-124-478-11	ELECT 100MF	20%	25V	
C2543	1-124-252-00	ELECT 0.33MF	20%	50V	
C2544	1-164-161-11	CERAMIC CHIP 0.0022MF	10%	50V	
C2545	1-126-301-11	ELECT 1MF	20%	50V	
C2546	1-126-163-11	ELECT 4.7MF	20%	50V	
C2547	1-126-163-11	ELECT 4.7MF	20%	25V	
C2548	1-163-809-11	CERAMIC CHIP 0.047MF	10%	25V	
C2549	1-126-163-11	ELECT 4.7MF	20%	50V	
C2550	1-126-163-11	ELECT 4.7MF	20%	25V	
C2551	1-126-301-11	ELECT 1MF	20%	50V	
C2552	1-126-163-11	ELECT 4.7MF	20%	50V	
C2553	1-126-301-11	ELECT 1MF	20%	50V	
C2554	1-124-234-00	ELECT 22MF	20%	16V	
C2555	1-164-004-11	CERAMIC CHIP 0.1MF	10%	25V	
C2556	1-124-257-00	ELECT 2.2MF	20%	50V	
C2557	1-124-234-00	ELECT 22MF	20%	16V	
C2558	1-126-301-11	ELECT 1MF	20%	50V	
C2559	1-164-004-11	CERAMIC CHIP 0.1MF	10%	25V	
C2560	1-164-161-11	CERAMIC CHIP 0.0022MF	10%	50V	
C2561	1-126-301-11	ELECT 1MF	20%	50V	
C2562	1-163-263-11	CERAMIC CHIP 330PF	5%	50V	
C2563	1-163-257-11	CERAMIC CHIP 180PF	5%	50V	
C2564	1-126-301-11	ELECT 1MF	20%	50V	
C2565	1-126-163-11	ELECT 4.7MF	20%	50V	
C2566	1-126-163-11	ELECT 4.7MF	20%	50V	
C2567	1-126-163-11	ELECT 4.7MF	20%	50V	
C2568	1-163-263-11	CERAMIC CHIP 330PF	5%	50V	
C2569	1-163-257-11	CERAMIC CHIP 180PF	5%	50V	
C2570	1-124-234-00	ELECT 22MF	20%	16V	
C2571	1-126-301-11	ELECT 1MF	20%	50V	
C2572	1-126-163-11	ELECT 4.7MF	20%	50V	
C2573	1-124-234-00	ELECT 22MF	20%	16V	
C2574	1-126-301-11	ELECT 1MF	20%	50V	
C2575	1-126-301-11	ELECT 1MF	20%	50V	
C2576	1-126-301-11	ELECT 1MF	20%	50V	
C2577	1-126-163-11	ELECT 4.7MF	20%	50V	
C2578	1-126-163-11	ELECT 4.7MF	20%	50V	
C2579	1-126-103-11	ELECT 470MF	20%	16V	
C2580	1-124-478-11	ELECT 100MF	20%	25V	
C2581	1-163-109-00	CERAMIC CHIP 47PF	5%	50V	
C2582	1-124-477-11	ELECT 47MF	20%	25V	
C2583	1-126-163-11	ELECT 4.7MF	20%	50V	
C2584	1-163-109-00	CERAMIC CHIP 47PF	5%	50V	
C2585	1-126-163-11	ELECT 4.7MF	20%	50V	
C2586	1-163-009-11	CERAMIC CHIP 0.001MF	10%	50V	
C2587	1-126-163-11	ELECT 4.7MF	20%	50V	
C2588	1-126-163-11	ELECT 4.7MF	20%	50V	
C2589	1-126-163-11	ELECT 4.7MF	20%	50V	
C2590	1-126-163-11	ELECT 4.7MF	20%	50V	
C2591	1-124-478-11	ELECT 100MF	20%	25V	
		<DIODE>			
D2501	8-719-104-34	DIODE 1S2836			
D2502	8-719-106-88	DIODE RD15M-B1			
D2503	8-719-106-88	DIODE RD15M-B1			
D2504	8-719-106-88	DIODE RD15M-B1			
		<IC>			
IC2501	8-759-031-31	IC MC33174M			
IC2502	8-752-050-75	IC CXA1373Q			
IC2503	8-759-604-70	IC M51523AL			
IC2504	8-759-031-31	IC MC33174M			
IC2505	8-759-604-70	IC M51523AL			
IC2506	8-759-106-22	IC UPD4052BG			
IC2507	8-759-038-68	IC MC33172ML			
IC2508	8-759-038-68	IC MC33172ML			
		<JACK>			
J2501	*1-573-966-11	PIN, CONNECTOR (PC BOARD) 36P			
		<TRANSISTOR>			
Q2501	8-729-230-49	TRANSISTOR 2SC2712-YG			
		<RESISTOR>			
R2501	1-216-079-00	METAL GLAZE	18K	5%	1/10W
R2502	1-216-097-00	METAL GLAZE	100K	5%	1/10W
R2503	1-216-091-00	METAL GLAZE	56K	5%	1/10W
R2504	1-216-109-00	METAL GLAZE	330K	5%	1/10W
R2505	1-216-109-00	METAL GLAZE	330K	5%	1/10W

X2 G

REF.NO.	PART NO.	DESCRIPTION				REMARK
R2506	1-216-101-00	METAL GLAZE	150K	5%	1/10W	
R2507	1-216-091-00	METAL GLAZE	56K	5%	1/10W	
R2508	1-216-079-00	METAL GLAZE	18K	5%	1/10W	
R2509	1-216-130-11	METAL GLAZE	2.4M	5%	1/10W	
R2510	1-216-097-00	METAL GLAZE	100K	5%	1/10W	
R2511	1-216-085-00	METAL GLAZE	33K	5%	1/10W	
R2512	1-216-103-00	METAL GLAZE	180K	5%	1/10W	
R2513	1-216-085-00	METAL GLAZE	33K	5%	1/10W	
R2514	1-216-103-00	METAL GLAZE	180K	5%	1/10W	
R2515	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R2516	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R2517	1-216-133-00	METAL GLAZE	3.3M	5%	1/10W	
R2518	1-216-072-00	METAL GLAZE	9.1K	5%	1/10W	
R2519	1-216-133-00	METAL GLAZE	3.3M	5%	1/10W	
R2520	1-216-133-00	METAL GLAZE	3.3M	5%	1/10W	
R2521	1-216-133-00	METAL GLAZE	3.3M	5%	1/10W	
R2522	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R2523	1-216-077-00	METAL GLAZE	15K	5%	1/10W	
R2524	1-216-129-00	METAL GLAZE	2.2M	5%	1/10W	
R2526	1-216-133-00	METAL GLAZE	3.3M	5%	1/10W	
R2527	1-216-133-00	METAL GLAZE	3.3M	5%	1/10W	
R2528	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R2529	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R2530	1-216-133-00	METAL GLAZE	3.3M	5%	1/10W	
R2531	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R2532	1-216-133-00	METAL GLAZE	3.3M	5%	1/10W	
R2533	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R2534	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R2535	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R2536	1-216-129-00	METAL GLAZE	2.2M	5%	1/10W	
R2537	1-216-077-00	METAL GLAZE	15K	5%	1/10W	
R2539	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R2540	1-216-075-00	METAL GLAZE	12K	5%	1/10W	
R2541	1-216-069-00	METAL GLAZE	6.8K	5%	1/10W	
R2542	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R2543	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R2544	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R2545	1-216-048-00	METAL GLAZE	910	5%	1/10W	
R2546	1-216-133-00	METAL GLAZE	3.3M	5%	1/10W	
R2547	1-216-133-00	METAL GLAZE	3.3M	5%	1/10W	
R2548	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R2549	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R2550	1-216-088-00	METAL GLAZE	43K	5%	1/10W	
R2551	1-216-088-00	METAL GLAZE	43K	5%	1/10W	
R2552	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R2553	1-216-078-00	METAL GLAZE	16K	5%	1/10W	
R2554	1-216-082-00	METAL GLAZE	24K	5%	1/10W	
R2555	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R2556	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R2557	1-216-085-00	METAL GLAZE	33K	5%	1/10W	
R2558	1-216-088-00	METAL GLAZE	43K	5%	1/10W	
R2559	1-216-091-00	METAL GLAZE	56K	5%	1/10W	
R2560	1-216-103-00	METAL GLAZE	180K	5%	1/10W	
R2561	1-216-097-00	METAL GLAZE	100K	5%	1/10W	
R2562	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R2563	1-216-088-00	METAL GLAZE	43K	5%	1/10W	
R2564	1-216-088-00	METAL GLAZE	43K	5%	1/10W	
R2565	1-216-103-00	METAL GLAZE	180K	5%	1/10W	
R2566	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R2567	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R2568	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R2569	1-216-097-00	METAL GLAZE	100K	5%	1/10W	
R2570	1-216-091-00	METAL GLAZE	56K	5%	1/10W	
R2571	1-216-078-00	METAL GLAZE	16K	5%	1/10W	
R2572	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R2573	1-216-082-00	METAL GLAZE	24K	5%	1/10W	
R2574	1-216-085-00	METAL GLAZE	33K	5%	1/10W	
R2575	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R2576	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R2577	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R2578	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R2579	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R2580	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R2581	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R2582	1-216-083-00	METAL GLAZE	27K	5%	1/10W	
R2583	1-216-083-00	METAL GLAZE	27K	5%	1/10W	
R2584	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R2585	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R2586	1-216-085-00	METAL GLAZE	33K	5%	1/10W	
R2587	1-216-085-00	METAL GLAZE	33K	5%	1/10W	
R2588	1-216-085-00	METAL GLAZE	33K	5%	1/10W	
R2589	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R2590	1-216-079-00	METAL GLAZE	18K	5%	1/10W	
R2591	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R2592	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R2593	1-216-079-00	METAL GLAZE	18K	5%	1/10W	
R2594	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R2595	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R2596	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R2597	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R2598	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R2599	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R2600	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R2601	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R2602	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R2604	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R2605	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R2606	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R2610	1-216-125-00	METAL GLAZE	1.5M	5%	1/10W	
R2611	1-216-125-00	METAL GLAZE	1.5M	5%	1/10W	
R2612	1-216-125-00	METAL GLAZE	1.5M	5%	1/10W	
R2613	1-216-125-00	METAL GLAZE	1.5M	5%	1/10W	
R2614	1-216-125-00	METAL GLAZE	1.5M	5%	1/10W	
R2615	1-216-125-00	METAL GLAZE	1.5M	5%	1/10W	
R2616	1-216-125-00	METAL GLAZE	1.5M	5%	1/10W	
R2617	1-216-125-00	METAL GLAZE	1.5M	5%	1/10W	
R2618	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R2619	1-216-049-00	METAL GLAZE	1K	5%	1/10W	

****

*A-1316-149-A G BOARD, COMPLETE
****

1-533-223-11 CLIP, FUSE
3-701-754-00 PLATE, INSULATING
4-382-854-11 SCREW (M3X10), P, SW (+)

<CAPACITOR>

C601	1-161-830-00	CERAMIC	4700PF	10%	500V
C602	1-130-317-00	FILM	0.068MF	5%	100V
C603	1-124-634-11	ELECT	1MF	20%	250V
C605	1-164-143-11	CERAMIC	0.001MF	10%	1KV
C606	1-124-563-11	ELECT	2200MF	20%	25V
C607	1-124-563-11	ELECT	2200MF	20%	25V
C608	1-128-484-11	ELECT	100MF	20%	200V
C609	1-137-141-11	FILM	0.082MF	3%	600V
C612	1-124-962-11	ELECT	2200MF	20%	25V

The components identified by shading and mark ⚠ are critical for safety.
Replace only with part number specified.

Les composants identifies par une trame et une marque ⚠ sont critiques pour la securite.
Ne les remplacer que par une piece portant le numero specifie.

REF.NO.	PART NO.	DESCRIPTION				REMARK
C614	1-126-326-51	ELECT	10MF	20%	200V	
C615	1-124-798-11	ELECT	1MF	20%	160V	
C616	1-124-557-11	ELECT	1000MF	20%	25V	
C617	1-164-143-11	CERAMIC	0.001MF	10%	1KV	
C618	1-136-853-11	FILM	0.56MF	5%	200V	
C619	1-164-735-11	CAP, CERAMIC	1500PF			
C620	1-136-721-21	FILM	1.5MF	10%	400V	
C621	1-164-143-11	CERAMIC	0.001MF	10%	1KV	
C622	1-136-853-11	FILM	0.56MF	5%	200V	
C623	1-137-087-11	FILM	0.068MF	3%	0	
C624	1-126-771-11	ELECT	100MF	20%	160V	
C625	1-126-183-11	ELECT	1000MF	20%	16V	
C626	1-126-373-11	ELECT	470MF	20%	10V	
C628	1-161-830-00	CERAMIC	4700PF	10%	500V	
C629	1-124-607-11	ELECT	2200MF	20%	50V	
C631	1-126-803-11	ELECT	47MF	20%	50V	
C632	1-124-903-11	ELECT	1MF	20%	50V	
C633	1-130-483-00	MYLAR	0.01MF	5%	50V	
C634	1-126-803-11	ELECT	47MF	20%	16V	
C637 ⚠	1-136-311-51	FILM	0.47MF	20%	125V	
C638 ⚠	1-161-743-12	CERAMIC	0.0047MF		400V	
C639 ⚠	1-125-692-11	ELECT(BLOCK)	820MF	20%	200V	
C640 ⚠	1-136-311-51	FILM	0.47MF	20%	125V	
C641	1-126-101-11	ELECT	100MF	20%	16V	
C642 ⚠	1-161-743-12	CERAMIC	0.0047MF		400V	
C644	1-126-104-11	ELECT	470MF	20%	35V	
C646	1-124-907-11	ELECT	10MF	20%	50V	
C647 ⚠	1-164-486-51	CERAMIC	0.0033MF	20%	400V	
C648 ⚠	1-125-692-11	ELECT(BLOCK)	820MF	20%	200V	
C649 ⚠	1-164-486-51	CERAMIC	0.0033MF	20%	400V	
C650 ⚠	1-161-743-12	CERAMIC	0.0047MF		400V	
C660	1-102-125-00	CERAMIC	0.0047MF	10%	50V	
C661	1-102-125-00	CERAMIC	0.0047MF	10%	50V	
C662	1-124-910-11	ELECT	47MF	20%	35V	
C663	1-126-017-11	ELECT	6800MF	20%	16V	
C664	1-126-017-11	ELECT	6800MF	20%	16V	
C670	1-102-074-00	CERAMIC	0.001MF	10%	50V	

<DIODE>

D602	8-719-979-58	DIODE	EGP10D
D603	8-719-500-67	DIODE	D5KC40H
D604	8-719-510-09	DIODE	D10SC6M
D605	8-719-988-31	DIODE	D10SC6MR
D607	8-719-025-81	DIODE	S3V10SB
D608	8-719-109-85	DIODE	RD5.1ES-B2
D609	8-719-109-84	DIODE	RD5.1ES-B1
D610	8-719-979-58	DIODE	EGP10D
D611	8-719-979-58	DIODE	EGP10D
D613	8-719-303-57	DIODE	RU2AM
D614	8-719-979-58	DIODE	EGP10D
D615	8-719-975-76	DIODE	SB140
D616	8-719-025-81	DIODE	S3V10SB
D617	8-719-110-02	DIODE	RD7.5ES-B1
D618	8-719-911-19	DIODE	1SS119
D619	8-719-975-76	DIODE	SB140
D620 ⚠	8-719-988-31	DIODE	D10SC6MR
D621	8-719-908-03	DIODE	GP08D
D622	8-719-908-03	DIODE	GP08D
D623	8-719-110-63	DIODE	RD24ES-B3
D624	8-719-109-89	DIODE	RD5.6ES-B2
D626	8-719-908-03	DIODE	GP08D
D628	8-719-110-49	DIODE	RD18ES-B2
D629	8-719-911-19	DIODE	1SS119
D631	8-719-911-19	DIODE	1SS119
D632	8-719-511-40	DIODE	S1VB40
D633 ⚠	8-719-505-60	DIODE	S5VB60
D634	8-719-911-19	DIODE	1SS119
D636	8-719-109-85	DIODE	RD5.1ES-B2
D638	8-719-911-19	DIODE	1SS119
D640 ⚠	8-719-510-09	DIODE	D10SC6M
D650	8-719-160-81	DIODE	RD27F-B2

<FUSE>

F601 ⚠	1-532-748-11	FUSE, GLASS TUBE	6.3A/125V

<FERRITE BEAD>

FB602	1-410-397-21	FERRITE BEAD INDUCTOR 1.1UH
FB604	1-410-396-41	FERRITE BEAD INDUCTOR 0.45UH
FB606	1-410-397-21	FERRITE BEAD INDUCTOR 1.1UH
FB607	1-410-397-21	FERRITE BEAD INDUCTOR 1.1UH
FB608	1-410-396-41	FERRITE BEAD INDUCTOR 0.45UH
FB612	1-410-397-21	FERRITE BEAD INDUCTOR 1.1UH
FB622	1-410-397-21	FERRITE BEAD INDUCTOR 1.1UH
FB630	1-410-396-41	FERRITE BEAD INDUCTOR 0.45UH
FB631	1-410-396-41	FERRITE BEAD INDUCTOR 0.45UH

<CONNECTOR>

G1	*1-508-786-00	PIN, CONNECTOR (5MM PITCH) 2P
G2	*1-564-512-11	PLUG, CONNECTOR 9P
G3	*1-564-507-11	PLUG, CONNECTOR 4P
G4	*1-564-511-11	PLUG, CONNECTOR 8P
G5	*1-564-508-11	PLUG, CONNECTOR 5P
G7	*1-564-507-11	PLUG, CONNECTOR 4P
G8	*1-580-843-11	PIN, CONNECTOR (POWER)
G9	*1-508-765-00	PIN, CONNECTOR (5MM PITCH) 3P
G10	*1-508-786-00	PIN, CONNECTOR (5MM PITCH) 2P
G11	*1-564-511-31	PLUG, CONNECTOR 8P
G12	*1-564-505-11	PLUG, CONNECTOR 2P

<IC>

IC601 ⚠	8-749-921-89	IC SE115N
IC602	8-759-231-58	IC TA7812S

<COIL>

L602	1-459-862-11	COIL, CHOKE	90UH
L604	1-408-404-00	INDUCTOR	3.9UH
L605	1-412-526-11	INDUCTOR	12UH
L607	1-408-404-00	INDUCTOR	3.9UH
L611	1-412-546-41	INDUCTOR	560UH
L612	1-412-540-31	INDUCTOR	180UH
L613	1-412-522-41	INDUCTOR	5.6UH

<TRANSISTOR>

Q603	8-729-011-15	TRANSISTOR 2SC4582NP
Q604	8-729-119-80	TRANSISTOR 2SC2688-LK
Q607	8-729-119-78	TRANSISTOR 2SC2785-HFE
Q608	8-729-326-11	TRANSISTOR 2SC2611
Q609	8-729-119-76	TRANSISTOR 2SA1175-HFE
Q610	8-729-019-58	TRANSISTOR 2SA1208T-TP
Q611	8-729-019-58	TRANSISTOR 2SA1208T-TP

G **CR**

• The components identified by ⊠ in this manual have been carefully factory-selected for each set in order to satisfy regulations regarding X-ray radiation. Should replacement be required, replace only with the value originally used.

Les composants identifies par une trame et une marque ⚠ sont critiques pour la securite. Ne les remplacer que par une piece portant le numero specifie.

The components identified by shading and mark ⚠ are critical for safety. Replace only with part number specified.

REF.NO.	PART NO.	DESCRIPTION				REMARK
Q612	8-729-386-12	TRANSISTOR 2SB861-C				
Q613	8-729-209-15	TRANSISTOR 2SD2012				
Q614	8-729-011-15	TRANSISTOR 2SC4582NP				
Q615	8-729-019-58	TRANSISTOR 2SA1208T-TP				
Q616	8-729-208-39	TRANSISTOR 2SA1306A-Y				
Q618	8-729-119-76	TRANSISTOR 2SA1175-HFE				
Q620	8-729-119-78	TRANSISTOR 2SC2785-HFE				
Q621	8-729-119-78	TRANSISTOR 2SC2785-HFE				
Q623	8-729-119-76	TRANSISTOR 2SA1175-HFE				
Q629	8-729-378-84	TRANSISTOR 2SD788-5				
Q630	8-729-255-12	TRANSISTOR 2SC2551-O				
		<RESISTOR>				
R604	1-202-933-11	FUSIBLE	0.1	10%	1/2W	F
R605	1-249-428-11	CARBON	8.2K	5%	1/4W	
R606	1-214-919-00	METAL	180K	1%	1/2W	
R609	1-249-434-11	CARBON	27K	5%	1/4W	F
R610	1-215-469-00	METAL	100K	1%	1/4W	
R611	1-249-421-11	CARBON	2.2K	5%	1/4W	F
R612	1-202-883-11	SOLID	680K	20%	1/2W	
R613	1-216-386-11	METAL OXIDE	0.56	5%	3W	F
R614	1-249-418-11	CARBON	1.2K	5%	1/4W	
R615	1-215-438-00	METAL	5.1K	1%	1/4W	
R616	1-215-436-00	METAL	4.3K	1%	1/4W	
R617	1-216-356-00	METAL OXIDE	3.9	5%	1W	F
R618	1-249-418-11	CARBON	1.2K	5%	1/4W	
R619	1-216-444-11	METAL OXIDE	82K	5%	1W	F
R620	1-249-418-11	CARBON	1.2K	5%	1/4W	F
R621	1-247-691-11	CARBON	18	5%	1/4W	F
R622	1-249-424-11	CARBON	3.9K	5%	1/4W	F
R623	1-249-417-11	CARBON	1K	5%	1/4W	
R624	1-214-780-00	METAL	130K	1%	1/4W	
R625	1-216-386-11	METAL OXIDE	0.56	5%	3W	F
R626	1-216-356-00	METAL OXIDE	3.9	5%	1W	F
R627	1-202-883-11	SOLID	680K	20%	1/2W	
R628	1-249-410-11	CARBON	270	5%	1/4W	F
R629	1-207-620-00	WIREWOUND	1	10%	3W	F
R631	1-249-417-11	CARBON	1K	5%	1/4W	F
R632	1-214-913-00	METAL	100K	1%	1/2W	
R633	1-249-429-11	CARBON	10K	5%	1/4W	
R634	1-249-441-11	CARBON	100K	5%	1/4W	
R635	1-215-897-11	METAL OXIDE	6.8K	5%	2W	F
R636	1-260-065-11	CARBON	1.2	5%	1/2W	
R638	1-249-405-11	CARBON	100	5%	1/4W	F
R639	1-249-405-11	CARBON	100	5%	1/4W	F
R640	1-249-421-11	CARBON	2.2K	5%	1/4W	F
R641	1-249-429-11	CARBON	10K	5%	1/4W	
R642	1-215-421-00	METAL	1K	1%	1/4W	
R643	1-260-123-11	CARBON	100K	5%	1/2W	
R644	1-249-415-11	CARBON	680	5%	1/4W	
R645	1-249-417-11	CARBON	1K	5%	1/4W	
R649	1-249-424-11	CARBON	3.9K	5%	1/4W	
R650	1-249-377-11	CARBON	0.47	5%	1/4W	F
R651	1-215-429-00	METAL	2.2K	1%	1/4W	
⊠R652 ⚠		METAL			1/4W	
R654	1-215-429-00	METAL	2.2K	1%	1/4W	
R655	1-249-426-11	CARBON	5.6K	5%	1/4W	
R656	1-215-454-00	METAL	24K	1%	1/4W	
R657	1-216-386-11	METAL OXIDE	0.56	5%	3W	F
R660	1-249-418-11	CARBON	1.2K	5%	1/4W	
R661 ⚠	1-202-884-91	SOLID	820K	20%	1/2W	
R662 ⚠	1-205-900-11	WIREWOUND	1.2	5%	15W	
R663 ⚠	1-215-904-91	METAL OXIDE	100K	5%	2W	F
R666	1-249-377-11	CARBON	0.47	5%	1/4W	F
R667 ⚠	1-202-888-91	SOLID	2.2M	20%	1/2W	
R668 ⚠	1-215-904-91	METAL OXIDE	100K	5%	2W	F
R669	1-249-377-11	CARBON	0.47	5%	1/4W	F
R675	1-249-377-11	CARBON	0.47	5%	1/4W	F
R687	1-249-417-11	CARBON	1K	5%	1/4W	F
R689	1-247-742-11	CARBON	180	5%	1/2W	F
R691	1-249-421-11	CARBON	2.2K	5%	1/4W	
R694	1-249-421-11	CARBON	2.2K	5%	1/4W	
R697	1-249-382-11	CARBON	1.2	5%	1/4W	F
R698	1-216-386-11	METAL OXIDE	0.56	5%	3W	F
		<RELAY>				
RY601 ⚠	1-515-805-11	RELAY, POWER				
RY602 ⚠	1-515-805-11	RELAY, POWER				
		<TRANSFORMER>				
T601 ⚠	1-450-791-12	TRANSFORMER, POWER ISOLATION				
T603 ⚠	1-424-020-11	PRT				
T604 ⚠	1-450-149-11	TRANSFORMER, HEATER				
T605 ⚠	1-424-023-12	TRANSFORMER, LINE FILTER				
T606 ⚠	1-421-372-21	TRANSFORMER, FERRITE (LFT)				
T608 ⚠	1-423-665-11	TRANSFORMER, POWER				
		<VARISTOR>				
VDR601 ⚠	1-809-786-11	VARISTOR				
		**********				
	*A-1331-259-A	CR BOARD, COMPLETE				
		**********				
		<CAPACITOR>				
C701	1-162-115-00	CERAMIC	330PF	10%	2KV	
C702	1-123-948-00	ELECT	22MF	20%	250V	
C703	1-102-050-00	CERAMIC	0.01MF		500V	
C704	1-162-115-00	CERAMIC	330PF	10%	2KV	
C705	1-130-479-00	MYLAR	0.0047MF	5%	50V	
C706	1-101-006-00	CERAMIC	0.047MF		50V	
C707	1-101-006-00	CERAMIC	0.047MF		50V	
C709	1-124-120-11	ELECT	220MF	20%	16V	
C710	1-124-120-11	ELECT	220MF	20%	16V	
C711	1-102-114-00	CERAMIC	470PF	10%	50V	
		<CONNECTOR>				
CR1	*1-508-784-00	PIN, CONNECTOR (5MM PITCH) 1P				
CR3	*1-508-765-00	PIN, CONNECTOR (5MM PITCH) 3P				
CR4	*1-564-511-31	PLUG, CONNECTOR 8P				
CR15	*1-564-508-11	PLUG, CONNECTOR 5P				
		<PICTURE TUBE SOCKET>				
CRT701 ⚠	1-251-026-11	SOCKET, PICTURE TUBE				
		<DIODE>				
D701	8-719-911-19	DIODE 1SS119				
D702	8-719-911-19	DIODE 1SS119				
D703	8-719-911-19	DIODE 1SS119				

CR | CG

The components identified by shading and mark ⚠ are critical for safety.
Replace only with part number specified.

Les composants identifies par une trame et une marque ⚠ sont critiques pour la securite.
Ne les remplacer que par une piece portant le numero specifie.

REF.NO.	PART NO.	DESCRIPTION				REMARK
D704	8-719-911-19	DIODE 1SS119				
D705	8-719-911-19	DIODE 1SS119				
D706	8-719-911-19	DIODE 1SS119				
D707	8-719-110-36	DIODE RD13ES-B2				
		<COIL>				
L701	1-408-429-00	INDUCTOR 470UH				
L702	1-408-159-00	COIL, SPOOK CHOKE 3.3UH				
L703	1-408-159-00	COIL, SPOOK CHOKE 3.3UH				
L704	1-408-413-00	INDUCTOR 22UH				
		<NEON LAMP>				
NL701	1-519-108-99	LAMP, NEON				
NL702	1-519-108-99	LAMP, NEON				
		<TRANSISTOR>				
Q701	8-729-119-78	TRANSISTOR 2SC2785-HFE				
Q702	8-729-119-78	TRANSISTOR 2SC2785-HFE				
Q703	8-729-119-80	TRANSISTOR 2SC2688-LK				
	4-373-933-01	SHEET (TRANSISTOR), BN; Q703				
	4-382-854-11	SCREW (M3X10), P, SW (+); Q703				
Q704	8-729-255-12	TRANSISTOR 2SC2551-O				
Q705	8-729-200-17	TRANSISTOR 2SA1091-O				
Q706	8-729-200-17	TRANSISTOR 2SA1091-O				
		<RESISTOR>				
R701	1-202-847-00	SOLID	560K	20%	1/2W	
R702	1-202-814-11	SOLID	33K	20%	1/2W	
R703	1-202-818-00	SOLID	1K	20%	1/2W	
R704	1-202-842-11	SOLID	220K	20%	1/2W	
R705	1-202-828-11	SOLID	6.8K	20%	1/2W	
R706	1-202-561-00	SOLID	330	20%	1/2W	
R707	1-216-510-11	METAL OXIDE	8.2K	5%	5W	F
R708	1-249-405-11	CARBON	100	5%	1/4W	F
R709	1-249-405-11	CARBON	100	5%	1/4W	F
R710	1-215-927-00	METAL OXIDE	47K	5%	3W	F
R711	1-249-405-11	CARBON	100	5%	1/4W	F
R712	1-249-421-11	CARBON	2.2K	5%	1/4W	F
R714	1-249-401-11	CARBON	47	5%	1/4W	
R716	1-249-405-11	CARBON	100	5%	1/4W	
R717	1-249-403-11	CARBON	68	5%	1/4W	
R718	1-249-412-11	CARBON	390	5%	1/4W	
R719	1-249-410-11	CARBON	270	5%	1/4W	
R720	1-249-405-11	CARBON	100	5%	1/4W	
R721	1-249-409-11	CARBON	220	5%	1/4W	
R722	1-215-423-00	METAL	1.2K	1%	1/4W	
R723	1-249-410-11	CARBON	270	5%	1/4W	
R724	1-215-429-00	METAL	2.2K	1%	1/4W	
		<SPARK GAP>				
SG701	1-519-422-11	GAP, SPARK				
SG702	1-519-422-11	GAP, SPARK				

****

*A-1331-260-A CG BOARD, COMPLETE
****

4-373-933-01 SHEET (TRANSISTOR), BN
4-382-854-11 SCREW (M3X10), P, SW (+)

REF.NO.	PART NO.	DESCRIPTION				REMARK
		<CAPACITOR>				
C731	1-162-115-00	CERAMIC	330PF	10%	2KV	
C732	1-123-948-00	ELECT	22MF	20%	250V	
C733	1-102-050-00	CERAMIC	0.01MF		500V	
C734	1-162-115-00	CERAMIC	330PF	10%	2KV	
C735	1-130-479-00	MYLAR	0.0047MF	5%	50V	
C736	1-101-006-00	CERAMIC	0.047MF		50V	
C737	1-101-006-00	CERAMIC	0.047MF		50V	
C739	1-124-120-11	ELECT	220MF	20%	16V	
C740	1-124-120-11	ELECT	220MF	20%	16V	
C741	1-102-114-00	CERAMIC	470PF	10%	50V	
		<CONNECTOR>				
CG1	*1-508-784-00	PIN, CONNECTOR (5MM PITCH) 1P				
CG3	*1-508-765-00	PIN, CONNECTOR (5MM PITCH) 3P				
CG16	*1-564-508-11	PLUG, CONNECTOR 5P				
		<PICTURE TUBE SOCKET>				
CRT731⚠	1-251-026-11	SOCKET, PICTURE TUBE				
		<DIODE>				
D731	8-719-911-19	DIODE 1SS119				
D732	8-719-911-19	DIODE 1SS119				
D733	8-719-911-19	DIODE 1SS119				
D734	8-719-911-19	DIODE 1SS119				
D735	8-719-911-19	DIODE 1SS119				
D736	8-719-911-19	DIODE 1SS119				
D737	8-719-911-19	DIODE 1SS119				
		<COIL>				
L731	1-408-429-00	INDUCTOR 470UH				
L732	1-408-159-00	COIL, SPOOK CHOKE 3.3UH				
L733	1-408-159-00	COIL, SPOOK CHOKE 3.3UH				
L734	1-408-413-00	INDUCTOR 22UH				
		<NEON LAMP>				
NL731	1-519-108-99	LAMP, NEON				
NL732	1-519-108-99	LAMP, NEON				
		<TRANSISTOR>				
Q731	8-729-119-78	TRANSISTOR 2SC2785-HFE				
Q732	8-729-119-78	TRANSISTOR 2SC2785-HFE				
Q733	8-729-119-80	TRANSISTOR 2SC2688-LK				
Q734	8-729-255-12	TRANSISTOR 2SC2551-O				
Q735	8-729-200-17	TRANSISTOR 2SA1091-O				
Q736	8-729-200-17	TRANSISTOR 2SA1091-O				
		<RESISTOR>				
R731	1-202-847-00	SOLID	560K	20%	1/2W	
R732	1-202-814-11	SOLID	33K	20%	1/2W	
R733	1-202-818-00	SOLID	1K	20%	1/2W	
R734	1-202-842-11	SOLID	220K	20%	1/2W	
R735	1-202-828-11	SOLID	6.8K	20%	1/2W	
R736	1-202-561-00	SOLID	330	20%	1/2W	
R737	1-216-510-11	METAL OXIDE	8.2K	5%	5W	F
R738	1-249-405-11	CARBON	100	5%	1/4W	F

Using Closed Caption



1 Press C. CAPTION.

The closed caption mode appears. CC1, CC2, TEXT1, TEXT2 or CC OFF appears in sequence each time you press C.CAPTION.

CC OFF → CC 1 → CC 2 → TEXT 1 → TEXT 2



2 Press C.CAPTION repeatedly.

Select CC1 or CC2 to view Captions.
A Caption is a printed version of the dialogue or sound effects of a program. (The mode should be set to CC1 for most programs.)



Select TEXT1 or TEXT2 to view Text.
Text is information that is presented using the half to full television screen. It is usually not related to the program.



Select CC OFF if you don't want to view Closed Caption nor Text.



Using Convenient Features



Front inner panel



Muting the sound — MUTING

Press MUTING.
"MUTING" appears on the screen.

To restore the sound
Press MUTING again, or press VOL +.

Keeping the displays on-screen — DISPLAY

Press DISPLAY.
All the existing displays appear: channel number, channel caption (if set), MTS mode ("SAP" only), window picture input mode, and the current time ("AM" or "PM" disappears after about three seconds).

To turn off the displays
Press DISPLAY again.

Setting the sleep timer — SLEEP

The sleep timer turns off the projection TV automatically after the amount of time you select.

Press SLEEP.
Each time you press SLEEP, the time increments "30," "60," "90" and "OFF" mode appear in sequence.



A red "SLEEP" display appears about one minute before the projection TV goes off.

To cancel the setting.
Press SLEEP until OFF mode appears.
A green "SLEEP OFF" display appears for about three seconds.
OR
Turn the projection TV off.
The sleep timer setting is cancelled.

Switching quickly between two channels — JUMP

Use this function to keep track of two programs alternately.

To recall the channel you were watching previously
Press JUMP.

To switch back to the first channel
Press JUMP again.

Previewing the features — DEMO

Press DEMO (front inner panel).
Functions and menus are displayed one by one.

To restart DEMO from the beginning
Press DEMO again.

To stop DEMO
Press any button.

Les composants identifies par une trame et une marque ⚠ sont critiques pour la securite. Ne les remplacer que par une piece portant le numero specifie.

The components identified by shading and mark ⚠ are critical for safety. Replace only with part number specified.

CG | CB | V

REF.NO.	PART NO.	DESCRIPTION				REMARK
R739	1-249-405-11	CARBON	100	5%	1/4W	F
R740	1-215-927-00	METAL OXIDE	47K	5%	3W	F
R741	1-249-405-11	CARBON	100	5%	1/4W	F
R742	1-249-421-11	CARBON	2.2K	5%	1/4W	F
R744	1-249-401-11	CARBON	47	5%	1/4W	
R745	1-215-455-00	METAL	27K	1%	1/4W	
R746	1-249-405-11	CARBON	100	5%	1/4W	
R747	1-249-403-11	CARBON	68	5%	1/4W	
R748	1-249-412-11	CARBON	390	5%	1/4W	
R749	1-249-410-11	CARBON	270	5%	1/4W	
R750	1-249-405-11	CARBON	100	5%	1/4W	
R751	1-249-409-11	CARBON	220	5%	1/4W	
R752	1-215-423-00	METAL	1.2K	1%	1/4W	
R754	1-215-429-00	METAL	2.2K	1%	1/4W	
		<SPARK GAP>				
SG731	1-519-422-11	GAP, SPARK				
SG732	1-519-422-11	GAP, SPARK				
**********						
	*A-1331-261-A	CB BOARD, COMPLETE				
		**********				
	4-373-933-01	SHEET (TRANSISTOR), BN				
	4-382-854-11	SCREW (M3X10), P, SW (+)				
		<CAPACITOR>				
C761	1-162-115-00	CERAMIC	330PF	10%	2KV	
C762	1-123-948-00	ELECT	22MF	20%	250V	
C763	1-102-050-00	CERAMIC	0.01MF		500V	
C764	1-162-115-00	CERAMIC	330PF	10%	2KV	
C765	1-130-479-00	MYLAR	0.0047MF	5%	50V	
C766	1-101-006-00	CERAMIC	0.047MF		50V	
C767	1-101-006-00	CERAMIC	0.047MF		50V	
C769	1-124-120-11	ELECT	220MF	20%	16V	
C770	1-124-120-11	ELECT	220MF	20%	16V	
C771	1-102-114-00	CERAMIC	470PF	10%	50V	
		<CONNECTOR>				
CB1	*1-508-784-00	PIN, CONNECTOR (5MM PITCH) 1P				
CB3	*1-508-765-00	PIN, CONNECTOR (5MM PITCH) 3P				
CB4	*1-564-511-11	PLUG, CONNECTOR 8P				
CB5	*1-564-511-21	PLUG, CONNECTOR 8P				
CB17	*1-564-508-11	PLUG, CONNECTOR 5P				
		<PICTURE TUBE SOCKET>				
CRT761⚠	1-251-026-11	SOCKET, PICTURE TUBE				
		<DIODE>				
D761	8-719-911-19	DIODE 1SS119				
D762	8-719-911-19	DIODE 1SS119				
D763	8-719-911-19	DIODE 1SS119				
D764	8-719-911-19	DIODE 1SS119				
D765	8-719-911-19	DIODE 1SS119				
D766	8-719-911-19	DIODE 1SS119				
D768	8-719-911-19	DIODE 1SS119				
D769	8-719-109-81	DIODE RD4.7ES-B2				

REF.NO.	PART NO.	DESCRIPTION				REMARK
		<COIL>				
L761	1-408-429-00	INDUCTOR	470UH			
L762	1-408-159-00	COIL, SPOOK CHOKE	3.3UH			
L763	1-408-159-00	COIL, SPOOK CHOKE	3.3UH			
L764	1-408-413-00	INDUCTOR	22UH			
		<NEON LAMP>				
NL761	1-519-108-99	LAMP, NEON				
NL762	1-519-108-99	LAMP, NEON				
		<TRANSISTOR>				
Q761	8-729-119-78	TRANSISTOR 2SC2785-HFE				
Q762	8-729-119-78	TRANSISTOR 2SC2785-HFE				
Q763	8-729-119-80	TRANSISTOR 2SC2688-LK				
Q764	8-729-255-12	TRANSISTOR 2SC2551-O				
Q765	8-729-200-17	TRANSISTOR 2SA1091-O				
Q766	8-729-200-17	TRANSISTOR 2SA1091-O				
		<RESISTOR>				
R761	1-202-847-00	SOLID	560K	20%	1/2W	
R762	1-202-814-11	SOLID	33K	20%	1/2W	
R763	1-202-818-00	SOLID	1K	20%	1/2W	
R764	1-202-842-11	SOLID	220K	20%	1/2W	
R765	1-202-828-11	SOLID	6.8K	20%	1/2W	
R766	1-202-561-00	SOLID	330	20%	1/2W	
R767	1-216-510-11	METAL OXIDE	8.2K	5%	5W	F
R768	1-249-405-11	CARBON	100	5%	1/4W	F
R769	1-249-405-11	CARBON	100	5%	1/4W	F
R770	1-215-927-00	METAL OXIDE	47K	5%	3W	F
R771	1-249-405-11	CARBON	100	5%	1/4W	F
R772	1-249-421-11	CARBON	2.2K	5%	1/4W	F
R773	1-249-413-11	CARBON	470	5%	1/4W	
R774	1-249-401-11	CARBON	47	5%	1/4W	
R776	1-249-405-11	CARBON	100	5%	1/4W	
R777	1-249-403-11	CARBON	68	5%	1/4W	
R778	1-249-412-11	CARBON	390	5%	1/4W	
R779	1-249-415-11	CARBON	680	5%	1/4W	
R780	1-249-405-11	CARBON	100	5%	1/4W	
R781	1-249-409-11	CARBON	220	5%	1/4W	
R782	1-215-423-00	METAL	1.2K	1%	1/4W	
R783	1-215-433-00	METAL	3.3K	1%	1/4W	
R784	1-215-429-00	METAL	2.2K	1%	1/4W	
R785	1-215-418-00	METAL	750	1%	1/4W	
		<SPARK GAP>				
SG761	1-519-422-11	GAP, SPARK				
SG762	1-519-422-11	GAP, SPARK				
**********						
	*A-1342-214-A	V BOARD, COMPLETE				
		**********				
	*4-395-527-01	HOLDER (B), TR				
		<CAPACITOR>				
C1501	1-102-129-00	CERAMIC	0.01MF	10%	50V	
C1502	1-126-101-11	ELECT	100MF	20%	16V	
C1504	1-106-383-00	MYLAR	0.047MF		200V	
C1505	1-124-907-11	ELECT	10MF	20%	50V	
C1506	1-106-359-00	MYLAR	0.0047MF	10%	200V	

REF.NO.	PART NO.	DESCRIPTION				REMARK
C1507	1-106-367-00	MYLAR	0.01MF	10%	100V	
C1508	1-162-318-11	CERAMIC	0.001MF	10%	500V	
C1509	1-106-367-00	MYLAR	0.01MF	10%	100V	
C1510	1-126-355-11	ELECT	33MF	20%	160V	
C1511	1-124-668-11	ELECT	2.2MF	20%	200V	
C1512	1-106-391-12	MYLAR	0.1MF	10%	200V	
C1513	1-162-318-11	CERAMIC	0.001MF	10%	500V	
C1514	1-102-951-00	CERAMIC	15PF	5%	50V	
C1515	1-102-959-00	CERAMIC	22PF	5%	50V	
C1516	1-102-963-00	CERAMIC	33PF	5%	50V	
C1517	1-123-875-11	ELECT	10MF	20%	50V	
C1518	1-102-074-00	CERAMIC	0.001MF	10%	50V	
C1519	1-106-359-00	MYLAR	0.0047MF	10%	200V	
C1520	1-126-803-11	ELECT	47MF	20%	16V	
C1521	1-124-907-11	ELECT	10MF	20%	50V	
C1534	1-101-003-00	CERAMIC	0.0047MF		50V	
C1551	1-124-122-11	ELECT	100MF	20%	50V	
C1552	1-124-122-11	ELECT	100MF	20%	50V	
C1553	1-102-824-00	CERAMIC	470PF	5%	50V	
C1554	1-102-824-00	CERAMIC	470PF	5%	50V	
C1555	1-130-483-00	MYLAR	0.01MF	5%	50V	
C1556	1-130-483-00	MYLAR	0.01MF	5%	50V	
C1557	1-102-824-00	CERAMIC	470PF	5%	50V	
C1558	1-102-824-00	CERAMIC	470PF	5%	50V	
C1559	1-102-824-00	CERAMIC	470PF	5%	50V	
C1560	1-102-824-00	CERAMIC	470PF	5%	50V	
C1561	1-130-483-00	MYLAR	0.01MF	5%	50V	
C1562	1-130-483-00	MYLAR	0.01MF	5%	50V	
C1563	1-130-483-00	MYLAR	0.01MF	5%	50V	

<DIODE>

D1501	8-719-911-19	DIODE 1SS119	
D1502	8-719-911-19	DIODE 1SS119	
D1503	8-719-911-19	DIODE 1SS119	
D1504	8-719-911-19	DIODE 1SS119	
D1505	8-719-911-19	DIODE 1SS119	
D1506	8-719-911-19	DIODE 1SS119	
D1507	8-719-110-88	DIODE RD39ES-B2	
D1508	8-719-110-88	DIODE RD39ES-B2	
D1509	8-719-911-19	DIODE 1SS119	

<IC>

IC1551	8-759-145-58	IC UPC4558C	
IC1552	8-759-912-77	IC LM324N	

<COIL>

L1502	1-408-418-00	INDUCTOR	56UH

<TRANSISTOR>

Q1501	8-729-208-39	TRANSISTOR 2SA1306A-Y	
Q1502	8-729-017-06	TRANSISTOR 2SC4793	
Q1503	8-729-119-78	TRANSISTOR 2SC2785-HFE	
Q1504	8-729-119-78	TRANSISTOR 2SC2785-HFE	
Q1505	8-729-119-76	TRANSISTOR 2SA1175-HFE	
Q1506	8-729-119-78	TRANSISTOR 2SC2785-HFE	
Q1507	8-729-119-78	TRANSISTOR 2SC2785-HFE	
Q1508	8-729-142-86	TRANSISTOR 2SC3733	
Q1551	8-729-231-60	TRANSISTOR 2SD1406-YGR	
Q1552	8-729-202-02	TRANSISTOR 2SB1015-Y	
Q1553	8-729-231-60	TRANSISTOR 2SD1406-YGR	
Q1554	8-729-202-02	TRANSISTOR 2SB1015-Y	
Q1555	8-729-231-60	TRANSISTOR 2SD1406-YGR	
Q1556	8-729-202-02	TRANSISTOR 2SB1015-Y	

<RESISTOR>

R1501	1-249-451-11	CARBON	2.2	5%	1/4W	F
R1502	1-249-414-11	CARBON	560	5%	1/4W	F
R1503	1-247-734-11	CARBON	39	5%	1/2W	F
R1504	1-249-384-11	CARBON	1.8	5%	1/4W	F
R1505	1-249-405-11	CARBON	100	5%	1/4W	
R1506	1-249-419-11	CARBON	1.5K	5%	1/4W	
R1507	1-249-412-11	CARBON	390	5%	1/4W	
R1508	1-249-436-11	CARBON	39K	5%	1/4W	
R1509	1-249-421-11	CARBON	2.2K	5%	1/4W	
R1510	1-249-436-11	CARBON	39K	5%	1/4W	
R1511	1-249-418-11	CARBON	1.2K	5%	1/4W	
R1512	1-249-441-11	CARBON	100K	5%	1/4W	
R1513	1-249-432-11	CARBON	18K	5%	1/4W	
R1514	1-249-405-11	CARBON	100	5%	1/4W	
R1515	1-249-435-11	CARBON	33K	5%	1/4W	
R1517	1-247-713-11	CARBON	1K	5%	1/4W	F
R1519	1-215-916-00	METAL OXIDE	680	5%	3W	F
R1520	1-249-432-11	CARBON	18K	5%	1/4W	
R1521	1-249-414-11	CARBON	560	5%	1/4W	
R1522	1-249-384-11	CARBON	1.8	5%	1/4W	F
R1523	1-249-400-11	CARBON	39	5%	1/4W	F
R1524	1-249-418-11	CARBON	1.2K	5%	1/4W	
R1525	1-249-421-11	CARBON	2.2K	5%	1/4W	
R1526	1-249-426-11	CARBON	5.6K	5%	1/4W	
R1527	1-249-414-11	CARBON	560	5%	1/4W	
R1528	1-249-429-11	CARBON	10K	5%	1/4W	
R1529	1-249-414-11	CARBON	560	5%	1/4W	
R1530	1-216-451-11	METAL OXIDE	120	5%	2W	F
R1531	1-249-429-11	CARBON	10K	5%	1/4W	
R1532	1-249-421-11	CARBON	2.2K	5%	1/4W	
R1533	1-247-903-91	CARBON	1M	5%	1/4W	
R1534	1-249-423-11	CARBON	3.3K	5%	1/4W	
R1535	1-249-392-11	CARBON	8.2	5%	1/4W	F
R1540	1-215-445-00	METAL	10K	1%	1/4W	
R1541	1-215-445-00	METAL	10K	1%	1/4W	
R1542	1-215-445-00	METAL	10K	1%	1/4W	
R1551	1-215-445-00	METAL	10K	1%	1/4W	
R1552	1-215-423-00	METAL	1.2K	1%	1/4W	
R1553	1-249-417-11	CARBON	1K	5%	1/4W	
R1554	1-215-445-00	METAL	10K	1%	1/4W	
R1555	1-215-375-00	METAL	12	1%	1/4W	
R1556	1-215-375-00	METAL	12	1%	1/4W	
R1557	1-215-375-00	METAL	12	1%	1/4W	
R1558	1-215-445-00	METAL	10K	1%	1/4W	
R1559	1-215-445-00	METAL	10K	1%	1/4W	
R1560	1-215-445-00	METAL	10K	1%	1/4W	
R1561	1-215-423-00	METAL	1.2K	1%	1/4W	
R1562	1-215-423-00	METAL	1.2K	1%	1/4W	
R1563	1-215-445-00	METAL	10K	1%	1/4W	
R1564	1-249-417-11	CARBON	1K	5%	1/4W	
R1565	1-215-445-00	METAL	10K	1%	1/4W	
R1566	1-215-375-00	METAL	12	1%	1/4W	
R1567	1-215-375-00	METAL	12	1%	1/4W	
R1568	1-215-375-00	METAL	12	1%	1/4W	
R1569	1-215-445-00	METAL	10K	1%	1/4W	
R1570	1-215-445-00	METAL	10K	1%	1/4W	
R1571	1-249-417-11	CARBON	1K	5%	1/4W	
R1572	1-215-445-00	METAL	10K	1%	1/4W	

V D

REF.NO.	PART NO.	DESCRIPTION				REMARK
R1573	1-215-375-00	METAL	12	1%	1/4W	
R1574	1-215-375-00	METAL	12	1%	1/4W	
R1575	1-215-375-00	METAL	12	1%	1/4W	
R1576	1-215-445-00	METAL	10K	1%	1/4W	
R1577	1-215-445-00	METAL	10K	1%	1/4W	
R1578	1-249-417-11	CARBON	1K	5%	1/4W	
R1579	1-249-417-11	CARBON	1K	5%	1/4W	
R1580	1-249-417-11	CARBON	1K	5%	1/4W	
R1581	1-249-432-11	CARBON	18K	5%	1/4W	
R1582	1-249-432-11	CARBON	18K	5%	1/4W	
		<CONNECTOR>				
V2	*1-564-518-11	PLUG, CONNECTOR 3P				
V22	1-573-300-11	CONNECTOR, BOARD TO BOARD 18P				
		**********				
	*A-1346-117-A	D BOARD, COMPLETE				
		**********				
	1-533-223-11	CLIP, FUSE				
	4-382-854-11	SCREW (M3X10), P, SW (+)				
	*4-395-527-01	HOLDER (B), TR				
		<CAPACITOR>				
C901	1-126-320-11	ELECT	10MF	20%	16V	
C902	1-124-477-11	ELECT	47MF	20%	16V	
C903	1-130-471-00	MYLAR	0.001MF	5%	50V	
C904	1-130-471-00	MYLAR	0.001MF	5%	50V	
C905	1-124-477-11	ELECT	47MF	20%	16V	
C906	1-126-233-11	ELECT	22MF	20%	50V	
C907	1-126-101-11	ELECT	100MF	20%	16V	
C908	1-124-907-11	ELECT	10MF	20%	50V	
C910	1-130-483-00	MYLAR	0.01MF	5%	50V	
C911	1-131-341-00	TANTALUM	0.1MF	20%	16V	
C912	1-124-903-11	ELECT	1MF	20%	50V	
C913	1-126-233-11	ELECT	22MF	20%	50V	
C914	1-126-803-11	ELECT	47MF	20%	16V	
C915	1-124-927-11	ELECT	4.7MF	20%	50V	
C916	1-102-074-00	CERAMIC	0.001MF	10%	50V	
C917	1-130-471-00	MYLAR	0.001MF	5%	50V	
C918	1-102-963-00	CERAMIC	33PF	5%	50V	
C919	1-102-963-00	CERAMIC	33PF	5%	50V	
C920	1-102-963-00	CERAMIC	33PF	5%	50V	
C921	1-102-963-00	CERAMIC	33PF	5%	50V	
C922	1-102-963-00	CERAMIC	33PF	5%	50V	
C923	1-102-963-00	CERAMIC	33PF	5%	50V	
C931	1-102-973-00	CERAMIC	100PF	5%	50V	
C932	1-124-903-11	ELECT	1MF	20%	50V	
C933	1-124-234-00	ELECT	22MF	20%	16V	
C934	1-124-234-00	ELECT	22MF	20%	16V	
C935	1-124-234-00	ELECT	22MF	20%	16V	
C936	1-124-234-00	ELECT	22MF	20%	16V	
C937	1-124-234-00	ELECT	22MF	20%	16V	
C938	1-124-234-00	ELECT	22MF	20%	16V	
C939	1-124-234-00	ELECT	22MF	20%	16V	
C940	1-124-916-11	ELECT	22MF	20%	25V	
C941	1-102-123-00	CERAMIC	0.0033MF	10%	50V	
C942	1-102-123-00	CERAMIC	0.0033MF	10%	50V	
C943	1-102-123-00	CERAMIC	0.0033MF	10%	50V	
C1701	1-124-907-11	ELECT	10MF	20%	50V	
C1702	1-124-907-11	ELECT	10MF	20%	50V	
C1703	1-124-907-11	ELECT	10MF	20%	50V	
C1704	1-123-875-11	ELECT	10MF	20%	50V	
C1705	1-102-963-00	CERAMIC	33PF	5%	50V	
C1706	1-102-963-00	CERAMIC	33PF	5%	50V	
C1707	1-102-963-00	CERAMIC	33PF	5%	50V	
C1708	1-102-963-00	CERAMIC	33PF	5%	50V	
C1709	1-102-963-00	CERAMIC	33PF	5%	50V	
C1710	1-102-963-00	CERAMIC	33PF	5%	50V	
C1711	1-126-233-11	ELECT	22MF	20%	50V	
C1712	1-124-916-11	ELECT	22MF	20%	25V	
C1713	1-102-074-00	CERAMIC	0.001MF	10%	50V	
C1714	1-124-478-11	ELECT	100MF	20%	25V	
C1715	1-124-478-11	ELECT	100MF	20%	25V	
C1716	1-126-803-11	ELECT	47MF	20%	25V	
C1717	1-126-803-11	ELECT	47MF	20%	25V	
C1718	1-102-074-00	CERAMIC	0.001MF	10%	50V	
C1719	1-124-234-00	ELECT	22MF	20%	16V	
C1720	1-130-491-00	MYLAR	0.047MF	5%	50V	
C1721	1-130-491-00	MYLAR	0.047MF	5%	50V	
C1722	1-130-491-00	MYLAR	0.047MF	5%	50V	
C1724	1-124-234-00	ELECT	22MF	20%	16V	
C1725	1-102-963-00	CERAMIC	33PF	5%	50V	
C1726	1-124-122-11	ELECT	100MF	20%	35V	
C1727	1-102-963-00	CERAMIC	33PF	5%	50V	
C1728	1-102-963-00	CERAMIC	33PF	5%	50V	
C1729	1-108-426-91	MYLAR	0.027MF		200V	
C1730	1-102-963-00	CERAMIC	33PF	5%	50V	
C1731	1-124-122-11	ELECT	100MF	20%	35V	
C1732	1-108-426-91	MYLAR	0.027MF		200V	
C1733	1-102-963-00	CERAMIC	33PF	5%	50V	
C1734	1-102-963-00	CERAMIC	33PF	5%	50V	
C1735	1-124-122-11	ELECT	100MF	20%	35V	
C1736	1-108-426-91	MYLAR	0.027MF		200V	
C1737	1-124-937-11	ELECT	10MF	20%	16V	
C1738	1-124-122-11	ELECT	100MF	20%	35V	
C1739	1-136-153-00	FILM	0.01MF	5%	50V	
C1740	1-124-122-11	ELECT	100MF	20%	35V	
C1741	1-124-122-11	ELECT	100MF	20%	35V	
C1742	1-126-104-11	ELECT	470MF	20%	35V	
C1744	1-124-478-11	ELECT	100MF	20%	25V	
C1745	1-126-375-11	ELECT	100MF	20%	25V	
C1755	1-106-220-00	MYLAR	0.1MF	10%	100V	
C1756	1-106-220-00	MYLAR	0.1MF	10%	100V	
C1757	1-106-220-00	MYLAR	0.1MF	10%	100V	
C1758	1-106-220-00	MYLAR	0.1MF	10%	100V	
C1759	1-106-220-00	MYLAR	0.1MF	10%	100V	
C1760	1-106-220-00	MYLAR	0.1MF	10%	100V	
C1763	1-126-096-11	ELECT	10MF	20%	25V	
C1764	1-124-477-11	ELECT	47MF	20%	16V	
C1765	1-124-477-11	ELECT	47MF	20%	16V	
C1766	1-126-101-11	ELECT	100MF	20%	16V	
C1769	1-126-157-11	ELECT	10MF	20%	16V	
C1770	1-130-495-00	MYLAR	0.1MF	5%	50V	
C1771	1-126-096-11	ELECT	10MF	20%	25V	
C1772	1-126-096-11	ELECT	10MF	20%	25V	
C1861	1-102-074-00	CERAMIC	0.001MF	10%	50V	
		<CONNECTOR>				
D1	*1-564-510-11	PLUG, CONNECTOR 7P				
D2	*1-564-511-11	PLUG, CONNECTOR 8P				
D3	*1-564-512-11	PLUG, CONNECTOR 9P				
D4	*1-564-508-11	PLUG, CONNECTOR 5P				
D5	*1-564-511-11	PLUG, CONNECTOR 8P				
D6	1-691-169-11	PIN, CONNECTOR 12P				

The components identified by shading and mark ⚠ are critical for safety.
Replace only with part number specified.

Les composants identifies par une trame et une marque ⚠ sont critiques pour la securite.
Ne les remplacer que par une piece portant le numero specifie.

REF.NO.	PART NO.	DESCRIPTION	REMARK
D7	*1-564-507-11	PLUG, CONNECTOR 4P	
D8	*1-564-506-11	PLUG, CONNECTOR 3P	
D9	*1-564-507-11	PLUG, CONNECTOR 4P	
D14	*1-564-513-31	PLUG, CONNECTOR 10P	
		<DIODE>	
D901	8-719-911-19	DIODE 1SS119	
D902	8-719-911-19	DIODE 1SS119	
D1701	8-719-900-95	DIODE V09G	
D1702	8-719-911-19	DIODE 1SS119	
D1703	8-719-900-95	DIODE V09G	
D1704	8-719-900-95	DIODE V09G	
D1705	8-719-900-95	DIODE V09G	
D1706	8-719-900-95	DIODE V09G	
D1707	8-719-911-19	DIODE 1SS119	
D1708	8-719-911-19	DIODE 1SS119	
D1709	8-719-911-19	DIODE 1SS119	
D1710	8-719-911-19	DIODE 1SS119	
D1711	8-719-911-19	DIODE 1SS119	
D1712	8-719-911-19	DIODE 1SS119	
D1713	8-719-911-19	DIODE 1SS119	
D1714	8-719-911-19	DIODE 1SS119	
D1715	8-719-911-19	DIODE 1SS119	
D1716	8-719-911-19	DIODE 1SS119	
D1717	8-719-911-19	DIODE 1SS119	
D1718	8-719-911-19	DIODE 1SS119	
D1720	8-719-109-50	DIODE RD2.0ES-B1	
D1721	8-719-109-50	DIODE RD2.0ES-B1	
D1722	8-719-109-50	DIODE RD2.0ES-B1	
D1723	8-719-109-50	DIODE RD2.0ES-B1	
		<FUSE>	
F901 ⚠	1-532-745-11	FUSE, GLASS TUBE 3.15A/125V	
F902 ⚠	1-532-745-11	FUSE, GLASS TUBE 3.15A/125V	
		<IC>	
IC901	8-759-145-58	IC UPC4558C	
IC902	8-752-033-68	IC CXA1268P	
IC903	8-759-701-56	IC NJM78M05FA	
IC904	8-759-701-65	IC NJM79M05FA	
IC905	8-759-701-89	IC NJM7915FA	
IC906	8-759-148-84	IC UPC2415HF	
IC907	8-759-140-53	IC UPD4053BC	
IC908	8-759-145-58	IC UPC4558C	
IC910	8-759-054-40	IC PA0036	
IC1701	8-759-602-19	IC M5220L	
IC1702	8-759-602-19	IC M5220L	
IC1703	8-759-602-19	IC M5220L	
IC1704	8-749-923-16	IC STK4278-L	
IC1705	8-749-923-16	IC STK4278-L	
IC1706	8-759-113-13	IC UPC1498H	
IC1707	8-759-113-13	IC UPC1498H	
IC1708	8-759-113-13	IC UPC1498H	
IC1709	8-759-145-58	IC UPC4558C	
IC1710	8-759-145-58	IC UPC4558C	
IC1714	8-759-145-58	IC UPC4558C	
IC1715	8-759-145-58	IC UPC4558C	
IC1718	8-759-145-58	IC UPC4558C	

REF.NO.	PART NO.	DESCRIPTION	REMARK
		<COIL>	
L901	1-459-313-00	COIL WITH CORE (HWC)	
L902	1-459-313-00	COIL WITH CORE (HWC)	
L903	1-459-313-00	COIL WITH CORE (HWC)	
L904	1-459-313-00	COIL WITH CORE (HWC)	
		<TRANSISTOR>	
Q902	8-729-900-89	TRANSISTOR DTC144ES	
Q906	8-729-119-78	TRANSISTOR 2SC2785-HFE	
Q907	8-729-119-78	TRANSISTOR 2SC2785-HFE	
Q908	8-729-900-89	TRANSISTOR DTC144ES	
Q909	8-729-119-78	TRANSISTOR 2SC2785-HFE	
Q910	8-729-119-78	TRANSISTOR 2SC2785-HFE	
Q911	8-729-119-76	TRANSISTOR 2SA1175-HFE	
Q912	8-729-119-76	TRANSISTOR 2SA1175-HFE	
		<RESISTOR>	
R901	1-215-463-00	METAL 56K 1% 1/4W	
R902	1-215-463-00	METAL 56K 1% 1/4W	
R903	1-215-449-00	METAL 15K 1% 1/4W	
R904	1-215-455-00	METAL 27K 1% 1/4W	
R905	1-215-449-00	METAL 15K 1% 1/4W	
R906	1-215-469-00	METAL 100K 1% 1/4W	
R907	1-215-469-00	METAL 100K 1% 1/4W	
R908	1-215-469-00	METAL 100K 1% 1/4W	
R909	1-215-473-00	METAL 150K 1% 1/4W	
R910	1-215-437-00	METAL 4.7K 1% 1/4W	
R911	1-215-453-00	METAL 22K 1% 1/4W	
R912	1-215-453-00	METAL 22K 1% 1/4W	
R913	1-215-437-00	METAL 4.7K 1% 1/4W	
R914	1-215-453-00	METAL 22K 1% 1/4W	
R915	1-215-413-00	METAL 470 1% 1/4W	
R916	1-215-457-00	METAL 33K 1% 1/4W	
R917	1-215-453-00	METAL 22K 1% 1/4W	
R919	1-215-399-00	METAL 120 1% 1/4W	
R920	1-215-399-00	METAL 120 1% 1/4W	
R921	1-215-399-00	METAL 120 1% 1/4W	
R922	1-215-399-00	METAL 120 1% 1/4W	
R923	1-215-441-00	METAL 6.8K 1% 1/4W	
R924	1-215-441-00	METAL 6.8K 1% 1/4W	
R925	1-215-441-00	METAL 6.8K 1% 1/4W	
R926	1-215-463-00	METAL 56K 1% 1/4W	
R927	1-215-463-00	METAL 56K 1% 1/4W	
R928	1-215-461-00	METAL 47K 1% 1/4W	
R929	1-215-433-00	METAL 3.3K 1% 1/4W	
R930	1-215-433-00	METAL 3.3K 1% 1/4W	
R931	1-215-433-00	METAL 3.3K 1% 1/4W	
R932	1-215-433-00	METAL 3.3K 1% 1/4W	
R933	1-215-433-00	METAL 3.3K 1% 1/4W	
R934	1-215-433-00	METAL 3.3K 1% 1/4W	
R935	1-215-439-00	METAL 5.6K 1% 1/4W	
R936	1-215-439-00	METAL 5.6K 1% 1/4W	
R937	1-215-439-00	METAL 5.6K 1% 1/4W	
R938	1-215-417-00	METAL 680 1% 1/4W	
R939	1-215-433-00	METAL 3.3K 1% 1/4W	
R940	1-215-429-00	METAL 2.2K 1% 1/4W	
R941	1-215-441-00	METAL 6.8K 1% 1/4W	
R942	1-215-451-00	METAL 18K 1% 1/4W	
R943	1-215-441-00	METAL 6.8K 1% 1/4W	
R944	1-215-439-00	METAL 5.6K 1% 1/4W	
R945	1-215-445-00	METAL 10K 1% 1/4W	
R946	1-215-445-00	METAL 10K 1% 1/4W	
R947	1-215-439-00	METAL 5.6K 1% 1/4W	

D

REF.NO.	PART NO.	DESCRIPTION				REMARK
R948	1-215-447-00	METAL	12K	1%	1/4W	
R949	1-215-439-00	METAL	5.6K	1%	1/4W	
R950	1-215-429-00	METAL	2.2K	1%	1/4W	
R951	1-215-429-00	METAL	2.2K	1%	1/4W	
R952	1-215-429-00	METAL	2.2K	1%	1/4W	
R953	1-215-439-00	METAL	5.6K	1%	1/4W	
R954	1-215-439-00	METAL	5.6K	1%	1/4W	
R955	1-215-435-00	METAL	3.9K	1%	1/4W	
R956	1-215-437-00	METAL	4.7K	1%	1/4W	
R957	1-215-441-00	METAL	6.8K	1%	1/4W	
R958	1-215-437-00	METAL	4.7K	1%	1/4W	
R959	1-215-439-00	METAL	5.6K	1%	1/4W	
R960	1-215-439-00	METAL	5.6K	1%	1/4W	
R961	1-215-439-00	METAL	5.6K	1%	1/4W	
R962	1-215-441-00	METAL	6.8K	1%	1/4W	
R963	1-215-441-00	METAL	6.8K	1%	1/4W	
R964	1-215-441-00	METAL	6.8K	1%	1/4W	
R965	1-215-909-11	METAL OXIDE	47	5%	3W	F
R966	1-215-469-00	METAL	100K	1%	1/4W	
R967	1-215-421-00	METAL	1K	1%	1/4W	
R968	1-215-437-00	METAL	4.7K	1%	1/4W	
R969	1-249-421-11	CARBON	2.2K	5%	1/4W	
R970	1-215-909-11	METAL OXIDE	47	5%	3W	F
R971	1-249-421-11	CARBON	2.2K	5%	1/4W	
R972	1-249-431-11	CARBON	15K	5%	1/4W	
R973	1-249-431-11	CARBON	15K	5%	1/4W	
R974	1-215-399-00	METAL	120	1%	1/4W	
R975	1-215-399-00	METAL	120	1%	1/4W	
R976	1-215-399-00	METAL	120	1%	1/4W	
R977	1-215-399-00	METAL	120	1%	1/4W	
R978	1-215-399-00	METAL	120	1%	1/4W	
R979	1-215-399-00	METAL	120	1%	1/4W	
R980	1-215-399-00	METAL	120	1%	1/4W	
R981	1-215-399-00	METAL	120	1%	1/4W	
R982	1-249-431-11	CARBON	15K	5%	1/4W	
R983	1-249-431-11	CARBON	15K	5%	1/4W	
R984	1-214-804-11	METAL	3.3	1%	1/2W	
R985	1-214-804-11	METAL	3.3	1%	1/2W	
R986	1-214-804-11	METAL	3.3	1%	1/2W	
R987	1-215-421-00	METAL	1K	1%	1/4W	
R988	1-215-421-00	METAL	1K	1%	1/4W	
R989	1-215-421-00	METAL	1K	1%	1/4W	
R990	1-215-421-00	METAL	1K	1%	1/4W	
R991	1-215-421-00	METAL	1K	1%	1/4W	
R992	1-215-421-00	METAL	1K	1%	1/4W	
R993	1-249-429-11	CARBON	10K	5%	1/4W	
R994	1-249-429-11	CARBON	10K	5%	1/4W	
R995	1-215-457-00	METAL	33K	1%	1/4W	
R997	1-215-463-00	METAL	56K	1%	1/4W	
R998	1-215-409-00	METAL	330	1%	1/4W	
R999	1-215-455-00	METAL	27K	1%	1/4W	
R1701	1-249-411-11	CARBON	330	5%	1/4W	
R1702	1-249-427-11	CARBON	6.8K	5%	1/4W	
R1703	1-249-427-11	CARBON	6.8K	5%	1/4W	
R1704	1-249-411-11	CARBON	330	5%	1/4W	
R1705	1-249-411-11	CARBON	330	5%	1/4W	
R1706	1-249-427-11	CARBON	6.8K	5%	1/4W	
R1707	1-249-411-11	CARBON	330	5%	1/4W	
R1708	1-249-427-11	CARBON	6.8K	5%	1/4W	
R1709	1-249-427-11	CARBON	6.8K	5%	1/4W	
R1710	1-249-411-11	CARBON	330	5%	1/4W	
R1711	1-249-411-11	CARBON	330	5%	1/4W	
R1712	1-249-427-11	CARBON	6.8K	5%	1/4W	
R1713	1-215-886-11	METAL OXIDE	100	5%	2W	F
R1714	1-249-411-11	CARBON	330	5%	1/4W	
R1715	1-249-411-11	CARBON	330	5%	1/4W	
R1716	1-215-886-11	METAL OXIDE	100	5%	2W	F
R1717	1-249-411-11	CARBON	330	5%	1/4W	
R1718	1-249-417-11	CARBON	1K	5%	1/4W	
R1719	1-214-792-00	METAL	1	1%	1/2W	
R1720	1-249-411-11	CARBON	330	5%	1/4W	
R1721	1-249-417-11	CARBON	1K	5%	1/4W	
R1722	1-249-411-11	CARBON	330	5%	1/4W	
R1723	1-249-417-11	CARBON	1K	5%	1/4W	
R1724	1-215-886-11	METAL OXIDE	100	5%	2W	F
R1725	1-215-886-11	METAL OXIDE	100	5%	2W	F
R1726	1-215-886-11	METAL OXIDE	100	5%	2W	F
R1727	1-214-792-00	METAL	1	1%	1/2W	
R1728	1-214-792-00	METAL	1	1%	1/2W	
R1729	1-214-792-00	METAL	1	1%	1/2W	
R1730	1-249-405-11	CARBON	100	5%	1/4W	
R1731	1-249-417-11	CARBON	1K	5%	1/4W	
R1732	1-249-405-11	CARBON	100	5%	1/4W	
R1733	1-249-405-11	CARBON	100	5%	1/4W	
R1734	1-249-405-11	CARBON	100	5%	1/4W	
R1735	1-249-405-11	CARBON	100	5%	1/4W	
R1736	1-249-423-11	CARBON	3.3K	5%	1/4W	
R1737	1-249-423-11	CARBON	3.3K	5%	1/4W	
R1738	1-249-423-11	CARBON	3.3K	5%	1/4W	
R1739	1-249-423-11	CARBON	3.3K	5%	1/4W	
R1740	1-249-417-11	CARBON	1K	5%	1/4W	
R1741	1-249-423-11	CARBON	3.3K	5%	1/4W	
R1742	1-249-423-11	CARBON	3.3K	5%	1/4W	
R1743	1-249-417-11	CARBON	1K	5%	1/4W	
R1744	1-249-411-11	CARBON	330	5%	1/4W	
R1745	1-249-405-11	CARBON	100	5%	1/4W	
R1746	1-214-792-00	METAL	1	1%	1/2W	
R1747	1-215-886-11	METAL OXIDE	100	5%	2W	F
R1748	1-215-421-00	METAL	1K	1%	1/4W	
R1749	1-215-421-00	METAL	1K	1%	1/4W	
R1750	1-215-421-00	METAL	1K	1%	1/4W	
R1751	1-215-421-00	METAL	1K	1%	1/4W	
R1752	1-215-421-00	METAL	1K	1%	1/4W	
R1753	1-215-421-00	METAL	1K	1%	1/4W	
R1754	1-214-792-00	METAL	1	1%	1/2W	
R1755	1-215-469-00	METAL	100K	1%	1/4W	
R1756	1-215-437-00	METAL	4.7K	1%	1/4W	
R1757	1-215-437-00	METAL	4.7K	1%	1/4W	
R1758	1-215-437-00	METAL	4.7K	1%	1/4W	
R1759	1-249-405-11	CARBON	100	5%	1/4W	
R1760	1-249-427-11	CARBON	6.8K	5%	1/4W	
R1761	1-249-419-11	CARBON	1.5K	5%	1/4W	
R1762	1-215-445-00	METAL	10K	1%	1/4W	
R1763	1-249-427-11	CARBON	6.8K	5%	1/4W	
R1764	1-249-419-11	CARBON	1.5K	5%	1/4W	
R1765	1-249-419-11	CARBON	1.5K	5%	1/4W	
R1766	1-249-427-11	CARBON	6.8K	5%	1/4W	
R1767	1-249-427-11	CARBON	6.8K	5%	1/4W	
R1768	1-249-439-11	CARBON	68K	5%	1/4W	
R1769	1-215-445-00	METAL	10K	1%	1/4W	
R1770	1-249-405-11	CARBON	100	5%	1/4W	
R1771	1-249-405-11	CARBON	100	5%	1/4W	
R1772	1-215-429-00	METAL	2.2K	1%	1/4W	
R1773	1-215-429-00	METAL	2.2K	1%	1/4W	
R1774	1-215-421-00	METAL	1K	1%	1/4W	
R1775	1-249-429-11	CARBON	10K	5%	1/4W	
R1776	1-215-421-00	METAL	1K	1%	1/4W	

REF.NO.	PART NO.	DESCRIPTION				REMARK
R1777	1-249-423-11	CARBON	3.3K	5%	1/4W	
R1778	1-215-421-00	METAL	1K	1%	1/4W	
R1779	1-215-898-11	METAL OXIDE	10K	5%	2W	F
R1780	1-214-804-11	METAL	3.3	1%	1/2W	
R1781	1-214-804-11	METAL	3.3	1%	1/2W	
R1782	1-215-898-11	METAL OXIDE	10K	5%	2W	F
R1783	1-214-804-11	METAL	3.3	1%	1/2W	
R1784	1-214-804-11	METAL	3.3	1%	1/2W	
R1785	1-215-898-11	METAL OXIDE	10K	5%	2W	F
R1786	1-214-804-11	METAL	3.3	1%	1/2W	
R1787	1-214-804-11	METAL	3.3	1%	1/2W	
R1788	1-249-433-11	CARBON	22K	5%	1/4W	
R1789	1-249-441-11	CARBON	100K	5%	1/4W	
R1790	1-249-433-11	CARBON	22K	5%	1/4W	
R1791	1-249-429-11	CARBON	10K	5%	1/4W	
R1792	1-215-445-00	METAL	10K	1%	1/4W	
R1793	1-249-405-11	CARBON	100	5%	1/4W	
R1794	1-215-429-00	METAL	2.2K	1%	1/4W	
R1795	1-249-433-11	CARBON	22K	5%	1/4W	
R1796	1-249-405-11	CARBON	100	5%	1/4W	
R1797	1-249-429-11	CARBON	10K	5%	1/4W	
R1798	1-249-423-11	CARBON	3.3K	5%	1/4W	
R1800	1-249-405-11	CARBON	100	5%	1/4W	
R1801	1-215-439-00	METAL	5.6K	1%	1/4W	
R1802	1-215-439-00	METAL	5.6K	1%	1/4W	
R1803	1-215-439-00	METAL	5.6K	1%	1/4W	
R1805	1-215-439-00	METAL	5.6K	1%	1/4W	
R1806	1-249-405-11	CARBON	100	5%	1/4W	
R1807	1-249-405-11	CARBON	100	5%	1/4W	
R1808	1-214-792-00	METAL	1	1%	1/2W	
R1809	1-214-792-00	METAL	1	1%	1/2W	
R1810	1-214-792-00	METAL	1	1%	1/2W	
R1811	1-214-792-00	METAL	1	1%	1/2W	
R1812	1-214-792-00	METAL	1	1%	1/2W	
R1813	1-214-792-00	METAL	1	1%	1/2W	
R1814	1-249-431-11	CARBON	15K	5%	1/4W	
R1815	1-247-885-00	CARBON	180K	5%	1/4W	
R1816	1-249-431-11	CARBON	15K	5%	1/4W	
R1817	1-247-885-00	CARBON	180K	5%	1/4W	
R1818	1-249-405-11	CARBON	100	5%	1/4W	
R1819	1-215-437-00	METAL	4.7K	1%	1/4W	
R1820	1-215-437-00	METAL	4.7K	1%	1/4W	
R1821	1-215-437-00	METAL	4.7K	1%	1/4W	
R1822	1-215-445-00	METAL	10K	1%	1/4W	
R1823	1-215-445-00	METAL	10K	1%	1/4W	
R1824	1-215-433-00	METAL	3.3K	1%	1/4W	
R1825	1-215-433-00	METAL	3.3K	1%	1/4W	
R1826	1-215-433-00	METAL	3.3K	1%	1/4W	
R1827	1-215-445-00	METAL	10K	1%	1/4W	
R1828	1-215-445-00	METAL	10K	1%	1/4W	
R1829	1-249-434-11	CARBON	27K	5%	1/4W	
R1830	1-249-434-11	CARBON	27K	5%	1/4W	
R1831	1-249-405-11	CARBON	100	5%	1/4W	
R1832	1-215-471-00	METAL	120K	1%	1/4W	
R1833	1-215-471-00	METAL	120K	1%	1/4W	
R1834	1-215-471-00	METAL	120K	1%	1/4W	
R1835	1-215-437-00	METAL	4.7K	1%	1/4W	
R1836	1-215-437-00	METAL	4.7K	1%	1/4W	
R1837	1-215-421-00	METAL	1K	1%	1/4W	
R1838	1-249-431-11	CARBON	15K	5%	1/4W	
R1839	1-249-431-11	CARBON	15K	5%	1/4W	
R1858	1-215-445-00	METAL	10K	1%	1/4W	
R1859	1-215-445-00	METAL	10K	1%	1/4W	
R1860	1-215-397-00	METAL	100	1%	1/4W	
R1861	1-215-453-00	METAL	22K	1%	1/4W	
R1862	1-215-453-00	METAL	22K	1%	1/4W	
R1863	1-215-397-00	METAL	100	1%	1/4W	
R1864	1-215-437-00	METAL	4.7K	1%	1/4W	
R1865	1-215-453-00	METAL	22K	1%	1/4W	
R1866	1-215-453-00	METAL	22K	1%	1/4W	
R1867	1-215-437-00	METAL	4.7K	1%	1/4W	
R1868	1-215-439-00	METAL	5.6K	1%	1/4W	
R1869	1-215-445-00	METAL	10K	1%	1/4W	
R1870	1-215-445-00	METAL	10K	1%	1/4W	
R1871	1-215-445-00	METAL	10K	1%	1/4W	
R1872	1-215-437-00	METAL	4.7K	1%	1/4W	
R1873	1-215-437-00	METAL	4.7K	1%	1/4W	
R1874	1-215-437-00	METAL	4.7K	1%	1/4W	
R1875	1-215-437-00	METAL	4.7K	1%	1/4W	
R1876	1-215-437-00	METAL	4.7K	1%	1/4W	
R1877	1-215-437-00	METAL	4.7K	1%	1/4W	
R1878	1-215-475-00	METAL	180K	1%	1/4W	
R1879	1-215-475-00	METAL	180K	1%	1/4W	
R1880	1-215-475-00	METAL	180K	1%	1/4W	
R1881	1-215-461-00	METAL	47K	1%	1/4W	
R1882	1-215-445-00	METAL	10K	1%	1/4W	
R1883	1-215-453-00	METAL	22K	1%	1/4W	
R1884	1-215-397-00	METAL	100	1%	1/4W	
R1885	1-215-445-00	METAL	10K	1%	1/4W	
R1886	1-215-445-00	METAL	10K	1%	1/4W	
R1887	1-215-397-00	METAL	100	1%	1/4W	
R1888	1-215-461-00	METAL	47K	1%	1/4W	
R1889	1-215-457-00	METAL	33K	1%	1/4W	
R1890	1-215-457-00	METAL	33K	1%	1/4W	
R1891	1-215-443-00	METAL	8.2K	1%	1/4W	
R1892	1-215-445-00	METAL	10K	1%	1/4W	
R1894	1-215-429-00	METAL	2.2K	1%	1/4W	
R1895	1-215-445-00	METAL	10K	1%	1/4W	
R1896	1-215-445-00	METAL	10K	1%	1/4W	
R1897	1-215-449-00	METAL	15K	1%	1/4W	
R1898	1-215-445-00	METAL	10K	1%	1/4W	
R1899	1-215-421-00	METAL	1K	1%	1/4W	
R1900	1-215-429-00	METAL	2.2K	1%	1/4W	
R1901	1-215-449-00	METAL	15K	1%	1/4W	
R1902	1-215-445-00	METAL	10K	1%	1/4W	
R1903	1-215-445-00	METAL	10K	1%	1/4W	
R1904	1-215-445-00	METAL	10K	1%	1/4W	
R1905	1-215-445-00	METAL	10K	1%	1/4W	
R1906	1-215-429-00	METAL	2.2K	1%	1/4W	
R1907	1-215-445-00	METAL	10K	1%	1/4W	
R1908	1-215-445-00	METAL	10K	1%	1/4W	
R1909	1-215-445-00	METAL	10K	1%	1/4W	
R1910	1-215-445-00	METAL	10K	1%	1/4W	
R1911	1-215-453-00	METAL	22K	1%	1/4W	
R1916	1-215-423-00	METAL	1.2K	1%	1/4W	
R1920	1-215-453-00	METAL	22K	1%	1/4W	
R1921	1-215-445-00	METAL	10K	1%	1/4W	
R1922	1-215-445-00	METAL	10K	1%	1/4W	
R1924	1-215-429-00	METAL	2.2K	1%	1/4W	
R1925	1-215-429-00	METAL	2.2K	1%	1/4W	
R1926	1-215-429-00	METAL	2.2K	1%	1/4W	
R1927	1-215-445-00	METAL	10K	1%	1/4W	
R1928	1-215-421-00	METAL	1K	1%	1/4W	
R1929	1-215-445-00	METAL	10K	1%	1/4W	
R1930	1-215-397-00	METAL	100	1%	1/4W	
R1931	1-215-397-00	METAL	100	1%	1/4W	
R1932	1-215-453-00	METAL	22K	1%	1/4W	

D DS

REF.NO.	PART NO.	DESCRIPTION				REMARK
R1933	1-215-453-00	METAL	22K	1%	1/4W	
R1934	1-215-429-00	METAL	2.2K	1%	1/4W	
R1937	1-215-445-00	METAL	10K	1%	1/4W	
		<VARIABLE RESISTOR>				
RV901	1-241-631-11	RES, ADJ, CARBON 22K				
RV902	1-241-631-11	RES, ADJ, CARBON 22K				
RV903	1-241-631-11	RES, ADJ, CARBON 22K				
RV904	1-241-631-11	RES, ADJ, CARBON 22K				
RV905	1-241-631-11	RES, ADJ, CARBON 22K				
RV906	1-241-631-11	RES, ADJ, CARBON 22K				
RV907	1-241-631-11	RES, ADJ, CARBON 22K				
RV908	1-241-631-11	RES, ADJ, CARBON 22K				
RV909	1-241-631-11	RES, ADJ, CARBON 22K				
RV910	1-241-631-11	RES, ADJ, CARBON 22K				
RV911	1-241-627-11	RES, ADJ, CARBON 1K				
RV912	1-241-631-11	RES, ADJ, CARBON 22K				
RV913	1-238-023-11	RES, ADJ, CARBON 470K				
RV914	1-241-630-11	RES, ADJ, CARBON 10K				
RV915	1-241-630-11	RES, ADJ, CARBON 10K				
RV916	1-241-631-11	RES, ADJ, CARBON 22K				
RV917	1-241-631-11	RES, ADJ, CARBON 22K				
RV918	1-241-631-11	RES, ADJ, CARBON 22K				
RV919	1-241-631-11	RES, ADJ, CARBON 22K				
RV920	1-241-631-11	RES, ADJ, CARBON 22K				
RV921	1-241-631-11	RES, ADJ, CARBON 22K				
RV922	1-241-631-11	RES, ADJ, CARBON 22K				
RV923	1-241-631-11	RES, ADJ, CARBON 22K				
RV924	1-241-631-11	RES, ADJ, CARBON 22K				
RV925	1-241-631-11	RES, ADJ, CARBON 22K				
RV926	1-241-631-11	RES, ADJ, CARBON 22K				
RV927	1-241-631-11	RES, ADJ, CARBON 22K				
RV928	1-241-630-11	RES, ADJ, CARBON 10K				
RV929	1-241-631-11	RES, ADJ, CARBON 22K				
RV930	1-241-630-11	RES, ADJ, CARBON 10K				
RV931	1-241-631-11	RES, ADJ, CARBON 22K				
RV932	1-241-631-11	RES, ADJ, CARBON 22K				
RV933	1-241-631-11	RES, ADJ, CARBON 22K				
RV934	1-241-631-11	RES, ADJ, CARBON 22K				
RV935	1-241-631-11	RES, ADJ, CARBON 22K				
RV936	1-241-631-11	RES, ADJ, CARBON 22K				
RV937	1-241-630-11	RES, ADJ, CARBON 10K				
RV938	1-241-630-11	RES, ADJ, CARBON 10K				
RV939	1-241-630-11	RES, ADJ, CARBON 10K				
RV940	1-241-631-11	RES, ADJ, CARBON 22K				
RV941	1-241-631-11	RES, ADJ, CARBON 22K				
RV942	1-241-631-11	RES, ADJ, CARBON 22K				
RV943	1-241-631-11	RES, ADJ, CARBON 22K				
RV944	1-241-631-11	RES, ADJ, CARBON 22K				
RV945	1-241-631-11	RES, ADJ, CARBON 22K				
RV946	1-241-631-11	RES, ADJ, CARBON 22K				
RV947	1-241-631-11	RES, ADJ, CARBON 22K				
RV948	1-241-631-11	RES, ADJ, CARBON 22K				
RV949	1-241-631-11	RES, ADJ, CARBON 22K				
RV950	1-241-631-11	RES, ADJ, CARBON 22K				
RV951	1-241-631-11	RES, ADJ, CARBON 22K				
RV952	1-241-631-11	RES, ADJ, CARBON 22K				
RV953	1-241-631-11	RES, ADJ, CARBON 22K				
RV954	1-241-631-11	RES, ADJ, CARBON 22K				
RV956	1-241-631-11	RES, ADJ, CARBON 22K				
RV957	1-241-631-11	RES, ADJ, CARBON 22K				
RV958	1-241-631-11	RES, ADJ, CARBON 22K				
RV959	1-241-631-11	RES, ADJ, CARBON 22K				
RV960	1-241-630-11	RES, ADJ, CARBON 10K				
RV961	1-241-631-11	RES, ADJ, CARBON 22K				
RV962	1-241-631-11	RES, ADJ, CARBON 22K				
RV963	1-241-631-11	RES, ADJ, CARBON 22K				
RV964	1-241-631-11	RES, ADJ, CARBON 22K				
RV965	1-241-631-11	RES, ADJ, CARBON 22K				
RV966	1-241-631-11	RES, ADJ, CARBON 22K				
RV967	1-241-631-11	RES, ADJ, CARBON 22K				
RV968	1-241-631-11	RES, ADJ, CARBON 22K				
RV969	1-241-631-11	RES, ADJ, CARBON 22K				
RV970	1-241-631-11	RES, ADJ, CARBON 22K				
RV971	1-241-631-11	RES, ADJ, CARBON 22K				
RV972	1-241-631-11	RES, ADJ, CARBON 22K				
RV973	1-241-631-11	RES, ADJ, CARBON 22K				
RV974	1-241-631-11	RES, ADJ, CARBON 22K				
RV975	1-241-631-11	RES, ADJ, CARBON 22K				
RV976	1-241-631-11	RES, ADJ, CARBON 22K				
RV977	1-241-631-11	RES, ADJ, CARBON 22K				
RV978	1-241-631-11	RES, ADJ, CARBON 22K				
RV979	1-241-631-11	RES, ADJ, CARBON 22K				
RV980	1-238-019-11	RES, ADJ, CARBON 47K				
RV981	1-241-631-11	RES, ADJ, CARBON 22K				
RV982	1-241-631-11	RES, ADJ, CARBON 22K				
**********						
	*1-644-278-11	DS BOARD				
		********				
		<CAPACITOR>				
C1745	1-126-101-11	ELECT	100MF	20%	16V	
C1746	1-126-101-11	ELECT	100MF	20%	16V	
C1747	1-126-101-11	ELECT	100MF	20%	16V	
C1748	1-126-101-11	ELECT	100MF	20%	16V	
C1750	1-124-916-11	ELECT	22MF	20%	25V	
C1751	1-126-101-11	ELECT	100MF	20%	16V	
C1752	1-124-916-11	ELECT	22MF	20%	25V	
C1753	1-124-916-11	ELECT	22MF	20%	25V	
C1851	1-102-074-00	CERAMIC	0.001MF	10%	50V	
		<CONNECTOR>				
DS6	1-691-182-11	CONNECTOR (BOARD TO BOARD) 12P				
		<IC>				
IC1711	8-759-111-69	IC UPC1037HA				
IC1712	8-759-602-19	IC M5220L				
IC1713	8-759-111-69	IC UPC1037HA				
		<RESISTOR>				
R1840	1-215-445-00	METAL	10K	1%	1/4W	
R1841	1-215-433-00	METAL	3.3K	1%	1/4W	
R1842	1-215-465-00	METAL	68K	1%	1/4W	
R1843	1-215-421-00	METAL	1K	1%	1/4W	
R1844	1-215-455-00	METAL	27K	1%	1/4W	
R1845	1-215-455-00	METAL	27K	1%	1/4W	
R1846	1-215-421-00	METAL	1K	1%	1/4W	
R1850	1-215-461-00	METAL	47K	1%	1/4W	
R1851	1-215-461-00	METAL	47K	1%	1/4W	
R1852	1-215-429-00	METAL	2.2K	1%	1/4W	
R1853	1-215-397-00	METAL	100	1%	1/4W	

The components identified by shading and mark ⚠ are critical for safety.
Replace only with part number specified.

Les composants identifies par une trame et une marque ⚠ sont critiques pour la securite.
Ne les remplacer que par une piece portant le numero specifie.

REF.NO.	PART NO.	DESCRIPTION				REMARK
R1854	1-215-429-00	METAL	2.2K	1%	1/4W	
R1855	1-215-397-00	METAL	100	1%	1/4W	
R1940	1-215-445-00	METAL	10K	1%	1/4W	
R1941	1-215-433-00	METAL	3.3K	1%	1/4W	
R1942	1-215-421-00	METAL	1K	1%	1/4W	
R1943	1-215-465-00	METAL	68K	1%	1/4W	
R1944	1-215-421-00	METAL	1K	1%	1/4W	
R1945	1-215-455-00	METAL	27K	1%	1/4W	
R1946	1-215-455-00	METAL	27K	1%	1/4W	
		<VARIABLE RESISTOR>				
RV983	1-241-630-11	RES, ADJ, CARBON 10K				
RV984	1-241-630-11	RES, ADJ, CARBON 10K				
		**********				
	*1-643-591-11	H1 BOARD				
		********				
	4-033-777-01	HOLDER, LED				
	*4-374-987-01	GUIDE, LIGHT				
	4-381-686-01	BRACKET (B), LIGHT GUIDE				
		<CAPACITOR>				
C1601	1-124-907-11	ELECT	10MF	20%	50V	
C1602	1-124-907-11	ELECT	10MF	20%	50V	
C1603	1-124-907-11	ELECT	10MF	20%	50V	
C1604	1-124-261-00	ELECT	10MF	20%	50V	
		<DIODE>				
D1601	8-719-812-41	DIODE TLR124				
D1602	8-719-812-41	DIODE TLR124				
		<CONNECTOR>				
H11	*1-564-526-11	PLUG, CONNECTOR 11P				
H15	*1-564-517-41	PLUG, CONNECTOR 2P				
		<IC>				
IC1601	8-741-148-33	IC SBX1483-59				
		<RESISTOR>				
R1601	1-249-430-11	CARBON	12K	5%	1/4W	
R1602	1-249-425-11	CARBON	4.7K	5%	1/4W	
R1603	1-249-421-11	CARBON	2.2K	5%	1/4W	
R1604	1-249-419-11	CARBON	1.5K	5%	1/4W	
R1606	1-249-405-11	CARBON	100	5%	1/4W	
R1607	1-249-405-11	CARBON	100	5%	1/4W	
R1608	1-249-411-11	CARBON	330	5%	1/4W	
R1609	1-249-411-11	CARBON	330	5%	1/4W	
		<SWITCH>				
S1601	1-554-303-21	SWITCH, TACTIL				
S1602	1-554-303-21	SWITCH, TACTIL				
S1603	1-554-303-21	SWITCH, TACTIL				
S1604	1-554-303-21	SWITCH, TACTIL				
S1605	1-554-303-21	SWITCH, TACTIL				
S1606⚠	1-571-731-21	SWITCH, TACTIL (POWER)				
		**********				
	*1-643-592-11	H2 BOARD				
		********				
		<CAPACITOR>				
C1651	1-124-477-11	ELECT	47MF	20%	16V	
C1655	1-124-927-11	ELECT	4.7MF	20%	50V	
		<DIODE>				
D1651	8-719-908-03	DIODE GP08D				
D1652	8-719-908-03	DIODE GP08D				
D1653	8-719-108-12	DIODE RD9.1E-W				
D1654	8-719-108-12	DIODE RD9.1E-W				
D1655	8-719-108-12	DIODE RD9.1E-W				
D1659	8-719-911-19	DIODE 1SS119				
D1660	8-719-110-88	DIODE RD39ES-B2				
D1661	8-719-110-88	DIODE RD39ES-B2				
D1662	8-719-110-88	DIODE RD39ES-B2				
D1663	8-719-110-88	DIODE RD39ES-B2				
		<CONNECTOR>				
H22	*1-564-519-41	PLUG, CONNECTOR 4P				
H25	*1-564-517-41	PLUG, CONNECTOR 2P				
H26	*1-564-519-11	PLUG, CONNECTOR 4P				
H28	*1-564-518-11	PLUG, CONNECTOR 3P				
H211	*1-564-517-11	PLUG, CONNECTOR 2P				
H216	*1-564-525-11	PLUG, CONNECTOR 10P				
H225	*1-564-518-11	PLUG, CONNECTOR 3P				
		<JACK>				
J1651	1-695-817-11	JACK BLOCK, PIN 3P				
		<TRANSISTOR>				
Q1651	8-729-119-78	TRANSISTOR 2SC2785-HFE				
Q1652	8-729-119-78	TRANSISTOR 2SC2785-HFE				
Q1653	8-729-119-78	TRANSISTOR 2SC2785-HFE				
		<RESISTOR>				
R1651	1-249-419-11	CARBON	1.5K	5%	1/4W	
R1652	1-249-421-11	CARBON	2.2K	5%	1/4W	
R1653	1-249-425-11	CARBON	4.7K	5%	1/4W	
R1654	1-249-430-11	CARBON	12K	5%	1/4W	
R1655	1-249-417-11	CARBON	1K	5%	1/4W	
R1656	1-249-417-11	CARBON	1K	5%	1/4W	
R1657	1-249-436-11	CARBON	39K	5%	1/4W	
R1658	1-249-437-11	CARBON	47K	5%	1/4W	
R1659	1-249-437-11	CARBON	47K	5%	1/4W	
		<RELAY>				
RY1651	1-515-586-11	RELAY (DS-2)				
RY1652	1-515-586-11	RELAY (DS-2)				
		<SWITCH>				
S1651	1-554-303-21	SWITCH, TACTIL				
S1652	1-554-303-21	SWITCH, TACTIL				
S1653	1-554-303-21	SWITCH, TACTIL				
S1654	1-554-303-21	SWITCH, TACTIL				

Les composants identifies par une trame et une marque ⚠ sont critiques pour la securite. Ne les remplacer que par une piece portant le numero specifie.

The components identified by shading and mark ⚠ are critical for safety. Replace only with part number specified.

H2 ZR ZG ZB N

REF.NO.	PART NO.	DESCRIPTION				REMARK
S1655	1-554-303-21	SWITCH, TACTIL				
**********						
	*A-1390-340-A	ZR BOARD, COMPLETE				
		**********				
		<CAPACITOR>				
C1901	1-162-115-00	CERAMIC	330PF	10%	2KV	
C1902	1-162-115-00	CERAMIC	330PF	10%	2KV	
		<RESISTOR>				
R1901	1-202-818-00	SOLID	1K	20%	1/2W	
R1902	1-202-818-00	SOLID	1K	20%	1/2W	
R1903	1-249-414-11	CARBON	560	5%	1/4W	
R1904	1-249-414-11	CARBON	560	5%	1/4W	
		<CONNECTOR>				
ZR1	*1-564-522-11	PLUG, CONNECTOR 7P				
ZR2	*1-564-518-11	PLUG, CONNECTOR 3P				
ZR18	*1-691-292-11	PIN, CONNECTOR (PC BOARD) 3P				
**********						
	*A-1390-346-A	ZG BOARD, COMPLETE				
		**********				
		<CAPACITOR>				
C1911	1-162-115-00	CERAMIC	330PF	10%	2KV	
C1912	1-162-115-00	CERAMIC	330PF	10%	2KV	
		<RESISTOR>				
R1911	1-202-818-00	SOLID	1K	20%	1/2W	
R1912	1-202-818-00	SOLID	1K	20%	1/2W	
R1913	1-249-414-11	CARBON	560	5%	1/4W	
R1914	1-249-414-11	CARBON	560	5%	1/4W	
		<CONNECTOR>				
ZG2	*1-564-523-11	PLUG, CONNECTOR 8P				
ZG19	*1-691-292-11	PIN, CONNECTOR (PC BOARD) 3P				
**********						
	*A-1390-347-A	ZB BOARD, COMPLETE				
		**********				
		<CAPACITOR>				
C1921	1-162-115-00	CERAMIC	330PF	10%	2KV	
C1922	1-162-115-00	CERAMIC	330PF	10%	2KV	
		<RESISTOR>				
R1921	1-202-818-00	SOLID	1K	20%	1/2W	
R1922	1-202-818-00	SOLID	1K	20%	1/2W	
R1923	1-249-414-11	CARBON	560	5%	1/4W	
R1924	1-249-414-11	CARBON	560	5%	1/4W	
		<CONNECTOR>				
ZB3	*1-564-524-11	PLUG, CONNECTOR 9P				
ZB20	*1-691-292-11	PIN, CONNECTOR (PC BOARD) 3P				
**********						
	*A-1390-351-A	N BOARD, COMPLETE				
		**********				
	4-039-042-01	SPACER, INSULATING				
	4-382-854-11	SCREW (M3X10), P, SW (+)				
	4-383-023-01	SPACER, MICA				
		<CAPACITOR>				
C801	1-125-489-00	ELECT(BLOCK)	560MF	20%	200V	
C802	1-123-024-21	ELECT	33MF		160V	
C803	1-136-729-11	FILM	1.5MF	5%	400V	
C804	1-106-383-00	MYLAR	0.047MF		200V	
C805	1-102-030-00	CERAMIC	330PF	10%	500V	
C806	1-130-495-00	MYLAR	0.1MF	5%	50V	
C807	1-123-875-11	ELECT	10MF	20%	50V	
C808	1-126-183-11	ELECT	1000MF	20%	16V	
C809	1-124-903-11	ELECT	1MF	20%	50V	
C810	1-124-903-11	ELECT	1MF	20%	50V	
C811	1-124-902-00	ELECT	0.47MF	20%	50V	
C812	1-102-973-00	CERAMIC	100PF	5%	50V	
C813	1-102-244-00	CERAMIC	220PF	10%	500V	
C814	1-106-391-12	MYLAR	0.1MF	10%	200V	
C815	1-106-367-00	MYLAR	0.01MF	10%	200V	
C816	1-124-907-11	ELECT	10MF	20%	50V	
C817	1-124-119-00	ELECT	330MF	20%	16V	
C818	1-102-824-00	CERAMIC	470PF	5%	50V	
C819	1-124-907-11	ELECT	10MF	20%	50V	
C820	1-124-907-11	ELECT	10MF	20%	50V	
C821	1-124-907-11	ELECT	10MF	20%	50V	
C822	1-124-034-51	ELECT	33MF	20%	16V	
C823	1-124-907-11	ELECT	10MF	20%	50V	
C824	1-124-034-51	ELECT	33MF	20%	16V	
C825	1-124-034-51	ELECT	33MF	20%	16V	
C826	1-124-907-11	ELECT	10MF	20%	50V	
C827	1-124-907-11	ELECT	10MF	20%	50V	
C828	1-124-907-11	ELECT	10MF	20%	50V	
C829	1-124-034-51	ELECT	33MF	20%	16V	
C830	1-124-907-11	ELECT	10MF	20%	50V	
C831	1-106-220-00	MYLAR	0.1MF	10%	100V	
C832	1-124-907-11	ELECT	10MF	20%	50V	
C833	1-124-916-11	ELECT	22MF	20%	50V	
C834	1-102-121-00	CERAMIC	0.0022MF	10%	50V	
C835	1-124-927-11	ELECT	4.7MF	20%	50V	
C836	1-130-475-00	MYLAR	0.0022MF	5%	50V	
C837	1-136-169-00	FILM	0.22MF	5%	50V	
C838	1-130-475-00	MYLAR	0.0022MF	5%	50V	
C839	1-102-106-00	CERAMIC	100PF	10%	50V	
C840	⚠ 1-136-807-11	FILM	0.018MF	3%	1.6KV	
C841	1-136-729-11	FILM	1.5MF	5%	400V	
C842	1-130-471-00	MYLAR	0.001MF	5%	50V	
C844	1-106-391-12	MYLAR	0.1MF	10%	200V	
C850	1-136-169-00	FILM	0.22MF	5%	50V	
C851	1-124-907-11	ELECT	10MF	20%	50V	
C852	1-124-907-11	ELECT	10MF	20%	50V	
C853	1-106-220-00	MYLAR	0.1MF	10%	100V	
C854	1-126-329-11	ELECT	470MF	20%	50V	
C855	1-124-514-11	ELECT	100MF	20%	50V	
C856	1-162-114-00	CERAMIC	0.0047MF		2KV	
C858	1-124-119-00	ELECT	330MF	20%	16V	
C888	1-124-903-11	ELECT	1MF	20%	50V	

The components identified by shading and mark ⚠ are critical for safety.
Replace only with part number specified.

Les composants identifies par une trame et une marque ⚠ sont critiques pour la securite.
Ne les remplacer que par une piece portant le numero specifie.

REF.NO.	PART NO.	DESCRIPTION	REMARK
		<DIODE>	
D801	8-719-928-08	DIODE ERD28-08S	
D802	8-719-300-80	DIODE RU-1C	
D803	8-719-109-85	DIODE RD5.1ES-B2	
D804	8-719-911-19	DIODE 1SS119	
D805	8-719-911-19	DIODE 1SS119	
D806	8-719-109-85	DIODE RD5.1ES-B2	
D807	8-719-109-85	DIODE RD5.1ES-B2	
D808	8-719-911-19	DIODE 1SS119	
D809	8-719-911-19	DIODE 1SS119	
D810	8-719-911-19	DIODE 1SS119	
D811	8-719-109-85	DIODE RD5.1ES-B2	
D812	8-719-911-19	DIODE 1SS119	
D813	8-719-911-19	DIODE 1SS119	
D814	8-719-911-19	DIODE 1SS119	
D815	8-719-110-36	DIODE RD13ES-B2	
D817	8-719-945-80	DIODE ERC06-15S	
D818	8-719-911-19	DIODE 1SS119	
D820	8-719-911-19	DIODE 1SS119	
D850	8-719-109-71	DIODE RD3.9ES-B1	
D851	⚠ 8-719-903-09	DIODE V30N	
D852	8-719-911-19	DIODE 1SS119	
D853	⚠ 8-719-903-09	DIODE V30N	
D891	8-719-110-49	DIODE RD18ES-B2	
D892	8-719-110-49	DIODE RD18ES-B2	
		<IC>	
IC801	8-759-231-58	IC TA7812S	
IC802	8-759-103-93	IC UPC393C	
IC803	8-759-990-82	IC TL082CP	
IC804	8-759-103-93	IC UPC393C	
IC805	8-759-100-75	IC UPC1394C	
		<COIL>	
L801	1-459-862-11	COIL, CHOKE 90UH	
L802	1-424-603-11	COIL, CHOKE 1.05MMH	
L803	1-459-313-00	COIL WITH CORE (HWC)	
L804	1-410-482-31	INDUCTOR 100UH	
L805	⚠ 1-424-603-11	COIL, CHOKE 1.05MMH	
		<CONNECTOR>	
N1	1-506-348-99	PIN, CONNECTOR 3P	
N2	*1-564-508-11	PLUG, CONNECTOR 5P	
N3	*1-508-766-00	PIN, CONNECTOR (5MM PITCH) 4P	
N4	*1-564-507-11	PLUG, CONNECTOR 4P	
N5	*1-564-508-11	PLUG, CONNECTOR 5P	
N6	*1-508-786-00	PIN, CONNECTOR (5MM PITCH) 2P	
N7	*1-508-765-00	PIN, CONNECTOR (5MM PITCH) 3P	
N8	*1-508-766-00	PIN, CONNECTOR (5MM PITCH) 4P	
N9	1-506-348-99	PIN, CONNECTOR 3P	
N10	*1-564-511-41	PLUG, CONNECTOR 8P	
N20	*1-560-126-00	PLUG, CONNECTOR (2.5MM) 6P	
N21	*1-560-123-00	PLUG, CONNECTOR (2.5MM) 3P	
N30	*1-508-784-00	PIN, CONNECTOR (5MM PITCH) 1P	
N851	*1-506-371-00	PIN, CONNECTOR 2P	
N853	*1-506-371-00	PIN, CONNECTOR 2P	
		<NEON LAMP>	
NL801	1-519-108-99	LAMP, NEON	

REF.NO.	PART NO.	DESCRIPTION				REMARK
		<TRANSISTOR>				
Q801	⚠ 8-729-201-61	TRANSISTOR 2SC2555-I				
Q802	8-729-119-80	TRANSISTOR 2SC2688-LK				
Q803	8-729-119-76	TRANSISTOR 2SA1175-HFE				
Q804	8-729-119-78	TRANSISTOR 2SC2785-HFE				
Q805	8-729-119-78	TRANSISTOR 2SC2785-HFE				
Q806	8-729-119-80	TRANSISTOR 2SC2688-LK				
Q807	8-729-119-78	TRANSISTOR 2SC2785-HFE				
Q808	8-729-119-78	TRANSISTOR 2SC2785-HFE				
Q809	8-729-119-76	TRANSISTOR 2SA1175-HFE				
Q811	⚠ 8-729-805-07	TRANSISTOR 2SD1887-CA				
Q812	8-729-019-88	TRANSISTOR 2SC3675-CB				
Q820	8-729-119-76	TRANSISTOR 2SA1175-HFE				
Q851	8-729-119-78	TRANSISTOR 2SC2785-HFE				
Q852	8-729-119-78	TRANSISTOR 2SC2785-HFE				
Q853	8-729-820-98	TRANSISTOR 2SC4256CB				
		<RESISTOR>				
R801	1-216-378-11	METAL OXIDE	5.6	5%	2W	F
R802	1-215-926-00	METAL OXIDE	33K	5%	3W	F
R803	1-215-926-00	METAL OXIDE	33K	5%	3W	F
R804	1-249-429-11	CARBON	10K	5%	1/4W	
R805	1-249-423-11	CARBON	3.3K	5%	1/4W	
R806	1-249-425-11	CARBON	4.7K	5%	1/4W	
R807	1-249-441-11	CARBON	100K	5%	1/4W	
R808	1-249-417-11	CARBON	1K	5%	1/4W	
R809	1-249-417-11	CARBON	1K	5%	1/4W	
R810	1-249-441-11	CARBON	100K	5%	1/4W	
R811	1-249-421-11	CARBON	2.2K	5%	1/4W	
R812	1-249-420-11	CARBON	1.8K	5%	1/4W	F
R813	1-215-921-11	METAL OXIDE	4.7K	5%	3W	F
R814	1-249-409-11	CARBON	220	5%	1/4W	
R815	1-249-415-11	CARBON	680	5%	1/4W	
R816	1-214-777-00	METAL	100K	1%	1/4W	
R817	1-215-471-00	METAL	120K	1%	1/4W	
R818	1-215-471-00	METAL	120K	1%	1/4W	
R819	1-215-450-00	METAL	16K	1%	1/4W	
R820	1-215-451-00	METAL	18K	1%	1/4W	
R821	1-249-423-11	CARBON	3.3K	5%	1/4W	
R822	1-249-433-11	CARBON	22K	5%	1/4W	
R823	1-249-429-11	CARBON	10K	5%	1/4W	
R824	1-215-469-00	METAL	100K	1%	1/4W	
R825	1-215-453-00	METAL	22K	1%	1/4W	
R826	1-214-962-00	METAL	820K	1%	1/4W	
R827	1-214-764-00	METAL	30K	1%	1/4W	
R828	1-215-455-00	METAL	27K	1%	1/4W	
R829	1-215-455-00	METAL	27K	1%	1/4W	
R830	1-215-928-11	METAL OXIDE	68K	5%	3W	F
R831	1-215-928-11	METAL OXIDE	68K	5%	3W	F
R832	1-249-417-11	CARBON	1K	5%	1/4W	
R833	1-249-419-11	CARBON	1.5K	5%	1/4W	
R834	1-249-419-11	CARBON	1.5K	5%	1/4W	
R835	1-215-429-00	METAL	2.2K	1%	1/4W	
R836	1-215-435-00	METAL	3.9K	1%	1/4W	
R837	1-249-433-11	CARBON	22K	5%	1/4W	
R838	1-249-435-11	CARBON	33K	5%	1/4W	
R839	1-249-438-11	CARBON	56K	5%	1/4W	
R840	1-249-434-11	CARBON	27K	5%	1/4W	
R841	1-249-429-11	CARBON	10K	5%	1/4W	
R842	1-249-435-11	CARBON	33K	5%	1/4W	
R843	1-249-423-11	CARBON	3.3K	5%	1/4W	

Selecting a Picture and Sound Mode

This projection TV features four modes (STANDARD, MOVIE, SPORTS, NEWS) that offer different picture and sound qualities. Choose the one that best suits the type of program that you want to watch.

Example: Select MOVIE mode for picture and sound that gives you the sense of being in a movie theater.



(with video control cover open)

1 Press MENU.
The main menu appears, and the cursor points to "PROG PALETTE."



2 Press RETURN.
The program palette menu appears.



3 Press A/V WINDOW +/– until the cursor points to "MOVIE."





4 Press RETURN.
The "MOVIE" display turns green, indicating that MOVIE mode is selected.



To select a different mode
Repeat steps 3 – 4.

Selecting standard mode (without using the menus)

Follow these instructions to select standard mode without using the on-screen menus.

Press STANDARD.

When you select STANDARD mode
You receive standard picture and sound quality. Any video or audio adjustments you made ("Adjusting the Projection TV," pp. 44 – 52) are cancelled and the original factory settings are restored.

When you select MOVIE mode
You receive a finely detailed picture, and a theatrical audio effect.
To further adjust picture and sound qualities, follow the instructions on pp. 44 – 52.

When you select SPORTS mode
You receive a vivid, bright picture, and sound with a sports stadium effect.
To further adjust picture and sound qualities, follow the instructions on pp. 44 – 52.

When you select NEWS mode
Picture noise is reduced, and you receive clear voice reproduction.
To further adjust picture and sound qualities, follow the instructions on pp. 44 – 52.

To return to the previous menu
Press A/V WINDOW +/– until the cursor points to "⊃ MENU."
Then press RETURN.

To return to the main menu
Repeat the above, until you reach the main menu.

To return to the normal screen.
Press MENU.

N **S**

• The components identified by ⊠ in this manual have been carefully factory-selected for each set in order to satisfy regulations regarding X-ray radiation. Should replacement be required, replace only with the value originally used.

Les composants identifies par une trame et une marque ⚠ sont critiques pour la securite. Ne les remplacer que par une piece portant le numero specifie.

The components identified by shading and mark ⚠ are critical for safety. Replace only with part number specified.

REF.NO.	PART NO.	DESCRIPTION				REMARK
R844	1-249-433-11	CARBON	22K	5%	1/4W	
R845	1-249-435-11	CARBON	33K	5%	1/4W	
R846	1-249-429-11	CARBON	10K	5%	1/4W	
R847	1-214-761-00	METAL	22K	1%	1/4W	
R848	1-215-429-00	METAL	2.2K	1%	1/4W	
R849	1-215-421-00	METAL	1K	1%	1/4W	
R850	1-215-429-00	METAL	2.2K	1%	1/4W	
R851	1-215-404-00	METAL	200	1%	1/4W	
⊠R852 ⚠		METAL			1/4W	
R853	1-215-469-00	METAL	100K	1%	1/4W	
R854	1-249-430-11	CARBON	12K	5%	1/4W	
R855	1-215-469-00	METAL	100K	1%	1/4W	
R856	1-249-430-11	CARBON	12K	5%	1/4W	
R857	1-249-433-11	CARBON	22K	5%	1/4W	
R858	1-249-413-11	CARBON	470	5%	1/4W	
R859	1-249-435-11	CARBON	33K	5%	1/4W	
R860	1-249-441-11	CARBON	100K	5%	1/4W	
R861	1-249-421-11	CARBON	2.2K	5%	1/4W	
R862	1-249-434-11	CARBON	27K	5%	1/4W	
R863	1-249-431-11	CARBON	15K	5%	1/4W	
R864	1-249-423-11	CARBON	3.3K	5%	1/4W	
R865	1-249-440-11	CARBON	82K	5%	1/4W	
R866	1-249-436-11	CARBON	39K	5%	1/4W	
R867	1-249-437-11	CARBON	47K	5%	1/4W	
R868	1-249-428-11	CARBON	8.2K	5%	1/4W	
R869	1-249-429-11	CARBON	10K	5%	1/4W	
R870	1-249-417-11	CARBON	1K	5%	1/4W	
R871	1-249-440-11	CARBON	82K	5%	1/4W	
R872	1-249-423-11	CARBON	3.3K	5%	1/4W	
R873	1-249-441-11	CARBON	100K	5%	1/4W	
R874	1-249-435-11	CARBON	33K	5%	1/4W	
R875	1-249-421-11	CARBON	2.2K	5%	1/4W	
R876	1-215-426-00	METAL	1.6K	1%	1/4W	
R877	1-249-435-11	CARBON	33K	5%	1/4W	
R878	1-249-441-11	CARBON	100K	5%	1/4W	
R879	1-216-489-11	METAL OXIDE	27K	5%	3W	F
R880	1-249-429-11	CARBON	10K	5%	1/4W	
R881	1-214-761-00	METAL	22K	1%	1/4W	
R882	1-249-433-11	CARBON	22K	5%	1/4W	
R883	1-249-417-11	CARBON	1K	5%	1/4W	
R884	1-215-894-11	METAL OXIDE	2.2K	5%	2W	F
R885	1-249-438-11	CARBON	56K	5%	1/4W	
R886	1-249-414-11	CARBON	560	5%	1/4W	
R887	1-215-397-00	METAL	100	1%	1/4W	
R888	1-249-410-11	CARBON	270	5%	1/4W	
R889	1-249-417-11	CARBON	1K	5%	1/4W	
R890	1-249-417-11	CARBON	1K	5%	1/4W	
R891	1-216-489-11	METAL OXIDE	27K	5%	3W	F
R892	1-249-417-11	CARBON	1K	5%	1/4W	F
R893	1-215-453-00	METAL	22K	1%	1/4W	
R894	1-249-401-11	CARBON	47	5%	1/4W	
R895	1-202-731-00	SOLID	10M	20%	1/2W	
R896	1-260-111-11	CARBON	10K	5%	1/2W	
R897	1-247-881-00	CARBON	120K	5%	1/4W	
R898	1-202-730-00	SOLID	8.2M	20%	1/2W	
R899	1-249-429-11	CARBON	10K	5%	1/4W	
R903	1-247-735-11	SOLID	47	20%	1/2W	
R904	1-215-928-11	METAL OXIDE	68K	5%	3W	F
R905	1-215-911-11	METAL OXIDE	100	5%	3W	F

<SPARK GAP>

SG801	1-519-422-11	GAP, SPARK	

REF.NO.	PART NO.	DESCRIPTION				REMARK
		<TRANSFORMER>				
T801 ⚠	1-437-078-11	TRANSFORMER, HORIZONTAL DRIVE				
T802	1-437-090-00	HDT				
T803 ⚠	1-453-121-11	TRANSFORMER ASSY, FLYBACK (NX-2630B4)				
**********						
	*A-1394-421-A	S BOARD, COMPLETE				
		**********				
	*1-565-514-11	SOCKET, CONNECTOR 2P				
		<CAPACITOR>				
C3403	1-164-161-11	CERAMIC CHIP	0.0022MF	10%	50V	
C3408	1-164-232-11	CERAMIC CHIP	0.01MF	10%	50V	
C3409	1-124-477-11	ELECT	47MF	20%	16V	
C3411	1-124-034-51	ELECT	33MF	20%	16V	
C3442	1-164-161-11	CERAMIC CHIP	0.0022MF	10%	50V	
C3446	1-163-129-00	CERAMIC CHIP	330PF	5%	50V	
C3447	1-163-117-00	CERAMIC CHIP	100PF	5%	50V	
C3448	1-163-023-00	CERAMIC CHIP	0.015MF	10%	50V	
C3449	1-164-182-11	CERAMIC CHIP	0.0033MF	10%	50V	
C3450	1-163-109-00	CERAMIC CHIP	47PF	5%	50V	
C3451	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	
C3452	1-163-989-11	CERAMIC CHIP	0.033MF	10%	25V	
C3453	1-124-477-11	ELECT	47MF	20%	16V	
C3454	1-126-162-11	ELECT	3.3MF	20%	50V	
C3455	1-126-163-11	ELECT	4.7MF	20%	16V	
C3456	1-163-129-00	CERAMIC CHIP	330PF	5%	50V	
C3457	1-163-117-00	CERAMIC CHIP	100PF	5%	50V	
C3459	1-124-477-11	ELECT	47MF	20%	16V	
C3460	1-163-099-00	CERAMIC CHIP	18PF	5%	50V	
C3461	1-163-099-00	CERAMIC CHIP	18PF	5%	50V	
C3507	1-164-232-11	CERAMIC CHIP	0.01MF	10%	50V	
C3508	1-164-005-11	CERAMIC CHIP	0.47MF		25V	
C3509	1-163-139-00	CERAMIC CHIP	820PF	5%	50V	
C3515	1-163-121-00	CERAMIC CHIP	150PF	5%	50V	
C3540	1-126-157-11	ELECT	10MF	20%	16V	
		<DIODE>				
D3444	8-719-404-46	DIODE MA110				
		<IC>				
IC3401	8-759-403-44	IC MN1280-S				
IC3402	8-759-070-42	IC M37201M6-A18FP				
IC3441	8-759-982-21	IC RC78L05A				
IC3442	8-759-084-12	IC LA7945				
IC3443	8-759-158-03	IC LC7458A-02				
IC3444	8-759-403-44	IC MN1280-S				
		<COIL>				
L3401	1-408-421-00	INDUCTOR	100UH			
L3461	1-408-409-00	INDUCTOR	10UH			
L3462	1-408-421-00	INDUCTOR	100UH			
		<TRANSISTOR>				
Q3441	8-729-422-27	TRANSISTOR 2SD601A-Q				
Q3444	8-729-903-10	TRANSISTOR FMW1				

REF.NO.	PART NO.	DESCRIPTION				REMARK
		<RESISTOR>				
R3401	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R3402	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R3403	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R3404	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R3405	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	
R3406	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R3407	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R3408	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R3409	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R3441	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R3442	1-216-041-00	METAL GLAZE	470	5%	1/10W	
R3443	1-216-041-00	METAL GLAZE	470	5%	1/10W	
R3444	1-216-077-00	METAL GLAZE	15K	5%	1/10W	
R3445	1-216-689-11	METAL GLAZE	39K	5%	1/10W	
R3446	1-216-085-00	METAL GLAZE	33K	5%	1/10W	
R3449	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R3450	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	
R3451	1-216-093-00	METAL GLAZE	68K	5%	1/10W	
R3452	1-216-079-00	METAL GLAZE	18K	5%	1/10W	
R3453	1-216-679-11	METAL CHIP	15K	0.50%	1/10W	
R3454	1-216-037-00	METAL GLAZE	330	5%	1/10W	
R3455	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	
R3456	1-216-077-00	METAL GLAZE	15K	5%	1/10W	
R3463	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R3464	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R3465	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R3472	1-216-091-00	METAL GLAZE	56K	5%	1/10W	
R3473	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R3474	1-216-295-00	METAL GLAZE	0	5%	1/10W	
R3504	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	
R3509	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R3511	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R3512	1-216-059-00	METAL GLAZE	2.7K	5%	1/10W	
R3513	1-216-059-00	METAL GLAZE	2.7K	5%	1/10W	
R3514	1-216-059-00	METAL GLAZE	2.7K	5%	1/10W	
R3519	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R3520	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R3521	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R3525	1-216-295-00	METAL GLAZE	0	5%	1/10W	
R3526	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R3528	1-216-295-00	METAL GLAZE	0	5%	1/10W	
R3529	1-216-295-00	METAL GLAZE	0	5%	1/10W	
R3530	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R3531	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R3532	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R3535	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R3537	1-216-295-00	METAL GLAZE	0	5%	1/10W	
R3540	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
		<CONNECTOR>				
S42	*1-568-378-21	PIN, CONNECTOR 3P				
S43	*1-564-508-11	PLUG, CONNECTOR 5P				
S45	*1-564-511-71	PLUG, CONNECTOR 8P				
S46	*1-564-506-11	PLUG, CONNECTOR 3P				
S47	*1-564-506-11	PLUG, CONNECTOR 3P				
		<CRYSTAL>				
X3401	1-577-082-11	VIBRATOR, CERAMIC				
X3441	1-577-364-11	VIBRATOR, CERAMIC				

REF.NO.	PART NO.	DESCRIPTION				REMARK
**********						
	*A-1394-422-A	U BOARD, COMPLETE				
		**********				
		<CAPACITOR>				
C1004	1-102-125-00	CERAMIC	0.0047MF	10%	50V	
C1005	1-126-301-11	ELECT	1MF	20%	50V	
C1006	1-164-096-11	CERAMIC	0.01MF		50V	
C1007	1-124-598-11	ELECT	22MF	20%	25V	
C1008	1-124-598-11	ELECT	22MF	20%	25V	
C1010	1-124-465-00	ELECT	0.47MF	20%	50V	
C1011	1-124-465-00	ELECT	0.47MF	20%	50V	
C1012	1-124-465-00	ELECT	0.47MF	20%	50V	
C1013	1-102-125-00	CERAMIC	0.0047MF	10%	50V	
C1014	1-126-163-11	ELECT	4.7MF	20%	50V	
C1016	1-126-163-11	ELECT	4.7MF	20%	50V	
C1018	1-126-301-11	ELECT	1MF	20%	50V	
C1020	1-124-242-00	ELECT	33MF	20%	25V	
C1021	1-124-465-00	ELECT	0.47MF	20%	50V	
C1022	1-124-242-00	ELECT	33MF	20%	25V	
C1026	1-102-949-00	CERAMIC	12PF	5%	50V	
C1027	1-102-949-00	CERAMIC	12PF	5%	50V	
C1028	1-124-242-00	ELECT	33MF	20%	25V	
C1029	1-124-282-00	ELECT	22MF	20%	16V	
C1030	1-124-478-11	ELECT	100MF	20%	25V	
C1031	1-102-963-00	CERAMIC	33PF	5%	50V	
C1033	1-124-598-11	ELECT	22MF	20%	25V	
C1034	1-124-282-00	ELECT	22MF	20%	16V	
C1036	1-124-282-00	ELECT	22MF	20%	16V	
C1037	1-124-282-00	ELECT	22MF	20%	16V	
C1039	1-124-478-11	ELECT	100MF	20%	25V	
C1047	1-124-465-00	ELECT	0.47MF	20%	50V	
C1048	1-126-301-11	ELECT	1MF	20%	50V	
C1049	1-124-598-11	ELECT	22MF	20%	25V	
C1051	1-124-465-00	ELECT	0.47MF	20%	50V	
C1055	1-124-589-11	ELECT	47MF	20%	16V	
C1056	1-124-499-11	ELECT	1MF	20%	50V	
C1057	1-124-768-11	ELECT	4.7MF	20%	50V	
C1059	1-124-499-11	ELECT	1MF	20%	50V	
C1060	1-124-499-11	ELECT	1MF	20%	50V	
C1061	1-124-499-11	ELECT	1MF	20%	50V	
C1062	1-102-129-00	CERAMIC	0.01MF	10%	50V	
C1063	1-124-768-11	ELECT	4.7MF	20%	50V	
C1066	1-126-101-11	ELECT	100MF	20%	16V	
		<BLOCK>				
CM1002	1-466-162-31	BLOCK, COM FILTER (CFB-4)				
		<DIODE>				
D1005	8-719-110-36	DIODE RD13ES-B2				
D1009	8-719-110-36	DIODE RD13ES-B2				
D1010	8-719-110-36	DIODE RD13ES-B2				
D1011	8-719-110-36	DIODE RD13ES-B2				
D1012	8-719-110-36	DIODE RD13ES-B2				
D1013	8-719-110-36	DIODE RD13ES-B2				
D1017	8-719-110-36	DIODE RD13ES-B2				
D1018	8-719-110-36	DIODE RD13ES-B2				
D1019	8-719-110-36	DIODE RD13ES-B2				
D1020	8-719-109-66	DIODE RD3.3ES-B2				
D1021	8-719-109-66	DIODE RD3.3ES-B2				

U UT

REF.NO.	PART NO.	DESCRIPTION				REMARK
D1022	8-719-109-66	DIODE RD3.3ES-B2				
		<IC>				
IC1002	8-752-056-50	IC CXA1545S				
IC1011	8-759-145-57	IC UPC4557C				
		<COIL>				
L1001	1-408-422-00	INDUCTOR	120UH			
L1002	1-408-422-00	INDUCTOR	120UH			
		<TRANSISTOR>				
Q1009	8-729-119-78	TRANSISTOR 2SC2785-HFE				
Q1010	8-729-119-78	TRANSISTOR 2SC2785-HFE				
Q1016	8-729-119-76	TRANSISTOR 2SA1175-HFE				
Q1017	8-729-119-76	TRANSISTOR 2SA1175-HFE				
Q1018	8-729-141-26	TRANSISTOR 2SC3622A-LK				
Q1019	8-729-119-76	TRANSISTOR 2SA1175-HFE				
Q1020	8-729-119-76	TRANSISTOR 2SA1175-HFE				
Q1021	8-729-119-76	TRANSISTOR 2SA1175-HFE				
Q1022	8-729-141-26	TRANSISTOR 2SC3622A-LK				
Q1023	8-729-119-78	TRANSISTOR 2SC2785-HFE				
Q1029	8-729-119-76	TRANSISTOR 2SA1175-HFE				
Q1030	8-729-119-78	TRANSISTOR 2SC2785-HFE				
Q1031	8-729-119-78	TRANSISTOR 2SC2785-HFE				
Q1032	8-729-119-76	TRANSISTOR 2SA1175-HFE				
Q1033	8-729-119-76	TRANSISTOR 2SA1175-HFE				
Q1034	8-729-119-76	TRANSISTOR 2SA1175-HFE				
		<RESISTOR>				
R1011	1-249-435-11	CARBON	33K	5%	1/4W	
R1012	1-249-434-11	CARBON	27K	5%	1/4W	
R1013	1-249-417-11	CARBON	1K	5%	1/4W	
R1014	1-249-441-11	CARBON	100K	5%	1/4W	
R1015	1-249-425-11	CARBON	4.7K	5%	1/4W	
R1016	1-249-441-11	CARBON	100K	5%	1/4W	
R1017	1-249-405-11	CARBON	100	5%	1/4W	
R1018	1-249-427-11	CARBON	6.8K	5%	1/4W	
R1019	1-249-427-11	CARBON	6.8K	5%	1/4W	
R1023	1-249-405-11	CARBON	100	5%	1/4W	
R1026	1-249-425-11	CARBON	4.7K	5%	1/4W	
R1028	1-249-434-11	CARBON	27K	5%	1/4W	
R1029	1-249-435-11	CARBON	33K	5%	1/4W	
R1030	1-249-417-11	CARBON	1K	5%	1/4W	
R1032	1-249-417-11	CARBON	1K	5%	1/4W	
R1033	1-249-393-11	CARBON	10	5%	1/4W	F
R1034	1-249-417-11	CARBON	1K	5%	1/4W	
R1036	1-249-440-11	CARBON	82K	5%	1/4W	
R1037	1-249-440-11	CARBON	82K	5%	1/4W	
R1038	1-249-440-11	CARBON	82K	5%	1/4W	
R1043	1-249-417-11	CARBON	1K	5%	1/4W	
R1046	1-249-413-11	CARBON	470	5%	1/4W	
R1048	1-249-405-11	CARBON	100	5%	1/4W	
R1050	1-249-405-11	CARBON	100	5%	1/4W	
R1051	1-249-417-11	CARBON	1K	5%	1/4W	
R1052	1-249-413-11	CARBON	470	5%	1/4W	
R1054	1-249-405-11	CARBON	100	5%	1/4W	
R1055	1-249-413-11	CARBON	470	5%	1/4W	
R1056	1-249-405-11	CARBON	100	5%	1/4W	
R1057	1-249-441-11	CARBON	100K	5%	1/4W	
R1059	1-249-405-11	CARBON	100	5%	1/4W	
R1061	1-249-409-11	CARBON	220	5%	1/4W	
R1062	1-249-441-11	CARBON	100K	5%	1/4W	
R1063	1-249-409-11	CARBON	220	5%	1/4W	
R1066	1-215-437-00	METAL	4.7K	1%	1/4W	
R1067	1-215-437-00	METAL	4.7K	1%	1/4W	
R1068	1-215-437-00	METAL	4.7K	1%	1/4W	
R1069	1-215-437-00	METAL	4.7K	1%	1/4W	
R1070	1-249-411-11	CARBON	330	5%	1/4W	
R1071	1-249-431-11	CARBON	15K	5%	1/4W	
R1073	1-249-431-11	CARBON	15K	5%	1/4W	
R1077	1-249-418-11	CARBON	1.2K	5%	1/4W	
R1078	1-249-418-11	CARBON	1.2K	5%	1/4W	
R1079	1-249-405-11	CARBON	100	5%	1/4W	
R1080	1-215-423-00	METAL	1.2K	1%	1/4W	
R1081	1-215-421-00	METAL	1K	1%	1/4W	
R1089	1-249-405-11	CARBON	100	5%	1/4W	
R1094	1-249-405-11	CARBON	100	5%	1/4W	
R1096	1-249-405-11	CARBON	100	5%	1/4W	
R1099	1-249-413-11	CARBON	470	5%	1/4W	
R1110	1-249-405-11	CARBON	100	5%	1/4W	
R1116	1-249-441-11	CARBON	100K	5%	1/4W	
R1118	1-249-413-11	CARBON	470	5%	1/4W	
R1121	1-249-441-11	CARBON	100K	5%	1/4W	
R1133	1-249-405-11	CARBON	100	5%	1/4W	
R1134	1-249-405-11	CARBON	100	5%	1/4W	
R1137	1-249-411-11	CARBON	330	5%	1/4W	
R1138	1-249-415-11	CARBON	680	5%	1/4W	
R1139	1-249-413-11	CARBON	470	5%	1/4W	
R1140	1-249-413-11	CARBON	470	5%	1/4W	
R1141	1-249-413-11	CARBON	470	5%	1/4W	
R1142	1-249-415-11	CARBON	680	5%	1/4W	
R1147	1-249-405-11	CARBON	100	5%	1/4W	
R1148	1-249-405-11	CARBON	100	5%	1/4W	
R1149	1-249-417-11	CARBON	1K	5%	1/4W	
R1150	1-249-405-11	CARBON	100	5%	1/4W	
R1151	1-249-405-11	CARBON	100	5%	1/4W	
R1152	1-249-417-11	CARBON	1K	5%	1/4W	
		<CONNECTOR>				
U12	1-573-300-11	CONNECTOR, BOARD TO BOARD 18P				
U13	1-573-300-11	CONNECTOR, BOARD TO BOARD 18P				
U16	*1-564-513-11	PLUG, CONNECTOR 10P				
U22	1-566-942-11	CONNECTOR,HINGE(RECEPTACLE)30P				
U23	*1-566-367-11	CONNECTOR, HINGE (RECEPTACLE)				
U47	*1-564-506-11	PLUG, CONNECTOR 3P				
**********						
	*A-1394-432-A	UT BOARD, COMPLETE **********				
		<CAPACITOR>				
C1152	1-102-074-00	CERAMIC	0.001MF	10%	50V	
C1154	1-164-096-11	CERAMIC	0.01MF		50V	
C1155	1-126-103-11	ELECT	470MF	20%	16V	
C1158	1-124-598-11	ELECT	22MF	20%	25V	
C1160	1-124-598-11	ELECT	22MF	20%	25V	
C1161	1-124-598-11	ELECT	22MF	20%	25V	
C1164	1-126-103-11	ELECT	470MF	20%	16V	
C1165	1-126-301-11	ELECT	1MF	20%	50V	
C1166	1-126-301-11	ELECT	1MF	20%	50V	
C1167	1-126-301-11	ELECT	1MF	20%	50V	

The components identified by shading and mark ⚠ are critical for safety.
Replace only with part number specified.

Les composants identifies par une trame et une marque ⚠ sont critiques pour la securite.
Ne les remplacer que par une piece portant le numero specifie.

• The components identified by ⊠ in this manual have been carefully factory-selected for each set in order to satisfy regulations regarding X-ray radiation. Should replacement be required, replace only with the value originally used.

REF.NO.	PART NO.	DESCRIPTION				REMARK
C1168	1-126-301-11	ELECT	1MF	20%	50V	
C1199	1-102-129-00	CERAMIC	0.01MF	10%	50V	
C1200	1-102-129-00	CERAMIC	0.01MF	10%	50V	
		<DIODE>				
D1152	8-719-110-36	DIODE RD13ES-B2				
D1158	8-719-110-36	DIODE RD13ES-B2				
D1159	8-719-110-36	DIODE RD13ES-B2				
D1160	8-719-110-36	DIODE RD13ES-B2				
D1163	8-719-110-36	DIODE RD13ES-B2				
D1164	8-719-110-36	DIODE RD13ES-B2				
D1165	8-719-110-36	DIODE RD13ES-B2				
D1166	8-719-110-36	DIODE RD13ES-B2				
D1167	8-719-110-36	DIODE RD13ES-B2				
D1168	8-719-110-36	DIODE RD13ES-B2				
D1169	8-719-110-36	DIODE RD13ES-B2				
D1170	8-719-110-36	DIODE RD13ES-B2				
		<JACK>				
J1001	1-537-187-11	TERMINAL, PUSH (4P)				
J1003	1-573-970-11	BLOCK, (S) TERMINAL				
J1004	1-695-049-11	BLOCK, (S) TERMINAL				
J1005	1-695-054-11	JACK BLOCK, PIN				
J1006	1-573-970-11	BLOCK, (S) TERMINAL				
J1007	1-573-969-11	JACK BLOCK, PIN				
J1008	1-573-969-11	JACK BLOCK, PIN				
		<RESISTOR>				
R1153	1-249-403-11	CARBON	68	5%	1/4W	
R1164	1-247-895-00	CARBON	470K	5%	1/4W	
R1165	1-247-895-00	CARBON	470K	5%	1/4W	
R1166	1-247-895-00	CARBON	470K	5%	1/4W	
R1167	1-247-895-00	CARBON	470K	5%	1/4W	
R1168	1-247-895-00	CARBON	470K	5%	1/4W	
R1169	1-249-403-11	CARBON	68	5%	1/4W	
R1170	1-249-403-11	CARBON	68	5%	1/4W	
R1171	1-247-895-00	CARBON	470K	5%	1/4W	
R1172	1-247-895-00	CARBON	470K	5%	1/4W	
R1173	1-247-804-11	CARBON	75	5%	1/4W	
R1174	1-247-895-00	CARBON	470K	5%	1/4W	
R1175	1-247-895-00	CARBON	470K	5%	1/4W	
R1176	1-247-804-11	CARBON	75	5%	1/4W	
R1178	1-247-895-00	CARBON	470K	5%	1/4W	
R1179	1-247-895-00	CARBON	470K	5%	1/4W	
R1180	1-247-804-11	CARBON	75	5%	1/4W	
R1181	1-247-804-11	CARBON	75	5%	1/4W	
R1183	1-247-895-00	CARBON	470K	5%	1/4W	
R1184	1-247-895-00	CARBON	470K	5%	1/4W	
R1185	1-247-895-00	CARBON	470K	5%	1/4W	
R1186	1-247-895-00	CARBON	470K	5%	1/4W	
R1188	1-247-804-11	CARBON	75	5%	1/4W	
R1191	1-249-425-11	CARBON	4.7K	5%	1/4W	
R1192	1-249-425-11	CARBON	4.7K	5%	1/4W	
R1193	1-249-425-11	CARBON	4.7K	5%	1/4W	
R1194	1-249-425-11	CARBON	4.7K	5%	1/4W	
R1196	1-249-426-11	CARBON	5.6K	5%	1/4W	
		<SWITCH>				
S1150	1-572-198-11	SWITCH, KEYBOARD				

REF.NO.	PART NO.	DESCRIPTION	REMARK
		<CONNECTOR>	
UT11	*1-564-519-11	PLUG, CONNECTOR 4P	
UT22	*1-566-941-11	CONNECTOR, HINGE (TAB) 30P	
UT23	*1-566-641-11	CONNECTOR, HINGE (TAB) 18P	
UT35	*1-564-518-11	PLUG, CONNECTOR 3P	
		**********	
		MISCELLANEOUS	
		**********	
	⚠1-241-744-11	RESISTOR ASSY (HIGH-VOLTAGE)	
	⚠1-451-396-21	DEFLECTION YOKE (Y936PA)	
	⚠1-452-443-13	NECK ASSY, PICTURE TUBE(NA367)	
	⚠1-453-108-11	DC BLOCK, HIGH-VOLTAGE	
	1-544-768-11	SPEAKER (13CM) (COAXIAL)	
	*1-555-110-00	CABLE, PIN	
	1-561-306-00	JACK, PIN (F)	
	1-574-590-31	LEAD ASSY, HIGH-VOLTAGE	
	⚠1-696-002-12	CORD, POWER (WITH NOISE FILTER)	
V902	⚠8-736-631-05	PICTURE TUBE (SD-249 (G))	
V903	⚠8-736-632-05	PICTURE TUBE (SD-249 (B))	
V901	⚠8-736-633-05	PICTURE TUBE (SD-249 (R))	
⊠R900	⚠	METAL FILM 1/4W	
⊠R901	⚠	METAL FILM 1/4W	
⊠R902	⚠	METAL FILM 1/4W	
		**********	
		ACCESSORIES AND PACKING MATERIALS	
		**********	
	*3-704-356-01	SHEET (STANDARD), PROTECTION	
	3-756-987-21	MANUAL, INSTRUCTION	
	3-756-987-31	MANUAL, INSTRUCTION (KP-41EXR96(C))	
	3-756-987-41	MANUAL, INSTRUCTION (KP-41EXR96(U))	
	*4-030-895-01	JOINT	
	*4-036-102-01	CUSHION (UPPER) (ASSY)	
	*4-036-106-01	INDIVIDUAL CARTON	
	*4-036-107-01	TRAY	
	*4-036-108-01	CUSHION (LOWER) (ASSY)	
	*4-381-155-01	BAG, PROTECTION	
		REMOTE COMMANDER	
	1-693-114-21	REMOTE COMMANDER (RM-Y112A)	
	9-902 719-01	COVER (FOR RM-Y112A)	
	9-998-214-01	COVER, BATTERY (FOR RM-Y112A)	

9-964-938-01

Sony Corporation
TV Group

English
93DJ0247-1
Printed in Japan

Watching Two Pictures at Once (PIP)

You can watch both the main picture and a window picture simultaneously, using the Picture-in-Picture (PIP) function.

KP-41EXR96 is equipped with one-tuner PIP. To watch two TV channels simultaneously, you must first connect a VCR to the projection TV, which will enable you to watch a second TV channel through the VCR tuner. (See "Connecting Other Equipment," pp. 15 –19.)
Other models are equipped with two-tuner PIP, allowing you to watch two TV channels at once.



Picture-in-Picture special features
When watching the main picture and a window picture, you can:
- Swap the main and window pictures (SWAP).
- Change the position of the window picture (POSITION).
- Display a still picture (FREEZE).
- Choose the sound from the main or window picture (AUDIO).

Notes
- The window picture sound is also output from the AUDIO (VAR) OUT jacks. The AUDIO OUT and MONITOR OUT jacks output the main picture sound only.
- The video label and channel caption will not appear with the window picture even if you have set them.
- If you select a blocked channel in the window picture, the display "BLOCKED" appears with the window picture. (See "Setting CHANNEL BLOCK," pp. 62 – 63.)

Displaying a window picture

Remote Commander



Press PIP to display a window picture



A window picture appears in the last mode you watched. Each time you press PIP, a 1/9 or 1/16 size window picture appears alternately.

To turn PIP function off
Press OFF.
The window picture disappears.

To receive the window picture sound
Press AUDIO.

The ♪ display appears for a few seconds, indicating that the window picture sound is being received.

To restore the main picture sound
Press AUDIO again.

Changing the window picture input mode

Remote Commander



1 Press PIP to display a window picture.



2 Press TV/VIDEO in the Picture-in-Picture control area to select the input mode.
Each time you press TV/VIDEO, "TV," "VIDEO 1," "VIDEO 2" and "VIDEO 3" appear in sequence.



To change TV channels in the window picture
Press CH +/– in the PIP control area.

Displaying CATV input as a window picture

To use Picture-in-Picture with pay cable TV input, make the connections to your cable converter box as shown below.



After making the above connections, turn the cable connection on by following the steps on pp. 26 – 27; then continue with the steps below.

1–2 Follow steps 1 – 2 in "Changing the window picture input mode" on this page to select the video input mode for your connected VCR.

3 Put your VCR on an inactive channel (channel 3 or 4).

4 Change pay cable TV channels with the decoder box.

To control your cable converter box with the supplied Remote Commander
See p. 70.

Changing the position of the window picture

Follow these instructions to change the position of the window picture on the screen.

Remote Commander



1 Press PIP to display a window picture.



2 Press POSITION.
Each time you press POSITION, the window picture moves as illustrated.



Displaying a still picture

Use the FREEZE function to display a still picture. This function is useful when you want to write down a recipe from a cooking program, a displayed address or phone number and so on.

Remote Commander



1 Press PIP to display a window picture.



2 Press FREEZE.
The window picture image remains still on the screen.



To restore the normal picture
Press FREEZE again.

Swapping the main and window pictures

Follow these instructions to swap the input signals of the main and window pictures.

Remote Commander



1 Press PIP to display a window picture.



2 Press SWAP.
Each time you press SWAP, the images from the main and window pictures switch places.



Adjusting the Projection TV

You can adjust the picture and sound for each input mode (TV, VIDEO 1, VIDEO 2, VIDEO 3) by pressing TV/VIDEO on the projection TV or on the Remote Commander to select the input mode, before making the adjustments. These adjustments are retained in memory even when you turn off the projection TV, but are cancelled after you change the adjustments, or select a picture and sound mode (pp. 38 – 39).

Adjusting the picture

Follow these instructions to adjust PICTURE, HUE, COLOR, BRIGHT (brightness) and SHARP (sharpness).

Remote Commander (with video control cover open)



1 Press MENU.
The main menu appears, and the cursor points to "PROG PALETTE."



2 Press RETURN.
The program palette menu appears.



3 Press A/V WINDOW +/– until the cursor points to "VIDEO."

4 Press RETURN.
The VIDEO screen appears.



5 Press A/V WINDOW +/– until the cursor points to the item you want to adjust.

6 Press RETURN.
The adjustment screen appears.

7 Press A/V WINDOW +/– to make the adjustment.

Picture quality	Press A/V WINDOW –	Press A/V WINDOW +
PICTURE	For decreased picture contrast with soft color	For increased picture with vivid color
HUE	Skin tones become purplish	Skin tones become greenish
COLOR	For less color intensity	For more color intensity
BRIGHT	For less brightness	For more brightness
SHARP	For less sharpness	For more sharpness

8 Press RETURN.
The adjustment is complete, and the VIDEO screen automatically reappears.



To adjust other items
Repeat steps 5 – 8.

To restore the factory settings for all the items
Select "STANDARD" on the program palette menu, and press RETURN;
or, press STANDARD on the Remote Commander.
All the items, including TRINITONE (p. 46) and NR (p. 47) return to their original factory settings.

To adjust picture contrast
You can also adjust picture contrast with the PICTURE +/– buttons on the Remote Commander.

Press + to increase picture contrast with vivid color.
Press – to decrease picture contrast with soft color.
The picture adjustment screen appears.

To return to the previous menu
Press A/V WINDOW +/– until the cursor points to "MENU."
Then press RETURN.

To return to the main menu
Repeat the above, until you reach the main menu.

To return to the normal screen
Press MENU.

Setting the TRINITONE mode

Color picture tubes are usually manufactured with a fixed color temperature (tint) that determines the "warmth" (red tint) or "coolness" (blue tint) of the picture. Use the Sony Trinitone feature to adjust the picture color to your preference.

Remote Commander



1 Press MENU.
The main menu appears, and the cursor points to "PROG PALETTE."



2 Press RETURN.
The program palette menu appears.



3 Press A/V WINDOW +/– until the cursor points to "VIDEO."

4 Press RETURN.
The VIDEO screen appears.



5 Press A/V WINDOW +/– until the cursor points to "TRINITONE."

6 Press RETURN.
The mode display turns red.

7 Press A/V WINDOW +/– to select "HIGH" or "LOW."

Select "HIGH" to make the picture cool (bluish).
Select "LOW" to make the picture warm (reddish).

8 Press RETURN.
The setting is complete.

To return to the previous menu
Press A/V WINDOW +/– until the cursor points to " ⊃ MENU."
Then press RETURN.

To return to the main menu
Repeat the above, until you reach the main menu.

To return to the normal screen
Press MENU.

Setting NR (picture noise reduction) ON or OFF

Follow these instructions to reduce picture noise.

Remote Commander



1 Press MENU.
The main menu appears, and the cursor points to "PROG PALETTE."



2 Press RETURN.
The program palette menu appears.



3 Press A/V WINDOW +/– until the cursor points to "VIDEO."

4 Press RETURN.
The VIDEO screen appears.

5 Press A/V WINDOW +/– until the cursor points to "NR."



6 Press RETURN.
The mode display turns red.

7 Press A/V WINDOW +/– to select "ON" or "OFF."

Select "ON" to reduce picture noise.
Select "OFF" to restore the normal picture.

8 Press RETURN.
The setting is complete.

To return to the previous menu
Press A/V WINDOW +/– until the cursor points to " ⊃ MENU."
Then press RETURN.

To return to the main menu
Repeat the above, until you reach the main menu.

To return to the normal screen
Press MENU.

Setting S-VIDEO ON or OFF

Follow these instructions to set S-VIDEO on or off, depending on the kind of video equipment you have connected to the projection TV. For instructions on connecting video equipment, see pp. 15 – 18.

Note
If the projection TV is in TV, VIDEO 2 or VIDEO 3 mode, the "S-VIDEO" display is shaded and cannot be selected. Press TV/VIDEO on the projection TV or on the Remote Commander to change to VIDEO 1 mode.

Remote Commander



1 Press MENU.
The main menu appears.



2 Press A/V WINDOW +/– until the cursor points to "MODE SET."

3 Press RETURN.
The mode set menu appears, with the cursor pointing to "S-VIDEO."



4 Press RETURN.
The mode display turns red.

5 Press A/V WINDOW +/– to select "ON" or "OFF."

6 Press RETURN.
The setting is complete.

To return to the previous menu
Press A/V WINDOW +/– until the cursor points to "⊃ MENU."
Then press RETURN.

To return to the main menu
Repeat the above, until you reach the main menu.

To return to the normal screen
Press MENU.

Adjusting the sound

Follow these instructions to adjust the TREBLE, BASS and BALANCE.

Remote Commander (with video control cover open)



1 Press MENU.
The main menu appears, and the cursor points to "PROG PALETTE."

2 Press RETURN.
The program palette menu appears.



3 Press A/V WINDOW +/– until the cursor points to "AUDIO."

4 Press RETURN.
The AUDIO screen appears.

5 Press A/V WINDOW +/– until the cursor points to the item you want to adjust.

6 Press RETURN.
The adjustment screen appears.

7 Press A/V WINDOW +/– to make the adjustment.

Sound quality	Press A/V WINDOW –	Press A/V WINDOW +
TREBLE	To decrease the treble response	To increase the treble response
BASS	To decrease the bass response	To increase the bass response
BALANCE	To emphasize the left speaker's volume	To emphasize the right speaker's volume

8 Press RETURN.
The adjustment is complete, and the AUDIO screen automatically reappears.

To adjust other items
Repeat steps 5 – 9.

To restore the factory settings for all the items
Select "STANDARD" on the program palette menu, and press RETURN; or, press STANDARD on the Remote Commander.
All the items, including SRS mode (p. 50) return to their original factory settings.

To return to the previous menu
Press A/V WINDOW +/– until the cursor points to "⊃ MENU."
Then press RETURN.

To return to the main menu
Repeat the above, until you reach the main menu.

To return to the normal screen
Press MENU.

Selecting an SRS (Sound Retrieval System) mode

For lifelike sound reproduction, follow the instructions below to select the SRS mode you prefer.

In SRS AUTO mode, SRS functions in both monaural and stereo modes.

Monaural sound programs will have a 'simulated stereo' effect.

In SRS STEREO mode, SRS functions only when a stereo program is received.
The STEREO lamp on the TV lights up whenever a stereo broadcast is received.

Select SRS OFF mode to return to normal sound mode.

Remote Commander



1 Press MENU.
The main menu appears, and the cursor points to "PROG PALETTE."



2 Press RETURN.
The program palette menu appears.



3 Press A/V WINDOW +/– until the cursor points to "AUDIO."

4 Press RETURN.
The AUDIO screen appears.

5 Press A/V WINDOW +/– until the cursor points to the SRS mode you want.

6 Press RETURN.
The mode is selected.

To change the SRS mode
Repeat steps 5 – 6.

To return to the previous menu
Press A/V WINDOW +/– until the cursor points to " ⊃ MENU."
Then press RETURN.

To return to the main menu
Repeat the above, until you reach the main menu.

To return to the normal screen
Press MENU.

Selecting an MTS (Multichannel TV Sound) mode

Follow these instructions to select an MTS mode.

Select MAIN mode to listen to stereo sound.
The STEREO lamp on the projection TV lights up whenever a stereo broadcast is received.

Select SAP mode to listen to Second Audio Programs.

Select MONO mode to eliminate excessive noise during stereo broadcasts, caused by a weak incoming signal.

Note
If the projection TV is in video mode, the "MTS" display is shaded and cannot be selected.
Press TV/VIDEO on the projection TV or on the Remote Commander to change to TV mode.

Remote Commander



1 Press MENU.
The main menu appears.



2 Press A/V WINDOW +/– until the cursor points to "MODE SET."

3 Press RETURN.
The mode set menu appears.



4 Press A/V WINDOW +/– until the cursor points to "MTS."

5 Press RETURN.
The mode display turns red.

6 Press A/V WINDOW +/– to select the mode you want.
Each time you press A/V WINDOW +/–, "MAIN," "SAP" and "MONO" appear in sequence.

7 Press RETURN.
The mode is selected.

To return to the previous menu
Press A/V WINDOW +/– until the cursor points to " ⊃ MENU."
Then press RETURN.

To return to the main menu
Repeat the above, until you reach the main menu.

To return to the normal screen
Press MENU.

Setting SPEAKER — MAIN or CENTER

Follow these instructions to set SPEAKER to "CENTER" when you connect an audio system (p.19), and to "MAIN" when you want to listen to the sound from the projection TV speakers.

Remote Commander



1 Press MENU.
The main menu appears.



2 Press A/V WINDOW +/– until the cursor points to "MODE SET."

3 Press RETURN.
The mode set menu appears.



4 Press A/V WINDOW +/– until the cursor points to "SPEAKER."

5 Press RETURN.
The mode display turns red.

6 Press A/V WINDOW +/– to select "MAIN" or "CENTER."

7 Press RETURN.
The setting is complete.

To return to the previous menu
Press A/V WINDOW +/– until the cursor points to "MENU."
Then press RETURN.

To return to the main menu
Repeat the above, until you reach the main menu.

To return to the normal screen
Press MENU.

Setting channel captions — CH CAPTION

Follow these instructions to caption each channel number display with a name, for instance, the television station call letters. (You can set up to four letters or numbers).

Example: Caption channel 15 as "NBC."

Remote Commander



1 Press MENU.
The main menu appears.



2 Press A/V WINDOW +/– until the cursor points to "SET UP."

3 Press RETURN.
The set up menu appears.



4 Press A/V WINDOW +/– until the cursor points to "CH CAPTION."

5 Press RETURN.
The CH CAPTION screen appears.



6 Press CH +/–, or press 1, 5 and ENTER to set channel "15."



7 Press RETURN.
The first caption space turns red.

8 Press A/V WINDOW +/– to select "N."
Each time you press A/V WINDOW +/–, "0" – "9," "A" – "Z," "&," "/," "-" and "_" (blank space) appear in sequence.



9 Press RETURN.
The second caption space turns red.

(Continued)

Setting channel captions – CH CAPTION
(Cont'd. from prev. page)

Remote Commander



10 Press A/V WINDOW +/– to select "B."



11 Press RETURN.
The third caption space turns red.

12 Press A/V WINDOW +/– to select "C."



13 Press RETURN.
The fourth caption space turns red.

14 Press A/V WINDOW +/– to select a blank space.



15 Press RETURN.
The setting is complete.
When you select or display the channel number, the channel caption also appears.

To caption more channels
Repeat steps 6 – 15.

To erase unnecessary captions
Display the CH CAPTION screen, select the channel with the caption you want to erase, and select blank spaces for the channel caption; then press RETURN.
The caption for that channel is erased.

To return to the previous menu
Press A/V WINDOW +/– until the cursor points to " ⊃ MENU."
Then press RETURN.

To return to the main menu
Repeat the above, until you reach the main menu.

To return to the normal screen
Press MENU.

Note
You can set up to 32 channel captions. If the memory is full, "The memory is full, sorry" appears on the screen. Erase any unnecessary captions, and begin again.

Setting VIDEO LABEL

Follow these instructions to label each input mode, in order to identify the equipment connected to each input terminal.

Example: Label VIDEO 1 IN as "VHS."

Remote Commander



1 Press MENU.
The main menu appears.

2 Press A/V WINDOW +/– until the cursor points to "SET UP."

3 Press RETURN.
The set up menu appears.



4 Press A/V WINDOW +/– until the cursor points to "VIDEO LABEL."

5 Press RETURN.
The VIDEO LABEL screen appears.

6 Press A/V WINDOW +/– until the cursor points to the input mode you want to label. (In this case, the cursor is already pointing to "VIDEO 1.")

7 Press RETURN.
The label display turns red.

8 Press A/V WINDOW +/– to select "VHS."

Each time you press A/V WINDOW +/–, the label changes:

VIDEO 1
VIDEO 1 → BETA → 8mm → VHS → LD → S-VIDEO

VIDEO 2
VIDEO 2 → BETA → 8mm → VHS → LD

VIDEO 3
VIDEO 3 → BETA → 8mm → VHS → LD

9 Press RETURN.
The setting is complete.
When you select or display the video mode, the video label appears.

To label other input modes
Repeat steps 6 – 9.

To change a label
Same as above.

To return to the previous menu
Press A/V WINDOW +/– until the cursor points to " ⊃ MENU."
Then press RETURN.

To return to the main menu
Repeat the above, until you reach the main menu.

To return to the normal screen
Press MENU.

Using Timer-Activated Functions

Setting DAYLIGHT SAVING

If you live in an area that uses daylight savings time, set DAYLIGHT SAVING to "YES" or "NO" depending on the season, before setting the current time. At the next daylight savings date, you will be able to automatically adjust all the time-related settings (CURRENT TIME, ON/OFF TIMER and CHANNEL BLOCK) simply by changing the DAYLIGHT SAVING setting.

When setting DAYLIGHT SAVING:

- **After the first Sunday in April (spring daylight savings)**
  Set to "YES" before setting the current time.
  Then, on the last Sunday in October (fall daylight savings), set to "NO."
  All the time-related settings automatically move one hour back.
- **After the last Sunday in October (fall daylight savings)**
  Set to "NO" before setting the current time.
  Then, on the first Sunday in April (spring daylight savings), set to "YES."
  All the time-related settings automatically move one hour ahead.

Remote Commander



Follow these instructions to set DAYLIGHT SAVING to "YES" or "NO."

1 Press MENU.
The main menu appears.



2 Press A/V WINDOW +/– until the cursor points to "TIME."

3 Press RETURN.
The time menu appears.



4 Press A/V WINDOW +/– until the cursor points to "DAYLIGHT SAVING."

5 Press RETURN.
The mode display turns red.

6 Press A/V WINDOW +/– to select "YES" or "NO."

7 Press RETURN.
The setting is complete.

To return to the previous menu
Press A/V WINDOW +/– until the cursor points to " ⊃ MENU."
Then press RETURN.

To return to the main menu
Repeat the above, until you reach the main menu.

To return to the normal screen.
Press MENU.

Setting the clock — CURRENT TIME SET

Follow these instructions to set the current time. The correct current time must be set in order to use the other time-related functions (DAYLIGHT SAVING, ON/OFF TIMER, CHANNEL BLOCK).

Example: Set the time to 3:15 PM, Monday.

Remote Commander



1 Press MENU.
The main menu appears.



2 Press A/V WINDOW +/– until the cursor points to "TIME."

3 Press RETURN.
The time menu appears, and the cursor points to "CURRENT TIME SET."



4 Press RETURN again.
The CURRENT TIME SET screen appears, with a reminder to set DAYLIGHT SAVING.

If you do not need to set DAYLIGHT SAVING, press RETURN and continue from step 5.

To set daylight saving

a Press A/V WINDOW +/– until the cursor points to "DAYLIGHT SAVING."

b Press RETURN.
The time menu appears, and the cursor points to "DAYLIGHT SAVING."

c Press RETURN.

d Press A/V WINDOW +/– to select "YES" or "NO."

e Press RETURN.
The setting is complete.

To set the time, press A/V WINDOW +/– until the cursor points to "CURRENT TIME SET"; press RETURN, then continue from step 5.

5 Press RETURN.
The CURRENT TIME SET screen appears, and the "SUN" display appears (red).

6 Press A/V WINDOW +/– to select "MON."
Each time you press A/V WINDOW +/–, the day changes consecutively.



(Continued)

Setting the clock — CURRENT TIME SET
(Cont'd. from prev. page)

Remote Commander



7 Press RETURN.
The hour and am/pm displays turn red.

8 Press A/V WINDOW +/– to set "3:00PM."
Each time you press A/V WINDOW +/–, the hour changes in sequence beginning with "12:00AM."



9 Press RETURN.
The minute display turns red.

10 Press A/V WINDOW +/– to select "15" (minutes).
Each time you press A/V WINDOW +/–, the minutes change in sequence.



11 Press RETURN.
The cursor points to "START."

12 Check the actual time, and press RETURN to start the clock.
The setting is complete.

To reset the time
Display the CURRENT TIME SET screen and repeat steps 5 – 12.

To display the current time
Press DISPLAY.

To return to the previous menu
Press A/V WINDOW +/– until the cursor points to " ⊃ MENU."
Then press RETURN.

To return to the main menu
Repeat the above, until you reach the main menu.

To return to the normal screen.
Press MENU.

Setting the ON/OFF TIMER

Follow these instructions to make the program of your choice appear on the screen at a specified time.

Example: Set the timer to turn on the projection TV every Monday through Friday at 1:30 AM for 3 hours, on channel 8, as PROGRAM 1. (You can set up to three programs.)

Remote Commander



1 Press MENU.
The main menu appears.



2 Press A/V WINDOW +/– until the cursor points to "TIME."

3 Press RETURN.
The time menu appears.



4 Press A/V WINDOW +/– until the cursor points to "ON/OFF TIMER."

5 Press RETURN.
The ON/OFF TIMER screen appears, and the cursor points to "1."



6 To set program 1, press RETURN.
(To set program 2 or 3, press A/V WINDOW +/– until the cursor points to that program; then press RETURN.)
The day input space turns red.

7 Press A/V WINDOW +/– to select "EVERY MON-FRI"; then press RETURN.
Each time you press A/V WINDOW +/–, the days of the week change as shown in Fig. 1 (p. 61).



8 Press A/V WINDOW +/– to select "1:00AM"; then press RETURN.
Each time you press A/V WINDOW +/–, the hour changes in sequence.



(Continued)

Setting the ON-OFF TIMER *(Cont'd from prev. page)*

Remote Commander



9 Press A/V WINDOW +/– to select "30" (minutes); then press RETURN.
Each time you press A/V WINDOW +/–, the minutes change in sequence.



10 Press A/V WINDOW +/– to select "3" (hour duration); then press RETURN.
Each time you press A/V WINDOW +/–, the duration changes from "1" – "6" in sequence.



11 Press A/V WINDOW +/– to select "8" (channel); then press RETURN.
The TIMER/STAND BY lamp lights, indicating that the setting is complete.
Each time you press A/V WINDOW +/–, the channel number changes from 1 – 125 in sequence.



The display "TIMER WILL BE OFF" appears on the screen one minute before the timer duration ends.

To set program 2 or 3.
Press RETURN and repeat steps 6 – 11.

To erase an ON/OFF TIMER setting
Display the ON/OFF TIMER screen, select the setting you want to erase, and select a blank space for the day.
The ON/OFF TIMER setting is erased.

To enter a new ON/OFF TIMER setting
Display the ON/OFF TIMER screen and repeat steps 6 – 11.

To return to the previous menu
Press A/V WINDOW +/– until the cursor points to "⊃ MENU."
Then press RETURN.

To return to the main menu
Repeat the above, until you reach the main menu.

To return to the normal screen.
Press MENU.

Note
If you unplug the projection TV or a power failure occurs, both the clock and timer settings will be erased. Reset the current time; then set the timer.

Fig. 1
Selecting the day(s) of the week
When you press A/V WINDOW +, the days of the week appear in the following order:



The components identified by shading and mark ⚠ are critical for safety.
Replace only with part number specified.

Les composants identifies par une trame et une marque ⚠ sont critiques pour la securite.
Ne les remplacer que par une piece portant le numero specifie.

REF.NO.	PART NO.	DESCRIPTION	REMARK
		<DIODE>	
D801	8-719-928-08	DIODE ERD28-08S	
D802	8-719-300-80	DIODE RU-1C	
D803	8-719-109-85	DIODE RD5.1ES-B2	
D804	8-719-911-19	DIODE 1SS119	
D805	8-719-911-19	DIODE 1SS119	
D806	8-719-109-85	DIODE RD5.1ES-B2	
D807	8-719-109-85	DIODE RD5.1ES-B2	
D808	8-719-911-19	DIODE 1SS119	
D809	8-719-911-19	DIODE 1SS119	
D810	8-719-911-19	DIODE 1SS119	
D811	8-719-109-85	DIODE RD5.1ES-B2	
D812	8-719-911-19	DIODE 1SS119	
D813	8-719-911-19	DIODE 1SS119	
D814	8-719-911-19	DIODE 1SS119	
D815	8-719-110-36	DIODE RD13ES-B2	
D817	8-719-945-80	DIODE ERC06-15S	
D818	8-719-911-19	DIODE 1SS119	
D820	8-719-911-19	DIODE 1SS119	
D850	8-719-109-71	DIODE RD3.9ES-B1	
D851	⚠ 8-719-903-09	DIODE V30N	
D852	8-719-911-19	DIODE 1SS119	
D853	⚠ 8-719-903-09	DIODE V30N	
D891	8-719-110-49	DIODE RD18ES-B2	
D892	8-719-110-49	DIODE RD18ES-B2	
		<IC>	
IC801	8-759-231-58	IC TA7812S	
IC802	8-759-103-93	IC UPC393C	
IC803	8-759-990-82	IC TL082CP	
IC804	8-759-103-93	IC UPC393C	
IC805	8-759-100-75	IC UPC1394C	
		<COIL>	
L801	1-459-862-11	COIL, CHOKE 90UH	
L802	1-424-603-11	COIL, CHOKE 1.05MMH	
L803	1-459-313-00	COIL WITH CORE (HWC)	
L804	1-410-482-31	INDUCTOR 100UH	
L805	⚠ 1-424-603-11	COIL, CHOKE 1.05MMH	
		<CONNECTOR>	
N1	1-506-348-99	PIN, CONNECTOR 3P	
N2	*1-564-508-11	PLUG, CONNECTOR 5P	
N3	*1-508-766-00	PIN, CONNECTOR (5MM PITCH) 4P	
N4	*1-564-507-11	PLUG, CONNECTOR 4P	
N5	*1-564-508-11	PLUG, CONNECTOR 5P	
N6	*1-508-786-00	PIN, CONNECTOR (5MM PITCH) 2P	
N7	*1-508-765-00	PIN, CONNECTOR (5MM PITCH) 3P	
N8	*1-508-766-00	PIN, CONNECTOR (5MM PITCH) 4P	
N9	1-506-348-99	PIN, CONNECTOR 3P	
N10	*1-564-511-41	PLUG, CONNECTOR 8P	
N20	*1-560-126-00	PLUG, CONNECTOR (2.5MM) 6P	
N21	*1-560-123-00	PLUG, CONNECTOR (2.5MM) 3P	
N30	*1-508-784-00	PIN, CONNECTOR (5MM PITCH) 1P	
N851	*1-506-371-00	PIN, CONNECTOR 2P	
N853	*1-506-371-00	PIN, CONNECTOR 2P	
		<NEON LAMP>	
NL801	1-519-108-99	LAMP, NEON	

REF.NO.	PART NO.	DESCRIPTION				REMARK
		<TRANSISTOR>				
Q801	⚠ 8-729-201-61	TRANSISTOR 2SC2555-I				
Q802	8-729-119-80	TRANSISTOR 2SC2688-LK				
Q803	8-729-119-76	TRANSISTOR 2SA1175-HFE				
Q804	8-729-119-78	TRANSISTOR 2SC2785-HFE				
Q805	8-729-119-78	TRANSISTOR 2SC2785-HFE				
Q806	8-729-119-80	TRANSISTOR 2SC2688-LK				
Q807	8-729-119-78	TRANSISTOR 2SC2785-HFE				
Q808	8-729-119-78	TRANSISTOR 2SC2785-HFE				
Q809	8-729-119-76	TRANSISTOR 2SA1175-HFE				
Q811	⚠ 8-729-805-07	TRANSISTOR 2SD1887-CA				
Q812	8-729-019-88	TRANSISTOR 2SC3675-CB				
Q820	8-729-119-76	TRANSISTOR 2SA1175-HFE				
Q851	8-729-119-78	TRANSISTOR 2SC2785-HFE				
Q852	8-729-119-78	TRANSISTOR 2SC2785-HFE				
Q853	8-729-820-98	TRANSISTOR 2SC4256CB				
		<RESISTOR>				
R801	1-216-378-11	METAL OXIDE	5.6	5%	2W	F
R802	1-215-926-00	METAL OXIDE	33K	5%	3W	F
R803	1-215-926-00	METAL OXIDE	33K	5%	3W	F
R804	1-249-429-11	CARBON	10K	5%	1/4W	
R805	1-249-423-11	CARBON	3.3K	5%	1/4W	
R806	1-249-425-11	CARBON	4.7K	5%	1/4W	
R807	1-249-441-11	CARBON	100K	5%	1/4W	
R808	1-249-417-11	CARBON	1K	5%	1/4W	
R809	1-249-417-11	CARBON	1K	5%	1/4W	
R810	1-249-441-11	CARBON	100K	5%	1/4W	
R811	1-249-421-11	CARBON	2.2K	5%	1/4W	
R812	1-249-420-11	CARBON	1.8K	5%	1/4W	F
R813	1-215-921-11	METAL OXIDE	4.7K	5%	3W	F
R814	1-249-409-11	CARBON	220	5%	1/4W	
R815	1-249-415-11	CARBON	680	5%	1/4W	
R816	1-214-777-00	METAL	100K	1%	1/4W	
R817	1-215-471-00	METAL	120K	1%	1/4W	
R818	1-215-471-00	METAL	120K	1%	1/4W	
R819	1-215-450-00	METAL	16K	1%	1/4W	
R820	1-215-451-00	METAL	18K	1%	1/4W	
R821	1-249-423-11	CARBON	3.3K	5%	1/4W	
R822	1-249-433-11	CARBON	22K	5%	1/4W	
R823	1-249-429-11	CARBON	10K	5%	1/4W	
R824	1-215-469-00	METAL	100K	1%	1/4W	
R825	1-215-453-00	METAL	22K	1%	1/4W	
R826	1-214-962-00	METAL	820K	1%	1/4W	
R827	1-214-764-00	METAL	30K	1%	1/4W	
R828	1-215-455-00	METAL	27K	1%	1/4W	
R829	1-215-455-00	METAL	27K	1%	1/4W	
R830	1-215-928-11	METAL OXIDE	68K	5%	3W	F
R831	1-215-928-11	METAL OXIDE	68K	5%	3W	F
R832	1-249-417-11	CARBON	1K	5%	1/4W	
R833	1-249-419-11	CARBON	1.5K	5%	1/4W	
R834	1-249-419-11	CARBON	1.5K	5%	1/4W	
R835	1-215-429-00	METAL	2.2K	1%	1/4W	
R836	1-215-435-00	METAL	3.9K	1%	1/4W	
R837	1-249-433-11	CARBON	22K	5%	1/4W	
R838	1-249-435-11	CARBON	33K	5%	1/4W	
R839	1-249-438-11	CARBON	56K	5%	1/4W	
R840	1-249-434-11	CARBON	27K	5%	1/4W	
R841	1-249-429-11	CARBON	10K	5%	1/4W	
R842	1-249-435-11	CARBON	33K	5%	1/4W	
R843	1-249-423-11	CARBON	3.3K	5%	1/4W	

Selecting a Picture and Sound Mode

This projection TV features four modes (STANDARD, MOVIE, SPORTS, NEWS) that offer different picture and sound qualities. Choose the one that best suits the type of program that you want to watch.

Example: Select MOVIE mode for picture and sound that gives you the sense of being in a movie theater.



(with video control cover open)

1 Press MENU.
The main menu appears, and the cursor points to "PROG PALETTE."



2 Press RETURN.
The program palette menu appears.



3 Press A/V WINDOW +/– until the cursor points to "MOVIE."





4 Press RETURN.
The "MOVIE" display turns green, indicating that MOVIE mode is selected.



To select a different mode
Repeat steps 3 – 4.

Selecting standard mode (without using the menus)

Follow these instructions to select standard mode without using the on-screen menus.

Press STANDARD.

When you select STANDARD mode
You receive standard picture and sound quality. Any video or audio adjustments you made ("Adjusting the Projection TV," pp. 44 – 52) are cancelled and the original factory settings are restored.

When you select MOVIE mode
You receive a finely detailed picture, and a theatrical audio effect.
To further adjust picture and sound qualities, follow the instructions on pp. 44 – 52.

When you select SPORTS mode
You receive a vivid, bright picture, and sound with a sports stadium effect.
To further adjust picture and sound qualities, follow the instructions on pp. 44 – 52.

When you select NEWS mode
Picture noise is reduced, and you receive clear voice reproduction.
To further adjust picture and sound qualities, follow the instructions on pp. 44 – 52.

To return to the previous menu
Press A/V WINDOW +/– until the cursor points to "⊃ MENU."
Then press RETURN.

To return to the main menu
Repeat the above, until you reach the main menu.

To return to the normal screen.
Press MENU.

N **S**

• The components identified by ⊠ in this manual have been carefully factory-selected for each set in order to satisfy regulations regarding X-ray radiation. Should replacement be required, replace only with the value originally used.

Les composants identifies par une trame et une marque ⚠ sont critiques pour la securite. Ne les remplacer que par une piece portant le numero specifie.

The components identified by shading and mark ⚠ are critical for safety. Replace only with part number specified.

REF.NO.	PART NO.	DESCRIPTION				REMARK
R844	1-249-433-11	CARBON	22K	5%	1/4W	
R845	1-249-435-11	CARBON	33K	5%	1/4W	
R846	1-249-429-11	CARBON	10K	5%	1/4W	
R847	1-214-761-00	METAL	22K	1%	1/4W	
R848	1-215-429-00	METAL	2.2K	1%	1/4W	
R849	1-215-421-00	METAL	1K	1%	1/4W	
R850	1-215-429-00	METAL	2.2K	1%	1/4W	
R851	1-215-404-00	METAL	200	1%	1/4W	
⊠R852 ⚠		METAL			1/4W	
R853	1-215-469-00	METAL	100K	1%	1/4W	
R854	1-249-430-11	CARBON	12K	5%	1/4W	
R855	1-215-469-00	METAL	100K	1%	1/4W	
R856	1-249-430-11	CARBON	12K	5%	1/4W	
R857	1-249-433-11	CARBON	22K	5%	1/4W	
R858	1-249-413-11	CARBON	470	5%	1/4W	
R859	1-249-435-11	CARBON	33K	5%	1/4W	
R860	1-249-441-11	CARBON	100K	5%	1/4W	
R861	1-249-421-11	CARBON	2.2K	5%	1/4W	
R862	1-249-434-11	CARBON	27K	5%	1/4W	
R863	1-249-431-11	CARBON	15K	5%	1/4W	
R864	1-249-423-11	CARBON	3.3K	5%	1/4W	
R865	1-249-440-11	CARBON	82K	5%	1/4W	
R866	1-249-436-11	CARBON	39K	5%	1/4W	
R867	1-249-437-11	CARBON	47K	5%	1/4W	
R868	1-249-428-11	CARBON	8.2K	5%	1/4W	
R869	1-249-429-11	CARBON	10K	5%	1/4W	
R870	1-249-417-11	CARBON	1K	5%	1/4W	
R871	1-249-440-11	CARBON	82K	5%	1/4W	
R872	1-249-423-11	CARBON	3.3K	5%	1/4W	
R873	1-249-441-11	CARBON	100K	5%	1/4W	
R874	1-249-435-11	CARBON	33K	5%	1/4W	
R875	1-249-421-11	CARBON	2.2K	5%	1/4W	
R876	1-215-426-00	METAL	1.6K	1%	1/4W	
R877	1-249-435-11	CARBON	33K	5%	1/4W	
R878	1-249-441-11	CARBON	100K	5%	1/4W	
R879	1-216-489-11	METAL OXIDE	27K	5%	3W	F
R880	1-249-429-11	CARBON	10K	5%	1/4W	
R881	1-214-761-00	METAL	22K	1%	1/4W	
R882	1-249-433-11	CARBON	22K	5%	1/4W	
R883	1-249-417-11	CARBON	1K	5%	1/4W	
R884	1-215-894-11	METAL OXIDE	2.2K	5%	2W	F
R885	1-249-438-11	CARBON	56K	5%	1/4W	
R886	1-249-414-11	CARBON	560	5%	1/4W	
R887	1-215-397-00	METAL	100	1%	1/4W	
R888	1-249-410-11	CARBON	270	5%	1/4W	
R889	1-249-417-11	CARBON	1K	5%	1/4W	
R890	1-249-417-11	CARBON	1K	5%	1/4W	
R891	1-216-489-11	METAL OXIDE	27K	5%	3W	F
R892	1-249-417-11	CARBON	1K	5%	1/4W	F
R893	1-215-453-00	METAL	22K	1%	1/4W	
R894	1-249-401-11	CARBON	47	5%	1/4W	
R895	1-202-731-00	SOLID	10M	20%	1/2W	
R896	1-260-111-11	CARBON	10K	5%	1/2W	
R897	1-247-881-00	CARBON	120K	5%	1/4W	
R898	1-202-730-00	SOLID	8.2M	20%	1/2W	
R899	1-249-429-11	CARBON	10K	5%	1/4W	
R903	1-247-735-11	SOLID	47	20%	1/2W	
R904	1-215-928-11	METAL OXIDE	68K	5%	3W	F
R905	1-215-911-11	METAL OXIDE	100	5%	3W	F

<SPARK GAP>

SG801	1-519-422-11	GAP, SPARK	

REF.NO.	PART NO.	DESCRIPTION				REMARK
		<TRANSFORMER>				
T801 ⚠	1-437-078-11	TRANSFORMER, HORIZONTAL DRIVE				
T802	1-437-090-00	HDT				
T803 ⚠	1-453-121-11	TRANSFORMER ASSY, FLYBACK (NX-2630B4)				
**********						
	*A-1394-421-A	S BOARD, COMPLETE				
		**********				
	*1-565-514-11	SOCKET, CONNECTOR 2P				
		<CAPACITOR>				
C3403	1-164-161-11	CERAMIC CHIP	0.0022MF	10%	50V	
C3408	1-164-232-11	CERAMIC CHIP	0.01MF	10%	50V	
C3409	1-124-477-11	ELECT	47MF	20%	16V	
C3411	1-124-034-51	ELECT	33MF	20%	16V	
C3442	1-164-161-11	CERAMIC CHIP	0.0022MF	10%	50V	
C3446	1-163-129-00	CERAMIC CHIP	330PF	5%	50V	
C3447	1-163-117-00	CERAMIC CHIP	100PF	5%	50V	
C3448	1-163-023-00	CERAMIC CHIP	0.015MF	10%	50V	
C3449	1-164-182-11	CERAMIC CHIP	0.0033MF	10%	50V	
C3450	1-163-109-00	CERAMIC CHIP	47PF	5%	50V	
C3451	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	
C3452	1-163-989-11	CERAMIC CHIP	0.033MF	10%	25V	
C3453	1-124-477-11	ELECT	47MF	20%	16V	
C3454	1-126-162-11	ELECT	3.3MF	20%	50V	
C3455	1-126-163-11	ELECT	4.7MF	20%	16V	
C3456	1-163-129-00	CERAMIC CHIP	330PF	5%	50V	
C3457	1-163-117-00	CERAMIC CHIP	100PF	5%	50V	
C3459	1-124-477-11	ELECT	47MF	20%	16V	
C3460	1-163-099-00	CERAMIC CHIP	18PF	5%	50V	
C3461	1-163-099-00	CERAMIC CHIP	18PF	5%	50V	
C3507	1-164-232-11	CERAMIC CHIP	0.01MF	10%	50V	
C3508	1-164-005-11	CERAMIC CHIP	0.47MF		25V	
C3509	1-163-139-00	CERAMIC CHIP	820PF	5%	50V	
C3515	1-163-121-00	CERAMIC CHIP	150PF	5%	50V	
C3540	1-126-157-11	ELECT	10MF	20%	16V	
		<DIODE>				
D3444	8-719-404-46	DIODE MA110				
		<IC>				
IC3401	8-759-403-44	IC MN1280-S				
IC3402	8-759-070-42	IC M37201M6-A18FP				
IC3441	8-759-982-21	IC RC78L05A				
IC3442	8-759-084-12	IC LA7945				
IC3443	8-759-158-03	IC LC7458A-02				
IC3444	8-759-403-44	IC MN1280-S				
		<COIL>				
L3401	1-408-421-00	INDUCTOR	100UH			
L3461	1-408-409-00	INDUCTOR	10UH			
L3462	1-408-421-00	INDUCTOR	100UH			
		<TRANSISTOR>				
Q3441	8-729-422-27	TRANSISTOR 2SD601A-Q				
Q3444	8-729-903-10	TRANSISTOR FMW1				

REF.NO.	PART NO.	DESCRIPTION				REMARK
		<RESISTOR>				
R3401	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R3402	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R3403	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R3404	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R3405	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	
R3406	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R3407	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R3408	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R3409	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R3441	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R3442	1-216-041-00	METAL GLAZE	470	5%	1/10W	
R3443	1-216-041-00	METAL GLAZE	470	5%	1/10W	
R3444	1-216-077-00	METAL GLAZE	15K	5%	1/10W	
R3445	1-216-689-11	METAL GLAZE	39K	5%	1/10W	
R3446	1-216-085-00	METAL GLAZE	33K	5%	1/10W	
R3449	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R3450	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	
R3451	1-216-093-00	METAL GLAZE	68K	5%	1/10W	
R3452	1-216-079-00	METAL GLAZE	18K	5%	1/10W	
R3453	1-216-679-11	METAL CHIP	15K	0.50%	1/10W	
R3454	1-216-037-00	METAL GLAZE	330	5%	1/10W	
R3455	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	
R3456	1-216-077-00	METAL GLAZE	15K	5%	1/10W	
R3463	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R3464	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R3465	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R3472	1-216-091-00	METAL GLAZE	56K	5%	1/10W	
R3473	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R3474	1-216-295-00	METAL GLAZE	0	5%	1/10W	
R3504	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	
R3509	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R3511	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R3512	1-216-059-00	METAL GLAZE	2.7K	5%	1/10W	
R3513	1-216-059-00	METAL GLAZE	2.7K	5%	1/10W	
R3514	1-216-059-00	METAL GLAZE	2.7K	5%	1/10W	
R3519	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R3520	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R3521	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R3525	1-216-295-00	METAL GLAZE	0	5%	1/10W	
R3526	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R3528	1-216-295-00	METAL GLAZE	0	5%	1/10W	
R3529	1-216-295-00	METAL GLAZE	0	5%	1/10W	
R3530	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R3531	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R3532	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R3535	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R3537	1-216-295-00	METAL GLAZE	0	5%	1/10W	
R3540	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
		<CONNECTOR>				
S42	*1-568-378-21	PIN, CONNECTOR 3P				
S43	*1-564-508-11	PLUG, CONNECTOR 5P				
S45	*1-564-511-71	PLUG, CONNECTOR 8P				
S46	*1-564-506-11	PLUG, CONNECTOR 3P				
S47	*1-564-506-11	PLUG, CONNECTOR 3P				
		<CRYSTAL>				
X3401	1-577-082-11	VIBRATOR, CERAMIC				
X3441	1-577-364-11	VIBRATOR, CERAMIC				

REF.NO.	PART NO.	DESCRIPTION				REMARK
**********						
	*A-1394-422-A	U BOARD, COMPLETE				
		**********				
		<CAPACITOR>				
C1004	1-102-125-00	CERAMIC	0.0047MF	10%	50V	
C1005	1-126-301-11	ELECT	1MF	20%	50V	
C1006	1-164-096-11	CERAMIC	0.01MF		50V	
C1007	1-124-598-11	ELECT	22MF	20%	25V	
C1008	1-124-598-11	ELECT	22MF	20%	25V	
C1010	1-124-465-00	ELECT	0.47MF	20%	50V	
C1011	1-124-465-00	ELECT	0.47MF	20%	50V	
C1012	1-124-465-00	ELECT	0.47MF	20%	50V	
C1013	1-102-125-00	CERAMIC	0.0047MF	10%	50V	
C1014	1-126-163-11	ELECT	4.7MF	20%	50V	
C1016	1-126-163-11	ELECT	4.7MF	20%	50V	
C1018	1-126-301-11	ELECT	1MF	20%	50V	
C1020	1-124-242-00	ELECT	33MF	20%	25V	
C1021	1-124-465-00	ELECT	0.47MF	20%	50V	
C1022	1-124-242-00	ELECT	33MF	20%	25V	
C1026	1-102-949-00	CERAMIC	12PF	5%	50V	
C1027	1-102-949-00	CERAMIC	12PF	5%	50V	
C1028	1-124-242-00	ELECT	33MF	20%	25V	
C1029	1-124-282-00	ELECT	22MF	20%	16V	
C1030	1-124-478-11	ELECT	100MF	20%	25V	
C1031	1-102-963-00	CERAMIC	33PF	5%	50V	
C1033	1-124-598-11	ELECT	22MF	20%	25V	
C1034	1-124-282-00	ELECT	22MF	20%	16V	
C1036	1-124-282-00	ELECT	22MF	20%	16V	
C1037	1-124-282-00	ELECT	22MF	20%	16V	
C1039	1-124-478-11	ELECT	100MF	20%	25V	
C1047	1-124-465-00	ELECT	0.47MF	20%	50V	
C1048	1-126-301-11	ELECT	1MF	20%	50V	
C1049	1-124-598-11	ELECT	22MF	20%	25V	
C1051	1-124-465-00	ELECT	0.47MF	20%	50V	
C1055	1-124-589-11	ELECT	47MF	20%	16V	
C1056	1-124-499-11	ELECT	1MF	20%	50V	
C1057	1-124-768-11	ELECT	4.7MF	20%	50V	
C1059	1-124-499-11	ELECT	1MF	20%	50V	
C1060	1-124-499-11	ELECT	1MF	20%	50V	
C1061	1-124-499-11	ELECT	1MF	20%	50V	
C1062	1-102-129-00	CERAMIC	0.01MF	10%	50V	
C1063	1-124-768-11	ELECT	4.7MF	20%	50V	
C1066	1-126-101-11	ELECT	100MF	20%	16V	
		<BLOCK>				
CM1002	1-466-162-31	BLOCK, COM FILTER (CFB-4)				
		<DIODE>				
D1005	8-719-110-36	DIODE RD13ES-B2				
D1009	8-719-110-36	DIODE RD13ES-B2				
D1010	8-719-110-36	DIODE RD13ES-B2				
D1011	8-719-110-36	DIODE RD13ES-B2				
D1012	8-719-110-36	DIODE RD13ES-B2				
D1013	8-719-110-36	DIODE RD13ES-B2				
D1017	8-719-110-36	DIODE RD13ES-B2				
D1018	8-719-110-36	DIODE RD13ES-B2				
D1019	8-719-110-36	DIODE RD13ES-B2				
D1020	8-719-109-66	DIODE RD3.3ES-B2				
D1021	8-719-109-66	DIODE RD3.3ES-B2				

U UT

REF.NO.	PART NO.	DESCRIPTION				REMARK
D1022	8-719-109-66	DIODE RD3.3ES-B2				
		<IC>				
IC1002	8-752-056-50	IC CXA1545S				
IC1011	8-759-145-57	IC UPC4557C				
		<COIL>				
L1001	1-408-422-00	INDUCTOR	120UH			
L1002	1-408-422-00	INDUCTOR	120UH			
		<TRANSISTOR>				
Q1009	8-729-119-78	TRANSISTOR 2SC2785-HFE				
Q1010	8-729-119-78	TRANSISTOR 2SC2785-HFE				
Q1016	8-729-119-76	TRANSISTOR 2SA1175-HFE				
Q1017	8-729-119-76	TRANSISTOR 2SA1175-HFE				
Q1018	8-729-141-26	TRANSISTOR 2SC3622A-LK				
Q1019	8-729-119-76	TRANSISTOR 2SA1175-HFE				
Q1020	8-729-119-76	TRANSISTOR 2SA1175-HFE				
Q1021	8-729-119-76	TRANSISTOR 2SA1175-HFE				
Q1022	8-729-141-26	TRANSISTOR 2SC3622A-LK				
Q1023	8-729-119-78	TRANSISTOR 2SC2785-HFE				
Q1029	8-729-119-76	TRANSISTOR 2SA1175-HFE				
Q1030	8-729-119-78	TRANSISTOR 2SC2785-HFE				
Q1031	8-729-119-78	TRANSISTOR 2SC2785-HFE				
Q1032	8-729-119-76	TRANSISTOR 2SA1175-HFE				
Q1033	8-729-119-76	TRANSISTOR 2SA1175-HFE				
Q1034	8-729-119-76	TRANSISTOR 2SA1175-HFE				
		<RESISTOR>				
R1011	1-249-435-11	CARBON	33K	5%	1/4W	
R1012	1-249-434-11	CARBON	27K	5%	1/4W	
R1013	1-249-417-11	CARBON	1K	5%	1/4W	
R1014	1-249-441-11	CARBON	100K	5%	1/4W	
R1015	1-249-425-11	CARBON	4.7K	5%	1/4W	
R1016	1-249-441-11	CARBON	100K	5%	1/4W	
R1017	1-249-405-11	CARBON	100	5%	1/4W	
R1018	1-249-427-11	CARBON	6.8K	5%	1/4W	
R1019	1-249-427-11	CARBON	6.8K	5%	1/4W	
R1023	1-249-405-11	CARBON	100	5%	1/4W	
R1026	1-249-425-11	CARBON	4.7K	5%	1/4W	
R1028	1-249-434-11	CARBON	27K	5%	1/4W	
R1029	1-249-435-11	CARBON	33K	5%	1/4W	
R1030	1-249-417-11	CARBON	1K	5%	1/4W	
R1032	1-249-417-11	CARBON	1K	5%	1/4W	
R1033	1-249-393-11	CARBON	10	5%	1/4W	F
R1034	1-249-417-11	CARBON	1K	5%	1/4W	
R1036	1-249-440-11	CARBON	82K	5%	1/4W	
R1037	1-249-440-11	CARBON	82K	5%	1/4W	
R1038	1-249-440-11	CARBON	82K	5%	1/4W	
R1043	1-249-417-11	CARBON	1K	5%	1/4W	
R1046	1-249-413-11	CARBON	470	5%	1/4W	
R1048	1-249-405-11	CARBON	100	5%	1/4W	
R1050	1-249-405-11	CARBON	100	5%	1/4W	
R1051	1-249-417-11	CARBON	1K	5%	1/4W	
R1052	1-249-413-11	CARBON	470	5%	1/4W	
R1054	1-249-405-11	CARBON	100	5%	1/4W	
R1055	1-249-413-11	CARBON	470	5%	1/4W	
R1056	1-249-405-11	CARBON	100	5%	1/4W	
R1057	1-249-441-11	CARBON	100K	5%	1/4W	
R1059	1-249-405-11	CARBON	100	5%	1/4W	
R1061	1-249-409-11	CARBON	220	5%	1/4W	
R1062	1-249-441-11	CARBON	100K	5%	1/4W	
R1063	1-249-409-11	CARBON	220	5%	1/4W	
R1066	1-215-437-00	METAL	4.7K	1%	1/4W	
R1067	1-215-437-00	METAL	4.7K	1%	1/4W	
R1068	1-215-437-00	METAL	4.7K	1%	1/4W	
R1069	1-215-437-00	METAL	4.7K	1%	1/4W	
R1070	1-249-411-11	CARBON	330	5%	1/4W	
R1071	1-249-431-11	CARBON	15K	5%	1/4W	
R1073	1-249-431-11	CARBON	15K	5%	1/4W	
R1077	1-249-418-11	CARBON	1.2K	5%	1/4W	
R1078	1-249-418-11	CARBON	1.2K	5%	1/4W	
R1079	1-249-405-11	CARBON	100	5%	1/4W	
R1080	1-215-423-00	METAL	1.2K	1%	1/4W	
R1081	1-215-421-00	METAL	1K	1%	1/4W	
R1089	1-249-405-11	CARBON	100	5%	1/4W	
R1094	1-249-405-11	CARBON	100	5%	1/4W	
R1096	1-249-405-11	CARBON	100	5%	1/4W	
R1099	1-249-413-11	CARBON	470	5%	1/4W	
R1110	1-249-405-11	CARBON	100	5%	1/4W	
R1116	1-249-441-11	CARBON	100K	5%	1/4W	
R1118	1-249-413-11	CARBON	470	5%	1/4W	
R1121	1-249-441-11	CARBON	100K	5%	1/4W	
R1133	1-249-405-11	CARBON	100	5%	1/4W	
R1134	1-249-405-11	CARBON	100	5%	1/4W	
R1137	1-249-411-11	CARBON	330	5%	1/4W	
R1138	1-249-415-11	CARBON	680	5%	1/4W	
R1139	1-249-413-11	CARBON	470	5%	1/4W	
R1140	1-249-413-11	CARBON	470	5%	1/4W	
R1141	1-249-413-11	CARBON	470	5%	1/4W	
R1142	1-249-415-11	CARBON	680	5%	1/4W	
R1147	1-249-405-11	CARBON	100	5%	1/4W	
R1148	1-249-405-11	CARBON	100	5%	1/4W	
R1149	1-249-417-11	CARBON	1K	5%	1/4W	
R1150	1-249-405-11	CARBON	100	5%	1/4W	
R1151	1-249-405-11	CARBON	100	5%	1/4W	
R1152	1-249-417-11	CARBON	1K	5%	1/4W	
		<CONNECTOR>				
U12	1-573-300-11	CONNECTOR, BOARD TO BOARD 18P				
U13	1-573-300-11	CONNECTOR, BOARD TO BOARD 18P				
U16	*1-564-513-11	PLUG, CONNECTOR 10P				
U22	1-566-942-11	CONNECTOR,HINGE(RECEPTACLE)30P				
U23	*1-566-367-11	CONNECTOR, HINGE (RECEPTACLE)				
U47	*1-564-506-11	PLUG, CONNECTOR 3P				
**********						
	*A-1394-432-A	UT BOARD, COMPLETE **********				
		<CAPACITOR>				
C1152	1-102-074-00	CERAMIC	0.001MF	10%	50V	
C1154	1-164-096-11	CERAMIC	0.01MF		50V	
C1155	1-126-103-11	ELECT	470MF	20%	16V	
C1158	1-124-598-11	ELECT	22MF	20%	25V	
C1160	1-124-598-11	ELECT	22MF	20%	25V	
C1161	1-124-598-11	ELECT	22MF	20%	25V	
C1164	1-126-103-11	ELECT	470MF	20%	16V	
C1165	1-126-301-11	ELECT	1MF	20%	50V	
C1166	1-126-301-11	ELECT	1MF	20%	50V	
C1167	1-126-301-11	ELECT	1MF	20%	50V	

The components identified by shading and mark ⚠ are critical for safety.
Replace only with part number specified.

Les composants identifies par une trame et une marque ⚠ sont critiques pour la securite.
Ne les remplacer que par une piece portant le numero specifie.

• The components identified by ⊠ in this manual have been carefully factory-selected for each set in order to satisfy regulations regarding X-ray radiation. Should replacement be required, replace only with the value originally used.

REF.NO.	PART NO.	DESCRIPTION				REMARK
C1168	1-126-301-11	ELECT	1MF	20%	50V	
C1199	1-102-129-00	CERAMIC	0.01MF	10%	50V	
C1200	1-102-129-00	CERAMIC	0.01MF	10%	50V	
		<DIODE>				
D1152	8-719-110-36	DIODE RD13ES-B2				
D1158	8-719-110-36	DIODE RD13ES-B2				
D1159	8-719-110-36	DIODE RD13ES-B2				
D1160	8-719-110-36	DIODE RD13ES-B2				
D1163	8-719-110-36	DIODE RD13ES-B2				
D1164	8-719-110-36	DIODE RD13ES-B2				
D1165	8-719-110-36	DIODE RD13ES-B2				
D1166	8-719-110-36	DIODE RD13ES-B2				
D1167	8-719-110-36	DIODE RD13ES-B2				
D1168	8-719-110-36	DIODE RD13ES-B2				
D1169	8-719-110-36	DIODE RD13ES-B2				
D1170	8-719-110-36	DIODE RD13ES-B2				
		<JACK>				
J1001	1-537-187-11	TERMINAL, PUSH (4P)				
J1003	1-573-970-11	BLOCK, (S) TERMINAL				
J1004	1-695-049-11	BLOCK, (S) TERMINAL				
J1005	1-695-054-11	JACK BLOCK, PIN				
J1006	1-573-970-11	BLOCK, (S) TERMINAL				
J1007	1-573-969-11	JACK BLOCK, PIN				
J1008	1-573-969-11	JACK BLOCK, PIN				
		<RESISTOR>				
R1153	1-249-403-11	CARBON	68	5%	1/4W	
R1164	1-247-895-00	CARBON	470K	5%	1/4W	
R1165	1-247-895-00	CARBON	470K	5%	1/4W	
R1166	1-247-895-00	CARBON	470K	5%	1/4W	
R1167	1-247-895-00	CARBON	470K	5%	1/4W	
R1168	1-247-895-00	CARBON	470K	5%	1/4W	
R1169	1-249-403-11	CARBON	68	5%	1/4W	
R1170	1-249-403-11	CARBON	68	5%	1/4W	
R1171	1-247-895-00	CARBON	470K	5%	1/4W	
R1172	1-247-895-00	CARBON	470K	5%	1/4W	
R1173	1-247-804-11	CARBON	75	5%	1/4W	
R1174	1-247-895-00	CARBON	470K	5%	1/4W	
R1175	1-247-895-00	CARBON	470K	5%	1/4W	
R1176	1-247-804-11	CARBON	75	5%	1/4W	
R1178	1-247-895-00	CARBON	470K	5%	1/4W	
R1179	1-247-895-00	CARBON	470K	5%	1/4W	
R1180	1-247-804-11	CARBON	75	5%	1/4W	
R1181	1-247-804-11	CARBON	75	5%	1/4W	
R1183	1-247-895-00	CARBON	470K	5%	1/4W	
R1184	1-247-895-00	CARBON	470K	5%	1/4W	
R1185	1-247-895-00	CARBON	470K	5%	1/4W	
R1186	1-247-895-00	CARBON	470K	5%	1/4W	
R1188	1-247-804-11	CARBON	75	5%	1/4W	
R1191	1-249-425-11	CARBON	4.7K	5%	1/4W	
R1192	1-249-425-11	CARBON	4.7K	5%	1/4W	
R1193	1-249-425-11	CARBON	4.7K	5%	1/4W	
R1194	1-249-425-11	CARBON	4.7K	5%	1/4W	
R1196	1-249-426-11	CARBON	5.6K	5%	1/4W	
		<SWITCH>				
S1150	1-572-198-11	SWITCH, KEYBOARD				

REF.NO.	PART NO.	DESCRIPTION	REMARK
		<CONNECTOR>	
UT11	*1-564-519-11	PLUG, CONNECTOR 4P	
UT22	*1-566-941-11	CONNECTOR, HINGE (TAB) 30P	
UT23	*1-566-641-11	CONNECTOR, HINGE (TAB) 18P	
UT35	*1-564-518-11	PLUG, CONNECTOR 3P	
		**********	
		MISCELLANEOUS	
		**********	
	⚠1-241-744-11	RESISTOR ASSY (HIGH-VOLTAGE)	
	⚠1-451-396-21	DEFLECTION YOKE (Y936PA)	
	⚠1-452-443-13	NECK ASSY, PICTURE TUBE(NA367)	
	⚠1-453-108-11	DC BLOCK, HIGH-VOLTAGE	
	1-544-768-11	SPEAKER (13CM) (COAXIAL)	
	*1-555-110-00	CABLE, PIN	
	1-561-306-00	JACK, PIN (F)	
	1-574-590-31	LEAD ASSY, HIGH-VOLTAGE	
	⚠1-696-002-12	CORD, POWER (WITH NOISE FILTER)	
V902	⚠8-736-631-05	PICTURE TUBE (SD-249 (G))	
V903	⚠8-736-632-05	PICTURE TUBE (SD-249 (B))	
V901	⚠8-736-633-05	PICTURE TUBE (SD-249 (R))	
⊠R900	⚠	METAL FILM 1/4W	
⊠R901	⚠	METAL FILM 1/4W	
⊠R902	⚠	METAL FILM 1/4W	
		**********	
		ACCESSORIES AND PACKING MATERIALS	
		**********	
	*3-704-356-01	SHEET (STANDARD), PROTECTION	
	3-756-987-21	MANUAL, INSTRUCTION	
	3-756-987-31	MANUAL, INSTRUCTION (KP-41EXR96(C))	
	3-756-987-41	MANUAL, INSTRUCTION (KP-41EXR96(U))	
	*4-030-895-01	JOINT	
	*4-036-102-01	CUSHION (UPPER) (ASSY)	
	*4-036-106-01	INDIVIDUAL CARTON	
	*4-036-107-01	TRAY	
	*4-036-108-01	CUSHION (LOWER) (ASSY)	
	*4-381-155-01	BAG, PROTECTION	
		REMOTE COMMANDER	
	1-693-114-21	REMOTE COMMANDER (RM-Y112A)	
	9-902 719-01	COVER (FOR RM-Y112A)	
	9-998-214-01	COVER, BATTERY (FOR RM-Y112A)	

9-964-938-01

Sony Corporation
TV Group

English
93DJ0247-1
Printed in Japan

Watching Two Pictures at Once (PIP)

You can watch both the main picture and a window picture simultaneously, using the Picture-in-Picture (PIP) function.

KP-41EXR96 is equipped with one-tuner PIP. To watch two TV channels simultaneously, you must first connect a VCR to the projection TV, which will enable you to watch a second TV channel through the VCR tuner. (See "Connecting Other Equipment," pp. 15 –19.)
Other models are equipped with two-tuner PIP, allowing you to watch two TV channels at once.



Picture-in-Picture special features
When watching the main picture and a window picture, you can:
- Swap the main and window pictures (SWAP).
- Change the position of the window picture (POSITION).
- Display a still picture (FREEZE).
- Choose the sound from the main or window picture (AUDIO).

Notes
- The window picture sound is also output from the AUDIO (VAR) OUT jacks. The AUDIO OUT and MONITOR OUT jacks output the main picture sound only.
- The video label and channel caption will not appear with the window picture even if you have set them.
- If you select a blocked channel in the window picture, the display "BLOCKED" appears with the window picture. (See "Setting CHANNEL BLOCK," pp. 62 – 63.)

Displaying a window picture

Remote Commander



Press PIP to display a window picture



A window picture appears in the last mode you watched. Each time you press PIP, a 1/9 or 1/16 size window picture appears alternately.

To turn PIP function off
Press OFF.
The window picture disappears.

To receive the window picture sound
Press AUDIO.

The ♪ display appears for a few seconds, indicating that the window picture sound is being received.

To restore the main picture sound
Press AUDIO again.

Changing the window picture input mode

Remote Commander



1 Press PIP to display a window picture.



2 Press TV/VIDEO in the Picture-in-Picture control area to select the input mode.
Each time you press TV/VIDEO, "TV," "VIDEO 1," "VIDEO 2" and "VIDEO 3" appear in sequence.



To change TV channels in the window picture
Press CH +/– in the PIP control area.

Displaying CATV input as a window picture

To use Picture-in-Picture with pay cable TV input, make the connections to your cable converter box as shown below.



After making the above connections, turn the cable connection on by following the steps on pp. 26 – 27; then continue with the steps below.

1–2 Follow steps 1 – 2 in "Changing the window picture input mode" on this page to select the video input mode for your connected VCR.

3 Put your VCR on an inactive channel (channel 3 or 4).

4 Change pay cable TV channels with the decoder box.

To control your cable converter box with the supplied Remote Commander
See p. 70.

Changing the position of the window picture

Follow these instructions to change the position of the window picture on the screen.

Remote Commander



1 Press PIP to display a window picture.



2 Press POSITION.
Each time you press POSITION, the window picture moves as illustrated.



Displaying a still picture

Use the FREEZE function to display a still picture. This function is useful when you want to write down a recipe from a cooking program, a displayed address or phone number and so on.

Remote Commander



1 Press PIP to display a window picture.



2 Press FREEZE.
The window picture image remains still on the screen.



To restore the normal picture
Press FREEZE again.

Swapping the main and window pictures

Follow these instructions to swap the input signals of the main and window pictures.

Remote Commander



1 Press PIP to display a window picture.



2 Press SWAP.
Each time you press SWAP, the images from the main and window pictures switch places.



Adjusting the Projection TV

You can adjust the picture and sound for each input mode (TV, VIDEO 1, VIDEO 2, VIDEO 3) by pressing TV/VIDEO on the projection TV or on the Remote Commander to select the input mode, before making the adjustments. These adjustments are retained in memory even when you turn off the projection TV, but are cancelled after you change the adjustments, or select a picture and sound mode (pp. 38 – 39).

Adjusting the picture

Follow these instructions to adjust PICTURE, HUE, COLOR, BRIGHT (brightness) and SHARP (sharpness).

Remote Commander (with video control cover open)



1 Press MENU.
The main menu appears, and the cursor points to "PROG PALETTE."



2 Press RETURN.
The program palette menu appears.



3 Press A/V WINDOW +/– until the cursor points to "VIDEO."

4 Press RETURN.
The VIDEO screen appears.



5 Press A/V WINDOW +/– until the cursor points to the item you want to adjust.

6 Press RETURN.
The adjustment screen appears.

7 Press A/V WINDOW +/– to make the adjustment.

Picture quality	Press A/V WINDOW –	Press A/V WINDOW +
PICTURE	For decreased picture contrast with soft color	For increased picture with vivid color
HUE	Skin tones become purplish	Skin tones become greenish
COLOR	For less color intensity	For more color intensity
BRIGHT	For less brightness	For more brightness
SHARP	For less sharpness	For more sharpness

8 Press RETURN.
The adjustment is complete, and the VIDEO screen automatically reappears.



To adjust other items
Repeat steps 5 – 8.

To restore the factory settings for all the items
Select "STANDARD" on the program palette menu, and press RETURN;
or, press STANDARD on the Remote Commander.
All the items, including TRINITONE (p. 46) and NR (p. 47) return to their original factory settings.

To adjust picture contrast
You can also adjust picture contrast with the PICTURE +/– buttons on the Remote Commander.

Press + to increase picture contrast with vivid color.
Press – to decrease picture contrast with soft color.
The picture adjustment screen appears.

To return to the previous menu
Press A/V WINDOW +/– until the cursor points to "MENU."
Then press RETURN.

To return to the main menu
Repeat the above, until you reach the main menu.

To return to the normal screen
Press MENU.

Setting the TRINITONE mode

Color picture tubes are usually manufactured with a fixed color temperature (tint) that determines the "warmth" (red tint) or "coolness" (blue tint) of the picture. Use the Sony Trinitone feature to adjust the picture color to your preference.

Remote Commander



1 Press MENU.
The main menu appears, and the cursor points to "PROG PALETTE."



2 Press RETURN.
The program palette menu appears.



3 Press A/V WINDOW +/– until the cursor points to "VIDEO."

4 Press RETURN.
The VIDEO screen appears.



5 Press A/V WINDOW +/– until the cursor points to "TRINITONE."

6 Press RETURN.
The mode display turns red.

7 Press A/V WINDOW +/– to select "HIGH" or "LOW."

Select "HIGH" to make the picture cool (bluish).
Select "LOW" to make the picture warm (reddish).

8 Press RETURN.
The setting is complete.

To return to the previous menu
Press A/V WINDOW +/– until the cursor points to " ⊃ MENU."
Then press RETURN.

To return to the main menu
Repeat the above, until you reach the main menu.

To return to the normal screen
Press MENU.

Setting NR (picture noise reduction) ON or OFF

Follow these instructions to reduce picture noise.

Remote Commander



1 Press MENU.
The main menu appears, and the cursor points to "PROG PALETTE."



2 Press RETURN.
The program palette menu appears.



3 Press A/V WINDOW +/– until the cursor points to "VIDEO."

4 Press RETURN.
The VIDEO screen appears.

5 Press A/V WINDOW +/– until the cursor points to "NR."



6 Press RETURN.
The mode display turns red.

7 Press A/V WINDOW +/– to select "ON" or "OFF."

Select "ON" to reduce picture noise.
Select "OFF" to restore the normal picture.

8 Press RETURN.
The setting is complete.

To return to the previous menu
Press A/V WINDOW +/– until the cursor points to " ⊃ MENU."
Then press RETURN.

To return to the main menu
Repeat the above, until you reach the main menu.

To return to the normal screen
Press MENU.

Setting S-VIDEO ON or OFF

Follow these instructions to set S-VIDEO on or off, depending on the kind of video equipment you have connected to the projection TV. For instructions on connecting video equipment, see pp. 15 – 18.

Note
If the projection TV is in TV, VIDEO 2 or VIDEO 3 mode, the "S-VIDEO" display is shaded and cannot be selected. Press TV/VIDEO on the projection TV or on the Remote Commander to change to VIDEO 1 mode.

Remote Commander



1 Press MENU.
The main menu appears.



2 Press A/V WINDOW +/– until the cursor points to "MODE SET."

3 Press RETURN.
The mode set menu appears, with the cursor pointing to "S-VIDEO."



4 Press RETURN.
The mode display turns red.

5 Press A/V WINDOW +/– to select "ON" or "OFF."

6 Press RETURN.
The setting is complete.

To return to the previous menu
Press A/V WINDOW +/– until the cursor points to "⊃ MENU."
Then press RETURN.

To return to the main menu
Repeat the above, until you reach the main menu.

To return to the normal screen
Press MENU.

Adjusting the sound

Follow these instructions to adjust the TREBLE, BASS and BALANCE.

Remote Commander (with video control cover open)



1 Press MENU.
The main menu appears, and the cursor points to "PROG PALETTE."

2 Press RETURN.
The program palette menu appears.



3 Press A/V WINDOW +/– until the cursor points to "AUDIO."

4 Press RETURN.
The AUDIO screen appears.

5 Press A/V WINDOW +/– until the cursor points to the item you want to adjust.

6 Press RETURN.
The adjustment screen appears.

7 Press A/V WINDOW +/– to make the adjustment.

Sound quality	Press A/V WINDOW –	Press A/V WINDOW +
TREBLE	To decrease the treble response	To increase the treble response
BASS	To decrease the bass response	To increase the bass response
BALANCE	To emphasize the left speaker's volume	To emphasize the right speaker's volume

8 Press RETURN.
The adjustment is complete, and the AUDIO screen automatically reappears.

To adjust other items
Repeat steps 5 – 9.

To restore the factory settings for all the items
Select "STANDARD" on the program palette menu, and press RETURN; or, press STANDARD on the Remote Commander.
All the items, including SRS mode (p. 50) return to their original factory settings.

To return to the previous menu
Press A/V WINDOW +/– until the cursor points to "⊃ MENU."
Then press RETURN.

To return to the main menu
Repeat the above, until you reach the main menu.

To return to the normal screen
Press MENU.

Selecting an SRS (Sound Retrieval System) mode

For lifelike sound reproduction, follow the instructions below to select the SRS mode you prefer.

In SRS AUTO mode, SRS functions in both monaural and stereo modes.

Monaural sound programs will have a 'simulated stereo' effect.

In SRS STEREO mode, SRS functions only when a stereo program is received.
The STEREO lamp on the TV lights up whenever a stereo broadcast is received.

Select SRS OFF mode to return to normal sound mode.

Remote Commander



1 Press MENU.
The main menu appears, and the cursor points to "PROG PALETTE."



2 Press RETURN.
The program palette menu appears.



3 Press A/V WINDOW +/– until the cursor points to "AUDIO."

4 Press RETURN.
The AUDIO screen appears.

5 Press A/V WINDOW +/– until the cursor points to the SRS mode you want.

6 Press RETURN.
The mode is selected.

To change the SRS mode
Repeat steps 5 – 6.

To return to the previous menu
Press A/V WINDOW +/– until the cursor points to " ⊃ MENU."
Then press RETURN.

To return to the main menu
Repeat the above, until you reach the main menu.

To return to the normal screen
Press MENU.

Selecting an MTS (Multichannel TV Sound) mode

Follow these instructions to select an MTS mode.

Select MAIN mode to listen to stereo sound.
The STEREO lamp on the projection TV lights up whenever a stereo broadcast is received.

Select SAP mode to listen to Second Audio Programs.

Select MONO mode to eliminate excessive noise during stereo broadcasts, caused by a weak incoming signal.

Note
If the projection TV is in video mode, the "MTS" display is shaded and cannot be selected.
Press TV/VIDEO on the projection TV or on the Remote Commander to change to TV mode.

Remote Commander



1 Press MENU.
The main menu appears.



2 Press A/V WINDOW +/– until the cursor points to "MODE SET."

3 Press RETURN.
The mode set menu appears.



4 Press A/V WINDOW +/– until the cursor points to "MTS."

5 Press RETURN.
The mode display turns red.

6 Press A/V WINDOW +/– to select the mode you want.
Each time you press A/V WINDOW +/–, "MAIN," "SAP" and "MONO" appear in sequence.

7 Press RETURN.
The mode is selected.

To return to the previous menu
Press A/V WINDOW +/– until the cursor points to " ⊃ MENU."
Then press RETURN.

To return to the main menu
Repeat the above, until you reach the main menu.

To return to the normal screen
Press MENU.

Setting SPEAKER — MAIN or CENTER

Follow these instructions to set SPEAKER to "CENTER" when you connect an audio system (p.19), and to "MAIN" when you want to listen to the sound from the projection TV speakers.

Remote Commander



1 Press MENU.
The main menu appears.



2 Press A/V WINDOW +/– until the cursor points to "MODE SET."

3 Press RETURN.
The mode set menu appears.



4 Press A/V WINDOW +/– until the cursor points to "SPEAKER."

5 Press RETURN.
The mode display turns red.

6 Press A/V WINDOW +/– to select "MAIN" or "CENTER."

7 Press RETURN.
The setting is complete.

To return to the previous menu
Press A/V WINDOW +/– until the cursor points to "MENU."
Then press RETURN.

To return to the main menu
Repeat the above, until you reach the main menu.

To return to the normal screen
Press MENU.

Setting channel captions — CH CAPTION

Follow these instructions to caption each channel number display with a name, for instance, the television station call letters. (You can set up to four letters or numbers).

Example: Caption channel 15 as "NBC."

Remote Commander



1 Press MENU.
The main menu appears.



2 Press A/V WINDOW +/– until the cursor points to "SET UP."

3 Press RETURN.
The set up menu appears.



4 Press A/V WINDOW +/– until the cursor points to "CH CAPTION."

5 Press RETURN.
The CH CAPTION screen appears.



6 Press CH +/–, or press 1, 5 and ENTER to set channel "15."



7 Press RETURN.
The first caption space turns red.

8 Press A/V WINDOW +/– to select "N."
Each time you press A/V WINDOW +/–, "0" – "9," "A" – "Z," "&," "/," "-" and "_" (blank space) appear in sequence.



9 Press RETURN.
The second caption space turns red.

(Continued)

Setting channel captions – CH CAPTION
(Cont'd. from prev. page)

Remote Commander



10 Press A/V WINDOW +/– to select "B."



11 Press RETURN.
The third caption space turns red.

12 Press A/V WINDOW +/– to select "C."



13 Press RETURN.
The fourth caption space turns red.

14 Press A/V WINDOW +/– to select a blank space.



15 Press RETURN.
The setting is complete.
When you select or display the channel number, the channel caption also appears.

To caption more channels
Repeat steps 6 – 15.

To erase unnecessary captions
Display the CH CAPTION screen, select the channel with the caption you want to erase, and select blank spaces for the channel caption; then press RETURN.
The caption for that channel is erased.

To return to the previous menu
Press A/V WINDOW +/– until the cursor points to " ⊃ MENU."
Then press RETURN.

To return to the main menu
Repeat the above, until you reach the main menu.

To return to the normal screen
Press MENU.

Note
You can set up to 32 channel captions. If the memory is full, "The memory is full, sorry" appears on the screen. Erase any unnecessary captions, and begin again.

Setting VIDEO LABEL

Follow these instructions to label each input mode, in order to identify the equipment connected to each input terminal.

Example: Label VIDEO 1 IN as "VHS."

Remote Commander



1 Press MENU.
The main menu appears.

2 Press A/V WINDOW +/– until the cursor points to "SET UP."

3 Press RETURN.
The set up menu appears.



4 Press A/V WINDOW +/– until the cursor points to "VIDEO LABEL."

5 Press RETURN.
The VIDEO LABEL screen appears.

6 Press A/V WINDOW +/– until the cursor points to the input mode you want to label. (In this case, the cursor is already pointing to "VIDEO 1.")

7 Press RETURN.
The label display turns red.

8 Press A/V WINDOW +/– to select "VHS."

Each time you press A/V WINDOW +/–, the label changes:

VIDEO 1
VIDEO 1 → BETA → 8mm → VHS → LD → S-VIDEO

VIDEO 2
VIDEO 2 → BETA → 8mm → VHS → LD

VIDEO 3
VIDEO 3 → BETA → 8mm → VHS → LD

9 Press RETURN.
The setting is complete.
When you select or display the video mode, the video label appears.

To label other input modes
Repeat steps 6 – 9.

To change a label
Same as above.

To return to the previous menu
Press A/V WINDOW +/– until the cursor points to " ⊃ MENU."
Then press RETURN.

To return to the main menu
Repeat the above, until you reach the main menu.

To return to the normal screen
Press MENU.

Using Timer-Activated Functions

Setting DAYLIGHT SAVING

If you live in an area that uses daylight savings time, set DAYLIGHT SAVING to "YES" or "NO" depending on the season, before setting the current time. At the next daylight savings date, you will be able to automatically adjust all the time-related settings (CURRENT TIME, ON/OFF TIMER and CHANNEL BLOCK) simply by changing the DAYLIGHT SAVING setting.

When setting DAYLIGHT SAVING:

- **After the first Sunday in April (spring daylight savings)**
  Set to "YES" before setting the current time.
  Then, on the last Sunday in October (fall daylight savings), set to "NO."
  All the time-related settings automatically move one hour back.
- **After the last Sunday in October (fall daylight savings)**
  Set to "NO" before setting the current time.
  Then, on the first Sunday in April (spring daylight savings), set to "YES."
  All the time-related settings automatically move one hour ahead.

Remote Commander



Follow these instructions to set DAYLIGHT SAVING to "YES" or "NO."

1 Press MENU.
The main menu appears.



2 Press A/V WINDOW +/– until the cursor points to "TIME."

3 Press RETURN.
The time menu appears.



4 Press A/V WINDOW +/– until the cursor points to "DAYLIGHT SAVING."

5 Press RETURN.
The mode display turns red.

6 Press A/V WINDOW +/– to select "YES" or "NO."

7 Press RETURN.
The setting is complete.

To return to the previous menu
Press A/V WINDOW +/– until the cursor points to " ⊃ MENU."
Then press RETURN.

To return to the main menu
Repeat the above, until you reach the main menu.

To return to the normal screen.
Press MENU.

Setting the clock — CURRENT TIME SET

Follow these instructions to set the current time. The correct current time must be set in order to use the other time-related functions (DAYLIGHT SAVING, ON/OFF TIMER, CHANNEL BLOCK).

Example: Set the time to 3:15 PM, Monday.

Remote Commander



1 Press MENU.
The main menu appears.



2 Press A/V WINDOW +/– until the cursor points to "TIME."

3 Press RETURN.
The time menu appears, and the cursor points to "CURRENT TIME SET."



4 Press RETURN again.
The CURRENT TIME SET screen appears, with a reminder to set DAYLIGHT SAVING.

If you do not need to set DAYLIGHT SAVING, press RETURN and continue from step 5.

To set daylight saving

a Press A/V WINDOW +/– until the cursor points to "DAYLIGHT SAVING."

b Press RETURN.
The time menu appears, and the cursor points to "DAYLIGHT SAVING."

c Press RETURN.

d Press A/V WINDOW +/– to select "YES" or "NO."

e Press RETURN.
The setting is complete.

To set the time, press A/V WINDOW +/– until the cursor points to "CURRENT TIME SET"; press RETURN, then continue from step 5.

5 Press RETURN.
The CURRENT TIME SET screen appears, and the "SUN" display appears (red).

6 Press A/V WINDOW +/– to select "MON."
Each time you press A/V WINDOW +/–, the day changes consecutively.



(Continued)

Setting the clock — CURRENT TIME SET
(Cont'd. from prev. page)

Remote Commander



7 Press RETURN.
The hour and am/pm displays turn red.

8 Press A/V WINDOW +/– to set "3:00PM."
Each time you press A/V WINDOW +/–, the hour changes in sequence beginning with "12:00AM."



9 Press RETURN.
The minute display turns red.

10 Press A/V WINDOW +/– to select "15" (minutes).
Each time you press A/V WINDOW +/–, the minutes change in sequence.



11 Press RETURN.
The cursor points to "START."

12 Check the actual time, and press RETURN to start the clock.
The setting is complete.

To reset the time
Display the CURRENT TIME SET screen and repeat steps 5 – 12.

To display the current time
Press DISPLAY.

To return to the previous menu
Press A/V WINDOW +/– until the cursor points to " ⊃ MENU."
Then press RETURN.

To return to the main menu
Repeat the above, until you reach the main menu.

To return to the normal screen.
Press MENU.

Setting the ON/OFF TIMER

Follow these instructions to make the program of your choice appear on the screen at a specified time.

Example: Set the timer to turn on the projection TV every Monday through Friday at 1:30 AM for 3 hours, on channel 8, as PROGRAM 1. (You can set up to three programs.)

Remote Commander



1 Press MENU.
The main menu appears.



2 Press A/V WINDOW +/– until the cursor points to "TIME."

3 Press RETURN.
The time menu appears.



4 Press A/V WINDOW +/– until the cursor points to "ON/OFF TIMER."

5 Press RETURN.
The ON/OFF TIMER screen appears, and the cursor points to "1."



6 To set program 1, press RETURN.
(To set program 2 or 3, press A/V WINDOW +/– until the cursor points to that program; then press RETURN.)
The day input space turns red.

7 Press A/V WINDOW +/– to select "EVERY MON-FRI"; then press RETURN.
Each time you press A/V WINDOW +/–, the days of the week change as shown in Fig. 1 (p. 61).



8 Press A/V WINDOW +/– to select "1:00AM"; then press RETURN.
Each time you press A/V WINDOW +/–, the hour changes in sequence.



(Continued)

Setting the ON-OFF TIMER *(Cont'd from prev. page)*

Remote Commander



9 Press A/V WINDOW +/– to select "30" (minutes); then press RETURN.
Each time you press A/V WINDOW +/–, the minutes change in sequence.



10 Press A/V WINDOW +/– to select "3" (hour duration); then press RETURN.
Each time you press A/V WINDOW +/–, the duration changes from "1" – "6" in sequence.



11 Press A/V WINDOW +/– to select "8" (channel); then press RETURN.
The TIMER/STAND BY lamp lights, indicating that the setting is complete.
Each time you press A/V WINDOW +/–, the channel number changes from 1 – 125 in sequence.



The display "TIMER WILL BE OFF" appears on the screen one minute before the timer duration ends.

To set program 2 or 3.
Press RETURN and repeat steps 6 – 11.

To erase an ON/OFF TIMER setting
Display the ON/OFF TIMER screen, select the setting you want to erase, and select a blank space for the day.
The ON/OFF TIMER setting is erased.

To enter a new ON/OFF TIMER setting
Display the ON/OFF TIMER screen and repeat steps 6 – 11.

To return to the previous menu
Press A/V WINDOW +/– until the cursor points to "⊃ MENU."
Then press RETURN.

To return to the main menu
Repeat the above, until you reach the main menu.

To return to the normal screen.
Press MENU.

Note
If you unplug the projection TV or a power failure occurs, both the clock and timer settings will be erased. Reset the current time; then set the timer.

Fig. 1
Selecting the day(s) of the week
When you press A/V WINDOW +, the days of the week appear in the following order:



Setting CHANNEL BLOCK

Follow these instructions to prevent a channel from appearing on the screen during the time that you specify. You can use this function to prevent children from watching unsuitable programs.

Example: Set CHANNEL BLOCK every Saturday at 4:30 PM for 1 hour, on Channel 12.

Remote Commander



Note
If you have not set the current time, the "CHANNEL BLOCK" display is shaded and cannot be selected.

1 Press MENU.
The main menu appears.



2 Press A/V WINDOW +/– until the cursor points to "TIME."

3 Press RETURN.
The time menu appears.



4 Press A/V WINDOW +/– until the cursor points to "CHANNEL BLOCK."

5 Press RETURN.
The CHANNEL BLOCK screen appears, and the cursor points to the day input space.



6 Press RETURN.
The day input space turns red.



7 Press A/V WINDOW +/– to select "EVERY SAT"; then press RETURN.
Each time you press A/V WINDOW +/–, the days of the week change as shown in Fig. 1 (p. 61).

8 Press A/V WINDOW +/– to select "4:00PM"; then press RETURN.
Each time you press A/V WINDOW +/–, the hour changes in sequence.

9 Press A/V WINDOW +/– to select ":30" (minutes); then press RETURN.
Each time you press A/V WINDOW +/–, the minutes change in sequence.



10 Press A/V WINDOW +/– to select "1" (hour duration); then press RETURN.
Each time you press A/V WINDOW +/–, the duration changes from "1" – "6" in sequence.

11 Press A/V WINDOW +/– to select "12" (channel); then press RETURN.
The setting is complete.
Each time you press A/V WINDOW +/–, the channel number changes from "1" – "125" in sequence.



At the specified time, "BLOCKED" appears in red on the screen, and the picture of the specified channel is blocked and the sound is muted.



To erase a CHANNEL BLOCK setting
Display the CHANNEL BLOCK screen and select a blank space for the day.
The CHANNEL BLOCK setting is erased.

To enter a new CHANNEL BLOCK setting
Display the CHANNEL BLOCK screen and repeat steps 4 – 10. (You can only set one CHANNEL BLOCK at a time.)

To return to the previous menu
Press A/V WINDOW +/– until the cursor points to " ⊃ MENU."
Then press RETURN.

To return to the main menu
Repeat the above, until you reach the main menu.

To return to the normal screen.
Press MENU.

Note
If the ON/OFF TIMER is set for an overlapping time (pp. 59 – 61), the later time setting takes precedence. For example, if CHANNEL BLOCK is set for 2:00 PM and ON/OFF TIMER is set for 3:00 PM, ON/OFF TIMER will take effect at 3:00 PM.

Setting FAVORITE CHANNEL

By setting FAVORITE CHANNEL, you can select the channels you use most frequently (up to seven channels) simply by pressing RETURN.

Remote Commander



Follow these instructions to set the channels.

1 Press MENU.
The main menu appears.



2 Press A/V WINDOW +/– until the cursor points to "SET UP."

3 Press RETURN.
The set up menu appears.



4 Press A/V WINDOW +/– until the cursor points to "FAVORITE CHANNEL."

5 Press RETURN.
The FAVORITE CHANNEL screen appears, and the cursor points to the first channel position.



6 Press A/V WINDOW +/– to select the channel position; then press RETURN.

7 Press 0 – 9 and ENTER to set the channel number.



8 Press RETURN.
The setting is complete.

To set other channels
Repeat steps 6 – 8.

To erase a favorite channel setting
Press A/V WINDOW +/– until the cursor points to the channel number you want to erase; press RETURN, then press 0 and ENTER.

To reset a favorite channel setting
Display the FAVORITE CHANNEL screen and repeat steps 6 – 8.

To return to the previous menu
Press A/V WINDOW +/– until the cursor points to " ⊃ MENU."
Then press RETURN.

To return to the main menu
Repeat the above, until you reach the main menu.

To return to the normal screen.
Press MENU.

Selecting a favorite channel

After setting the channels, follow these instructions to select the channel you want to watch.

1 Press RETURN.
The FAVORITE CHANNEL display appears.



Note
If you have set channel captions (pp. 53 – 54), the captions appear with the channel numbers.

2 Press A/V WINDOW +/– to select the channel you want to watch; then press RETURN.
The channel is selected.

If you press RETURN on the Remote Commander before setting FAVORITE CHANNEL, this screen appears.

Follow steps 1 – 8 to set your favorite channels, and then make the selection.

Using the Pre-Programmed Remote Commander

You can operate other video equipment (such as VCRs, video disc players and cable boxes) that have an infrared remote detector with this supplied Remote Commander.

Operating Sony video equipment

Follow these instructions to operate Sony video cassette recorders (Beta, 8 mm and VHS) and video disc players (including multi-disc players).

Remote Commander (with video control cover open)



1 Set the VTR1-2-3 MDP selector according to the video equipment you want to operate.



Fig. 2: Video equipment settings

If you want to operate a:	set to:
Beta, ED Beta VCR	VTR 1
8 mm VCR	VTR 2
VHS VCR	VTR 3
Video disc player	MDP

2 Use the video operating buttons to control the connected equipment.

Fig. 3: Operating a VCR (VTR1, 2, 3)	
To turn on or off	Press POWER.
To change channels (when watching TV programs through the VCR's tuner)	Press CH +/–.
To record	Press ● and REC simultaneously.
To play	Press ▶.
To stop	Press ■.
To fast forward	Press ▶▶.
To rewind the tape	Press ◀◀.
To pause	Press ❚❚. *To resume normal playback, press again.*
To search the picture forward and backward	Keep pressing ▶▶ or ◀◀ during playback. *To resume normal playback, release the button.*
To change input mode	Press TV/VTR.

Fig. 4: Operating a Video Disc Player (MDP)	
To turn on or off	Press POWER.
To play	Press ▶.
To stop	Press ■.
To pause	Press ❚❚. *To resume normal playback, press again.* **Note** This function is effective only for CAV (standard-play disc). With CLV (extended-play disc), the projection TV goes off (standby mode) if you press ❚❚.
To search the picture forward and backward	Keep pressing ▶▶ or ◀◀ during playback. *To resume normal playback, release the button.*

Notes

- If the video equipment does not have a certain function, the corresponding button on this Remote Commander will not operate.
- If you set another manufacturer's code to a VTR1-2-3 MDP selector position (pp. 68 – 69), you must also set the Sony code to operate Sony equipment.

Caution

When you replace the batteries, do so within approximately 30 minutes. Otherwise the settings you made under the Pre-Programmed function (pp. 68 – 70) may be erased.

Operating non-Sony or Sony video equipment

Follow these instructions to set the manufacturer's code, which will enable you to operate non-Sony and Sony video equipment with the pre-programmed Remote Commander.

Example: Operate an RCA video cassette recorder connected to the VIDEO 2 IN jacks.

Remote Commander (with video control cover open)



1 Set the VTR1-2-3 MDP selector to VTR2.



Note

To use another manufacturer's equipment besides a Sony VCR, set the selector to a position not being used for your Sony video equipment.

2 While pressing CODE SET, press 0, 7 and ENTER to set RCA's code number. (For manufacturer code numbers, see Figs. 5, 6 and 7 on p. 69.)



3 Use the video operating buttons to operate the connected equipment. (see Fig. 3 on p. 66 and Fig. 4 on p. 67.)

Fig. 5: VCR manufacturer code numbers

MANUFACTURER	CODE
SONY	01, 02, 03
CANON	05
EMERSON	22, 30, 33
FISHER	10, 11, 12, 15
FUNAI	29
GENERAL ELECTRIC	05, 08
GOLDSTAR	25
HITACHI	07, 08, 36
JVC	16, 35
MAGNAVOX	05, 06, 09
MITSUBISHI	18, 19, 26, 27
MULTITECH	29
NEC	16, 23, 31
PANASONIC	05, 06
PHILCO	05, 06
PHILIPS	05, 06, 09
QUASAR	05, 06
RCA	07, 08
SAMSUNG	24, 32
SANYO	11, 15
SCOTT	21
SHARP	13, 14
SHINTOM	34
SYLVANIA	05, 06, 09
SYMPHONIC	29
TEKNIKA	28, 29
TOSHIBA	20, 21
TOTE VISION	25
ZENITH	17

Fig. 6: MDP manufacturer code numbers

MANUFACTURER	CODE
SONY	04
KENWOOD	58
MAGNAVOX	52
MARANZ	54
MITSUBISHI	51
PANASONIC	55
PHILIPS	52
PIONEER	51
RCA	51
SANYO	57
SHARP	56
YAMAHA	53

Fig. 7: Sony Equipment and Code Numbers

SONY EQUIPMENT	CODE
Beta, ED Beta VCR	01
8 mm VCR	02
VHS VCR	03
Video disc player	04

Note

In some rare cases, you may not be able to operate your non-Sony video equipment with the supplied Remote Commander. This is because your equipment may use a code that is not provided with this Remote Commander. In this case, please use the equipment's own remote control unit.

Operating a cable converter box

Follow these instructions to set the manufacturer's code, which will enable you to operate a connected cable converter box with the pre-programmed Remote Commander.

Example: Operate a connected Zenith cable converter box.

Remote Commander (with video control cover open)



1 Set the TV/CABLE BOX selector to CABLE BOX.



Notes

- If more than one code number is listed, try entering them one by one, until you come to the correct code for your equipment.
- If you enter a new code number, the code number you previously entered at that setting is erased.
- In some rare cases, your equipment may use a code that is not provided with this Remote Commander and you may not be able to operate your cable converter box with the supplied Remote Commander. In this case, use the equipment's own remote control unit.

2 While pressing CODE SET, press 6 and 8 (Zenith's code number — see Fig. 8) and ENTER.



3 Use the projection TV control buttons (POWER, 0 – 9, ENTER and CH +/–) to operate the cable converter box.



To return to the normal screen
Set the TV/CABLE BOX selector to TV; then use the projection TV control buttons to control the projection TV.

For more details on operating the cable box
Refer to the operating instructions that come with the cable box.

Fig. 8: Cable box manufacturer code numbers

MANUFACTURER	CODE
JERROLD	60, 61, 62, 63, 64, 65
PIONEER	69, 70
SCIENTIFIC ATLANTA	66, 67
TOCOM	71, 72
ZENITH	68

Selecting a VCR mode directly — DIRECT PLAY

Follow these instructions to switch from TV to VCR mode by simply pressing the ▶ (playback) button on the supplied Remote Commander.

Example: Connect your VCR to the VIDEO 2 IN jacks, and set the VTR1-2-3 MDP selector to VTR2. When you press ▶, the input mode changes to the VCR connected to the VIDEO 2 IN jacks.

After completing the steps below, the VTR selector position is retained in the projection TV's memory.

Remote Commander (with video control cover open)



1 Press MENU.
The main menu appears.



2 Press A/V WINDOW +/– until the cursor points to "SET UP."

3 Press RETURN.
The set up menu appears.



4 Press A/V WINDOW +/– until the cursor points to "DIRECT PLAY."

5 Press RETURN.
A message screen appears.

Note
This screen reminds you to set the manufacturer's code, if you have not already done so (pp. 68 – 69).

6 Press RETURN again.
The DIRECT PLAY screen appears.



7 Press A/V WINDOW +/– until the cursor points to the video input mode. (When the video equipment is connected to VIDEO 1 IN, select "VIDEO1.")

8 Press RETURN.
The mode display turns red.

(Continued)

Selecting a VCR mode directly – DIRECT PLAY

(Cont'd. from prev. page)

Remote Commander



9 Press A/V WINDOW +/– to select the VTR selector mode you have set on the Remote Commander. (When the VTR1-2-3 MDP selector is set to VTR2, select "VTR 2.")

Each time you press A/V WINDOW +/–, "VTR 1," "VTR 2," "VTR 3," "MDP" and "OFF" appear in sequence.



10 Press RETURN.

The direct play setting is complete.

To set direct play for other connected video equipment
Repeat steps 7 – 10.

To return to the previous menu
Press A/V WINDOW +/– until the cursor points to " ⊃ MENU."
Then press RETURN.

To return to the main menu
Repeat the above, until you reach the main menu.

To return to the normal screen.
Press MENU.

Appendix

Troubleshooting

Disturbances in picture and sound can often be eliminated by checking the symptoms and following the suggestions listed here. If the problem still cannot be solved, contact your nearest service facility.

Symptom	Possible causes and remedies
No picture (screen not lit), no sound	• Make sure POWER is switched on. • Check the power cord connection. • Check that the TV/VIDEO and VTR1-2-3 MDP controls are set correctly. • Make sure that the TV/CABLE BOX selector is set to TV.
Poor or no picture (screen not lit), good sound	• Adjust the picture using the VIDEO screen (pp. 44 – 47). • Check the antenna/cable connections. • Adjust the color registration (pp. 24 – 25).
Good picture, no sound	• Press VOLUME + on the projection TV or VOL + on the Remote Commander. • Press MUTING on the Remote Commander. • Check the MTS setting (p. 51). • Check that the TV/VIDEO and VTR1-2-3 MDP controls are set correctly. • Make sure SPEAKER is set correctly (p. 52).
No color for color programs	• Check the HUE and COLOR settings (pp. 44 – 45).
Snow and noise only	• Check that it is an active or correct channel. • Check the cable setting. • Check antenna/cable connections.
 Dotted lines or stripes	This is often caused by local interference (for example, cars, neon signs and hairdryers). Adjust the telescopic aerial for minimum interference.
 Double images or ghosts	Reflections from nearby mountains or buildings often cause this problem. Connecting a highly directional outdoor antenna or a CATV cable may improve the picture.
Remote control does not operate	• Check the battery in the Remote Commander.
No picture and/or sound for the connected equipment	• Check that the TV/VIDEO button is set correctly. • Check that the connections are properly made. • Check that the power of the connected equipment is turned on. • Check that the connected equipment is set correctly.
Try another channel. It could be station trouble.	

SECTION 2
DISASSEMBLY

2-1. H2 BOARD REMOVAL



2-2. D BOARD REMOVAL



2-3. H1 BOARD REMOVAL



2-4. REFLECTION MIRROR REMOVAL



2-5. BACK COVER REMOVAL



2-6. MAIN CHASSIS ASSY REMOVAL



2-7. SERVICE POSITION



NOTES INSERTED IN SERVICE POSITION

Service Position Procedure

1)Remove the path locks where the harness comes into.(MAIN bracket, G shield)
2)Remove the following connectors befor removing the main bracket.
※ HV grounding lead, G shield grounding lead, V-2 connector(V board).
3)Remove the main bracket.(Take care as the connector leads linking to the C and Z boards considerably short).
4)Before power ON,be sure to connect the connectors removed.
※ HV grounding lead, G shild grounding lead.
In case that grounding lead(Black) of HV Block is not connected with chassis grounding, it causes arcing of CRT and it is daigerous.
Be sure to connect grounding lead of HV Block with chassis grounding.

CONNECTOR CABLES

※ In order to put the set in the service position, use the extension connector cables below.

Parts No.	Connection
1-941-897-38	CB-4toCN1652(G BOARD)



Parts No.	Connection
1-941-897-39	CG-16toCN1608(A BOARD)



Parts No.	Connection
1-941-897-40	ZG-19toCN1308(DO BOARD)



Parts No.	Connection
1-941-897-41	ZR-18toCN1306(DO BOARD)



Parts No.	Connection
1-941-897-42	ZG-2toD-2



Parts No.	Connection
1-941-897-43	CR-15toCN1609(A BOARD)



Parts No.	Connection
1-941-897-44	ZR-1toD-1



Parts No.	Connection
1-941-897-45	A-21toCRT BRACKET



Parts No.	Connection
1-941-897-46	V-2toZR-3



2-8. SUB CONNECTOR PANEL REMOVAL



2-9. MAIN CONNECTOR PANEL REMOVAL



2-10. U BRACKET REMOVAL



2-11. V BOARD REMOVAL



2-12. N BRACKET REMOVAL



2-13. G BOARD REMOVAL



2-14. MIRROR COVER REMOVAL

① 2-1 H2 BOARD REMOVAL,
2-3 H1 BOARD REMOVAL,
2-4 REFLECTION MIRROR REMOVAL,



2-15. CHASSIS ASSY REMOVAL



2-16. PICTURE TUBE REMOVAL



2-17. HIGH-VOLTAGE CABLE INSTALLATION AND REMOVAL

(1) Remover



(2) Installation



2-18. CONNECTOR CABLE







SECTION 3
SET-UP ADJUSTMENTS

3-1. FOCUS LENS ADJUSTMENTS

1. Set the D-board registration variable resistors (VR) to mechanical center.
2. Set the centering magnets (for red, green, and blue) to 0 as shown in the figure.



3. Input monoscope signal. Set 50% BRIGHTNESS and minimum PICTURE. Make rough adjustment so that 10IRE of the monoscope signal becomes faintly luminous using the screen VRs.
4. Set PICTURE and BRIGHTNESS maximum. Press the commander menu button. Select CONVERGENCE to display test signal.
5. Enter service mode. Select R OFF of SERVICE MODE to cut off red output.
   Similarly, select B OFF to cut off blue output.
6. Turn the green lens to eliminate flare of the test signal.



(Lens)



(Focus block)

Verify that scanning lines are seen.



7. Turn the green focus VR in the focus block to adjust green focus to reduce both A and B of the test signal to minimum.



8. Repeat avobe 6 and 7. Couple of times to improve tracking and obtain an optimum focus. Then tighten the green lens screw.
9. Adjust the red and blue focuses similarly.

3-2. DEFLECTION YOKE POSITION ADJUSTMENTS

1. Input monoscope signal.
2. Enter service mode. Select R OFF of SERVICE MODE to cut off red output.
   Similarly, select B OFF to cut off blue output.
3. Loosen the deflection yoke (DY) fitting screws. Tilt the DY to obtain the best horizontal and vertical monoscope patterns.
4. After adjustment, press the DY onto the cathode ray tube (CRT) funnel and tighten the screws.
5. Also adjust DY positions for red and blue outputs in the same way.

3-3. 2-POLE MAGNET ADJUSTMENT

1. Input dot signal.
2. Enter service mode. Select R OFF of SERVICE MODE to cut off red output.
   Similarly, select B OFF to cut off blue output.
3. Set PICTURE to maximum. Turn the green focus variable resistor (VR) in the focus block counterclockwise from the just focus to brighten the point in the dot.
4. Adjust the 2-pole magnet to position the bright point at the center of the dot.
5. Adjust the red and blue dots in the same way.

* Use the center dot:red and green
  Use the vertical center and left end dot : blue



3-4. 4-POLE MAGNET ADJUSTMENT

1. Input dot signal.
2. Enter service mode. Select R OFF of SERVICE MODE to cut off red output.
   Similarly, select B OFF to cut off blue output.
3. Set PICTURE to maximum. Turn the green focus variable resistor (VR) in the focus block clockwise (counter clockwise : blue) from the just focus until the dot diameter becomes as shown below.
4. Adjust the 2-pole magnet to make the dot perfectly round.
5. Turn the green focus variable resistor to the just focus.
6. Adjust the red and blue dot in the same way.

* Use the center dot : red and green
  Use the vertical center and left end dot : blue



3-5. DE-FOCUS ADJUSTMENT (BLUE)

1. Input cross hatch signal.
2. Turn the blue focus variable resistor (VR) in the focus block counter clock wise so that thewidth of the left end vertical line becomes as shown below.



without flare

3-6. GREEN PICTURE ADJUSTMENTS

1. Input monoscope signal.
2. Enter service mode. Select R OFF of SERVICE MODE to cut off red output.
   Similarly, select B OFF to cut off blue output.
3. Turn RV913 and RV960, the vertical green linearity variable resistors (V.G LIN VRs) on the D-board, to obtain an optimum vertical linearity. Then turn RV911, the vertical green amplitube variable resistor (V.G SIZE VR) to set vertical amplitude to 11.7 flames.
   Note: The vertical position indicator of the monoscope signal must be positioned at the center by adjusting RV905, the vertical green center position variable resistor (V.G CENT VR) in advance.



Monoscope signal



RV905 V.G CENT
(vertical position)



RV911 V.G SIZE
(vertical amplitude)



RV913 V.G LIN
(vertical linearity)

5. Verify that the horizontal lines on the top and bottom of cross-hatched area of the monoscope signal are horizontal and linear.



6. Turn RV916, RV964 and RV969, the horizontal green linearity variable resistors (H.G LIN VRs) on the D-board, to obtain an optimum horizontal linearity.
   Then turn RV908, the horizontal green amplitude variable resistor (H.G SIZE VR) to set horizontal amplitude to 15.6 frames.
   Note: The horizontal position indicator of the monoscope signal must be positioned at the center by adjusting RV902, the horizontal green center position variable resistor (V.G CENT VR) in advance.



Monoscope signal



RV908 H.G SIZE
(horizontal position)



RV916 H.G LIN
(horizontal linearity)

7. Input cross hatch signal.
   Turn vertical green (V.G) and horizontal green (H.G) variable resistors (VRs) and make adjustments according to the following steps :

(Adjustment procedure)

1. [BOW] → [SKEW] → [CENT (center position)]
2. [PIN (pin warp)] → [SUB BOW] → [BOW]
3. [KEYS (trapezoid)] → [SUB SKEW] → [SKEW]
4. [M.WAVE (middle sine wave warp)] →
   [WAVE-A (upper and lower sine wave warp)] →
   [WAVE-U (upper sine wave warp)]
   ※ For vertical (V) only.
5. [V-M.PIN (vertical middle pin warp)] →
   [V/WING (vertical wing warp)]
   ※ For vertical (V) only.
6. [H-M.PIN (horizontal middle pin warp)]
   ※ For horizontal (H) only.

(Dot motion)



RV932 H.G BOW
(horizontal green bow)



RV941 H.G PIN
(horizontal green pin warp)



RV950 H.G SUB BOW
(horizontal green sub bow)



V.G BOW·····RV935
V.G PIN·····RV938
V.G SUB BOW·····RV953



RV920 H.G SKEW
(horizontal green skew)



RV925 H.G KEYS
(horizontal green trapezoid)



RV944 H.G SUB SKEW
(horizontal green sub skew)



V.G SKEW·····RV923
V.G KEYS·····RV929
V.G SUB SKEW·····RV947



RV962 V-M-WAVE
(vertical middle sine wave warp)



RV975 V-WAVE-A
(vertical upper and lower sine wave warp)



RV978 V-WAVE-U
(vertical upper sine wave warp)



RV980 V-M. PIN
(vertical middle pin warp)
※ Common in red, green, and blue



RV957 V/WING
(wing warp)
※ Common in red, green, and blue



RV956 H/M. PIN
(horizontal middle pin warp)

3-7. GREEN AND RED REGISTRATION ADJUSTMENTS

1. Input cross hatch signal.
2. Enter service mode. Select B OFF of SERVICE MODE to cut off blue output.
3. Turn the vertical red (V.R) and horizontal red (H. R) variable resistors (VRs) to adjust red picture convergence in relation to green picture according to the following steps :

(Adjustment procedure)

1. [LIN (linearity)] → [SIZE (amplitude)] → [CENT (center position)]
2. [BOW] → [SKEW] → [CENT (center position)]
3. [PIN (pin warp)] → [SUB BOW] → [BOW] [H/M. PIN (horizontal middle pin warp)]
4. [KEYS (trapezoid)] → [SUB SKEW] → [SKEW]
5. [M.WAVE (middle sine wave warp)] → [WAVE-A (upper and lower sine wave warp)] → [WAVE-U (upper sine wave warp)]

(Dot motion)



RV912 V.B SIZE
(vertical red amplitude)



RV952 V.R SUB BOW
(vertical red sub bow)



RV943 V.R BOW
(vertical red bow)



RV928 V.R KEYS
(vertical red trapezoid)



RV946 V.R SUB SKEW
(vertical red sub skew)



RV904 V.R CENT
(vertical red center position)



RV917 V.R LIN
(vertical red linearity)



RV922 V.R SKEW
(vertical red skew)

H.R LIN·····RV915
H.R SIZE·····RV907
H.R CENT·····RV901
H.R BOW·····RV931
H.R SKEW·····RV919
H.R PIN·····RV940
H.R KEYS·····RV926
H.R SUB BOW·····RV949
H.R SUB SKEW·····RV943
V-M-WAVE·····RV973
V-WAVE-A·····RV976
V-WAVE-U·····RV979
V-M.PIN·····RV980
V/WING·····RV957
H/M.PIN·····RV956

3-8. GREEN AND BLUE REGISTRATION ADJUSTMENTS

1. Input cross hatch signal.
2. Enter service mode. Select R OFF of SERVICE MODE to cut off red output.
3. Turn the vertical blue (V.B) and horizontal blue (H.B) variable resistors (VRs) to adjust blue picture convergence in relation to green picture according to the following steps :

(Adjustment procedure)

1. [LIN (linearity)] → [SIZE (amplitude)] → [CENT (center position)] →
2. [BOW] → [SKEW] → [CENT (center position)]
3. [PIN (pin warp)] → [SUB BOW] → [BOW] [H/M. PIN (horizontal middle pin warp)]
4. [KEYS (trapezoid)] → [SUB SKEW] → [SKEW]
5. [M.WAVE (middle sine wave warp)] → [WAVE-A (upper and lower sine wave warp)] → [WAVE-U (upper sine wave warp)] →

(Dot motion)



RV912 V.B SIZE
(vertical blue amplitude)



RV918 V.B LIN
(vertical blue linearity)



RV954 V.B SUB BOW
(horizontal blue sub bow)



RV936 V.B BOW
(vertical blue bow)



RV930 V.B KEYS
(vertical blue trapezoid)



RV948 V.B SUB SKEW
(vertical blue sub skew)



RV924 V.B SKEW
(vertical blue skew)



RV906 V.B CENT
(vertical blue center position)



RV939 V.B PIN
(vertical blue pin warp)



RV903 H.B CENT
(vertical blue center position)



RV909 H.B SIZE
(horizontal blue amplitude)



RV914 H.B LIN
(horizontal blue linearity)



RV942 H.B PIN
(horizontal blue pin warp)



RV954 H.B SUB SKEW
(horizontal blue sub skew)



RV951 H.B SUB BOW
(horizontal blue sub bow)



RV921 H.B SKEW
(horizontal blue skew)



RV927 H.B KEYS
(horizontal blue trapezoid)



RV933 H.B BOW
(horizontal blue bow)



RV981
※ Common in red, green, and blue



RV982
※ Common in red, green, and blue

H/M PIN·····RV958
M.WAVE·····RV961
WAVE-A·····RV974
WAVE-U·····RV977

3-9. REGISTRATION CHECK

1. Out put red, blue, and green.
2. Out put cross hatch and monoscope signals to check registration. Also check focus.

3-10. WHITE BALANCE ADJUSTMENTS

1) Screen adjustment

1. Input white signal.
2. Remove connectors CR-15, CG-16, and CB-17.
3. Fit jigs between the ground and R707, R737, and R767.



※ Resistors in each jig are connected serial.

4. Turn the RGB (red, green, and blue) screen variable resistors in the focus block to make the flyback line faint. Stop before the line completely disappears.
5. Insert connectors CR-15, CG-16, and CB-17.

2) White balance adjustments (SBRT, GAMP, BAMP, GCUT, BCUT)

1. Input monoscope signal and enter service mode.
2. Select the picture quality adjustment from the menu and set PICTURE minimum.
3. Use the commander to adjust SBRT so that 10 IRE of the monoscope pattern becomes faintly luminous.
4. Input white signal.
5. Set PICTURE minimum. Adjust item GCUT and BCUT to obtain an optimum white balance.
6. Set PICTURE maximum. Adjust GAMP and BAMP to obtain an optimum white balance.
7. Repeat white balance adjustment alternating PICTURE setting at the minimum and maximum.

SECTION 4
SAFETY RELATED ADJUSTMENTS

4-1. SAFETY RELATED ADJUSTMENTS

When replacing the following components, make the HV REGULATOR adjustments (on the N board)

◪·····HV block, IC803, IC805, D805, D807, C817, C818, C821, C836, C837, R824, R825, R827, R828, R834,R835, R836, R864, R865, R866, R902

When replacing the following components, make the HV HOLD DOWN adjustments (on the N board)

◪·····HV block, IC803, IC804, Q804, D806, D808, C809, C819, C820, C822, C823, C850, R807, R826, R829, R832, R833, R837, R838, R839, R840, R841, R892, R893, R900, R901

When replacing the following components, make the BEAM CURRENT PROTECTOR adjustments (on the N board)

◪·····① IC802, Q805, Q807, D811, D812,C810, C824, C825, C826, C827, C831, R810, R843, R844, R847, R848, R849, R850, R851, R852, R853, R854, R881

② IC804, Q804, Q808, D808, D809, C809, C828,C829, C830, C831, R807, R839, R840, R841,R847, R848, R849, R850, R851, R852, R855, R856, R857, R881

When replacing the following components, make the OVP CIRCUIT adjustments (on the G board)

◪·····Q618, Q621, D628, C634, R639, R649, R652, R655, R656

— Checking with static voltmeter —

HV HOLD DOWN ADJUSTMENTS (◪R900, R901)

1. Verify that the power switch is off.
2. Connect the HV hold down adjustment resistance jig to the N20 connector on the N board.



3. Connect an external variable resistor (RV) to R 902 of the N board.
4. Remove the cap off from the unused terminal of the high voltage block. Connect a static voltmeter to the terminal.



5. Receive 120 VAC power voltage and monoscope pattern signal. Maximize PICTURE and BRIGHTNESS.
6. Use the external variable resistor of the hold down adjustment jig to make the static voltmeter to read 33.50 ± 0.50kVDC.
7. Raise resistances with the jig until the HV hold down circuit is activated. Read the figures then, and mount resistance of the measured figures to R900 and R901.
   R900 : Must be 1kΩ to 12kΩ
   R901 : Must be Jw 100Ω to 820Ω
8. Turn on power again. Vary external variable resistance and confirm that the HV hold down circuit is activated at the reated value, 33.50± 0.50kV.

HV REGULATOR ADJUSTMENTS (⊠R902)

1. Connect the HV adjustment resistance jig to R902 of the N board.



(Adjustment jig)

2. Remove the red anode lead wire for the CRT tube from the high-voltage block and connect the static voltmeter instead.
3. Receive 120 VAC power voltage and monoscope pattern signal. Set PICTURE and BRIGHTNESS to the standard.
4. Turn on power. To adjust the resistance of R902 with the adjustment jig to read the rated value, 31.50±0.50kV.
5. Receive all-white signal. Set BRIGHTNESS to the standard. Maximize PICTURE. Confirm that the rated value, 31.50±0.50kV is read.
6. Cut off RGB by R OFF, G OFF, B OFF of the service commander. Verify that the rated value, 31.50±0.50kV, is read.

+B VOLTAGE CONFIRMATION

1. Receive 120±1 VAC power voltage and monoscope pattern signal. Set BRIGHTNESS to standard and maximize PICTURE.
2. Connect a digital multimeter between the 115V line and the ground on the G board, and confirm that the rated value, 115.0$^{+2.0}_{-3.0}$V is read.

CHECKING AFTER REPLACING IC601

1. When replacing IC601, check the +B voltage.

CHECKING THE OVP (overvoltage protection) CIRCUIT (⊠R652)

1. Receive 120 VAC power voltage and monoscope pattern signal. Maximize PICTURE and BRIGHTNESS.
2. Remove R638 from the G board and connect a variable resistor (4.7 to 10kΩ) instead.
3. Turn the variable resistor of 10kΩ and confirm that the OVP circuit is activated and luster disappears when +B voltage reads the rated value, 125.0±5.0 VDC.

BEAM CURRENT PROTECTOR CHECK (⊠R852)

1. Receive 120 VAC power voltage and monoscope pattern signal. Maximize BRIGHTNESS.
2. Connect pin① and pin② of the N-21 connector. (on the N board)
3. Remove the jumper connector from the N-8 connector on the N board. Then connect an ABL ammeter between pin ① and pin ④ of the N-8 connector.



4. Raise PICTURE current gradually. Confirm that the beam current protector circuit is activated and luster disappears under the rated value, 3400 μA.
5. Connect pin③ and pin② of the N-21 connector. Verify that the protector circuit is activated and luster disappears similarly.


N Board
R852
Jumper
N6
N20
N5
N7
R900
R902


G Board
variable resistor
50 kΩ
R638
R652
G5
15V
digital multi-meter

— Checking without static voltmeter —

HV HOLD DOWN ADJUSTMENT (⊠R900, ⊠R901)

1. Receive all-white signal. Maximize PICTURE and BRIGHTNESS.
2. Remove R902 from the N board. Connect a variable resistor of 50kΩ on each end, and minimize the resistance.
3. Remove R900 and R901 from the N board. Connect a variable resistor of 50kΩ on each end, and minimize the resistance.
4. Connect a digital voltmeter between the D801 cathode and chassis ground of the N board.
5. Turn on the power switch. Adjust the variable resistors connected to the R902 of the N board to make the digital multimeter to read 145.0VDC.
6. Adjust the variable resistors connected to R900 and R901 on the N board so as to activate the HV hold down circuit and turn off the display.
7. Read the variable resistors connected to R900 and R901 and mount fixed resistors of measured resistance to the terminals.

   Note : Select fixed resistance from the following ranges.

   R900 : 1kΩ to 12kΩ

   R901 : Jw 100Ω to 820Ω
8. Maximize resistance of the variable resistor connected to R902 of the N board and turn on power.
9. Vary variable resistance at R902. Confirm that the HV hold down circuit is activated and the display is turned off when voltage reads 134±1.0V.



HV REGULATOR ADJUSTMENT (⊠R902)

1. Receive all-white signal. Maximize PICTURE and BRIGHTNESS.
2. Connect a variable resistor of 50kΩ on each end of R902 of the N board. Maximize resistance.
3. Connect a digital voltmeter between the D801 cathode and the chassis of the N board.
4. Turn on power. Adjust the variable resistor so that the digital multimeter reads 135.0V±1.0V.
5. Read the variable resistance then.
6. Mount a fixed resistor of the measured resistance to R902.

   Note : R902 : Must be 2.2kΩ to 27kΩ
7. Turn on power again. Confirm that the digital multimeter reads 135.0V±1.0V.



SECTION 5
CIRCUIT ADJUSTMENTS

5-1. ELECTRICAL ADJUSTMENT BY REMOTE COMMANDER

Use of Remote Commander (RM-Y112A) can be performed circuit adjustments about this model.

1. METHOD OF SETTING THE SERVICE MODE

1) Press [POWER] button on the Remote Commander while pressing switch on the rear of the set.

NOTE : Test Equipment Required.

1. Pattern Generator
2. Frequency counter
3. Digital multimeter
4. Audio OSC



2. ADJUST BUTTONS AND INDICATOR



3. AN ITEM OF ADJUSTMENT

ITEM	REFERENCE DATA	NAME REGIST	
AFC	0	VP	AFC 1.0
HFRE	74	VP	H. FREQUENCE
VFRE	16	VP	V. FREQUENCE
HPOS	5	VP	H. PHASE
GAMP	25	VP	GREEN AMP.
BAMP	26	VP	BLUE AMP.
GCUT	9	VP	GREEN CUT OFF.
BCUT	6	VP	BLUE CUT OFF
SPIX	40	VP	PICTURE
SHUE	29	VP	HUE
SCOL	28	VP	COLOR
SBRT	11	VP	BRIGHT
RGBP	28	VP	RGB PICTURE
SHAR	13		SHARPNESS
DISP	24		OUTPUT
VSMO	0	VP	VSMO
REF	1	VP	REF 1.0
ROFF	1	VP	OFF NR
GOFF	1	VP	OFF NG
BOFF	1	VP	OFF NB
ABLM	0	VP	ABLM
DRGB	0	VP	D RGB
TEST	0	AP	T
MPX	7	AP	ATT
FILO	31	AP	I 1
DEEM	7	AP	I 2
STEV	31	AP	OSC 1
SAPV	31	AP	OSC 2
PILO	7	AP	PILOT
SEP	31	AP	WIDE BAND
VD	7	AP	SPECTRAL
LVOL	0	AP	VOLUME-L
RVOL	0	AP	VOLUME-R
BASS	8	AP	BASS
TRE	8	AP	TREBLE
PHPO	32	PI	READ DELAY H
PVPO	8	PI	READ DELAY V
PLEV	6	PI	PICTURE LEVEL
PFCO	7	PI	FRAME COLOR
PPLL	1	PI	PLLOF
PPVS	6	PI	VSPDEL
NRLE	31		NR LEVEL
DSPP	43		
SHAD	1	PJ	SHADON
VMSW	1	PJ	RS HAD
SCUT	16	PJ	SHAD CUT OFF

4. METHOD OF CANCELLATION FROM SERVICE MODE

Set the standby condition (Press POWER button on the commander) in the next place, press POWER button again, hereupon it becomes TV mode.

5. METHOD OF WRITE FOR MEMORY

1) Set to Service Mode.
2) Press 1 (UP) and 4 (DOWN), select an item of adjustments.
3) Press MUTING button indicate WRITE (RED) on screen.
4) Press ENTER button to write for memory.

6. MEMORY WRITE CONFIRMATION METHOD



1) After adjustment, pull out the plug from AC outlet, and next place, plug in AC outlet again.
2) Turn the power switch ON and set to Service Mode.
3) Call the adjusted items again, confirm they were adjusted.

7. PUB PICTURE POSITION ADJUSTMENT (PHPO, PUPO)

Note : Before doing any Service Adjustments on the models above you must make sure that the PIP Screen is in the number 1 position, even if there are no adjustments being made to PIP.



PIP Positions

After making adjustments into the PIP 1 position, write the information into the ROM.
Next, unplug the unit and recheck the other three positions. Adjustments made to the number 1 position will affect the other three positions.

5-2. A BOARD ADJUSTMENTS

RF AGC ADJUSTMENT(IF BLOCK VR)

1) Input a color-bar signal.
2) Adjust AGC VR of TU 101 so that snow noise and cross-modulation disappear from the picture.
3) Confirm them at every channel.

H.FREQUENCY ADJUSTMENT (HFRE)

1) Set to Service Mode.
2) Input a color-bar signal.
3) Connect a frequency counter to pin③ of A-10 connector.
4) Call the item of AFC, set to 3 level (free run).
5) Select HFRE with 1 and 4.
6) Adjust 3 and 6 to the 15735± 60 Hz level.
7) Call the item of AFC again, adjust the level" 01 ".
8) Write into the memory by pressing MUTING → then ENTER.

V.FREQUENCY ADJUSTMENT (VFRE)

1) Set to the Service Mode.
2) Input an off-air signal (VIDEO IN → no signal).
3) Connect the frequency counter across connector ⑬pin of E 1-1 connector and ground.
4) Select VFRE with 1 and 4.
5) Adjust 3 and 6 to the ~~55~~ 56 ±0.5 Hz.
6) Write the memory by pressing MUTING → then ENTER.

SUB CONTRAST ADJUSTMENT (SPIX)

1) Set to Service Mode.
2) Input a color-bar signal. (75 IRE)
3) Set the conditions as follows.

PICTURE	····· MAX
COLOR	····· MIN
BRIGHTNESS	····· MIN
TRINITONE	····· LOW
R OFF	····· ON
G OFF	····· OFF
B OFF	····· OFF



4) Connect an oscilloscope to ⑳pin of E1-1 connector on A board and ground.
5) Adjust 3 and 6 to the 2.10 ± 0.05Vp-p level by select-ing SPIX with 1 and 4.
6) Write the memory by pressing MUTING → then ENTER.
7) Return the following back to normal after adjustment.

G OFF	····· ON
B OFF	····· ON
COLOR	····· CENTER
BRIGHTNESS	····· CENTER
TRINITONE	····· HIGH
PICTURE	····· 80%

SUB HUE, SUB COLOR ADJUSTMENT (SHUE, SCOL)

1) Input a color-bar signal.
2) Press STANDARD to normal.
3) Set to Service Mode.
4) Connect an oscilloscope to pin㉒ of E1-1 connector on A board and ground.
5) Adjust 3 and 4 to the V1=V4 and V2=V3 by select to SHUE and SCOL with 1 and 4. Lower the data 4 steps from this point.



4) Make the data "00" by selecting FILO with 1 and 4 And then, send up the data gradually by pressing 6 . Set the data to D1 before SAT3 changing to 1 from 0.
5) Send up the data gradually. Set data D2 when SAT3 changes 0 from 1.
6) Adjust the data of FILO to $\frac{D1+D2}{2}$.
7) Write into the memory by pressing MUTING → then ENTER .



6) Write into the memory by pressing MUTING →then ENTER .

FILTER ADJUSTMENT (MPX, FILO)

1) Set to Service Mode.
2) Select to TEST with 1 and 4, set the data to "1". Then select MPX and change data to "8".
3) Connect an audio oscillator to R224 using a capacitor (10μ F/16V), set frequency to 62.936 kHz±0.1 kHz.
And then, through the 10kΩ resistor, feed 9.0V into the mute of TUVIF TU 101.



V 4 fh : SINE-WAVE 62.936 KHz±0.1 KHz
LEVEL 3.0 Vp-p

ST VCO ADJUSTMENT (MPX, STEV)

1) Set to Service Mode.
2) Select TEST with 1 and 4 , set the data to "1". And then press MTS to MONO.
3) Select MPX, set the data "8" .
4) Connect an audio oscillator to R 224 using electrolytic capacitor (10μ F/16V) and appply the frequency Vst. Then, apply DC voltage to mute of TUVIF TU 101 using 10kΩ connect to 9.0 V line.



Vfh : SINE-WAVE 15.734 KHz±0.1 KHz
LEVEL 0.28 Vp-p

5) Select STEV with [1] and [4], set the data to "00" with [6]. And then, send up the data gradually. Set the data to D1 before SAT2 changes from 0 to 1.
6) Send up data gradually, set the data to D2 when SAT2 changes 1 from 0.
7) Adjust the data of STEV to (D 1+D 2)/2.
8) Write into the memory by pressing [MUTING] → then [ENTER] .



MPX IN LEVEL ADJUSTMENT (MPX)

1) Set to Service Mode.
2) Select TEST with [1] and [4], set the data to "0" with [6]. And then press [MTS] to MONO.
3) Select MPX with [1] and [4], set the data to "8" with [3] and [6].
4) Write into the memory by pressing [MUTING] → then [ENTER] .

PILOT CANCEL ADJUSTMENT (PILO)

1) Set to the Service Mode.
2) Select PILO with [1] and [4], set the data to "08" with [3] and [6].
3) Write into the memory by pressing [MUTING] → then [ENTER] .

SAP VCO f_0 ADJUSTMENT (SAPV)

1) Set to Service Mode.
2) Input a stereo broadcast signal with SAP.
3) Select TEST with [1] and [4], set the data to "0" . And then, press [MTS] to MAIN.
4) Connect a digital multimeter to TP-1(DBX). This voltage reading will equal V 1.
5) Press MTS to SAP and this voltage will equal V 2.
6) Select SAPV with [1] and [4], adjust [3] and [6] so that V 2=V 1±0.03 VDC.
7) Write the memory by [MUTING] → [ENTER] .

SEPARATION ADJUSTMENT (SEP)

1) Set to Service Mode.
2) Press [MTS] to MAIN and receive a monoral broad -cast signal.
In the next step, receive a stereo broadcast signal.
3) Select SEP and VD with [1] and [4], adjust [3] and [6] so that a clear stereo sound is effected.

SUB PICTURE POSITION ADJUSTMENT (PHPO, PVPO)

1) Input a cross hatch signal.
2) Set to service mode.
3) Press PIP to display a sub picture. (RIGHT LOWER Position)
4) Select PHPO, PVPO with [1] and [4].
5) Adjust [3] and [6] to the standard as shown below.
6) Write the memory by pressing [MUTING] → then [ENTER] .



PUB PICTURE POSITION ADJUSTMENT (PHPO, PUPO)

Note : Before doing any Service Adjustments on the models above you must make sure that the PIP Screen is in the number 1 position, even if there are no adjustments being made to PIP.



PIP Positions

After making adjustments into the PIP 1 position, write the information into the ROM.
Next, unplug the unit and recheck the other three positions. Adjustments made to the number 1 position will affect the other three positions.

5-3. DS BOARD ADJUSTMENTS

V. 3 WAVE ADJUSTMENT (RV983)

1) Input a color-bar signal.
2) Connect an oscilloscope IC1712 Pin⑦ of DS board ground.
3) Adjust RV983 as shown the following figure.



NG

NG

H. 3 WAVE ADJUSTMENT (RV984)

1) Input a color-bar signal.
2) Connect an oscilloscope IC1712 Pin① of DS board ground.
3) Adjust RV984 as shown the following figure.





NG

NG

5-4. P1 BOARD ADJUSTMENTS



SUB HUE ADJUSTMENT (RV 3001)

1) Set HUE and COLOR to the standard condition.
2) Make adjustment so that B-Y signal as shown to the right is obtained at the crossing point of R 3009 (0 Ω) and C 3033.
3) Supply the color bar signal of 75 IRE (white) at 2 Vpp to Pin ㉑ (SUB V) of P 1-1 and make adjustment by turning RV 3001.



H. FREQUENCY (H OSC) ADJUSTMENT (RV-3002)

1) Connect a frequency counter to Pin ④ (H OUT) of IC 3003.
2) Connect Pin ⑫ of IC 3003 to ground.
3) Adjust RV3002 for a frequency of 15.734 kHz ± 50 Hz at Pin ④ of IC 3003.
(or until the frequency comes to a standstill.)

KP-41EXR96
RM-Y112A

SECTION 6
DIAGRAMS

6-1.BLOCK DIAGRAM (1)





KP-41EXR96 KP-41EXR96
RM-Y112A RM-Y112A

6-2.BLOCK DIAGRAM (2)



KP-41EXR96 KP-41EXR96
RM-Y112A RM-Y112A

6-3.BLOCK DIAGRAM (3)



6-4.FRAME SCHEMATIC DIAGRAM



6-5.CIRCUIT BOARDS LOCATION



6-6.SCHEMATIC DIAGRAMS AND PRINTED WIRING BOARDS

Note :

- All capacitors are in μF unless otherwise noted. pF : μμF
  50WV or less are not indicated except for electrolytics and tantaliums.
- All electrolytics are in 50V unless otherwise specified.
- All resistors are in ohms.
  kΩ = 1000Ω, MΩ = 1000kΩ
- Indication of resistance, which does not have one for rating electrical power, is as follows.

  Pitch : 5mm
  Rating electrical power : ¼W
- Chips resistors are 1/10W.
- : nonflammable resistor.
- : internal component.
- : panel designation and adjustment for repair.
- All variable and adjustable resistors have characteristic curve B, unless otherwise noted.
- : earth-ground
- : earthchassis
- The components identified by ⊠ in this manual have been carefully factory-selected for each set in order to satisfy regulations regarding X-ray radiation. Should replacement be required, replace only with the value originally used.
- When replacing components identified by ◪, make the necessary adjustments indicated. If results do not meet the specified value, change the component identified by ⊠ and repeat the adjustment until the specified value is achieved.
  (Refer to R852, R852, R900, R901, and R902 adjustment on Page 53~56.)
  When replacing the part in below table, be sure to perform the related adjustment.

Part replaced (◪)		Adjustment (⊠)
HV Block IC803, IC805, D805, D807 C817, C818, C821, C836, C837, R824, R825, R827, R828, R834, R835, R836, R864, R865, R866, R902	N Board	HV Repurater (R902)
HV Block IC803, IC804, Q804, D806 D808, C809, C819, C820, C822, C823, C850, R807, R826, R829, R832, R833, R837, R838, R839, R840, R841, R892, R893, R900, R901	N Board	HV Hold down (R900, R901)
Q618, Q621, D628, C634, R639, R649, R652, R655, R656,	G Board	OVP (R652)
① IC802, Q805, Q807, D811, D812, C810, C824, C825, C826, C827, C831, R810, R843, R844, R847, R848, R849, R850, R851, R852, R853, R854, R881	N Board	Beme current protecter ①R852 ②R852
② IC804, Q804, Q808, D808, D809, C809, C828, C829, C830, C831, R807, R839, R840, R841, R847, R848, R849, R850, R851, R852, R855, R856, R857, R881	N Board	

Reference information

RESISTOR	: RN	METAL FILM
	: RC	SOLID
	: FPRD	NONFLAMMABLE CARBON
	: FUSE	NONFLAMMABLE FUSIBLE
	: RS	NONFLAMMABLE METAL OXIDE
	: RB	NONFLAMMABLE CEMENT
	: RW	NONFLAMMABLE WIREWOUND
	: ※	ADJUSTMENT RESISTOR
COIL	: LF-8L	MICRO INDUCTOR
CAPACITOR	: TA	TANTALUM
	: PS	STYROL
	: PP	POLYPROPYLENE
	: PT	MYLAR
	: MPS	METALIZED POLYESTER
	: MPP	METALIZED POLYPROPYLENE
	: ALB	BIPOLAR
	: ALT	HIGH TEMPERATURE
	: ALR	HIGH RIPPLE

- Readings are taken with a color-bar signal input.
- Readings are taken with a 10M Ω digital multimeter.
- Voltage are dc with respect to ground unless otherwise noted.
- Voltage variations may be noted due to normal production tolerances.
- All voltages are in V.
- Circuled numbers are waveform references.
- ●——● : B + bus.
- ●- - -● : B − bus.
- ●⟶● : signal path.

Note: The components identified by shading and mark ⚠ are critical for safety. Replace only with part number specified.

Note: Les composants identifiés par une trame et par une marque ⚠ sont d'une importance critique pour la sécurité. Ne les remplacer que par des pièces de numéro spécifié.

• A BOARD IC201,207 SI-3090CA



• A BOARD IC1401 TA8216H



• A BOARD WAVEFORMS

① 1.2Vp-p (H)	② 1.2Vp-p (H)	③ 2.5Vp-p (H)
④ 2.0Vp-p (V)	⑤ 2.0 Vp-p (V)	⑥ 2.0Vp-p(V)
⑦ 1.8Vp-p (V)	⑧ 1.0Vp-p (H)	⑨ 1.2 Vp-p (H)
⑩ 1.0Vp-p (H)	⑪ 0.8Vp-p (H)	⑫ 1.4 Vp-p (H)
⑬ 58 Vp-p (H)	⑭ 450Vp-p (H)	⑮ 0.7Vp-p (V)
⑯ 12.0Vp-p (V)	⑰ 1.5Vp-p (H)	⑱ 1.5Vp-p (H)
⑲ 1.4Vp-p (H)	⑳ 1.6Vp-p (H)	㉑ 1.6Vp-p (H)
㉒ 1.4Vp-p (H)	㉓ 1.5Vp-p (V)	



A [Y/C JUNGLE, SHR, P IN P, μ CON, AUDIO SHADING, H DEF]

– A BOARD –



NOTE:
The circuit indicated as left contains high voltage of over 600 Vp-p. Care must be paid to prevent an electric shock in inspection or repairing.

IC		TRANSISTOR		DIODE	
IC201	D-5	Q201	C-4	D203	G-9
IC204	D-6	Q202	G-3	D204	B-2
IC205	E-1	Q203	G-9	D205	E-4
IC206	B-6	Q501	C-9	D206	D-7
IC207	A-2	Q502	B-9	D207	D-7
IC506	G-9	Q504	G-7	D208	E-7
IC1401	C-5	Q505	C-9	D209	B-6
IC1601	F-9	Q506	C-9	D211	E-4
		Q507	D-10	D213	A-6
		Q508	B-10	D214	A-5
		Q509	G-8	D215	E-2
		Q510	C-8	D216	E-1
		Q511	A-2	D217	E-1
		Q512	A-2	D219	G-5
		Q1401	B-4	D220	E-5
		Q1402	C-7	D221	B-1
		Q1407	B-5	D222	D-6
		Q1408	B-4	D223	D-6
		Q1601	E-9	D501	C-7
		Q1602	E-10	D502	C-7
		Q1603	E-10	D503	B-9
		Q1604	E-10	D504	C-7
		Q1605	E-9	D505	F-7
		Q1606	E-9	D506	F-7
		Q1620	D-8	D507	B-8
				D509	C-7
				D510	A-1
				D511	A-2
				D512	C-9
				D513	D-7
				D514	G-7
				D515	G-8
				D1401	A-3
				D1402	B-4
				D1403	C-7
				D1404	A-3
				D1405	A-3
				D1406	B-5
				D1407	A-4
				D1408	B-5
				D1409	A-4
				D1410	D-4
				D1607	G-10
				D1608	G-10

U [AUDIO IN/OUT, VIDEO IN/OUT] **UT** [IN/OUT TERMINAL, SP. TERMINAL]

– U BOARD –

IC	
IC1002	B-3
IC1011	F-2

TRANSISTOR	
Q1009	D-2
Q1016	E-3
Q1017	B-5
Q1018	E-2
Q1019	E-3
Q1020	B-5
Q1021	B-2
Q1022	E-1
Q1023	C-2
Q1029	B-2
Q1030	D-2
Q1031	E-2
Q1032	C-4
Q1033	E-2
Q1034	G-2

DIODE	
D1005	A-2
D1009	B-4
D1010	A-4
D1011	B-3
D1012	D-3
D1013	E-3
D1015	B-4
D1017	B-2
D1018	G-2
D1019	G-2
D1020	E-2
D1021	E-3
D1022	E-3



– UT BOARD –







• U BOARD WAVEFORMS

① 3.0Vp-p (H)	② 2.2Vp-p (H)	③ 2.3Vp-p (H)
④ 1.3Vp-p (H)	⑤ 2.2 Vp-p (H)	⑥ 2.2Vp-p (H)
⑦ 2.3Vp-p (H)	⑧ 2.1Vp-p (H)	⑨ 1.8 Vp-p (H)
⑩ 2.2Vp-p (H)		



• D BOARD WAVEFORMS

① 2.6Vp-p (H)	② 2.7Vp-p (H)	③ 2.2Vp-p (V)
④ 4.4Vp-p (H)	⑤ 2.4 Vp-p (V)	⑥ 2.4Vp-p (H)
⑦ 4.2Vp-p (H)	⑧ 4.0Vp-p (V)	⑨ 2.3 Vp-p (V)
⑩ 2.3Vp-p (V)	⑪ 2.2Vp-p (V)	⑫ 2.6 Vp-p (V)
⑬ 1.8Vp-p (V)	⑭ 2.2Vp-p (H)	⑮ 1.3Vp-p (V)
⑯ 2.1Vp-p (V)	⑰ 2.3Vp-p (H)	⑱ 6.2Vp-p (V)
⑲ 2.7Vp-p (V)	⑳ 6.6Vp-p (V)	㉑ 2.8Vp-p (V)
㉒ 0.48Vp-p (V)	㉓ 2.4 Vp-p (H)	㉔ 2.2Vp-p (V)
㉕ 36.0Vp-p (V)	㉖ 32.0Vp-p (H)	㉗ 20.0Vp-p (V)
㉘ 26.0Vp-p (H)	㉙ 32.0Vp-p (V)	㉚ 24.0Vp-p (H)
㉛ 1.3Vp-p (V)	㉜ 68.0Vp-p (V)	㉝ 1.6Vp-p (H)
㉞ 2.2Vp-p (V)		



D REGISTRATION, DEFLECTION V—OUT, SUB—OUT.

– D BOARD –



IC		VARIABLE RESISTOR	
IC801	C-3	RV901	C-9
IC802	B-6	RV902	D-9
IC803	B-8	RV903	D-9
IC804	B-8	RV904	E-9
IC805	B-9	RV905	D-9
IC806	B-9	RV906	E-9
IC807	D-4	RV907	C-8
IC808	C-3	RV908	D-8
IC810	B-5	RV909	D-8
IC1701	A-1	RV910	E-8
IC1702	C-2	RV911	E-8
IC1703	E-1	RV912	E-8
IC1704	B-1	RV913	E-8
IC1705	E-1	RV914	D-8
IC1706	B-10	RV915	C-8
IC1707	D-10	RV916	D-8
IC1708	E-9	RV917	E-8
IC1709	E-10	RV918	E-8
IC1710	C-10	RV919	C-7
IC1714	B-3	RV920	D-7
IC1715	B-4	RV921	D-7
IC1718	B-4	RV922	E-7
		RV923	E-7
TRANSISTOR		RV924	E-7
		RV925	D-7
Q902	A-5	RV926	C-7
Q906	A-9	RV927	D-7
Q907	A-9	RV928	E-7
Q908	A-4	RV929	E-7
Q909	D-9	RV930	E-7
Q910	A-10	RV931	C-7
Q911	B-10	RV932	D-7
Q912	B-9	RV933	D-7
		RV934	E-7
DIODE		RV935	E-7
		RV936	E-7
D901	A-6	RV937	E-6
D902	A-6	RV938	E-6
D1701	B-1	RV939	E-6
D1702	C-5	RV940	C-6
D1703	C-1	RV941	D-6
D1704	B-10	RV942	D-6
D1075	D-10	RV943	C-6
D1706	E-10	RV944	D-6
D1707	A-9	RV945	D-6
D1708	A-9	RV946	E-6
D1709	E-9	RV947	E-6
D1710	C-10	RV948	E-6
D1711	A-4	RV949	C-6
D1712	A-4	RV950	D-6
D1713	C-5	RV951	D-6
D1714	B-6	RV952	E-6
D1715	B-6	RV953	E-6
D1716	C-4	RV954	E-6
D1717	C-4	RV956	C-5
D1718	C-4	RV957	D-5
D1720	B-4	RV958	D-5
D1721	B-4	RV959	C-4
D1722	A-4	RV960	E-5
D1723	A-4	RV961	E-4
		RV962	E-4
		RV963	C-5
		RV964	D-5
		RV965	D-5
		RV966	E-5
		RV967	E-5
		RV968	C-5
		RV969	D-5
		RV970	D-5
		RV971	E-5
		RV972	E-5
		RV973	E-4
		RV974	E-4
		RV975	E-4
		RV976	E-4
		RV977	E-3
		RV978	E-3
		RV979	E-3
		RV980	E-3
		RV981	E-3
		RV982	D-3

• D BOARD IC1706,1707,1708 μPC1498H



• D BOARD IC902 CXA1268P



G [POWER SUPPLY] **H1** [USER CONTROL] **H2** [USER CONTROL] **DS** [SIN. WAVE. GEN]

– G BOARD –



IC	
IC601	E-3
IC602	A-5

TRANSISTOR	
Q603	C-3
Q604	G-2
Q607	G-3
Q608	G-3
Q609	C-7
Q610	C-7
Q611	C-7
Q612	C-7
Q613	F-2
Q614	D-2
Q615	F-4
Q616	E-4
Q618	F-3
Q620	F-3
Q621	F-3
Q623	G-6
Q629	A-7
Q630	G-3

DIODE	
D602	E-6
D603	G-5
D604	G-6
D605	F-7
D607	D-4
D608	C-7
D609	G-4
D610	C-3
D611	E-6
D613	G-4
D614	E-2
D615	G-2
D616	D-3
D617	G-2
D618	G-4
D619	F-2
D620	F-6
D621	G-4
D622	F-2
D623	F-3
D624	F-4
D626	D-6
D628	F-4
D629	F-4
D631	C-2
D632	A-3
D633	B-4
D634	C-6
D636	G-5
D638	A-7
D640	G-6
D650	F-7

KP-41EXR96
RM-Y112A

– H1 BOARD –



– H2 BOARD –



– DS BOARD –









• DS BOARD WAVEFORMS











• CB BOARD WAVEFORMS



• CG BOARD WAVEFORMS



• CR BOARD WAVEFORMS











CB [B OUT] **CG** [G OUT] **CR** [R OUT] **ZB** [DY I/F] **ZG** [DY I/F] **ZR** [DY I/F] **V** [VM]

– CB BOARD –



– CG BOARD –



– CR BOARD –



– ZB BOARD –



– ZG BOARD –



– ZR BOARD –



– V BOARD –



S [SUB-CONTROL, μ-CON, CLOSED CAPTAIN DECORDER] **N** [H.V]

– S BOARD –



IC		TRANSISTOR	
IC3401	C-3, F-1	Q3441	C-1
IC3402	C-3	Q3444	B-5
IC3441	B-1, G-1	DIODE	
IC3442	C-2, F2	D3444	B-5
IC3443	B-3, G-3		
IC3444	A-4, H-4		

: Pattern from the side which enables seeing.
: Pattern of the rear side.

– N BOARD –

IC	
IC801	B-3
IC802	C-2
IC803	A-1
IC804	D-2
IC805	D-4
TRANSISTOR	
Q801	B-5
Q802	B-3
Q803	D-6
Q804	D-5
Q805	D-5
Q806	D-5
Q807	C-1
Q808	C-1
Q809	D-4
Q811	C-7
Q812	B-2
Q820	B-3
Q851	C-5
Q852	C-4
Q853	C-4
DIODE	
D801	A-6
D802	B-5
D803	B-2
D804	C-2
D805	B-2
D806	C-2
D807	D-4
D808	D-2
D809	D-1
D810	D-3
D811	B-1
D812	C-2
D813	C-2
D814	A-3
D815	D-3
D817	D-7
D818	B-3
D820	A-3
D850	C-4
D851	E-5
D852	C-4
D853	E-5
D891	B-2
D892	C-2



NOTE:
The circuit indicated as left contains high voltage of over 600 Vp-p. Care must be paid to prevent an electric shock in inspection or repairing.

KP-41EXR96 RM-Y112A KP-41EXR96 RM-Y112A

KP-41EXR96 RM-Y112A





• N BOARD WAVEFORMS

① 1.4Vp-p (H)	② 55 Vp-p (H)	③ 0.8Vp-p (H)
④ 2.6Vp-p (H)	⑤ 0.5 Vp-p (V)	⑥ 0.5Vp-p (V)
⑦ 5.0Vp-p (V)		

KP-41EXR96 KP-41EXR96
RM-Y112A RM-Y112A

X2

<SRS SURROUND>



B-SS326.<U/C>-X2.

• X2 BOARD IC2502 CXA1373Q



KP-41EXR96 KP-41EXR96
RM-Y112A RM-Y112A

X2 [SRS SURROUND] **E1** [Y/C JUNGLE] **M** [MAIN CONTROL, μ – CON]

– X2 BOARD –



IC	
IC2501	G-3
IC2502	C-2
IC2503	A-1 H-1
IC2504	E-4
IC2505	A-2 H-2
IC2506	G-4
IC2507	E-5
IC2508	H-4
TRANSISTOR	
Q2501	G-2
DIODE	
D2501	F-5
D2502	F-5
D2503	G-5
D2504	F-5

IC	
IC301	C-5
IC302	B-4, G-4
IC303	C-3
TRANSISTOR	
Q301	C-2
Q302	C-1
Q303	C-1
Q304	A-2
Q305	B-1
Q306	H-3
Q307	C-2
Q309	F-2
Q310	D-2
Q311	B-2
Q312	B-2
Q314	B-2
Q315	G-5
Q316	G-5
Q317	E-3
Q321	D-2
Q322	G-4
Q323	F-3
Q324	G-3
Q325	G-3
Q326	D-5
Q327	G-3
Q328	F-5
Q329	C-3
Q330	C-3
Q333	D-4
Q334	D-4
Q335	D-4
Q340	E-4
Q342	D-5
Q344	D-3
DIODE	
D301	F-1
D302	G-1
D303	G-1
D304	G-3
D305	F-3
D306	C-2
D307	C-4
D310	G-4
D312	G-4
D313	G-3
D314	G-3
D315	G-2
D316	G-3
D317	B-5
D318	F-5
D319	B-5
D320	G-5
D321	B-2

: Pattern from the side which enables seeing.
: Pattern of the rear side.



: Pattern from the side which enables seeing.
: Pattern of the rear side.

– M BOARD –



IC	
IC001	C-1
IC002	D-2, E-2
TRANSISTOR	
Q001	G-5
Q008	G-1
Q010	H-1
Q011	F-1
Q012	G-5
Q013	A-5
Q014	C-4
DIODE	
D001	H-5
D002	H-5
D009	F-1
D010	A-4
D011	D-2
D012	B-4
D014	A-1
D015	B-4

: Pattern from the side which enables seeing.
: Pattern of the rear side.

• M BOARD WAVEFORMS

①	②	③
5Vp-p (H)	4.2Vp-p (V)	2.4Vp-p (H)

• E1 BOARD WAVEFORMS

① 0.5 Vp-p (V)	② 0.3 Vp-p (V)	③ 1.5 Vp-p (H)
④ 0.8 Vp-p (H)	⑤ 0.8 Vp-p (H)	⑥ 22 Vp-p (H)
⑦ 1.6 Vp-p (V)	⑧ 2.0 Vp-p (H)	





• E2 BOARD WAVEFORMS



• E2 BOARD IC2304 CXA1387S







• Y2 BOARD IC406 CXA1264AS



• Y2 BOARD IC408 CXA1315P



E2 [SHARPNESS CONT, CHARACTOR GENERATER] **Y2** [MTS DECORDER, NVM, AUDIO CONT]

– E2 BOARD –



IC	
IC2031	B-4
IC2303	A-5
IC2304	D-3, E-2
IC2306	H-3
IC2307	B-3
TRANSISTOR	
Q2301	C-5
Q2303	C-5
Q2304	D-5
Q2305	C-5
Q2306	A-3
Q2307	B-4
Q2308	A-3
Q2309	B-2
Q2310	A-2
Q2311	A-2
Q2312	A-2
Q2313	A-2
Q2314	A-2
Q2315	A-2
Q2317	H-4
Q2318	G-4
Q2319	G-5
Q2320	A-4
Q2321	A-4
Q2322	A-4
Q2324	B-3
Q2326	E-1
Q2327	E-2
Q2328	D-4
Q2329	D-4
Q2330	C-4
Q2336	C-5
Q2337	B-3
Q2339	F-4
Q2340	F-4
Q2341	F-4
DIODE	
D2306	C-5
D2307	B-2
D2308	B-2
D2309	B-5
D2312	C-4
D2313	C-4
D2314	B-5
D2317	A-4

: Pattern from the side which enables seeing.
: Pattern of the rear side.

– Y2 BOARD –



IC	
IC403	H-1
IC404	D-5, E-5
IC406	C-2, F-2
IC407	A-4, G-4
IC408	C-4, F-4
TRANSISTOR	
Q404	H-3
Q405	H-3
Q409	D-5
Q410	E-5
DIODE	
D405	F-2
D406	F-2
D407	F-3
D408	E-4
D409	A-5
D410	C-5, F-5
D413	E-6
D414	F-4
D415	B-5

: Pattern from the side which enables seeing.
: Pattern of the rear side.

• **P1 BOARD IC3001 TDA3769**



• **P1 BOARD IC3003 TDA2595**



P1 [PICTURE IN PICTURE]

– P1 BOARD –

IC	
IC3001	A-2, G-2
IC3002	D-2
IC3003	B-2, F-2
IC3004	D-4
IC3005	C-4
IC3006	B-5, G-5
IC3007	A-4, G-4
IC3008	C-5, F-5

TRANSISTOR	
Q3003	A-3
Q3004	C-3
Q3006	F-4
Q3007	G-4
Q3008	H-3
Q3009	G-4
Q3010	H-5
Q3011	F-4
Q3012	F-1
Q3013	C-1
Q3014	F-4
Q3100	B-4

DIODE	
D3003	E-4
D3004	B-5
D3009	C-1

VARIABLE RESISTOR	
RV3001	B-1, G-1
RV3002	D-1, E-1
RV3003	A-1, G-1



Pattern from the side which enables seeing.
: Pattern of the rear side.



B-SS347.<U/C>-P1.

• **P1 BOARD WAVEFORMS**

①	②
	
2.0 Vp-p (H)	1.6 Vp-p (H)

6-7.SEMICONDUCTORS

CXA1387S



CXA1268P
SÐA9187X
SÐA9188X



CXA1315M
CXA1315P
MC141053CP
µPÐ4053BC



CXA1464AS

CXA1545S



CXA1373Q



LC7458A-02



CXA1656S
LA7945



24C04AI/P
SÐA9086-3
TL082CP
µPC393C
µPC4082C
µPC4557C
µPC4558C



LM324N
MB3614
µPC1394C



MC74HC4053F
MC14528BF
µPÐ4052BG
TC4528BFHB



MN1280-S

M51523AL



NJM78M05FA
TA78125
µPC7805H
µPC7812H



M5220L



M37201M6-A18FP



RC4558PS
µPC4570G2



CXA1264AS
PA0036



NJM79M05FA
NJM7915FA



SI-3090CA



MC33172ML
MC33174M
SN74HC05ANS



PCA8510T/012-T



STK-4278L



TA8216H



TÐA2595-V9



TMC73C247-10



µPC1037HA



µPC78N05H

µPC1498H



TA8184P
TÐA3769



ÐTA124ES
ÐTC144ES
2SC3622A-LK



FMW1

XN441



IMX3
IMZ1

2SA1013-O
2SÐ788-5
2SA1091-O
2SA1208-S
2SC2551-O



2SA1037K-QR
2SC1623-L5L6
2SC2412K-QR
2SÐ601A-Q



2SA1309A-Q
2SA1175-HFE
2SC3311A-Q
2SC2785-HFE



2SA1301-O



2SA1306A-Y
2SC3298B-Y

2SB649A-C
2SC2611
2SC2688-LK
2SC3271-N



2SB861-C
2SB1015-Y
2SC3675
2SÐ1406-YGR

2SC2555-2

2SC3733

2SC4256CB

2SC4582-NP
2SÐ2012

2SC4891-CA
2SÐ1887-CA

Ð10SC6M
Ð5KC40H

Ð10SC6MR

ÐÐ50R

Ð1N20R
EGP10Ð
RB-100A
RÐ13ES-B2
RÐ18ES-B2
RÐ2.0ES-B1
RÐ24ES-B3
RÐ3.3ES-B2
RÐ3.9ES-B1
RÐ33ES-B2
RÐ39ES-B2
RÐ4.7ES-B2
RÐ5.1ES-B1
RÐ5.1ES-B2
RÐ5.6ES-B2
RÐ7.5ES-B1
1SS119

ERC06-15S
RU-1C
RU-2AM

ERC38-06
V06C
V09G
V19F
V30N

GP08Ð
ERÐ28-08S
RÐ27FB2
SB140

MA110
MA3130

RÐ15M-B1
RÐ18M-B1
RÐ5.1M-B3

RÐ15S-B
RÐ5.6S-B
RÐ6.2S-B

RÐ9.1E-W

S1VB40

S3V10SB

S5VB60

1S2836

1T33

TLR124

SECTION 7
EXPLODED VIEWS

NOTE:
- Items with no part number and no description are not stocked because they are seldom required for routine service.
- The construction parts of an assembled part are indicated with a collation number in the remark column.
- Items marked " ★ " are not stocked since they are seldom required for routine service. Some delay should be anticipated when ordering these items.

The components identified by shading and mark ⚠ are critical for safety.
Replace only with part number specified.

Les composants identifies par une trame et une marque ⚠ sont critiques pour la securite.
Ne les remplacer que par une piece portant le numero specifie.

7-1.SCREEN FRAME AND CONTROL PANEL

● : BVTP3×12 7-685-648-79

□ : BVTP4×12 7-685-661-79



REF.NO.	PART NO.	DESCRIPTION	REMARK
1	X-4031-192-1	FRAME ASSY, SCREEN	2~4
2	3-704-179-01	EMBLEM (NO.9), SONY	
3	4-036-087-21	COVER, INDICATOR	
4	4-033-779-11	BUTTON, CONTROL	
5	4-378-522-31	SCREW, TAPPING, HEXAGON HEAD	
6	*1-643-591-11	H1 BOARD	
7	4-034-053-01	PLATE (L), DIFFUSION	
8	4-036-520-01	PLATE (R), DIFFUSION	
9	4-036-091-01	HOLDER (L), SCREEN	
10	4-036-092-01	HOLDER (S), SCREEN	
11	X-4030-346-1	GRILLE (L) ASSY, SPEAKER	
12	X-4030-348-1	GRILLE (R) ASSY, SPEAKER	
13	4-838-438-00	LATCH	
14	*1-643-592-11	H2 BOARD	
15	X-4030-354-4	PANEL ASSY, CONTROL	16~21
16	4-033-794-11	LID, FRONT	
17	4-374-714-01	CATCH, PUSH	
18	3-703-035-11	SHAFT, LID	
19	4-843-806-00	STRIKE	
20	*4-314-320-00	HOLDER, WIRE	
21	3-721-204-01	DAMPER	
22	X-4030-347-1	COVER ASSY, FRONT	19
23	4-304-851-11	SCREW (4X25), (+) PWH TAPPING	
24	4-039-110-01	SPACER (CA)	

7-2.CABINET AND BACK COVER

□: BVTP4×12 7-685-661-79



REF.NO.	PART NO.	DESCRIPTION	REMARK
51	*X-4031-104-1	CABINET ASSY	52~54
52	4-040-755-01	CASTER (DIA. 30)	
53	4-378-522-01	SCREW, TAPPING, HEXAGON HEAD	
54	4-378-522-21	SCREW, TAPPING, HEXAGON HEAD	
55	4-378-522-31	SCREW, TAPPING, HEXAGON HEAD	
56	1-544-768-11	SPEAKER (13CM) (COAXIAL)	
57	4-036-136-01	COVER, MIRROR	
58	4-036-527-01	PLATE, REAR	
59	X-4030-402-1	COVER ASSY, BACK	

7-3.CHASSIS

● : BVTP3×12 7-685-648-79

□ : BVTP4×12 7-685-661-79

△ : PSW4×14 7-682-663-09



The components identified by shading and mark ⚠ are critical for safety.
Replace only with part number specified.

Les composants identifies par une trame et une marque ⚠ sont critiques pour la securite.
Ne les remplacer que par une piece portant le numero specifie.

REF.NO.	PART NO.	DESCRIPTION	REMARK
101	*1-644-278-11	DS BOARD	
102	*A-1346-117-A	D BOARD, COMPLETE	
103	*4-393-401-11	SPRING, TRANSISTOR	
104	⚠1-241-744-11	RESISTOR ASSY (HIGH-VOLTAGE)	
105	*A-1394-421-A	S BOARD, COMPLETE	
106	*A-1297-079-A	A BOARD, COMPLETE	107~112
107	*A-1346-138-A	E1 BOARD, COMPLETE	
108	*A-1346-137-A	E2 BOARD, COMPLETE	
109	*A-1306-436-A	M BOARD, COMPLETE	
110	*A-1195-066-A	P1 BOARD, COMPLETE	
111	*A-1394-444-A	X2 BOARD, COMPLETE	
112	*A-1394-443-A	Y2 BOARD, COMPLETE	
113	⚠1-693-102-21	TUNER (BTF-XA401)	
114	*1-555-110-00	CABLE, PIN	
115	1-561-306-00	JACK, PIN (F)	
116	4-036-137-03	PANEL, SUB CONNECTOR	
117	*A-1394-422-A	U BOARD, COMPLETE	
118	*A-1394-432-A	UT BOARD, COMPLETE	
119	4-039-112-01	WASHER, WAVE	
120	*A-1342-214-A	V BOARD, COMPLETE	
121	4-373-137-01	CAP (Z), RUBBER	
122	⚠1-453-108-11	DC BLOCK, HIGH-VOLTAGE	
123	4-034-482-01	COVER, FBT	
124	*A-1390-351-A	N BOARD, COMPLETE	
125	⚠1-453-121-11	TRANSFORMER ASSY, FLYBACK (NX-2630B4)	
126	*A-1316-149-A	G BOARD, COMPLETE	
127	⚠4-388-328-12	GROMMET, AC CORD	
128	⚠1-696-002-12	CORD, POWER (WITH NOISE FILTER)	
129	*3-670-570-21	SPACER, SUPPORT	
130	4-866-147-00	WASHER	
131	1-574-590-31	LEAD ASSY, HIGH-VOLTAGE	
132	4-036-138-04	PANEL (A),TERMINAL	

7-4.PICTURE TUBE

□ : BVTP4×12 7-685-661-79



The components identified by shading and mark ⚠ are critical for safety.
Replace only with part number specified

Les composants identifies par une trame et une marque ⚠ sont critiques pour la securite
Ne les remplacer que par une piece portant le numero specifie

REF.NO.	PART NO.	DESCRIPTION	REMARK
151	4-034-057-01	LENS (LINNIT)	
152	4-034-057-11	LENS (LINNIT)	
153	⚠ 8-736-633-05	PICTURE TUBE (SD-249 (R))	
154	⚠ 8-736-631-05	PICTURE TUBE (SD-249 (G))	
155	⚠ 8-736-632-05	PICTURE TUBE (SD-249 (B))	
156	⚠ 1-451-396-21	DEFLECTION YOKE (Y936PA)	
157	*A-1390-340-A	ZR BOARD, COMPLETE	
158	*A-1390-346-A	ZG BOARD, COMPLETE	
159	*A-1390-347-A	ZB BOARD, COMPLETE	
160	⚠ 1-452-443-13	NECK ASSY, PICTURE TUBE(NA367)	
161	*A-1331-259-A	CR BOARD, COMPLETE	
162	*A-1331-260-A	CG BOARD, COMPLETE	
163	*A-1331-261-A	CB BOARD, COMPLETE	
164	4-378-522-31	SCREW, TAPPING, HEXAGON HEAD	
165	3-701-810-91	SCREW, TERMINAL	
166	4-036-134-01	MIRROR (41), REFLECTION	
167	4-033-775-31	PROTECTOR, MIRROR	
168	4-033-775-41	PROTECTOR, MIRROR	

NOTE:

The components identified by shading and mark ⚠ are critical for safety.
Replace only with part number specified.

Les composants identifies par une trame et une marque ⚠ sont critiques pour la securite.
Ne les remplacer que par une piece portant le numero specifie.

- Items marked " * " are not stocked since they are seldom required for routine service. Some delay should be anticipated when ordering these items.
- All variable and adjustable resistors have characteristic curve B, unless otherwise noted.

RESISTORS
- All resistors are in ohms
- F : nonflammable

When indicating parts by reference number, please include the board name.

CAPACITORS
- MF : μF, PF : μμF

COILS
- MMH : mH, UH : μH

- The components identified by ⧓ in this manual have been carefully factory-selected for each set in order to satisfy regulations regarding X-ray radiation. Should replacement be required, replace only with the value originally used.

REF.NO.	PART NO.	DESCRIPTION	REMARK
	*A-1297-079-A	A BOARD, COMPLETE	
		**********	
	4-382-854-11	SCREW (M3X10), P, SW (+)	
		<CONNECTOR>	
A1	*1-564-514-11	PLUG, CONNECTOR 11P	
A2	*1-564-512-11	PLUG, CONNECTOR 9P	
A3	*1-564-507-11	PLUG, CONNECTOR 4P	
A4	*1-564-508-11	PLUG, CONNECTOR 5P	
A5	*1-564-511-11	PLUG, CONNECTOR 8P	
A10	*1-564-511-41	PLUG, CONNECTOR 8P	
A11	*1-564-511-31	PLUG, CONNECTOR 8P	
A12	1-573-297-11	CONNECTOR, BOARD TO BOARD 18P	
A13	1-573-297-11	CONNECTOR, BOARD TO BOARD 18P	
A14	*1-564-513-31	PLUG, CONNECTOR 10P	
A15	*1-564-508-11	PLUG, CONNECTOR 5P	
A16	*1-564-508-11	PLUG, CONNECTOR 5P	
A17	*1-564-508-11	PLUG, CONNECTOR 5P	
A18	*1-691-291-11	PIN, CONNECTOR (PC BOARD) 5P	
A19	*1-691-291-11	PIN, CONNECTOR (PC BOARD) 5P	
A20	*1-691-291-11	PIN, CONNECTOR (PC BOARD) 5P	
A21	*1-508-786-00	PIN, CONNECTOR (5MM PITCH) 2P	
A22	1-573-297-11	CONNECTOR, BOARD TO BOARD 18P	
A25	*1-564-506-11	PLUG, CONNECTOR 3P	
A27	*1-573-979-11	CONNECTOR, BOARD TO BOARD 11P	
A56	*1-564-508-11	PLUG, CONNECTOR 5P	
		<CAPACITOR>	
C201	1-124-910-11	ELECT 47MF 20% 50V	
C202	1-124-903-11	ELECT 1MF 20% 50V	
C203	1-130-495-00	MYLAR 0.1MF 5% 50V	
C204	1-124-477-11	ELECT 47MF 20% 16V	
C205	1-124-557-11	ELECT 1000MF 20% 25V	
C206	1-126-101-11	ELECT 100MF 20% 16V	
C207	1-124-242-00	ELECT 33MF 20% 16V	
C210	1-102-121-00	CERAMIC 0.0022MF 10% 50V	
C212	1-126-803-11	ELECT 47MF 20% 16V	
C213	1-126-103-11	ELECT 470MF 20% 16V	
C214	1-126-101-11	ELECT 100MF 20% 16V	
C215	1-126-803-11	ELECT 47MF 20% 50V	
C216	1-126-101-11	ELECT 100MF 20% 16V	
C217	1-126-803-11	ELECT 47MF 20% 25V	
C218	1-126-103-11	ELECT 470MF 20% 16V	
C219	1-124-443-00	ELECT 100MF 20% 10V	
C220	1-126-803-11	ELECT 47MF 20% 25V	
C223	1-126-803-11	ELECT 47MF 20% 25V	
C224	1-124-261-00	ELECT 10MF 20% 50V	
C225	1-124-120-11	ELECT 220MF 20% 16V	
C226	1-124-120-11	ELECT 220MF 20% 16V	
C227	1-124-621-11	ELECT 3300MF 20% 6.3V	
C299	1-126-101-11	ELECT 100MF 20% 16V	
C502	1-126-182-11	ELECT 0.47MF 20% 50V	
C503	1-130-487-00	MYLAR 0.022MF 5% 50V	
C504	1-136-153-00	FILM 0.01MF 5% 50V	
C507	1-106-383-00	MYLAR 0.047MF 200V	
C508	1-102-973-00	CERAMIC 100PF 5% 50V	
C509	1-102-030-00	CERAMIC 330PF 10% 500V	
C510 ⚠	1-136-565-11	FILM 0.015MF 3% 1.4KV	
C512 ⚠	1-136-598-11	FILM 3MF 5% 200V	
C513	1-136-153-00	FILM 0.01MF 5% 50V	
C514	1-124-477-11	ELECT 47MF 20% 16V	
C522	1-123-024-21	ELECT 33MF 160V	
C523	1-106-383-00	MYLAR 0.047MF 200V	
C528	1-124-662-11	ELECT 220MF 20% 50V	
C534	1-124-011-00	ELECT 220MF 20% 16V	
C535	1-124-011-00	ELECT 220MF 20% 16V	
C536	1-124-662-11	ELECT 220MF 20% 50V	
C537	1-124-662-11	ELECT 220MF 20% 50V	
C539	1-124-907-11	ELECT 10MF 20% 50V	
C542	1-136-153-00	FILM 0.01MF 5% 50V	
C543	1-136-153-00	FILM 0.01MF 5% 50V	
C544	1-136-153-00	FILM 0.01MF 5% 50V	
C545	1-136-153-00	FILM 0.01MF 5% 50V	
C569	1-126-355-11	ELECT 33MF 20% 160V	
C1401	1-124-910-11	ELECT 47MF 20% 50V	
C1402	1-126-157-11	ELECT 10MF 20% 16V	
C1403	1-126-157-11	ELECT 10MF 20% 16V	
C1404	1-126-157-11	ELECT 10MF 20% 16V	
C1405	1-124-910-11	ELECT 47MF 20% 50V	
C1406	1-126-101-11	ELECT 100MF 20% 16V	
C1407	1-126-057-11	ELECT 2200MF 20% 50V	
C1408	1-136-165-00	FILM 0.1MF 5% 50V	
C1409	1-136-165-00	FILM 0.1MF 5% 50V	
C1413	1-124-234-00	ELECT 22MF 20% 16V	
C1424	1-126-057-11	ELECT 2200MF 20% 50V	
C1425	1-126-057-11	ELECT 2200MF 20% 50V	
C1426	1-126-157-11	ELECT 10MF 20% 16V	
C1429	1-126-101-11	ELECT 100MF 20% 16V	
C1430	1-126-101-11	ELECT 100MF 20% 16V	
C1431	1-124-916-11	ELECT 22MF 20% 50V	
C1435	1-124-916-11	ELECT 22MF 20% 25V	
C1440	1-126-336-11	ELECT 220MF 20% 25V	
C1601	1-130-483-00	MYLAR 0.01MF 5% 50V	
C1603	1-136-153-00	FILM 0.01MF 5% 50V	
C1607	1-124-907-11	ELECT 10MF 20% 50V	
C1608	1-136-153-00	FILM 0.01MF 5% 50V	
C1609	1-136-153-00	FILM 0.01MF 5% 50V	
C1610	1-124-916-11	ELECT 22MF 20% 50V	

A

Les composants identifies par une trame et une marque ⚠ sont critiques pour la securite. Ne les remplacer que par une piece portant le numero specifie.

The components identified by shading and mark ⚠ are critical for safety. Replace only with part number specified.

REF.NO.	PART NO.	DESCRIPTION	REMARK
		<DIODE>	
D203	8-719-911-19	DIODE 1SS119	
D204	8-719-911-19	DIODE 1SS119	
D205	8-719-110-36	DIODE RD13ES-B2	
D206	8-719-911-19	DIODE 1SS119	
D207	8-719-911-19	DIODE 1SS119	
D208	8-719-911-19	DIODE 1SS119	
D209	8-719-911-19	DIODE 1SS119	
D211	8-719-110-36	DIODE RD13ES-B2	
D213	8-719-110-78	DIODE RD33ES-B2	
D214	8-719-911-19	DIODE 1SS119	
D215	8-719-911-19	DIODE 1SS119	
D216	8-719-911-19	DIODE 1SS119	
D217	8-719-911-19	DIODE 1SS119	
D219	8-719-911-19	DIODE 1SS119	
D220	8-719-510-48	DIODE D1N20R	
D221	8-719-911-19	DIODE 1SS119	
D222	8-719-911-19	DIODE 1SS119	
D223	8-719-911-19	DIODE 1SS119	
D501	8-719-971-20	DIODE ERC38-06	
D502	8-719-971-20	DIODE ERC38-06	
D503	8-719-300-80	DIODE RU-1C	
D504	8-719-109-88	DIODE RD5.6ES-B1	
D505	8-719-900-95	DIODE V09G	
D506	8-719-900-95	DIODE V09G	
D507	8-719-970-89	DIODE DD50R	
D509	8-719-911-19	DIODE 1SS119	
D510	8-719-109-71	DIODE RD3.9ES-B1	
D511	8-719-911-19	DIODE 1SS119	
D512	8-719-911-19	DIODE 1SS119	
D513	8-719-911-19	DIODE 1SS119	
D514	8-719-911-19	DIODE 1SS119	
D515	8-719-911-19	DIODE 1SS119	
D1401	8-719-911-19	DIODE 1SS119	
D1402	8-719-911-19	DIODE 1SS119	
D1403	8-719-911-19	DIODE 1SS119	
D1404	8-719-110-88	DIODE RD39ES-B2	
D1405	8-719-110-88	DIODE RD39ES-B2	
D1406	8-719-911-19	DIODE 1SS119	
D1407	8-719-110-88	DIODE RD39ES-B2	
D1408	8-719-911-19	DIODE 1SS119	
D1409	8-719-110-88	DIODE RD39ES-B2	
D1607	8-719-911-19	DIODE 1SS119	
D1608	8-719-911-19	DIODE 1SS119	
		<IC>	
IC201	8-749-920-58	IC SI-3090CA	
IC204	8-759-171-05	IC UPC7805H	
IC205	8-759-144-82	IC UPC2405HF	
IC206	8-759-231-58	IC TA7812S	
IC207	8-749-920-58	IC SI-3090CA	
IC506	8-752-057-18	IC CXA1315P	
IC1401	8-759-246-70	IC TA8216H	
IC1601	8-752-058-71	IC CXA1656S	
		<COIL>	
L201	1-408-429-00	INDUCTOR 470UH	
L205	1-410-645-31	INDUCTOR 100UH	
L206	1-408-416-00	INDUCTOR 39UH	
L212	1-410-312-11	INDUCTOR 0.22UH	
L501 ⚠	1-460-196-11	COIL, HORIZONTAL LINEARITY	
L502	1-459-313-00	COIL WITH CORE (HWC)	
L515	1-410-645-31	INDUCTOR 100UH	
		<TRANSISTOR>	
Q201	8-729-119-78	TRANSISTOR 2SC2785-HFE	
Q202	8-729-119-78	TRANSISTOR 2SC2785-HFE	
Q203	8-729-119-76	TRANSISTOR 2SA1175-HFE	
Q501	8-729-119-80	TRANSISTOR 2SC2688-LK	
Q502	8-729-014-88	TRANSISTOR 2SC4891-CA	
Q504	8-729-119-78	TRANSISTOR 2SC2785-HFE	
Q505	8-729-201-32	TRANSISTOR 2SA1013-O	
Q506	8-729-201-32	TRANSISTOR 2SA1013-O	
Q507	8-729-304-92	TRANSISTOR 2SB649A-C	
Q508	8-729-204-16	TRANSISTOR 2SA1301-O	
Q509	8-729-119-78	TRANSISTOR 2SC2785-HFE	
Q510	8-729-119-78	TRANSISTOR 2SC2785-HFE	
Q511	8-729-119-76	TRANSISTOR 2SA1175-HFE	
Q512	8-729-119-78	TRANSISTOR 2SC2785-HFE	
Q1401	8-729-119-78	TRANSISTOR 2SC2785-HFE	
Q1402	8-729-900-63	TRANSISTOR DTA124ES	
Q1407	8-729-119-78	TRANSISTOR 2SC2785-HFE	
Q1408	8-729-119-78	TRANSISTOR 2SC2785-HFE	
Q1601	8-729-119-78	TRANSISTOR 2SC2785-HFE	
Q1602	8-729-119-76	TRANSISTOR 2SA1175-HFE	
Q1603	8-729-119-76	TRANSISTOR 2SA1175-HFE	
Q1604	8-729-119-76	TRANSISTOR 2SA1175-HFE	
Q1605	8-729-119-78	TRANSISTOR 2SC2785-HFE	
Q1606	8-729-119-78	TRANSISTOR 2SC2785-HFE	
Q1620	8-729-119-76	TRANSISTOR 2SA1175-HFE	
		<RESISTOR>	
R203	1-249-425-11	CARBON 4.7K 5% 1/4W	
R204	1-249-441-11	CARBON 100K 5% 1/4W	
R214	1-249-429-11	CARBON 10K 5% 1/4W	
R215	1-249-437-11	CARBON 47K 5% 1/4W	
R216	1-249-377-11	CARBON 0.47 5% 1/4W	F
R219	1-249-426-11	CARBON 5.6K 5% 1/4W	
R221	1-249-409-11	CARBON 220 5% 1/4W	
R222	1-249-436-11	CARBON 39K 5% 1/4W	
R223	1-249-434-11	CARBON 27K 5% 1/4W	
R224	1-249-409-11	CARBON 220 5% 1/4W	
R225	1-249-417-11	CARBON 1K 5% 1/4W	
R229	1-216-488-11	METAL OXIDE 18K 5% 3W	F
R231	1-249-409-91	CARBON 220 5% 1/4W	F
R232	1-215-906-11	METAL OXIDE 15 5% 3W	F
R233	1-249-409-11	CARBON 220 5% 1/4W	
R234	1-249-409-11	CARBON 220 5% 1/4W	
R235	1-249-409-11	CARBON 220 5% 1/4W	
R236	1-249-409-11	CARBON 220 5% 1/4W	
R237	1-249-409-11	CARBON 220 5% 1/4W	
R238	1-249-409-11	CARBON 220 5% 1/4W	
R239	1-249-409-11	CARBON 220 5% 1/4W	
R240	1-215-906-11	METAL OXIDE 15 5% 3W	F
R241	1-249-401-11	CARBON 47 5% 1/4W	
R242	1-215-906-11	METAL OXIDE 15 5% 3W	F
R243	1-217-294-00	WIREWOUND 4.7 10% 5W	F
R244	1-207-676-00	WIREWOUND 6.8 10% 5W	F
R296	1-249-417-11	CARBON 1K 5% 1/4W	
R501	1-247-895-00	CARBON 470K 5% 1/4W	
R502	1-249-377-11	CARBON 0.47 5% 1/4W	F
R503	1-249-377-11	CARBON 0.47 5% 1/4W	F
R504	1-249-417-11	CARBON 1K 5% 1/4W	

A P1

The components identified by shading and mark ⚠ are critical for safety.
Replace only with part number specified.

Les composants identifies par une trame et une marque ⚠ sont critiques pour la securite.
Ne les remplacer que par une piece portant le numero specifie.

REF.NO.	PART NO.	DESCRIPTION				REMARK
R505	1-249-423-11	CARBON	3.3K	5%	1/4W	
R506	1-215-922-11	METAL OXIDE	6.8K	5%	3W	F
R507	1-249-429-11	CARBON	10K	5%	1/4W	F
R508	1-216-373-11	METAL OXIDE	2.2	5%	2W	F
R509	1-216-478-11	METAL OXIDE	390	5%	3W	F
R511	1-249-407-11	CARBON	150	5%	1/4W	
R512	1-249-421-11	CARBON	2.2K	5%	1/4W	F
R513	1-249-417-11	CARBON	1K	5%	1/4W	
R514	1-216-441-00	METAL OXIDE	27K	5%	1W	F
R515	1-249-432-11	CARBON	18K	5%	1/4W	F
R516	1-249-417-11	CARBON	1K	5%	1/4W	
R517	1-249-427-11	CARBON	6.8K	5%	1/4W	F
R518	1-249-422-11	CARBON	2.7K	5%	1/4W	F
R519	1-249-417-11	CARBON	1K	5%	1/4W	F
R520	1-215-925-11	METAL OXIDE	22K	5%	3W	F
R521	1-215-925-11	METAL OXIDE	22K	5%	3W	F
R522	1-249-421-11	CARBON	2.2K	5%	1/4W	
R523	1-249-434-11	CARBON	27K	5%	1/4W	
R524	1-249-434-11	CARBON	27K	5%	1/4W	
R525	1-215-922-11	METAL OXIDE	6.8K	5%	3W	F
R526	1-249-417-11	CARBON	1K	5%	1/4W	
R528	1-216-447-00	METAL OXIDE	27	5%	2W	F
R529	1-216-447-00	METAL OXIDE	27	5%	2W	F
R530	1-249-431-11	CARBON	15K	5%	1/4W	
R531	1-249-431-11	CARBON	15K	5%	1/4W	
R532	1-249-385-11	CARBON	2.2	5%	1/4W	F
R533	1-249-405-11	CARBON	100	5%	1/4W	
R534	1-249-405-11	CARBON	100	5%	1/4W	
R535	1-249-405-11	CARBON	100	5%	1/4W	
R536	1-207-687-00	WIREWOUND	150	10%	5W	F
R537	1-207-687-00	WIREWOUND	150	10%	5W	F
R550	1-249-385-11	CARBON	2.2	5%	1/4W	F
R558	1-249-385-11	CARBON	2.2	5%	1/4W	F
R559	1-249-409-11	CARBON	220	5%	1/4W	
R560	1-249-409-11	CARBON	220	5%	1/4W	
R563	1-249-429-11	CARBON	10K	5%	1/4W	
R564	1-249-429-11	CARBON	10K	5%	1/4W	
R565	1-249-427-11	CARBON	6.8K	5%	1/4W	
R566	1-249-427-11	CARBON	6.8K	5%	1/4W	
R567	1-249-427-11	CARBON	6.8K	5%	1/4W	
R568	1-249-427-11	CARBON	6.8K	5%	1/4W	
R569	1-249-426-11	CARBON	5.6K	5%	1/4W	
R570	1-249-441-11	CARBON	100K	5%	1/4W	
R571	1-249-429-11	CARBON	10K	5%	1/4W	
R572	1-249-429-11	CARBON	10K	5%	1/4W	
R574	1-249-417-11	CARBON	1K	5%	1/4W	
R579	1-249-417-11	CARBON	1K	5%	1/4W	
R1401	1-215-445-00	METAL	10K	1%	1/4W	
R1402	1-215-445-00	METAL	10K	1%	1/4W	
R1403	1-215-445-00	METAL	10K	1%	1/4W	
R1404	1-215-445-00	METAL	10K	1%	1/4W	
R1405	1-249-385-11	CARBON	2.2	5%	1/4W	
R1406	1-249-385-11	CARBON	2.2	5%	1/4W	
R1409	1-249-433-11	CARBON	22K	5%	1/4W	
R1410	1-249-433-11	CARBON	22K	5%	1/4W	
R1411	1-249-437-11	CARBON	47K	5%	1/4W	
R1427	1-215-865-11	METAL OXIDE	220	5%	1W	F
R1428	1-215-865-11	METAL OXIDE	220	5%	1W	F
R1431	1-249-405-11	CARBON	100	5%	1/4W	
R1433	1-249-425-11	CARBON	4.7K	5%	1/4W	
R1434	1-249-423-11	CARBON	3.3K	5%	1/4W	
R1439	1-247-883-00	CARBON	150K	5%	1/4W	
R1440	1-249-417-11	CARBON	1K	5%	1/4W	
R1442	1-215-410-00	METAL	360	1%	1/4W	
R1443	1-215-410-00	METAL	360	1%	1/4W	
R1520	1-249-429-11	CARBON	10K	5%	1/4W	
R1601	1-249-423-11	CARBON	3.3K	5%	1/4W	
R1602	1-249-417-11	CARBON	1K	5%	1/4W	
R1603	1-249-423-11	CARBON	3.3K	5%	1/4W	
R1604	1-249-405-11	CARBON	100	5%	1/4W	
R1605	1-249-405-11	CARBON	100	5%	1/4W	
R1606	1-249-405-11	CARBON	100	5%	1/4W	
R1607	1-249-415-11	CARBON	680	5%	1/4W	
R1608	1-249-415-11	CARBON	680	5%	1/4W	
R1609	1-249-415-11	CARBON	680	5%	1/4W	
R1610	1-249-405-11	CARBON	100	5%	1/4W	
R1611	1-249-405-11	CARBON	100	5%	1/4W	
R1612	1-249-405-11	CARBON	100	5%	1/4W	
R1613	1-249-423-11	CARBON	3.3K	5%	1/4W	
R1614	1-249-411-11	CARBON	330	5%	1/4W	
R1622	1-249-423-11	CARBON	3.3K	5%	1/4W	
R1624	1-249-424-11	CARBON	3.9K	5%	1/4W	
R1627	1-249-429-11	CARBON	10K	5%	1/4W	
R1630	1-249-434-11	CARBON	27K	5%	1/4W	
R1631	1-249-433-11	CARBON	22K	5%	1/4W	
R1656	1-249-397-11	CARBON	22	5%	1/4W	
R1657	1-249-397-11	CARBON	22	5%	1/4W	
R1658	1-249-397-11	CARBON	22	5%	1/4W	

<TRANSFORMER>

T501 ⚠ 1-439-545-11 TRANSFORMER, FERRITE
T502 ⚠ 1-437-078-11 TRANSFORMER, HORIZONTAL DRIVE

<TUNER>

TU101 ⚠ 1-693-102-21 TUNER (BTF-XA401)

****

*A-1195-066-A P1 BOARD, COMPLETE
****

<CAPACITOR>

C3001	1-124-589-11	ELECT	47MF	20%	16V
C3002	1-164-346-11	CERAMIC CHIP	1MF		16V
C3003	1-164-232-11	CERAMIC CHIP	0.01MF	10%	50V
C3004	1-163-119-00	CERAMIC CHIP	120PF	5%	50V
C3005	1-163-235-11	CERAMIC CHIP	22PF	5%	50V
C3006	1-164-232-11	CERAMIC CHIP	0.01MF	10%	50V
C3007	1-164-005-11	CERAMIC CHIP	0.47MF		25V
C3008	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C3009	1-124-925-11	ELECT	2.2MF	20%	50V
C3010	1-163-145-00	CERAMIC CHIP	0.0015MF	5%	50V
C3011	1-163-018-00	CERAMIC CHIP	0.0056MF	10%	50V
C3012	1-164-336-11	CERAMIC CHIP	0.33MF		25V
C3013	1-164-222-11	CERAMIC CHIP	0.22MF		25V
C3014	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C3015	1-164-232-11	CERAMIC CHIP	0.01MF	10%	50V
C3016	1-163-107-00	CERAMIC CHIP	39PF	5%	50V
C3017	1-130-495-00	MYLAR	0.1MF	5%	50V
C3018	1-163-115-00	CERAMIC CHIP	82PF	5%	50V
C3019	1-164-232-11	CERAMIC CHIP	0.01MF	10%	50V
C3020	1-163-105-00	CERAMIC CHIP	33PF	5%	50V
C3021	1-163-115-00	CERAMIC CHIP	82PF	5%	50V
C3022	1-126-301-11	ELECT	1MF	20%	50V
C3023	1-124-589-11	ELECT	47MF	20%	16V

P1

REF.NO.	PART NO.	DESCRIPTION			REMARK
C3024	1-163-018-00	CERAMIC CHIP	0.0056MF	10% 50V	
C3025	1-164-343-11	CERAMIC CHIP	0.056MF	10% 25V	
C3026	1-126-163-11	ELECT	4.7MF	20% 50V	
C3027	1-163-275-11	CERAMIC CHIP	0.001MF	5% 50V	
C3028	1-124-589-11	ELECT	47MF	20% 16V	
C3029	1-163-133-00	CERAMIC CHIP	470PF	5% 50V	
C3030	1-163-037-11	CERAMIC CHIP	0.022MF	10% 25V	
C3031	1-126-177-11	ELECT	100MF	20% 6.3V	
C3032	1-164-004-11	CERAMIC CHIP	0.1MF	10% 25V	
C3033	1-164-004-11	CERAMIC CHIP	0.1MF	10% 25V	
C3034	1-164-336-11	CERAMIC CHIP	0.33MF	25V	
C3035	1-163-117-00	CERAMIC CHIP	100PF	5% 50V	
C3036	1-164-004-11	CERAMIC CHIP	0.1MF	10% 25V	
C3037	1-124-589-11	ELECT	47MF	20% 16V	
C3038	1-136-287-11	FILM	0.0047MF	5% 50V	
C3039	1-164-004-11	CERAMIC CHIP	0.1MF	10% 25V	
C3040	1-164-232-11	CERAMIC CHIP	0.01MF	10% 50V	
C3042	1-164-346-11	CERAMIC CHIP	1MF	16V	
C3043	1-124-465-00	ELECT	0.47MF	20% 50V	
C3044	1-126-301-11	ELECT	1MF	20% 50V	
C3045	1-124-589-11	ELECT	47MF	20% 16V	
C3046	1-126-301-11	ELECT	1MF	20% 50V	
C3047	1-126-301-11	ELECT	1MF	20% 50V	
C3048	1-164-161-11	CERAMIC CHIP	0.0022MF	10% 50V	
C3051	1-164-161-11	CERAMIC CHIP	0.0022MF	10% 50V	
C3052	1-126-177-11	ELECT	100MF	20% 6.3V	
C3053	1-164-004-11	CERAMIC CHIP	0.1MF	10% 25V	
C3054	1-126-177-11	ELECT	100MF	20% 6.3V	
C3055	1-163-133-00	CERAMIC CHIP	470PF	5% 50V	
C3057	1-124-589-11	ELECT	47MF	20% 16V	
C3058	1-163-009-11	CERAMIC CHIP	0.001MF	10% 50V	
C3059	1-164-222-11	CERAMIC CHIP	0.22MF	25V	
C3060	1-124-589-11	ELECT	47MF	20% 16V	
C3064	1-163-123-00	CERAMIC CHIP	180PF	5% 50V	
C3065	1-124-589-11	ELECT	47MF	20% 16V	
C3066	1-164-004-11	CERAMIC CHIP	0.1MF	10% 25V	
C3067	1-124-589-11	ELECT	47MF	20% 16V	
C3069	1-164-232-11	CERAMIC CHIP	0.01MF	10% 50V	
C3070	1-126-177-11	ELECT	100MF	20% 6.3V	
C3071	1-124-589-11	ELECT	47MF	20% 16V	
C3072	1-124-589-11	ELECT	47MF	20% 16V	
C3073	1-124-589-11	ELECT	47MF	20% 16V	
C3074	1-163-121-00	CERAMIC CHIP	150PF	5% 50V	
C3076	1-164-004-11	CERAMIC CHIP	0.1MF	10% 25V	
C3077	1-164-005-11	CERAMIC CHIP	0.47MF	25V	
C3081	1-163-095-00	CERAMIC CHIP	12PF	5% 50V	
C3100	1-164-004-11	CERAMIC CHIP	0.1MF	10% 25V	
C3101	1-162-926-11	CERAMIC CHIP	82PF	5% 50V	

<CONNECTOR>

CN151	1-573-965-21	PIN, CONNECTOR (PC BOARD) 50P	

<DIODE>

D3003	8-719-158-15	DIODE RD5.6S-B	
D3004	8-719-404-46	DIODE MA110	
D3009	8-719-404-46	DIODE MA110	

<IC>

IC3001	8-759-046-25	IC TDA3769	
IC3002	8-759-009-46	IC MC14528BF	
IC3003	8-759-513-48	IC TDA2595/V9	
IC3004	8-759-088-90	IC SDA9187X	
IC3005	8-759-088-91	IC SDA9188X	
IC3006	8-759-112-06	IC UPC78N05H	
IC3007	8-759-046-27	IC SDA9086-3	
IC3008	8-759-112-06	IC UPC78N05H	

<COIL>

L3001	1-410-476-11	INDUCTOR	33UH
L3002	1-408-424-00	INDUCTOR	180UH
L3003	1-408-424-00	INDUCTOR	180UH
L3004	1-410-470-11	INDUCTOR	10UH
L3005	1-410-472-41	INDUCTOR	15UH
L3006	1-412-788-41	INDUCTOR	10UH
L3007	1-410-472-41	INDUCTOR	15UH
L3008	1-410-472-41	INDUCTOR	15UH
L3009	1-410-472-41	INDUCTOR	15UH
L3010	1-410-466-41	INDUCTOR	4.7UH
L3011	1-410-470-11	INDUCTOR	10UH
L3012	1-410-676-31	INDUCTOR	150UH
L3013	1-412-911-11	INDUCTOR, FERRITE BEAD	
L3014	1-412-911-11	INDUCTOR, FERRITE BEAD	
L3015	1-412-911-11	INDUCTOR, FERRITE BEAD	
L3100	1-412-799-41	INDUCTOR	82UH

<TRANSISTOR>

Q3003	8-729-216-22	TRANSISTOR	2SA1162-G
Q3004	8-729-422-27	TRANSISTOR	2SD601A-Q
Q3006	8-729-422-27	TRANSISTOR	2SD601A-Q
Q3007	8-729-216-22	TRANSISTOR	2SA1162-G
Q3008	8-729-422-27	TRANSISTOR	2SD601A-Q
Q3009	8-729-216-22	TRANSISTOR	2SA1162-G
Q3010	8-729-422-27	TRANSISTOR	2SD601A-Q
Q3011	8-729-216-22	TRANSISTOR	2SA1162-G
Q3012	8-729-422-27	TRANSISTOR	2SD601A-Q
Q3013	8-729-422-27	TRANSISTOR	2SD601A-Q
Q3014	8-729-422-27	TRANSISTOR	2SD601A-Q
Q3100	8-729-216-22	TRANSISTOR	2SA1162-G

<RESISTOR>

JR3	1-216-295-00	METAL GLAZE	0	5%	1/10W
R3001	1-216-085-00	METAL GLAZE	33K	5%	1/10W
R3002	1-216-089-00	METAL GLAZE	47K	5%	1/10W
R3003	1-216-067-00	METAL GLAZE	5.6K	5%	1/10W
R3004	1-216-091-00	METAL GLAZE	56K	5%	1/10W
R3005	1-216-689-11	METAL GLAZE	39K	5%	1/10W
R3006	1-216-097-00	METAL GLAZE	100K	5%	1/10W
R3007	1-216-079-00	METAL GLAZE	18K	5%	1/10W
R3008	1-216-073-00	METAL GLAZE	10K	5%	1/10W
R3009	1-216-041-00	METAL GLAZE	470	5%	1/10W
R3010	1-216-049-00	METAL GLAZE	1K	5%	1/10W
R3011	1-216-073-00	METAL GLAZE	10K	5%	1/10W
R3012	1-216-053-00	METAL GLAZE	1.5K	5%	1/10W
R3013	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W
R3014	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W
R3015	1-216-049-00	METAL GLAZE	1K	5%	1/10W
R3017	1-216-083-00	METAL GLAZE	27K	5%	1/10W
R3018	1-216-097-00	METAL GLAZE	100K	5%	1/10W
R3019	1-216-077-00	METAL GLAZE	15K	5%	1/10W
R3020	1-216-099-00	METAL GLAZE	120K	5%	1/10W
R3021	1-216-075-00	METAL GLAZE	12K	5%	1/10W

REF.NO.	PART NO.	DESCRIPTION				REMARK
R3023	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R3025	1-216-015-00	METAL GLAZE	39	5%	1/10W	
R3026	1-216-041-00	METAL GLAZE	470	5%	1/10W	
R3027	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R3028	1-216-027-00	METAL GLAZE	120	5%	1/10W	
R3030	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R3031	1-216-047-00	METAL GLAZE	820	5%	1/10W	
R3032	1-216-041-00	METAL GLAZE	470	5%	1/10W	
R3033	1-216-295-00	METAL GLAZE	0	5%	1/10W	
R3034	1-216-041-00	METAL GLAZE	470	5%	1/10W	
R3035	1-216-045-00	METAL GLAZE	680	5%	1/10W	
R3036	1-216-045-00	METAL GLAZE	680	5%	1/10W	
R3037	1-216-083-00	METAL GLAZE	27K	5%	1/10W	
R3038	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R3039	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R3040	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R3041	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R3042	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	
R3043	1-216-099-00	METAL GLAZE	120K	5%	1/10W	
R3044	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R3045	1-216-295-00	METAL GLAZE	0	5%	1/10W	
R3050	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R3052	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R3053	1-216-037-00	METAL GLAZE	330	5%	1/10W	
R3055	1-216-063-00	METAL GLAZE	3.9K	5%	1/10W	
R3056	1-216-059-00	METAL GLAZE	2.7K	5%	1/10W	
R3057	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R3058	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R3059	1-216-079-00	METAL GLAZE	18K	5%	1/10W	
R3060	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R3061	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R3062	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R3063	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R3064	1-216-295-00	METAL GLAZE	0	5%	1/10W	
R3065	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R3066	1-216-053-00	METAL GLAZE	1.5K	5%	1/10W	
R3067	1-216-295-00	METAL GLAZE	0	5%	1/10W	
R3069	1-216-689-11	METAL GLAZE	39K	5%	1/10W	
R3071	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R3073	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R3074	1-216-295-00	METAL GLAZE	0	5%	1/10W	
R3075	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R3076	1-216-043-00	METAL GLAZE	560	5%	1/10W	
R3077	1-216-037-00	METAL GLAZE	330	5%	1/10W	
R3078	1-216-044-00	METAL GLAZE	620	5%	1/10W	
R3079	1-216-040-00	METAL GLAZE	430	5%	1/10W	
R3082	1-216-029-00	METAL GLAZE	150	5%	1/10W	
R3084	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R3085	1-216-119-00	METAL GLAZE	820K	5%	1/10W	
R3086	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R3087	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R3088	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R3089	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R3090	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R3091	1-216-053-00	METAL GLAZE	1.5K	5%	1/10W	
R3092	1-216-053-00	METAL GLAZE	1.5K	5%	1/10W	
R3098	1-216-296-00	METAL GLAZE	0	5%	1/8W	
R3099	1-216-296-00	METAL GLAZE	0	5%	1/8W	
R3100	1-216-296-00	METAL GLAZE	0	5%	1/8W	
R3101	1-216-051-00	METAL GLAZE	1.2K	5%	1/10W	
R3102	1-216-047-00	METAL GLAZE	820	5%	1/10W	
R3103	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	
R3104	1-216-049-00	METAL GLAZE	1K	5%	1/10W	

REF.NO.	PART NO.	DESCRIPTION				REMARK
		<VARIABLE RESISTOR>				
RV3001	1-241-630-11	RES, ADJ, CARBON 10K				
RV3002	1-238-019-11	RES, ADJ, CARBON 47K				
RV3003	1-241-630-11	RES, ADJ, CARBON 10K				
		<CRYSTAL>				
X3001	1-567-505-11	OSCILLATOR, CRYSTAL				
		**********				
	*A-1306-436-A	M BOARD, COMPLETE				
		**********				
		<CAPACITOR>				
C001	1-124-261-00	ELECT	10MF	20%	50V	
C002	1-163-125-00	CERAMIC CHIP	220PF	5%	50V	
C003	1-136-161-00	FILM	0.047MF	5%	50V	
C004	1-126-301-11	ELECT	1MF	20%	50V	
C005	1-163-125-00	CERAMIC CHIP	220PF	5%	50V	
C014	1-124-910-11	ELECT	47MF	20%	50V	
C017	1-124-589-11	ELECT	47MF	20%	16V	
C018	1-163-141-00	CERAMIC CHIP	0.001MF	5%	50V	
C019	1-164-695-11	CERAMIC CHIP	0.0022MF	5%	50V	
C020	1-163-241-11	CERAMIC CHIP	39PF	5%	50V	
C021	1-163-239-11	CERAMIC CHIP	33PF	5%	50V	
C029	1-163-115-00	CERAMIC CHIP	82PF	5%	50V	
C030	1-163-115-00	CERAMIC CHIP	82PF	5%	50V	
C034	1-163-125-00	CERAMIC CHIP	220PF	5%	50V	
C035	1-163-125-00	CERAMIC CHIP	220PF	5%	50V	
C036	1-163-125-00	CERAMIC CHIP	220PF	5%	50V	
C041	1-163-117-00	CERAMIC CHIP	100PF	5%	50V	
C042	1-163-117-00	CERAMIC CHIP	100PF	5%	50V	
C045	1-163-125-00	CERAMIC CHIP	220PF	5%	50V	
C047	1-124-261-00	ELECT	10MF	20%	50V	
C048	1-124-261-00	ELECT	10MF	20%	50V	
C049	1-124-261-00	ELECT	10MF	20%	50V	
C055	1-163-809-11	CERAMIC CHIP	0.047MF	10%	25V	
C064	1-163-121-00	CERAMIC CHIP	150PF	5%	50V	
C065	1-124-257-00	ELECT	2.2MF	20%	50V	
		<DIODE>				
D001	8-719-404-46	DIODE MA110				
D002	8-719-404-46	DIODE MA110				
D009	8-719-404-46	DIODE MA110				
D010	8-713-300-57	DIODE 1T33				
D011	8-719-404-46	DIODE MA110				
D012	8-719-404-46	DIODE MA110				
D014	8-719-404-46	DIODE MA110				
D015	8-719-404-46	DIODE MA110				
		<IC>				
IC001	8-759-169-06	IC TMC73C247-10				
IC002	8-759-403-44	IC MN1280-S				
		<COIL>				
L001	1-408-409-00	INDUCTOR	10UH			
L002	1-410-476-11	INDUCTOR	33UH			

M E2

REF.NO.	PART NO.	DESCRIPTION	REMARK
		<CONNECTOR>	
M001	1-573-965-21	PIN, CONNECTOR (PC BOARD) 50P	
M39	*1-564-521-11	PLUG, CONNECTOR 6P	
M45	*1-564-523-31	PLUG, CONNECTOR 8P	
		<TRANSISTOR>	
Q001	8-729-216-22	TRANSISTOR 2SA1162-G	
Q009	8-729-422-27	TRANSISTOR 2SD601A-Q	
Q010	8-729-422-27	TRANSISTOR 2SD601A-Q	
Q011	8-729-422-27	TRANSISTOR 2SD601A-Q	
Q012	8-729-422-27	TRANSISTOR 2SD601A-Q	
Q013	8-729-216-22	TRANSISTOR 2SA1162-G	
Q014	8-729-422-27	TRANSISTOR 2SD601A-Q	
		<RESISTOR>	
R001	1-216-045-00	METAL GLAZE 680 5% 1/10W	
R002	1-216-097-00	METAL GLAZE 100K 5% 1/10W	
R003	1-216-121-00	METAL GLAZE 1M 5% 1/10W	
R004	1-216-073-00	METAL GLAZE 10K 5% 1/10W	
R005	1-216-073-00	METAL GLAZE 10K 5% 1/10W	
R006	1-216-065-00	METAL GLAZE 4.7K 5% 1/10W	
R007	1-216-027-00	METAL GLAZE 120 5% 1/10W	
R008	1-216-041-00	METAL GLAZE 470 5% 1/10W	
R009	1-216-027-00	METAL GLAZE 120 5% 1/10W	
R011	1-216-033-00	METAL GLAZE 220 5% 1/10W	
R012	1-216-033-00	METAL GLAZE 220 5% 1/10W	
R013	1-216-067-00	METAL GLAZE 5.6K 5% 1/10W	
R014	1-216-057-00	METAL GLAZE 2.2K 5% 1/10W	
R015	1-216-089-00	METAL GLAZE 47K 5% 1/10W	
R016	1-216-067-00	METAL GLAZE 5.6K 5% 1/10W	
R017	1-216-067-00	METAL GLAZE 5.6K 5% 1/10W	
R018	1-216-065-00	METAL GLAZE 4.7K 5% 1/10W	
R019	1-216-073-00	METAL GLAZE 10K 5% 1/10W	
R033	1-216-073-00	METAL GLAZE 10K 5% 1/10W	
R034	1-216-033-00	METAL GLAZE 220 5% 1/10W	
R035	1-216-033-00	METAL GLAZE 220 5% 1/10W	
R036	1-216-033-00	METAL GLAZE 220 5% 1/10W	
R037	1-216-073-00	METAL GLAZE 10K 5% 1/10W	
R038	1-216-033-00	METAL GLAZE 220 5% 1/10W	
R039	1-216-073-00	METAL GLAZE 10K 5% 1/10W	
R040	1-216-089-00	METAL GLAZE 47K 5% 1/10W	
R041	1-216-057-00	METAL GLAZE 2.2K 5% 1/10W	
R042	1-216-065-00	METAL GLAZE 4.7K 5% 1/10W	
R043	1-216-033-00	METAL GLAZE 220 5% 1/10W	
R044	1-216-033-00	METAL GLAZE 220 5% 1/10W	
R045	1-216-025-00	METAL GLAZE 100 5% 1/10W	
R046	1-216-065-00	METAL GLAZE 4.7K 5% 1/10W	
R047	1-216-065-00	METAL GLAZE 4.7K 5% 1/10W	
R048	1-216-033-00	METAL GLAZE 220 5% 1/10W	
R049	1-216-065-00	METAL GLAZE 4.7K 5% 1/10W	
R050	1-216-295-00	METAL GLAZE 0 5% 1/10W	
R051	1-216-033-00	METAL GLAZE 220 5% 1/10W	
R052	1-216-065-00	METAL GLAZE 4.7K 5% 1/10W	
R053	1-216-065-00	METAL GLAZE 4.7K 5% 1/10W	
R054	1-216-073-00	METAL GLAZE 10K 5% 1/10W	
R055	1-216-073-00	METAL GLAZE 10K 5% 1/10W	
R056	1-216-065-00	METAL GLAZE 4.7K 5% 1/10W	
R057	1-216-065-00	METAL GLAZE 4.7K 5% 1/10W	
R058	1-216-065-00	METAL GLAZE 4.7K 5% 1/10W	
R059	1-216-073-00	METAL GLAZE 10K 5% 1/10W	
R060	1-216-065-00	METAL GLAZE 4.7K 5% 1/10W	
R063	1-216-033-00	METAL GLAZE 220 5% 1/10W	
R064	1-216-053-00	METAL GLAZE 1.5K 5% 1/10W	
R065	1-216-033-00	METAL GLAZE 220 5% 1/10W	
R066	1-216-033-00	METAL GLAZE 220 5% 1/10W	
R067	1-216-033-00	METAL GLAZE 220 5% 1/10W	
R068	1-216-033-00	METAL GLAZE 220 5% 1/10W	
R069	1-216-049-00	METAL GLAZE 1K 5% 1/10W	
R070	1-216-033-00	METAL GLAZE 220 5% 1/10W	
R071	1-216-033-00	METAL GLAZE 220 5% 1/10W	
R072	1-216-033-00	METAL GLAZE 220 5% 1/10W	
R073	1-216-057-00	METAL GLAZE 2.2K 5% 1/10W	
R074	1-216-033-00	METAL GLAZE 220 5% 1/10W	
R075	1-216-033-00	METAL GLAZE 220 5% 1/10W	
R076	1-216-089-00	METAL GLAZE 47K 5% 1/10W	
R077	1-216-057-00	METAL GLAZE 2.2K 5% 1/10W	
R078	1-216-033-00	METAL GLAZE 220 5% 1/10W	
R079	1-216-025-00	METAL GLAZE 100 5% 1/10W	
R080	1-216-061-00	METAL GLAZE 3.3K 5% 1/10W	
R081	1-216-033-00	METAL GLAZE 220 5% 1/10W	
R082	1-216-033-00	METAL GLAZE 220 5% 1/10W	
R083	1-216-033-00	METAL GLAZE 220 5% 1/10W	
R084	1-216-097-00	METAL GLAZE 100K 5% 1/10W	
R085	1-216-033-00	METAL GLAZE 220 5% 1/10W	
R086	1-216-033-00	METAL GLAZE 220 5% 1/10W	
R087	1-216-033-00	METAL GLAZE 220 5% 1/10W	
R088	1-216-033-00	METAL GLAZE 220 5% 1/10W	
R089	1-216-089-00	METAL GLAZE 47K 5% 1/10W	
R090	1-216-033-00	METAL GLAZE 220 5% 1/10W	
R091	1-216-065-00	METAL GLAZE 4.7K 5% 1/10W	
R092	1-216-077-00	METAL GLAZE 15K 5% 1/10W	
R093	1-216-065-00	METAL GLAZE 4.7K 5% 1/10W	
R094	1-216-033-00	METAL GLAZE 220 5% 1/10W	
R095	1-216-073-00	METAL GLAZE 10K 5% 1/10W	
R096	1-216-065-00	METAL GLAZE 4.7K 5% 1/10W	
R097	1-216-065-00	METAL GLAZE 4.7K 5% 1/10W	
R098	1-216-065-00	METAL GLAZE 4.7K 5% 1/10W	
R099	1-216-089-00	METAL GLAZE 47K 5% 1/10W	
R100	1-216-025-00	METAL GLAZE 100 5% 1/10W	
R101	1-216-025-00	METAL GLAZE 100 5% 1/10W	
R102	1-216-089-00	METAL GLAZE 47K 5% 1/10W	
R103	1-216-033-00	METAL GLAZE 220 5% 1/10W	
R104	1-216-033-00	METAL GLAZE 220 5% 1/10W	
		<CRYSTAL>	
X001	1-579-743-11	VIBRATOR, CRYSTAL	
		**********	
	*A-1346-137-A	E2 BOARD, COMPLETE	
		**********	
		<CAPACITOR>	
C2302	1-163-009-11	CERAMIC CHIP 0.001MF 10% 50V	
C2303	1-164-232-11	CERAMIC CHIP 0.01MF 10% 50V	
C2310	1-163-105-00	CERAMIC CHIP 33PF 5% 50V	
C2314	1-164-232-11	CERAMIC CHIP 0.01MF 10% 50V	
C2315	1-126-157-11	ELECT 10MF 20% 16V	
C2316	1-126-157-11	ELECT 10MF 20% 16V	
C2317	1-126-157-11	ELECT 10MF 20% 16V	
C2318	1-164-232-11	CERAMIC CHIP 0.01MF 10% 50V	
C2320	1-124-589-11	ELECT 47MF 20% 16V	
C2321	1-163-017-00	CERAMIC CHIP 0.0047MF 10% 50V	

REF.NO.	PART NO.	DESCRIPTION				REMARK
C2322	1-124-234-00	ELECT	22MF	20%	16V	
C2323	1-124-234-00	ELECT	22MF	20%	16V	
C2324	1-124-234-00	ELECT	22MF	20%	16V	
C2325	1-164-232-11	CERAMIC CHIP	0.01MF	10%	50V	
C2326	1-124-589-11	ELECT	47MF	20%	16V	
C2327	1-164-505-11	CERAMIC CHIP	2.2MF		16V	
C2328	1-164-232-11	CERAMIC CHIP	0.01MF	10%	50V	
C2329	1-164-232-11	CERAMIC CHIP	0.01MF	10%	50V	
C2331	1-164-232-11	CERAMIC CHIP	0.01MF	10%	50V	
C2332	1-124-234-00	ELECT	22MF	20%	16V	
C2333	1-124-234-00	ELECT	22MF	20%	16V	
C2334	1-164-232-11	CERAMIC CHIP	0.01MF	10%	50V	
C2335	1-164-232-11	CERAMIC CHIP	0.01MF	10%	50V	
C2336	1-126-163-11	ELECT	4.7MF	20%	16V	
C2337	1-164-232-11	CERAMIC CHIP	0.01MF	10%	50V	
C2338	1-163-038-00	CERAMIC CHIP	0.1MF		25V	
C2340	1-216-133-00	METAL GLAZE	3.3M 5%		1/10W	
C2341	1-135-217-21	TANTAL. CHIP	15MF	20%	6.3V	
C2345	1-164-505-11	CERAMIC CHIP	2.2MF		16V	
C2346	1-164-232-11	CERAMIC CHIP	0.01MF	10%	50V	
C2347	1-163-367-11	CERAMIC CHIP	39PF	5%	50V	
C2349	1-164-505-11	CERAMIC CHIP	2.2MF		16V	
C2350	1-164-232-11	CERAMIC CHIP	0.01MF	10%	50V	
C2351	1-164-505-11	CERAMIC CHIP	2.2MF		16V	
C2352	1-164-505-11	CERAMIC CHIP	2.2MF		16V	
C2353	1-164-232-11	CERAMIC CHIP	0.01MF	10%	50V	
C2354	1-164-232-11	CERAMIC CHIP	0.01MF	10%	50V	
C2357	1-126-301-11	ELECT	1MF	20%	50V	
C2360	1-163-109-00	CERAMIC CHIP	47PF	5%	50V	

<DIODE>

D2306	8-719-404-46	DIODE MA110	
D2307	8-719-946-98	DIODE FMN1	
D2308	8-719-946-98	DIODE FMN1	
D2309	8-719-404-46	DIODE MA110	
D2312	8-719-404-46	DIODE MA110	
D2313	8-719-404-46	DIODE MA110	
D2314	8-713-300-57	DIODE 1T33	
D2317	8-719-404-46	DIODE MA110	

<CONNECTOR>

E2-002	1-573-965-21	PIN, CONNECTOR (PC BOARD) 50P
E2-25	*1-564-521-31	PLUG, CONNECTOR 6P
E2-26	*1-564-522-11	PLUG, CONNECTOR 7P
E2-46	*1-564-518-11	PLUG, CONNECTOR 3P

<IC>

IC2301	8-759-066-52	IC PCA8510T/012-T
IC2303	8-759-925-75	IC SN74HC05ANS
IC2304	8-752-037-15	IC CXA1387S
IC2306	8-759-011-65	IC MC74HC4053F
IC2307	8-752-058-68	IC CXA1315M

<COIL>

L2304	1-408-414-00	INDUCTOR	27UH

<TRANSISTOR>

Q2301	8-729-903-10	TRANSISTOR FMW1
Q2303	8-729-403-27	TRANSISTOR XN4401
Q2304	8-729-925-79	TRANSISTOR IMX3
Q2305	8-729-903-10	TRANSISTOR FMW1
Q2306	8-729-403-27	TRANSISTOR XN4401
Q2307	8-729-403-27	TRANSISTOR XN4401
Q2308	8-729-403-27	TRANSISTOR XN4401
Q2309	8-729-903-10	TRANSISTOR FMW1
Q2310	8-729-403-27	TRANSISTOR XN4401
Q2311	8-729-903-10	TRANSISTOR FMW1
Q2312	8-729-403-27	TRANSISTOR XN4401
Q2313	8-729-903-10	TRANSISTOR FMW1
Q2314	8-729-403-27	TRANSISTOR XN4401
Q2315	8-729-903-10	TRANSISTOR FMW1
Q2317	8-729-216-22	TRANSISTOR 2SA1162-G
Q2318	8-729-216-22	TRANSISTOR 2SA1162-G
Q2319	8-729-216-22	TRANSISTOR 2SA1162-G
Q2320	8-729-422-27	TRANSISTOR 2SD601A-Q
Q2321	8-729-422-27	TRANSISTOR 2SD601A-Q
Q2322	8-729-422-27	TRANSISTOR 2SD601A-Q
Q2324	8-729-216-22	TRANSISTOR 2SA1162-G
Q2326	8-729-422-27	TRANSISTOR 2SD601A-Q
Q2327	8-729-422-27	TRANSISTOR 2SD601A-Q
Q2328	8-729-925-79	TRANSISTOR IMX3
Q2329	8-729-925-79	TRANSISTOR IMX3
Q2330	8-729-903-10	TRANSISTOR FMW1
Q2336	8-729-925-79	TRANSISTOR IMX3
Q2337	8-729-925-79	TRANSISTOR IMX3
Q2339	8-729-422-27	TRANSISTOR 2SD601A-Q
Q2340	8-729-422-27	TRANSISTOR 2SD601A-Q
Q2341	8-729-422-27	TRANSISTOR 2SD601A-Q

<RESISTOR>

R2302	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R2303	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R2304	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R2305	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R2306	1-216-045-00	METAL GLAZE	680	5%	1/10W	
R2307	1-216-045-00	METAL GLAZE	680	5%	1/10W	
R2308	1-216-045-00	METAL GLAZE	680	5%	1/10W	
R2309	1-216-041-00	METAL GLAZE	470	5%	1/10W	
R2310	1-216-055-00	METAL GLAZE	1.8K	5%	1/10W	
R2311	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R2312	1-216-043-00	METAL GLAZE	560	5%	1/10W	
R2313	1-216-055-00	METAL GLAZE	1.8K	5%	1/10W	
R2314	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R2315	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R2317	1-216-041-00	METAL GLAZE	470	5%	1/10W	
R2318	1-216-055-00	METAL GLAZE	1.8K	5%	1/10W	
R2319	1-216-079-00	METAL GLAZE	18K	5%	1/10W	
R2320	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R2321	1-216-063-00	METAL GLAZE	3.9K	5%	1/10W	
R2322	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R2323	1-216-067-00	METAL GLAZE	5.6K	5%	1/10W	
R2324	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R2325	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R2326	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R2327	1-216-063-00	METAL GLAZE	3.9K	5%	1/10W	
R2328	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R2329	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R2330	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R2331	1-216-063-00	METAL GLAZE	3.9K	5%	1/10W	
R2332	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R2333	1-216-067-00	METAL GLAZE	5.6K	5%	1/10W	
R2334	1-216-295-00	METAL GLAZE	0	5%	1/10W	

E2

REF.NO.	PART NO.	DESCRIPTION				REMARK
R2335	1-216-295-00	METAL GLAZE	0	5%	1/10W	
R2336	1-216-295-00	METAL GLAZE	0	5%	1/10W	
R2337	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R2338	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R2340	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R2341	1-216-041-00	METAL GLAZE	470	5%	1/10W	
R2342	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R2343	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R2344	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R2345	1-216-077-00	METAL GLAZE	15K	5%	1/10W	
R2346	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R2347	1-216-083-00	METAL GLAZE	27K	5%	1/10W	
R2348	1-216-655-11	METAL CHIP	1.5K	0.50%	1/10W	
R2349	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R2350	1-216-097-00	METAL GLAZE	100K	5%	1/10W	
R2351	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R2352	1-216-097-00	METAL GLAZE	100K	5%	1/10W	
R2353	1-216-097-00	METAL GLAZE	100K	5%	1/10W	
R2354	1-216-210-00	METAL GLAZE	3.3K	5%	1/8W	
R2355	1-216-178-00	METAL GLAZE	150	5%	1/8W	
R2356	1-216-677-11	METAL CHIP	12K	0.50%	1/10W	
R2357	1-216-670-11	METAL CHIP	6.2K	0.50%	1/10W	
R2359	1-216-053-00	METAL GLAZE	1.5K	5%	1/10W	
R2360	1-216-053-00	METAL GLAZE	1.5K	5%	1/10W	
R2361	1-216-053-00	METAL GLAZE	1.5K	5%	1/10W	
R2362	1-216-053-00	METAL GLAZE	1.5K	5%	1/10W	
R2363	1-216-041-00	METAL GLAZE	470	5%	1/10W	
R2364	1-216-053-00	METAL GLAZE	1.5K	5%	1/10W	
R2365	1-216-053-00	METAL GLAZE	1.5K	5%	1/10W	
R2366	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R2367	1-216-043-00	METAL GLAZE	560	5%	1/10W	
R2368	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R2371	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R2374	1-216-067-00	METAL GLAZE	5.6K	5%	1/10W	
R2375	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R2376	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R2377	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R2378	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R2379	1-216-043-00	METAL GLAZE	560	5%	1/10W	
R2380	1-216-043-00	METAL GLAZE	560	5%	1/10W	
R2381	1-216-043-00	METAL GLAZE	560	5%	1/10W	
R2382	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R2384	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R2385	1-216-075-00	METAL GLAZE	12K	5%	1/10W	
R2386	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R2387	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R2388	1-216-017-00	METAL GLAZE	47	5%	1/10W	
R2389	1-216-206-00	METAL GLAZE	2.2K	5%	1/8W	
R2390	1-216-043-00	METAL GLAZE	560	5%	1/10W	
R2392	1-216-206-00	METAL GLAZE	2.2K	5%	1/8W	
R2393	1-216-017-00	METAL GLAZE	47	5%	1/10W	
R2394	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R2395	1-216-001-00	METAL GLAZE	10	5%	1/10W	
R2396	1-216-206-00	METAL GLAZE	2.2K	5%	1/8W	
R2397	1-216-043-00	METAL GLAZE	560	5%	1/10W	
R2399	1-216-001-00	METAL GLAZE	10	5%	1/10W	
R3301	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R3302	1-216-001-00	METAL GLAZE	10	5%	1/10W	
R3303	1-216-069-00	METAL GLAZE	6.8K	5%	1/10W	
R3304	1-216-091-00	METAL GLAZE	56K	5%	1/10W	
R3306	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R3307	1-216-085-00	METAL GLAZE	33K	5%	1/10W	
R3308	1-216-043-00	METAL GLAZE	560	5%	1/10W	
R3309	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R3310	1-216-001-00	METAL GLAZE	10	5%	1/10W	
R3311	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R3312	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R3313	1-216-083-00	METAL GLAZE	27K	5%	1/10W	
R3314	1-216-689-11	METAL GLAZE	39K	5%	1/10W	
R3315	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R3316	1-216-071-00	METAL GLAZE	8.2K	5%	1/10W	
R3318	1-216-095-00	METAL GLAZE	82K	5%	1/10W	
R3319	1-216-095-00	METAL GLAZE	82K	5%	1/10W	
R3320	1-216-017-00	METAL GLAZE	47	5%	1/10W	
R3321	1-216-069-00	METAL GLAZE	6.8K	5%	1/10W	
R3323	1-216-101-00	METAL GLAZE	150K	5%	1/10W	
R3324	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R3325	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R3328	1-216-001-00	METAL GLAZE	10	5%	1/10W	
R3330	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R3331	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R3332	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R3333	1-216-657-11	METAL CHIP	1.8K	0.50%	1/10W	
R3334	1-216-661-11	METAL CHIP	2.7K	0.50%	1/10W	
R3335	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R3336	1-216-683-11	METAL CHIP	22K	0.50%	1/10W	
R3337	1-216-685-11	METAL CHIP	27K	0.50%	1/10W	
R3339	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R3340	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R3341	1-216-677-11	METAL CHIP	12K	0.50%	1/10W	
R3342	1-216-670-11	METAL CHIP	6.2K	0.50%	1/10W	
R3343	1-216-097-00	METAL GLAZE	100K	5%	1/10W	
R3344	1-216-097-00	METAL GLAZE	100K	5%	1/10W	
R3347	1-216-687-11	METAL CHIP	33K	0.50%	1/10W	
R3348	1-216-681-11	METAL CHIP	18K	0.50%	1/10W	
R3349	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R3350	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R3351	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R3352	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R3353	1-216-059-00	METAL GLAZE	2.7K	5%	1/10W	
R3354	1-216-059-00	METAL GLAZE	2.7K	5%	1/10W	
R3356	1-216-655-11	METAL CHIP	1.5K	0.50%	1/10W	
R3357	1-216-654-11	METAL CHIP	1.3K	0.50%	1/10W	
R3358	1-216-659-11	METAL CHIP	2.2K	0.50%	1/10W	
R3359	1-216-653-11	METAL CHIP	1.2K	0.50%	1/10W	
R3360	1-216-077-00	METAL GLAZE	15K	5%	1/10W	
R3361	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R3362	1-216-097-00	METAL GLAZE	100K	5%	1/10W	
R3364	1-216-295-00	METAL GLAZE	0	5%	1/10W	
R3365	1-216-097-00	METAL GLAZE	100K	5%	1/10W	
R3367	1-216-077-00	METAL GLAZE	15K	5%	1/10W	
R3368	1-216-083-00	METAL GLAZE	27K	5%	1/10W	
R3369	1-216-001-00	METAL GLAZE	10	5%	1/10W	
R3370	1-216-001-00	METAL GLAZE	10	5%	1/10W	
R3371	1-216-001-00	METAL GLAZE	10	5%	1/10W	
R3373	1-216-673-11	METAL CHIP	8.2K	0.50%	1/10W	
R3374	1-216-059-00	METAL GLAZE	2.7K	5%	1/10W	
R3375	1-216-658-11	METAL CHIP	2K	0.50%	1/10W	
R3376	1-216-647-11	METAL CHIP	680	0.50%	1/10W	
R3377	1-216-647-11	METAL CHIP	680	0.50%	1/10W	
R3378	1-216-659-11	METAL CHIP	2.2K	0.50%	1/10W	
R3379	1-216-655-11	METAL CHIP	1.5K	0.50%	1/10W	
R3380	1-216-661-11	METAL CHIP	2.7K	0.50%	1/10W	
R3381	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R3382	1-216-295-00	METAL GLAZE	0	5%	1/10W	
R3392	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R3401	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	

REF.NO.	PART NO.	DESCRIPTION				REMARK
R7312	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R7313	1-216-047-00	METAL GLAZE	820	5%	1/10W	
R7314	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	
		<CRYSTAL>				
X2301	1-577-071-11	VIBRATOR, CERAMIC				
		**********				
	*A-1346-138-A	BI BOARD, COMPLETE				
		**********				
		<CAPACITOR>				
C301	1-163-010-11	CERAMIC CHIP	0.0012MF	10%	50V	
C303	1-126-157-11	ELECT	10MF	20%	16V	
C304	1-164-232-11	CERAMIC CHIP	0.01MF	10%	50V	
C305	1-163-251-11	CERAMIC CHIP	100PF	5%	50V	
C306	1-163-117-00	CERAMIC CHIP	100PF	5%	50V	
C309	1-164-505-11	CERAMIC CHIP	2.2MF		16V	
C310	1-163-109-00	CERAMIC CHIP	47PF	5%	50V	
C314	1-124-915-11	ELECT	10MF	20%	16V	
C315	1-164-505-11	CERAMIC CHIP	2.2MF		16V	
C319	1-126-157-11	ELECT	10MF	20%	16V	
C320	1-124-465-00	ELECT	0.47MF	20%	50V	
C321	1-163-125-00	CERAMIC CHIP	220PF	5%	50V	
C322	1-163-003-11	CERAMIC CHIP	330PF	10%	50V	
C323	1-163-099-00	CERAMIC CHIP	18PF	5%	50V	
C324	1-124-234-00	ELECT	22MF	20%	16V	
C325	1-104-563-11	FILM CHIP	0.1MF	5%	16V	
C326	1-104-563-11	FILM CHIP	0.1MF	5%	16V	
C327	1-104-563-11	FILM CHIP	0.1MF	5%	16V	
C328	1-126-157-11	ELECT	10MF	20%	16V	
C329	1-126-157-11	ELECT	10MF	20%	16V	
C330	1-126-157-11	ELECT	10MF	20%	16V	
C331	1-126-301-11	ELECT	1MF	20%	50V	
C332	1-124-584-00	ELECT	100MF	20%	10V	
C333	1-163-037-11	CERAMIC CHIP	0.022MF	10%	25V	
C334	1-137-491-11	FILM CHIP	0.1MF	5%	25V	
C335	1-136-169-00	FILM	0.22MF	5%	50V	
C336	1-126-301-11	ELECT	1MF	20%	50V	
C337	1-126-301-11	ELECT	1MF	20%	50V	
C338	1-124-584-00	ELECT	100MF	20%	10V	
C339	1-124-791-11	ELECT	1MF	20%	50V	
C340	1-163-009-11	CERAMIC CHIP	0.001MF	10%	50V	
C341	1-126-157-11	ELECT	10MF	20%	16V	
C342	1-124-465-00	ELECT	0.47MF	20%	50V	
C343	1-124-589-11	ELECT	47MF	20%	16V	
C344	1-164-232-11	CERAMIC CHIP	0.01MF	10%	50V	
C345	1-124-767-00	ELECT	2.2MF	20%	50V	
C346	1-164-232-11	CERAMIC CHIP	0.01MF	10%	50V	
C347	1-136-169-00	FILM	0.22MF	5%	50V	
C348	1-163-117-00	CERAMIC CHIP	100PF	5%	50V	
C349	1-126-301-11	ELECT	1MF	20%	50V	
C350	1-126-301-11	ELECT	1MF	20%	50V	
C351	1-163-002-11	CERAMIC CHIP	270PF	10%	50V	
C352	1-164-489-11	CERAMIC CHIP	0.22MF	10%	16V	
C353	1-126-163-11	ELECT	4.7MF	20%	50V	
C354	1-136-169-00	FILM	0.22MF	5%	50V	
C355	1-124-465-00	ELECT	0.47MF	20%	50V	
C356	1-163-017-00	CERAMIC CHIP	0.0047MF	10%	50V	
C357	1-163-117-00	CERAMIC CHIP	100PF	5%	50V	
C358	1-124-767-00	ELECT	2.2MF	20%	50V	
C360	1-137-491-11	FILM CHIP	0.1MF	5%	25V	
C361	1-126-301-11	ELECT	1MF	20%	50V	
C362	1-164-232-11	CERAMIC CHIP	0.01MF	10%	50V	
C363	1-164-232-11	CERAMIC CHIP	0.01MF	10%	50V	
C364	1-126-301-11	ELECT	1MF	20%	50V	
C365	1-164-343-11	CERAMIC CHIP	0.056MF	10%	25V	
C366	1-124-257-00	ELECT	2.2MF	20%	50V	
C367	1-126-157-11	ELECT	10MF	20%	16V	
C368	1-124-234-00	ELECT	22MF	20%	16V	
C369	1-163-001-11	CERAMIC CHIP	220PF	10%	50V	
C370	1-164-232-11	CERAMIC CHIP	0.01MF	10%	50V	
C371	1-124-126-00	ELECT	47MF	20%	16V	
C372	1-124-589-11	ELECT	47MF	20%	16V	
C373	1-164-232-11	CERAMIC CHIP	0.01MF	10%	50V	
C378	1-163-117-00	CERAMIC CHIP	100PF	5%	50V	
C379	1-164-232-11	CERAMIC CHIP	0.01MF	10%	50V	
C380	1-163-137-00	CERAMIC CHIP	680PF	5%	50V	
C381	1-163-101-00	CERAMIC CHIP	22PF	5%	50V	
C382	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	
C383	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	
C384	1-163-095-00	CERAMIC CHIP	12PF	5%	50V	
		<DIODE>				
D301	8-719-404-46	DIODE MA110				
D302	8-719-404-46	DIODE MA110				
D303	8-719-404-46	DIODE MA110				
D304	8-719-404-46	DIODE MA110				
D305	8-719-404-46	DIODE MA110				
D306	8-719-158-15	DIODE RD5.6S-B				
D307	8-719-404-46	DIODE MA110				
D310	8-719-158-15	DIODE RD5.6S-B				
D312	8-719-404-46	DIODE MA110				
D313	8-719-404-46	DIODE MA110				
D314	8-719-404-46	DIODE MA110				
D315	8-719-404-46	DIODE MA110				
D316	8-719-404-46	DIODE MA110				
D317	8-719-404-46	DIODE MA110				
D318	8-719-404-46	DIODE MA110				
D319	8-719-404-46	DIODE MA110				
D320	8-719-404-46	DIODE MA110				
D321	8-719-400-94	DIODE MA3130				
		<DELAY LINE>				
DL302	1-415-817-11	DELAY LINE				
		<CONNECTOR>				
E1-001	1-573-965-21	PIN, CONNECTOR (PC BOARD) 50P				
E1-24	*1-564-523-11	PLUG, CONNECTOR 8P				
E1-25	*1-564-521-31	PLUG, CONNECTOR 6P				
E1-26	*1-564-522-11	PLUG, CONNECTOR 7P				
		<IC>				
IC301	8-752-058-68	IC CXA1315M				
IC302	8-752-057-68	IC CXA1464AS				
IC303	8-759-106-02	IC UPC4570G2				
		<COIL>				
L301	1-410-064-11	INDUCTOR	2.7MMH			
L307	1-410-944-31	INDUCTOR CHIP	15UH			
L308	1-410-946-31	INDUCTOR CHIP	22UH			

E1

REF.NO.	PART NO.	DESCRIPTION	REMARK
		<TRANSISTOR>	
Q301	8-729-925-79	TRANSISTOR IMX3	
Q302	8-729-925-79	TRANSISTOR IMX3	
Q303	8-729-422-27	TRANSISTOR 2SD601A-Q	
Q304	8-729-907-46	TRANSISTOR IMZ1	
Q305	8-729-925-79	TRANSISTOR IMX3	
Q306	8-729-422-27	TRANSISTOR 2SD601A-Q	
Q307	8-729-903-10	TRANSISTOR FMW1	
Q309	8-729-422-27	TRANSISTOR 2SD601A-Q	
Q310	8-729-422-27	TRANSISTOR 2SD601A-Q	
Q311	8-729-403-27	TRANSISTOR XN4401	
Q312	8-729-422-27	TRANSISTOR 2SD601A-Q	
Q314	8-729-403-27	TRANSISTOR XN4401	
Q315	8-729-422-27	TRANSISTOR 2SD601A-Q	
Q316	8-729-422-27	TRANSISTOR 2SD601A-Q	
Q317	8-729-216-22	TRANSISTOR 2SA1162-G	
Q321	8-729-925-79	TRANSISTOR IMX3	
Q322	8-729-216-22	TRANSISTOR 2SA1162-G	
Q323	8-729-422-27	TRANSISTOR 2SD601A-Q	
Q324	8-729-216-22	TRANSISTOR 2SA1162-G	
Q325	8-729-216-22	TRANSISTOR 2SA1162-G	
Q326	8-729-422-27	TRANSISTOR 2SD601A-Q	
Q327	8-729-422-27	TRANSISTOR 2SD601A-Q	
Q328	8-729-422-27	TRANSISTOR 2SD601A-Q	
Q329	8-729-925-79	TRANSISTOR IMX3	
Q330	8-729-925-79	TRANSISTOR IMX3	
Q333	8-729-925-79	TRANSISTOR IMX3	
Q334	8-729-422-27	TRANSISTOR 2SD601A-Q	
Q335	8-729-907-46	TRANSISTOR IMZ1	
Q340	8-729-422-27	TRANSISTOR 2SD601A-Q	
Q342	8-729-925-79	TRANSISTOR IMX3	
Q344	8-729-216-22	TRANSISTOR 2SA1162-G	
		<RESISTOR>	
R301	1-216-025-00	METAL GLAZE 100 5% 1/10W	
R302	1-216-057-00	METAL GLAZE 2.2K 5% 1/10W	
R303	1-216-079-00	METAL GLAZE 18K 5% 1/10W	
R304	1-216-081-00	METAL GLAZE 22K 5% 1/10W	
R305	1-216-069-00	METAL GLAZE 6.8K 5% 1/10W	
R306	1-216-081-00	METAL GLAZE 22K 5% 1/10W	
R307	1-216-089-00	METAL GLAZE 47K 5% 1/10W	
R308	1-216-037-00	METAL GLAZE 330 5% 1/10W	
R309	1-216-073-00	METAL GLAZE 10K 5% 1/10W	
R310	1-216-065-00	METAL GLAZE 4.7K 5% 1/10W	
R312	1-216-043-00	METAL GLAZE 560 5% 1/10W	
R313	1-216-035-00	METAL GLAZE 270 5% 1/10W	
R314	1-216-061-00	METAL GLAZE 3.3K 5% 1/10W	
R316	1-216-035-00	METAL GLAZE 270 5% 1/10W	
R317	1-216-121-00	METAL GLAZE 1M 5% 1/10W	
R320	1-216-039-00	METAL GLAZE 390 5% 1/10W	
R325	1-216-033-00	METAL GLAZE 220 5% 1/10W	
R326	1-216-057-00	METAL GLAZE 2.2K 5% 1/10W	
R331	1-216-017-00	METAL GLAZE 47 5% 1/10W	
R332	1-216-657-11	METAL CHIP 1.8K 0.50% 1/10W	
R333	1-216-051-00	METAL GLAZE 1.2K 5% 1/10W	
R336	1-216-047-00	METAL GLAZE 820 5% 1/10W	
R338	1-216-043-00	METAL GLAZE 560 5% 1/10W	
R339	1-216-047-00	METAL GLAZE 820 5% 1/10W	
R340	1-216-651-11	METAL CHIP 1K 0.50% 1/10W	
R341	1-216-043-00	METAL GLAZE 560 5% 1/10W	
R343	1-216-077-00	METAL GLAZE 15K 5% 1/10W	
R344	1-216-081-00	METAL GLAZE 22K 5% 1/10W	
R345	1-216-292-11	METAL GLAZE 8.2M 5% 1/8W	
R346	1-216-081-00	METAL GLAZE 22K 5% 1/10W	
R347	1-216-081-00	METAL GLAZE 22K 5% 1/10W	
R348	1-216-049-00	METAL GLAZE 1K 5% 1/10W	
R349	1-216-295-00	METAL GLAZE 0 5% 1/10W	
R350	1-216-089-00	METAL GLAZE 47K 5% 1/10W	
R351	1-216-674-11	METAL CHIP 9.1K 0.50% 1/10W	
R352	1-216-011-00	METAL GLAZE 27 5% 1/10W	
R353	1-216-001-00	METAL GLAZE 10 5% 1/10W	
R354	1-216-049-00	METAL GLAZE 1K 5% 1/10W	
R355	1-216-001-00	METAL GLAZE 10 5% 1/10W	
R356	1-216-001-00	METAL GLAZE 10 5% 1/10W	
R357	1-216-049-00	METAL GLAZE 1K 5% 1/10W	
R358	1-216-049-00	METAL GLAZE 1K 5% 1/10W	
R359	1-216-049-00	METAL GLAZE 1K 5% 1/10W	
R360	1-216-119-00	METAL GLAZE 820K 5% 1/10W	
R361	1-216-025-00	METAL GLAZE 100 5% 1/10W	
R362	1-216-079-00	METAL GLAZE 18K 5% 1/10W	
R363	1-216-295-00	METAL GLAZE 0 5% 1/10W	
R364	1-216-045-00	METAL GLAZE 680 5% 1/10W	
R365	1-216-017-00	METAL GLAZE 47 5% 1/10W	
R366	1-216-001-00	METAL GLAZE 10 5% 1/10W	
R367	1-216-045-00	METAL GLAZE 680 5% 1/10W	
R368	1-216-001-00	METAL GLAZE 10 5% 1/10W	
R369	1-216-033-00	METAL GLAZE 220 5% 1/10W	
R370	1-216-033-00	METAL GLAZE 220 5% 1/10W	
R371	1-216-033-00	METAL GLAZE 220 5% 1/10W	
R372	1-216-031-00	METAL GLAZE 180 5% 1/10W	
R373	1-216-671-11	METAL CHIP 6.8K 0.50% 1/10W	
R374	1-216-037-00	METAL GLAZE 330 5% 1/10W	
R375	1-216-037-00	METAL GLAZE 330 5% 1/10W	
R376	1-216-037-00	METAL GLAZE 330 5% 1/10W	
R377	1-216-033-00	METAL GLAZE 220 5% 1/10W	
R378	1-216-033-00	METAL GLAZE 220 5% 1/10W	
R379	1-216-033-00	METAL GLAZE 220 5% 1/10W	
R380	1-216-033-00	METAL GLAZE 220 5% 1/10W	
R381	1-216-033-00	METAL GLAZE 220 5% 1/10W	
R382	1-216-033-00	METAL GLAZE 220 5% 1/10W	
R383	1-216-653-11	METAL CHIP 1.2K 0.50% 1/10W	
R384	1-216-041-00	METAL GLAZE 470 5% 1/10W	
R385	1-216-081-00	METAL GLAZE 22K 5% 1/10W	
R386	1-216-687-11	METAL CHIP 33K 0.50% 1/10W	
R387	1-216-033-00	METAL GLAZE 220 5% 1/10W	
R388	1-216-033-00	METAL GLAZE 220 5% 1/10W	
R389	1-216-081-00	METAL GLAZE 22K 5% 1/10W	
R390	1-216-033-00	METAL GLAZE 220 5% 1/10W	
R391	1-216-049-00	METAL GLAZE 1K 5% 1/10W	
R393	1-216-051-00	METAL GLAZE 1.2K 5% 1/10W	
R394	1-216-109-00	METAL GLAZE 330K 5% 1/10W	
R395	1-216-071-00	METAL GLAZE 8.2K 5% 1/10W	
R396	1-216-105-00	METAL GLAZE 220K 5% 1/10W	
R397	1-216-081-00	METAL GLAZE 22K 5% 1/10W	
R398	1-216-081-00	METAL GLAZE 22K 5% 1/10W	
R399	1-216-077-00	METAL GLAZE 15K 5% 1/10W	
R1301	1-216-049-00	METAL GLAZE 1K 5% 1/10W	
R1302	1-216-045-00	METAL GLAZE 680 5% 1/10W	
R1303	1-216-085-00	METAL GLAZE 33K 5% 1/10W	
R1304	1-216-081-00	METAL GLAZE 22K 5% 1/10W	
R1305	1-216-025-00	METAL GLAZE 100 5% 1/10W	
R1306	1-216-057-00	METAL GLAZE 2.2K 5% 1/10W	
R1307	1-216-073-00	METAL GLAZE 10K 5% 1/10W	
R1308	1-216-065-00	METAL GLAZE 4.7K 5% 1/10W	

REF.NO.	PART NO.	DESCRIPTION				REMARK
R1309	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R1310	1-216-045-00	METAL GLAZE	680	5%	1/10W	
R1311	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R1312	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1313	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R1314	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R1315	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R1316	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R1317	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1318	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R1319	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R1320	1-216-063-00	METAL GLAZE	3.9K	5%	1/10W	
R1321	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R1322	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R1323	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R1324	1-216-045-00	METAL GLAZE	680	5%	1/10W	
R1325	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R1326	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1327	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R1328	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R1329	1-216-077-00	METAL GLAZE	15K	5%	1/10W	
R1330	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R1331	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R1332	1-216-093-00	METAL GLAZE	68K	5%	1/10W	
R1333	1-216-129-00	METAL GLAZE	2.2M	5%	1/10W	
R1334	1-216-097-00	METAL GLAZE	100K	5%	1/10W	
R1335	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R1336	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R1337	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R1338	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R1339	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R1340	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1342	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R1343	1-216-105-00	METAL GLAZE	220K	5%	1/10W	
R1344	1-216-091-00	METAL GLAZE	56K	5%	1/10W	
R1345	1-216-101-00	METAL GLAZE	150K	5%	1/10W	
R1346	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R1347	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R1348	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R1349	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R1350	1-216-091-00	METAL GLAZE	56K	5%	1/10W	
R1351	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R1352	1-216-039-00	METAL GLAZE	390	5%	1/10W	
R1353	1-216-053-00	METAL GLAZE	1.5K	5%	1/10W	
R1354	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R1355	1-216-017-00	METAL GLAZE	47	5%	1/10W	
R1356	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	
R1357	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R1358	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R1362	1-216-105-00	METAL GLAZE	220K	5%	1/10W	
R1363	1-216-041-00	METAL GLAZE	470	5%	1/10W	
R1364	1-216-053-00	METAL GLAZE	1.5K	5%	1/10W	
R1373	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R1374	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R1379	1-216-079-00	METAL GLAZE	18K	5%	1/10W	
R1380	1-216-075-00	METAL GLAZE	12K	5%	1/10W	
R1381	1-216-041-00	METAL GLAZE	470	5%	1/10W	
R1382	1-216-079-00	METAL GLAZE	18K	5%	1/10W	
R1383	1-216-077-00	METAL GLAZE	15K	5%	1/10W	
R1384	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R1385	1-216-037-00	METAL GLAZE	330	5%	1/10W	
R1386	1-216-037-00	METAL GLAZE	330	5%	1/10W	
R1387	1-216-045-00	METAL GLAZE	680	5%	1/10W	
R1388	1-216-001-00	METAL GLAZE	10	5%	1/10W	
R1389	1-216-097-00	METAL GLAZE	100K	5%	1/10W	
R1390	1-216-097-00	METAL GLAZE	100K	5%	1/10W	
R1391	1-216-097-00	METAL GLAZE	100K	5%	1/10W	
R1392	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R1394	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R1395	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R1396	1-216-125-00	METAL GLAZE	1.5M	5%	1/10W	
R1399	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R5301	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	
R5302	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R5303	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R5304	1-216-085-00	METAL GLAZE	33K	5%	1/10W	
R5305	1-216-085-00	METAL GLAZE	33K	5%	1/10W	

<CRYSTAL>

X301	1-567-505-11	OSCILLATOR, CRYSTAL	

****

	*A-1394-443-A	Y2 BOARD, COMPLETE	
		**********	

<CAPACITOR>

C401	1-124-234-00	ELECT	22MF	20%	16V
C424	1-126-301-11	ELECT	1MF	20%	50V
C425	1-126-301-11	ELECT	1MF	20%	50V
C426	1-126-301-11	ELECT	1MF	20%	50V
C427	1-124-465-00	ELECT	0.47MF	20%	50V
C428	1-126-163-11	ELECT	4.7MF	20%	50V
C429	1-124-478-11	ELECT	100MF	20%	25V
C430	1-124-261-00	ELECT	10MF	20%	50V
C431	1-126-301-11	ELECT	1MF	20%	50V
C432	1-126-301-11	ELECT	1MF	20%	50V
C433	1-131-347-00	TANTALUM	1MF	20%	16V
C434	1-126-301-11	ELECT	1MF	20%	50V
C435	1-130-309-00	FILM	0.033MF	5%	100V
C436	1-126-301-11	ELECT	1MF	20%	50V
C437	1-130-487-00	MYLAR	0.022MF	5%	50V
C438	1-126-301-11	ELECT	1MF	20%	50V
C439	1-124-034-51	ELECT	33MF	20%	16V
C440	1-126-301-11	ELECT	1MF	20%	50V
C441	1-126-301-11	ELECT	1MF	20%	50V
C442	1-124-261-00	ELECT	10MF	20%	50V
C443	1-124-589-11	ELECT	47MF	20%	16V
C446	1-124-234-00	ELECT	22MF	20%	16V
C447	1-126-301-11	ELECT	1MF	20%	50V
C448	1-136-170-00	FILM	0.27MF	5%	50V
C449	1-163-009-11	CERAMIC CHIP	0.001MF	10%	50V
C450	1-130-475-00	MYLAR	0.0022MF	5%	50V
C451	1-124-261-00	ELECT	10MF	20%	50V
C452	1-124-261-00	ELECT	10MF	20%	50V
C453	1-130-475-00	MYLAR	0.0022MF	5%	50V
C454	1-131-368-00	TANTALUM	3.3MF	10%	16V
C455	1-131-347-00	TANTALUM	1MF	20%	16V
C456	1-136-171-00	FILM	0.33MF	5%	50V
C457	1-136-175-00	FILM	0.68MF	5%	50V
C458	1-126-101-11	ELECT	100MF	20%	16V
C459	1-126-101-11	ELECT	100MF	20%	16V
C460	1-126-101-11	ELECT	100MF	20%	16V
C461	1-124-499-11	ELECT	1MF	20%	50V
C462	1-124-499-11	ELECT	1MF	20%	50V
C465	1-130-485-00	MYLAR	0.015MF	5%	50V

Y2

REF.NO.	PART NO.	DESCRIPTION				REMARK
C466	1-130-485-00	MYLAR	0.015MF	5%	50V	
C467	1-136-169-00	FILM	0.22MF	5%	50V	
C468	1-136-169-00	FILM	0.22MF	5%	50V	
C469	1-126-157-11	ELECT	10MF	20%	16V	
C470	1-126-157-11	ELECT	10MF	20%	16V	
C471	1-124-589-11	ELECT	47MF	20%	16V	
C472	1-164-232-11	CERAMIC CHIP	0.01MF	10%	50V	
C473	1-164-232-11	CERAMIC CHIP	0.01MF	10%	50V	
C474	1-124-234-00	ELECT	22MF	20%	16V	
C475	1-164-232-11	CERAMIC CHIP	0.01MF	10%	50V	
C476	1-124-234-00	ELECT	22MF	20%	16V	
C477	1-164-232-11	CERAMIC CHIP	0.01MF	10%	50V	
C478	1-124-478-11	ELECT	100MF	20%	25V	
C479	1-126-163-11	ELECT	4.7MF	20%	50V	
C480	1-124-768-11	ELECT	4.7MF	20%	50V	
C481	1-124-768-11	ELECT	4.7MF	20%	50V	
C482	1-126-163-11	ELECT	4.7MF	20%	50V	
C483	1-163-113-00	CERAMIC CHIP	68PF	5%	50V	
C484	1-163-113-00	CERAMIC CHIP	68PF	5%	50V	
C485	1-163-038-00	CERAMIC CHIP	0.1MF		25V	
C487	1-164-232-11	CERAMIC CHIP	0.01MF	10%	50V	
C488	1-164-232-11	CERAMIC CHIP	0.01MF	10%	50V	

<DIODE>

D405	8-719-107-13	DIODE	RD18M-B1
D406	8-719-107-13	DIODE	RD18M-B1
D407	8-719-107-13	DIODE	RD18M-B1
D408	8-719-105-83	DIODE	RD5.1M-B3
D409	8-719-981-50	DIODE	RB-100A
D410	8-719-981-50	DIODE	RB-100A
D413	8-719-158-19	DIODE	RD6.2S-B
D414	8-719-158-55	DIODE	RD15S-B
D415	8-719-158-55	DIODE	RD15S-B

<IC>

IC403	8-759-996-43	IC RC4558PS
IC404	8-759-067-24	IC 24C04AI/P
IC406	8-752-037-24	IC CXA1264AS
IC407	8-759-245-75	IC TA8184P
IC408	8-752-057-18	IC CXA1315P

<TRANSISTOR>

Q404	8-729-216-22	TRANSISTOR 2SA1162-G
Q405	8-729-216-22	TRANSISTOR 2SA1162-G
Q409	8-729-422-27	TRANSISTOR 2SD601A-Q
Q410	8-729-422-27	TRANSISTOR 2SD601A-Q

<RESISTOR>

R447	1-216-033-00	METAL GLAZE	220	5%	1/10W
R453	1-216-033-00	METAL GLAZE	220	5%	1/10W
R464	1-216-081-00	METAL GLAZE	22K	5%	1/10W
R465	1-216-081-00	METAL GLAZE	22K	5%	1/10W
R466	1-216-025-00	METAL GLAZE	100	5%	1/10W
R467	1-216-033-00	METAL GLAZE	220	5%	1/10W
R468	1-216-033-00	METAL GLAZE	220	5%	1/10W
R469	1-216-055-00	METAL GLAZE	1.8K	5%	1/10W
R470	1-216-033-00	METAL GLAZE	220	5%	1/10W
R471	1-216-033-00	METAL GLAZE	220	5%	1/10W
R472	1-216-686-11	METAL CHIP	30K	0.50%	1/10W
R473	1-216-295-00	METAL GLAZE	0	5%	1/10W
R474	1-216-295-00	METAL GLAZE	0	5%	1/10W
R475	1-216-055-00	METAL GLAZE	1.8K	5%	1/10W
R476	1-216-669-11	METAL CHIP	5.6K	0.50%	1/10W
R477	1-216-675-11	METAL CHIP	10K	0.50%	1/10W
R478	1-216-089-00	METAL GLAZE	47K	5%	1/10W
R479	1-216-669-11	METAL CHIP	5.6K	0.50%	1/10W
R480	1-216-675-11	METAL CHIP	10K	0.50%	1/10W
R481	1-216-089-00	METAL GLAZE	47K	5%	1/10W
R482	1-216-089-00	METAL GLAZE	47K	5%	1/10W
R483	1-216-089-00	METAL GLAZE	47K	5%	1/10W
R485	1-216-073-00	METAL GLAZE	10K	5%	1/10W
R486	1-216-073-00	METAL GLAZE	10K	5%	1/10W
R488	1-216-295-00	METAL GLAZE	0	5%	1/10W
R494	1-216-025-00	METAL GLAZE	100	5%	1/10W
R495	1-216-025-00	METAL GLAZE	100	5%	1/10W
R496	1-216-025-00	METAL GLAZE	100	5%	1/10W
R497	1-216-033-00	METAL GLAZE	220	5%	1/10W
R498	1-216-025-00	METAL GLAZE	100	5%	1/10W
R499	1-216-025-00	METAL GLAZE	100	5%	1/10W
R500	1-216-081-00	METAL GLAZE	22K	5%	1/10W
R501	1-216-669-11	METAL CHIP	5.6K	0.50%	1/10W
R502	1-216-033-00	METAL GLAZE	220	5%	1/10W
R503	1-216-663-11	METAL CHIP	3.3K	0.50%	1/10W
R504	1-216-675-11	METAL CHIP	10K	0.50%	1/10W
R507	1-216-295-00	METAL GLAZE	0	5%	1/10W
R509	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W
R510	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W
R512	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W
R513	1-216-667-11	METAL CHIP	4.7K	0.50%	1/10W
R515	1-216-295-00	METAL GLAZE	0	5%	1/10W
R517	1-216-025-00	METAL GLAZE	100	5%	1/10W
R518	1-216-089-00	METAL GLAZE	47K	5%	1/10W
R519	1-216-295-00	METAL GLAZE	0	5%	1/10W
R521	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W
R522	1-216-033-00	METAL GLAZE	220	5%	1/10W
R523	1-216-033-00	METAL GLAZE	220	5%	1/10W
R524	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W
R525	1-216-067-00	METAL GLAZE	5.6K	5%	1/10W
R526	1-216-049-00	METAL GLAZE	1K	5%	1/10W
R527	1-218-754-11	METAL CHIP	120K	0.50%	1/10W
R528	1-216-691-11	METAL CHIP	47K	0.50%	1/10W
R529	1-216-097-00	METAL GLAZE	100K	5%	1/10W
R531	1-216-097-00	METAL GLAZE	100K	5%	1/10W
R532	1-216-097-00	METAL GLAZE	100K	5%	1/10W
R533	1-216-097-00	METAL GLAZE	100K	5%	1/10W
R535	1-216-049-00	METAL GLAZE	1K	5%	1/10W
R536	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W
R537	1-216-067-00	METAL GLAZE	5.6K	5%	1/10W
R538	1-218-754-11	METAL CHIP	120K	0.50%	1/10W
R539	1-216-691-11	METAL CHIP	47K	0.50%	1/10W
R542	1-216-025-00	METAL GLAZE	100	5%	1/10W
R543	1-216-025-00	METAL GLAZE	100	5%	1/10W
R546	1-216-682-11	METAL CHIP	20K	0.50%	1/10W
R547	1-216-681-11	METAL CHIP	18K	0.50%	1/10W

<CONNECTOR>

Y2-401	1-573-966-11	PIN, CONNECTOR (PC BOARD) 36P

****

X2

REF.NO.	PART NO.	DESCRIPTION			REMARK
	*A-1394-444-A	X2 BOARD, COMPLETE			
		**********			
		<CAPACITOR>			
C2501	1-163-020-00	CERAMIC CHIP	0.0082MF	10% 50V	
C2502	1-163-020-00	CERAMIC CHIP	0.0082MF	10% 50V	
C2503	1-163-001-11	CERAMIC CHIP	220PF	10% 50V	
C2504	1-126-163-11	ELECT	4.7MF	20% 50V	
C2505	1-163-020-00	CERAMIC CHIP	0.0082MF	10% 50V	
C2506	1-163-020-00	CERAMIC CHIP	0.0082MF	10% 50V	
C2507	1-163-017-00	CERAMIC CHIP	0.0047MF	10% 50V	
C2508	1-163-020-00	CERAMIC CHIP	0.0082MF	10% 50V	
C2509	1-163-020-00	CERAMIC CHIP	0.0082MF	10% 50V	
C2510	1-163-989-11	CERAMIC CHIP	0.033MF	10% 25V	
C2511	1-164-004-11	CERAMIC CHIP	0.1MF	10% 25V	
C2512	1-164-004-11	CERAMIC CHIP	0.1MF	10% 25V	
C2513	1-164-004-11	CERAMIC CHIP	0.1MF	10% 25V	
C2514	1-164-004-11	CERAMIC CHIP	0.1MF	10% 25V	
C2515	1-164-004-11	CERAMIC CHIP	0.1MF	10% 25V	
C2516	1-164-232-11	CERAMIC CHIP	0.01MF	10% 50V	
C2517	1-126-157-11	ELECT	10MF	20% 16V	
C2518	1-126-163-11	ELECT	4.7MF	20% 50V	
C2519	1-126-301-11	ELECT	1MF	20% 50V	
C2520	1-126-163-11	ELECT	4.7MF	20% 50V	
C2521	1-163-809-11	CERAMIC CHIP	0.047MF	10% 25V	
C2522	1-124-252-00	ELECT	0.33MF	20% 50V	
C2523	1-126-163-11	ELECT	4.7MF	20% 50V	
C2524	1-164-004-11	CERAMIC CHIP	0.1MF	10% 25V	
C2525	1-126-163-11	ELECT	4.7MF	20% 50V	
C2526	1-164-004-11	CERAMIC CHIP	0.1MF	10% 25V	
C2527	1-126-157-11	ELECT	10MF	20% 16V	
C2528	1-124-465-00	ELECT	0.47MF	20% 50V	
C2529	1-163-989-11	CERAMIC CHIP	0.033MF	10% 25V	
C2530	1-164-182-11	CERAMIC CHIP	0.0033MF	10% 50V	
C2531	1-126-301-11	ELECT	1MF	20% 50V	
C2532	1-126-301-11	ELECT	1MF	20% 50V	
C2533	1-124-261-00	ELECT	10MF	20% 50V	
C2534	1-163-257-11	CERAMIC CHIP	180PF	5% 50V	
C2535	1-164-004-11	CERAMIC CHIP	0.1MF	10% 25V	
C2536	1-164-004-11	CERAMIC CHIP	0.1MF	10% 25V	
C2537	1-126-163-11	ELECT	4.7MF	20% 50V	
C2538	1-126-163-11	ELECT	4.7MF	20% 50V	
C2539	1-164-232-11	CERAMIC CHIP	0.01MF	10% 50V	
C2540	1-164-004-11	CERAMIC CHIP	0.1MF	10% 25V	
C2541	1-163-139-00	CERAMIC CHIP	820PF	5% 50V	
C2542	1-124-478-11	ELECT	100MF	20% 25V	
C2543	1-124-252-00	ELECT	0.33MF	20% 50V	
C2544	1-164-161-11	CERAMIC CHIP	0.0022MF	10% 50V	
C2545	1-126-301-11	ELECT	1MF	20% 50V	
C2546	1-126-163-11	ELECT	4.7MF	20% 50V	
C2547	1-126-163-11	ELECT	4.7MF	20% 25V	
C2548	1-163-809-11	CERAMIC CHIP	0.047MF	10% 25V	
C2549	1-126-163-11	ELECT	4.7MF	20% 50V	
C2550	1-126-163-11	ELECT	4.7MF	20% 25V	
C2551	1-126-301-11	ELECT	1MF	20% 50V	
C2552	1-126-163-11	ELECT	4.7MF	20% 50V	
C2553	1-126-301-11	ELECT	1MF	20% 50V	
C2554	1-124-234-00	ELECT	22MF	20% 16V	
C2555	1-164-004-11	CERAMIC CHIP	0.1MF	10% 25V	
C2556	1-124-257-00	ELECT	2.2MF	20% 50V	
C2557	1-124-234-00	ELECT	22MF	20% 16V	
C2558	1-126-301-11	ELECT	1MF	20% 50V	
C2559	1-164-004-11	CERAMIC CHIP	0.1MF	10% 25V	
C2560	1-164-161-11	CERAMIC CHIP	0.0022MF	10% 50V	
C2561	1-126-301-11	ELECT	1MF	20% 50V	
C2562	1-163-263-11	CERAMIC CHIP	330PF	5% 50V	
C2563	1-163-257-11	CERAMIC CHIP	180PF	5% 50V	
C2564	1-126-301-11	ELECT	1MF	20% 50V	
C2565	1-126-163-11	ELECT	4.7MF	20% 50V	
C2566	1-126-163-11	ELECT	4.7MF	20% 50V	
C2567	1-126-163-11	ELECT	4.7MF	20% 50V	
C2568	1-163-263-11	CERAMIC CHIP	330PF	5% 50V	
C2569	1-163-257-11	CERAMIC CHIP	180PF	5% 50V	
C2570	1-124-234-00	ELECT	22MF	20% 16V	
C2571	1-126-301-11	ELECT	1MF	20% 50V	
C2572	1-126-163-11	ELECT	4.7MF	20% 50V	
C2573	1-124-234-00	ELECT	22MF	20% 16V	
C2574	1-126-301-11	ELECT	1MF	20% 50V	
C2575	1-126-301-11	ELECT	1MF	20% 50V	
C2576	1-126-301-11	ELECT	1MF	20% 50V	
C2577	1-126-163-11	ELECT	4.7MF	20% 50V	
C2578	1-126-163-11	ELECT	4.7MF	20% 50V	
C2579	1-126-103-11	ELECT	470MF	20% 16V	
C2580	1-124-478-11	ELECT	100MF	20% 25V	
C2581	1-163-109-00	CERAMIC CHIP	47PF	5% 50V	
C2582	1-124-477-11	ELECT	47MF	20% 25V	
C2583	1-126-163-11	ELECT	4.7MF	20% 50V	
C2584	1-163-109-00	CERAMIC CHIP	47PF	5% 50V	
C2585	1-126-163-11	ELECT	4.7MF	20% 50V	
C2586	1-163-009-11	CERAMIC CHIP	0.001MF	10% 50V	
C2587	1-126-163-11	ELECT	4.7MF	20% 50V	
C2588	1-126-163-11	ELECT	4.7MF	20% 50V	
C2589	1-126-163-11	ELECT	4.7MF	20% 50V	
C2590	1-126-163-11	ELECT	4.7MF	20% 50V	
C2591	1-124-478-11	ELECT	100MF	20% 25V	
		<DIODE>			
D2501	8-719-104-34	DIODE 1S2836			
D2502	8-719-106-88	DIODE RD15M-B1			
D2503	8-719-106-88	DIODE RD15M-B1			
D2504	8-719-106-88	DIODE RD15M-B1			
		<IC>			
IC2501	8-759-031-31	IC MC33174M			
IC2502	8-752-050-75	IC CXA1373Q			
IC2503	8-759-604-70	IC M51523AL			
IC2504	8-759-031-31	IC MC33174M			
IC2505	8-759-604-70	IC M51523AL			
IC2506	8-759-106-22	IC UPD4052BG			
IC2507	8-759-038-68	IC MC33172ML			
IC2508	8-759-038-68	IC MC33172ML			
		<JACK>			
J2501	*1-573-966-11	PIN, CONNECTOR (PC BOARD) 36P			
		<TRANSISTOR>			
Q2501	8-729-230-49	TRANSISTOR 2SC2712-YG			
		<RESISTOR>			
R2501	1-216-079-00	METAL GLAZE	18K	5% 1/10W	
R2502	1-216-097-00	METAL GLAZE	100K	5% 1/10W	
R2503	1-216-091-00	METAL GLAZE	56K	5% 1/10W	
R2504	1-216-109-00	METAL GLAZE	330K	5% 1/10W	
R2505	1-216-109-00	METAL GLAZE	330K	5% 1/10W	

X2 G

REF.NO.	PART NO.	DESCRIPTION				REMARK
R2506	1-216-101-00	METAL GLAZE	150K	5%	1/10W	
R2507	1-216-091-00	METAL GLAZE	56K	5%	1/10W	
R2508	1-216-079-00	METAL GLAZE	18K	5%	1/10W	
R2509	1-216-130-11	METAL GLAZE	2.4M	5%	1/10W	
R2510	1-216-097-00	METAL GLAZE	100K	5%	1/10W	
R2511	1-216-085-00	METAL GLAZE	33K	5%	1/10W	
R2512	1-216-103-00	METAL GLAZE	180K	5%	1/10W	
R2513	1-216-085-00	METAL GLAZE	33K	5%	1/10W	
R2514	1-216-103-00	METAL GLAZE	180K	5%	1/10W	
R2515	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R2516	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R2517	1-216-133-00	METAL GLAZE	3.3M	5%	1/10W	
R2518	1-216-072-00	METAL GLAZE	9.1K	5%	1/10W	
R2519	1-216-133-00	METAL GLAZE	3.3M	5%	1/10W	
R2520	1-216-133-00	METAL GLAZE	3.3M	5%	1/10W	
R2521	1-216-133-00	METAL GLAZE	3.3M	5%	1/10W	
R2522	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R2523	1-216-077-00	METAL GLAZE	15K	5%	1/10W	
R2524	1-216-129-00	METAL GLAZE	2.2M	5%	1/10W	
R2526	1-216-133-00	METAL GLAZE	3.3M	5%	1/10W	
R2527	1-216-133-00	METAL GLAZE	3.3M	5%	1/10W	
R2528	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R2529	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R2530	1-216-133-00	METAL GLAZE	3.3M	5%	1/10W	
R2531	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R2532	1-216-133-00	METAL GLAZE	3.3M	5%	1/10W	
R2533	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R2534	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R2535	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R2536	1-216-129-00	METAL GLAZE	2.2M	5%	1/10W	
R2537	1-216-077-00	METAL GLAZE	15K	5%	1/10W	
R2539	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R2540	1-216-075-00	METAL GLAZE	12K	5%	1/10W	
R2541	1-216-069-00	METAL GLAZE	6.8K	5%	1/10W	
R2542	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R2543	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R2544	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R2545	1-216-048-00	METAL GLAZE	910	5%	1/10W	
R2546	1-216-133-00	METAL GLAZE	3.3M	5%	1/10W	
R2547	1-216-133-00	METAL GLAZE	3.3M	5%	1/10W	
R2548	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R2549	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R2550	1-216-088-00	METAL GLAZE	43K	5%	1/10W	
R2551	1-216-088-00	METAL GLAZE	43K	5%	1/10W	
R2552	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R2553	1-216-078-00	METAL GLAZE	16K	5%	1/10W	
R2554	1-216-082-00	METAL GLAZE	24K	5%	1/10W	
R2555	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R2556	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R2557	1-216-085-00	METAL GLAZE	33K	5%	1/10W	
R2558	1-216-088-00	METAL GLAZE	43K	5%	1/10W	
R2559	1-216-091-00	METAL GLAZE	56K	5%	1/10W	
R2560	1-216-103-00	METAL GLAZE	180K	5%	1/10W	
R2561	1-216-097-00	METAL GLAZE	100K	5%	1/10W	
R2562	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R2563	1-216-088-00	METAL GLAZE	43K	5%	1/10W	
R2564	1-216-088-00	METAL GLAZE	43K	5%	1/10W	
R2565	1-216-103-00	METAL GLAZE	180K	5%	1/10W	
R2566	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R2567	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R2568	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R2569	1-216-097-00	METAL GLAZE	100K	5%	1/10W	
R2570	1-216-091-00	METAL GLAZE	56K	5%	1/10W	
R2571	1-216-078-00	METAL GLAZE	16K	5%	1/10W	
R2572	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R2573	1-216-082-00	METAL GLAZE	24K	5%	1/10W	
R2574	1-216-085-00	METAL GLAZE	33K	5%	1/10W	
R2575	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R2576	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R2577	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R2578	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R2579	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R2580	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R2581	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R2582	1-216-083-00	METAL GLAZE	27K	5%	1/10W	
R2583	1-216-083-00	METAL GLAZE	27K	5%	1/10W	
R2584	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R2585	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R2586	1-216-085-00	METAL GLAZE	33K	5%	1/10W	
R2587	1-216-085-00	METAL GLAZE	33K	5%	1/10W	
R2588	1-216-085-00	METAL GLAZE	33K	5%	1/10W	
R2589	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R2590	1-216-079-00	METAL GLAZE	18K	5%	1/10W	
R2591	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R2592	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R2593	1-216-079-00	METAL GLAZE	18K	5%	1/10W	
R2594	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R2595	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R2596	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R2597	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R2598	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R2599	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R2600	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R2601	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R2602	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R2604	1-216-089-00	METAL GLAZE	47K	5%	1/10W	
R2605	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R2606	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R2610	1-216-125-00	METAL GLAZE	1.5M	5%	1/10W	
R2611	1-216-125-00	METAL GLAZE	1.5M	5%	1/10W	
R2612	1-216-125-00	METAL GLAZE	1.5M	5%	1/10W	
R2613	1-216-125-00	METAL GLAZE	1.5M	5%	1/10W	
R2614	1-216-125-00	METAL GLAZE	1.5M	5%	1/10W	
R2615	1-216-125-00	METAL GLAZE	1.5M	5%	1/10W	
R2616	1-216-125-00	METAL GLAZE	1.5M	5%	1/10W	
R2617	1-216-125-00	METAL GLAZE	1.5M	5%	1/10W	
R2618	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R2619	1-216-049-00	METAL GLAZE	1K	5%	1/10W	

****

*A-1316-149-A G BOARD, COMPLETE
****

1-533-223-11 CLIP, FUSE
3-701-754-00 PLATE, INSULATING
4-382-854-11 SCREW (M3X10), P, SW (+)

<CAPACITOR>

C601	1-161-830-00	CERAMIC	4700PF	10%	500V
C602	1-130-317-00	FILM	0.068MF	5%	100V
C603	1-124-634-11	ELECT	1MF	20%	250V
C605	1-164-143-11	CERAMIC	0.001MF	10%	1KV
C606	1-124-563-11	ELECT	2200MF	20%	25V
C607	1-124-563-11	ELECT	2200MF	20%	25V
C608	1-128-484-11	ELECT	100MF	20%	200V
C609	1-137-141-11	FILM	0.082MF	3%	600V
C612	1-124-962-11	ELECT	2200MF	20%	25V

The components identified by shading and mark ⚠ are critical for safety.
Replace only with part number specified.

Les composants identifies par une trame et une marque ⚠ sont critiques pour la securite.
Ne les remplacer que par une piece portant le numero specifie.

REF.NO.	PART NO.	DESCRIPTION				REMARK
C614	1-126-326-51	ELECT	10MF	20%	200V	
C615	1-124-798-11	ELECT	1MF	20%	160V	
C616	1-124-557-11	ELECT	1000MF	20%	25V	
C617	1-164-143-11	CERAMIC	0.001MF	10%	1KV	
C618	1-136-853-11	FILM	0.56MF	5%	200V	
C619	1-164-735-11	CAP, CERAMIC	1500PF			
C620	1-136-721-21	FILM	1.5MF	10%	400V	
C621	1-164-143-11	CERAMIC	0.001MF	10%	1KV	
C622	1-136-853-11	FILM	0.56MF	5%	200V	
C623	1-137-087-11	FILM	0.068MF	3%	0	
C624	1-126-771-11	ELECT	100MF	20%	160V	
C625	1-126-183-11	ELECT	1000MF	20%	16V	
C626	1-126-373-11	ELECT	470MF	20%	10V	
C628	1-161-830-00	CERAMIC	4700PF	10%	500V	
C629	1-124-607-11	ELECT	2200MF	20%	50V	
C631	1-126-803-11	ELECT	47MF	20%	50V	
C632	1-124-903-11	ELECT	1MF	20%	50V	
C633	1-130-483-00	MYLAR	0.01MF	5%	50V	
C634	1-126-803-11	ELECT	47MF	20%	16V	
C637 ⚠	1-136-311-51	FILM	0.47MF	20%	125V	
C638 ⚠	1-161-743-12	CERAMIC	0.0047MF		400V	
C639 ⚠	1-125-692-11	ELECT(BLOCK)	820MF	20%	200V	
C640 ⚠	1-136-311-51	FILM	0.47MF	20%	125V	
C641	1-126-101-11	ELECT	100MF	20%	16V	
C642 ⚠	1-161-743-12	CERAMIC	0.0047MF		400V	
C644	1-126-104-11	ELECT	470MF	20%	35V	
C646	1-124-907-11	ELECT	10MF	20%	50V	
C647 ⚠	1-164-486-51	CERAMIC	0.0033MF	20%	400V	
C648 ⚠	1-125-692-11	ELECT(BLOCK)	820MF	20%	200V	
C649 ⚠	1-164-486-51	CERAMIC	0.0033MF	20%	400V	
C650 ⚠	1-161-743-12	CERAMIC	0.0047MF		400V	
C660	1-102-125-00	CERAMIC	0.0047MF	10%	50V	
C661	1-102-125-00	CERAMIC	0.0047MF	10%	50V	
C662	1-124-910-11	ELECT	47MF	20%	35V	
C663	1-126-017-11	ELECT	6800MF	20%	16V	
C664	1-126-017-11	ELECT	6800MF	20%	16V	
C670	1-102-074-00	CERAMIC	0.001MF	10%	50V	

<DIODE>

D602	8-719-979-58	DIODE EGP10D	
D603	8-719-500-67	DIODE D5KC40H	
D604	8-719-510-09	DIODE D10SC6M	
D605	8-719-988-31	DIODE D10SC6MR	
D607	8-719-025-81	DIODE S3V10SB	
D608	8-719-109-85	DIODE RD5.1ES-B2	
D609	8-719-109-84	DIODE RD5.1ES-B1	
D610	8-719-979-58	DIODE EGP10D	
D611	8-719-979-58	DIODE EGP10D	
D613	8-719-303-57	DIODE RU2AM	
D614	8-719-979-58	DIODE EGP10D	
D615	8-719-975-76	DIODE SB140	
D616	8-719-025-81	DIODE S3V10SB	
D617	8-719-110-02	DIODE RD7.5ES-B1	
D618	8-719-911-19	DIODE 1SS119	
D619	8-719-975-76	DIODE SB140	
D620 ⚠	8-719-988-31	DIODE D10SC6MR	
D621	8-719-908-03	DIODE GP08D	
D622	8-719-908-03	DIODE GP08D	
D623	8-719-110-63	DIODE RD24ES-B3	
D624	8-719-109-89	DIODE RD5.6ES-B2	
D626	8-719-908-03	DIODE GP08D	
D628	8-719-110-49	DIODE RD18ES-B2	
D629	8-719-911-19	DIODE 1SS119	
D631	8-719-911-19	DIODE 1SS119	
D632	8-719-511-40	DIODE S1VB40	
D633 ⚠	8-719-505-60	DIODE S5VB60	
D634	8-719-911-19	DIODE 1SS119	
D636	8-719-109-85	DIODE RD5.1ES-B2	
D638	8-719-911-19	DIODE 1SS119	
D640 ⚠	8-719-510-09	DIODE D10SC6M	
D650	8-719-160-81	DIODE RD27F-B2	

<FUSE>

F601 ⚠	1-532-748-11	FUSE, GLASS TUBE 6.3A/125V	

<FERRITE BEAD>

FB602	1-410-397-21	FERRITE BEAD INDUCTOR 1.1UH	
FB604	1-410-396-41	FERRITE BEAD INDUCTOR 0.45UH	
FB606	1-410-397-21	FERRITE BEAD INDUCTOR 1.1UH	
FB607	1-410-397-21	FERRITE BEAD INDUCTOR 1.1UH	
FB608	1-410-396-41	FERRITE BEAD INDUCTOR 0.45UH	
FB612	1-410-397-21	FERRITE BEAD INDUCTOR 1.1UH	
FB622	1-410-397-21	FERRITE BEAD INDUCTOR 1.1UH	
FB630	1-410-396-41	FERRITE BEAD INDUCTOR 0.45UH	
FB631	1-410-396-41	FERRITE BEAD INDUCTOR 0.45UH	

<CONNECTOR>

G1	*1-508-786-00	PIN, CONNECTOR (5MM PITCH) 2P	
G2	*1-564-512-11	PLUG, CONNECTOR 9P	
G3	*1-564-507-11	PLUG, CONNECTOR 4P	
G4	*1-564-511-11	PLUG, CONNECTOR 8P	
G5	*1-564-508-11	PLUG, CONNECTOR 5P	
G7	*1-564-507-11	PLUG, CONNECTOR 4P	
G8	*1-580-843-11	PIN, CONNECTOR (POWER)	
G9	*1-508-765-00	PIN, CONNECTOR (5MM PITCH) 3P	
G10	*1-508-786-00	PIN, CONNECTOR (5MM PITCH) 2P	
G11	*1-564-511-31	PLUG, CONNECTOR 8P	
G12	*1-564-505-11	PLUG, CONNECTOR 2P	

<IC>

IC601 ⚠	8-749-921-89	IC SE115N	
IC602	8-759-231-58	IC TA7812S	

<COIL>

L602	1-459-862-11	COIL, CHOKE 90UH	
L604	1-408-404-00	INDUCTOR	3.9UH
L605	1-412-526-11	INDUCTOR	12UH
L607	1-408-404-00	INDUCTOR	3.9UH
L611	1-412-546-41	INDUCTOR	560UH
L612	1-412-540-31	INDUCTOR	180UH
L613	1-412-522-41	INDUCTOR	5.6UH

<TRANSISTOR>

Q603	8-729-011-15	TRANSISTOR 2SC4582NP	
Q604	8-729-119-80	TRANSISTOR 2SC2688-LK	
Q607	8-729-119-78	TRANSISTOR 2SC2785-HFE	
Q608	8-729-326-11	TRANSISTOR 2SC2611	
Q609	8-729-119-76	TRANSISTOR 2SA1175-HFE	
Q610	8-729-019-58	TRANSISTOR 2SA1208T-TP	
Q611	8-729-019-58	TRANSISTOR 2SA1208T-TP	

• The components identified by ⊠ in this manual have been carefully factory-selected for each set in order to satisfy regulations regarding X-ray radiation. Should replacement be required, replace only with the value originally used.

Les composants identifies par une trame et une marque ⚠ sont critiques pour la securite. Ne les remplacer que par une piece portant le numero specifie.

The components identified by shading and mark ⚠ are critical for safety. Replace only with part number specified.

REF.NO.	PART NO.	DESCRIPTION				REMARK
Q612	8-729-386-12	TRANSISTOR 2SB861-C				
Q613	8-729-209-15	TRANSISTOR 2SD2012				
Q614	8-729-011-15	TRANSISTOR 2SC4582NP				
Q615	8-729-019-58	TRANSISTOR 2SA1208T-TP				
Q616	8-729-208-39	TRANSISTOR 2SA1306A-Y				
Q618	8-729-119-76	TRANSISTOR 2SA1175-HFE				
Q620	8-729-119-78	TRANSISTOR 2SC2785-HFE				
Q621	8-729-119-78	TRANSISTOR 2SC2785-HFE				
Q623	8-729-119-76	TRANSISTOR 2SA1175-HFE				
Q629	8-729-378-84	TRANSISTOR 2SD788-5				
Q630	8-729-255-12	TRANSISTOR 2SC2551-O				
		<RESISTOR>				
R604	1-202-933-11	FUSIBLE	0.1	10%	1/2W	F
R605	1-249-428-11	CARBON	8.2K	5%	1/4W	
R606	1-214-919-00	METAL	180K	1%	1/2W	
R609	1-249-434-11	CARBON	27K	5%	1/4W	F
R610	1-215-469-00	METAL	100K	1%	1/4W	
R611	1-249-421-11	CARBON	2.2K	5%	1/4W	F
R612	1-202-883-11	SOLID	680K	20%	1/2W	
R613	1-216-386-11	METAL OXIDE	0.56	5%	3W	F
R614	1-249-418-11	CARBON	1.2K	5%	1/4W	
R615	1-215-438-00	METAL	5.1K	1%	1/4W	
R616	1-215-436-00	METAL	4.3K	1%	1/4W	
R617	1-216-356-00	METAL OXIDE	3.9	5%	1W	F
R618	1-249-418-11	CARBON	1.2K	5%	1/4W	
R619	1-216-444-11	METAL OXIDE	82K	5%	1W	F
R620	1-249-418-11	CARBON	1.2K	5%	1/4W	F
R621	1-247-691-11	CARBON	18	5%	1/4W	F
R622	1-249-424-11	CARBON	3.9K	5%	1/4W	F
R623	1-249-417-11	CARBON	1K	5%	1/4W	
R624	1-214-780-00	METAL	130K	1%	1/4W	
R625	1-216-386-11	METAL OXIDE	0.56	5%	3W	F
R626	1-216-356-00	METAL OXIDE	3.9	5%	1W	F
R627	1-202-883-11	SOLID	680K	20%	1/2W	
R628	1-249-410-11	CARBON	270	5%	1/4W	F
R629	1-207-620-00	WIREWOUND	1	10%	3W	F
R631	1-249-417-11	CARBON	1K	5%	1/4W	F
R632	1-214-913-00	METAL	100K	1%	1/2W	
R633	1-249-429-11	CARBON	10K	5%	1/4W	
R634	1-249-441-11	CARBON	100K	5%	1/4W	
R635	1-215-897-11	METAL OXIDE	6.8K	5%	2W	F
R636	1-260-065-11	CARBON	1.2	5%	1/2W	
R638	1-249-405-11	CARBON	100	5%	1/4W	F
R639	1-249-405-11	CARBON	100	5%	1/4W	F
R640	1-249-421-11	CARBON	2.2K	5%	1/4W	F
R641	1-249-429-11	CARBON	10K	5%	1/4W	
R642	1-215-421-00	METAL	1K	1%	1/4W	
R643	1-260-123-11	CARBON	100K	5%	1/2W	
R644	1-249-415-11	CARBON	680	5%	1/4W	
R645	1-249-417-11	CARBON	1K	5%	1/4W	
R649	1-249-424-11	CARBON	3.9K	5%	1/4W	
R650	1-249-377-11	CARBON	0.47	5%	1/4W	F
R651	1-215-429-00	METAL	2.2K	1%	1/4W	
⊠R652 ⚠		METAL			1/4W	
R654	1-215-429-00	METAL	2.2K	1%	1/4W	
R655	1-249-426-11	CARBON	5.6K	5%	1/4W	
R656	1-215-454-00	METAL	24K	1%	1/4W	
R657	1-216-386-11	METAL OXIDE	0.56	5%	3W	F
R660	1-249-418-11	CARBON	1.2K	5%	1/4W	
R661 ⚠	1-202-884-91	SOLID	820K	20%	1/2W	
R662 ⚠	1-205-900-11	WIREWOUND	1.2	5%	15W	
R663 ⚠	1-215-904-91	METAL OXIDE	100K	5%	2W	F
R666	1-249-377-11	CARBON	0.47	5%	1/4W	F
R667 ⚠	1-202-888-91	SOLID	2.2M	20%	1/2W	
R668 ⚠	1-215-904-91	METAL OXIDE	100K	5%	2W	F
R669	1-249-377-11	CARBON	0.47	5%	1/4W	F
R675	1-249-377-11	CARBON	0.47	5%	1/4W	F
R687	1-249-417-11	CARBON	1K	5%	1/4W	F
R689	1-247-742-11	CARBON	180	5%	1/2W	F
R691	1-249-421-11	CARBON	2.2K	5%	1/4W	
R694	1-249-421-11	CARBON	2.2K	5%	1/4W	
R697	1-249-382-11	CARBON	1.2	5%	1/4W	F
R698	1-216-386-11	METAL OXIDE	0.56	5%	3W	F
		<RELAY>				
RY601 ⚠	1-515-805-11	RELAY, POWER				
RY602 ⚠	1-515-805-11	RELAY, POWER				
		<TRANSFORMER>				
T601 ⚠	1-450-791-12	TRANSFORMER, POWER ISOLATION				
T603 ⚠	1-424-020-11	PRT				
T604 ⚠	1-450-149-11	TRANSFORMER, HEATER				
T605 ⚠	1-424-023-12	TRANSFORMER, LINE FILTER				
T606 ⚠	1-421-372-21	TRANSFORMER, FERRITE (LPT)				
T608 ⚠	1-423-665-11	TRANSFORMER, POWER				
		<VARISTOR>				
VDR601 ⚠	1-809-786-11	VARISTOR				

****

	*A-1331-259-A	CR BOARD, COMPLETE			
		**********			
		<CAPACITOR>			
C701	1-162-115-00	CERAMIC	330PF	10%	2KV
C702	1-123-948-00	ELECT	22MF	20%	250V
C703	1-102-050-00	CERAMIC	0.01MF		500V
C704	1-162-115-00	CERAMIC	330PF	10%	2KV
C705	1-130-479-00	MYLAR	0.0047MF	5%	50V
C706	1-101-006-00	CERAMIC	0.047MF		50V
C707	1-101-006-00	CERAMIC	0.047MF		50V
C709	1-124-120-11	ELECT	220MF	20%	16V
C710	1-124-120-11	ELECT	220MF	20%	16V
C711	1-102-114-00	CERAMIC	470PF	10%	50V
		<CONNECTOR>			
CR1	*1-508-784-00	PIN, CONNECTOR (5MM PITCH) 1P			
CR3	*1-508-765-00	PIN, CONNECTOR (5MM PITCH) 3P			
CR4	*1-564-511-31	PLUG, CONNECTOR 8P			
CR15	*1-564-508-11	PLUG, CONNECTOR 5P			
		<PICTURE TUBE SOCKET>			
CRT701 ⚠	1-251-026-11	SOCKET, PICTURE TUBE			
		<DIODE>			
D701	8-719-911-19	DIODE 1SS119			
D702	8-719-911-19	DIODE 1SS119			
D703	8-719-911-19	DIODE 1SS119			

The components identified by shading and mark ⚠ are critical for safety.
Replace only with part number specified.

Les composants identifies par une trame et une marque ⚠ sont critiques pour la securite.
Ne les remplacer que par une piece portant le numero specifie.

REF.NO.	PART NO.	DESCRIPTION				REMARK
D704	8-719-911-19	DIODE 1SS119				
D705	8-719-911-19	DIODE 1SS119				
D706	8-719-911-19	DIODE 1SS119				
D707	8-719-110-36	DIODE RD13ES-B2				
		<COIL>				
L701	1-408-429-00	INDUCTOR 470UH				
L702	1-408-159-00	COIL, SPOOK CHOKE 3.3UH				
L703	1-408-159-00	COIL, SPOOK CHOKE 3.3UH				
L704	1-408-413-00	INDUCTOR 22UH				
		<NEON LAMP>				
NL701	1-519-108-99	LAMP, NEON				
NL702	1-519-108-99	LAMP, NEON				
		<TRANSISTOR>				
Q701	8-729-119-78	TRANSISTOR 2SC2785-HFE				
Q702	8-729-119-78	TRANSISTOR 2SC2785-HFE				
Q703	8-729-119-80	TRANSISTOR 2SC2688-LK				
	4-373-933-01	SHEET (TRANSISTOR), BN; Q703				
	4-382-854-11	SCREW (M3X10), P, SW (+); Q703				
Q704	8-729-255-12	TRANSISTOR 2SC2551-O				
Q705	8-729-200-17	TRANSISTOR 2SA1091-O				
Q706	8-729-200-17	TRANSISTOR 2SA1091-O				
		<RESISTOR>				
R701	1-202-847-00	SOLID	560K	20%	1/2W	
R702	1-202-814-11	SOLID	33K	20%	1/2W	
R703	1-202-818-00	SOLID	1K	20%	1/2W	
R704	1-202-842-11	SOLID	220K	20%	1/2W	
R705	1-202-828-11	SOLID	6.8K	20%	1/2W	
R706	1-202-561-00	SOLID	330	20%	1/2W	
R707	1-216-510-11	METAL OXIDE	8.2K	5%	5W	F
R708	1-249-405-11	CARBON	100	5%	1/4W	F
R709	1-249-405-11	CARBON	100	5%	1/4W	F
R710	1-215-927-00	METAL OXIDE	47K	5%	3W	F
R711	1-249-405-11	CARBON	100	5%	1/4W	F
R712	1-249-421-11	CARBON	2.2K	5%	1/4W	F
R714	1-249-401-11	CARBON	47	5%	1/4W	
R716	1-249-405-11	CARBON	100	5%	1/4W	
R717	1-249-403-11	CARBON	68	5%	1/4W	
R718	1-249-412-11	CARBON	390	5%	1/4W	
R719	1-249-410-11	CARBON	270	5%	1/4W	
R720	1-249-405-11	CARBON	100	5%	1/4W	
R721	1-249-409-11	CARBON	220	5%	1/4W	
R722	1-215-423-00	METAL	1.2K	1%	1/4W	
R723	1-249-410-11	CARBON	270	5%	1/4W	
R724	1-215-429-00	METAL	2.2K	1%	1/4W	
		<SPARK GAP>				
SG701	1-519-422-11	GAP, SPARK				
SG702	1-519-422-11	GAP, SPARK				
**********						
	*A-1331-260-A	CG BOARD, COMPLETE				
		**********				
	4-373-933-01	SHEET (TRANSISTOR), BN				
	4-382-854-11	SCREW (M3X10), P, SW (+)				

REF.NO.	PART NO.	DESCRIPTION				REMARK
		<CAPACITOR>				
C731	1-162-115-00	CERAMIC	330PF	10%	2KV	
C732	1-123-948-00	ELECT	22MF	20%	250V	
C733	1-102-050-00	CERAMIC	0.01MF		500V	
C734	1-162-115-00	CERAMIC	330PF	10%	2KV	
C735	1-130-479-00	MYLAR	0.0047MF	5%	50V	
C736	1-101-006-00	CERAMIC	0.047MF		50V	
C737	1-101-006-00	CERAMIC	0.047MF		50V	
C739	1-124-120-11	ELECT	220MF	20%	16V	
C740	1-124-120-11	ELECT	220MF	20%	16V	
C741	1-102-114-00	CERAMIC	470PF	10%	50V	
		<CONNECTOR>				
CG1	*1-508-784-00	PIN, CONNECTOR (5MM PITCH) 1P				
CG3	*1-508-765-00	PIN, CONNECTOR (5MM PITCH) 3P				
CG16	*1-564-508-11	PLUG, CONNECTOR 5P				
		<PICTURE TUBE SOCKET>				
CRT731	⚠ 1-251-026-11	SOCKET, PICTURE TUBE				
		<DIODE>				
D731	8-719-911-19	DIODE 1SS119				
D732	8-719-911-19	DIODE 1SS119				
D733	8-719-911-19	DIODE 1SS119				
D734	8-719-911-19	DIODE 1SS119				
D735	8-719-911-19	DIODE 1SS119				
D736	8-719-911-19	DIODE 1SS119				
D737	8-719-911-19	DIODE 1SS119				
		<COIL>				
L731	1-408-429-00	INDUCTOR 470UH				
L732	1-408-159-00	COIL, SPOOK CHOKE 3.3UH				
L733	1-408-159-00	COIL, SPOOK CHOKE 3.3UH				
L734	1-408-413-00	INDUCTOR 22UH				
		<NEON LAMP>				
NL731	1-519-108-99	LAMP, NEON				
NL732	1-519-108-99	LAMP, NEON				
		<TRANSISTOR>				
Q731	8-729-119-78	TRANSISTOR 2SC2785-HFE				
Q732	8-729-119-78	TRANSISTOR 2SC2785-HFE				
Q733	8-729-119-80	TRANSISTOR 2SC2688-LK				
Q734	8-729-255-12	TRANSISTOR 2SC2551-O				
Q735	8-729-200-17	TRANSISTOR 2SA1091-O				
Q736	8-729-200-17	TRANSISTOR 2SA1091-O				
		<RESISTOR>				
R731	1-202-847-00	SOLID	560K	20%	1/2W	
R732	1-202-814-11	SOLID	33K	20%	1/2W	
R733	1-202-818-00	SOLID	1K	20%	1/2W	
R734	1-202-842-11	SOLID	220K	20%	1/2W	
R735	1-202-828-11	SOLID	6.8K	20%	1/2W	
R736	1-202-561-00	SOLID	330	20%	1/2W	
R737	1-216-510-11	METAL OXIDE	8.2K	5%	5W	F
R738	1-249-405-11	CARBON	100	5%	1/4W	F

CG | CB | V

Les composants identifies par une trame et une marque ⚠ sont critiques pour la securite. Ne les remplacer que par une piece portant le numero specifie.

The components identified by shading and mark ⚠ are critical for safety. Replace only with part number specified.

REF.NO.	PART NO.	DESCRIPTION				REMARK
R739	1-249-405-11	CARBON	100	5%	1/4W	F
R740	1-215-927-00	METAL OXIDE	47K	5%	3W	F
R741	1-249-405-11	CARBON	100	5%	1/4W	F
R742	1-249-421-11	CARBON	2.2K	5%	1/4W	F
R744	1-249-401-11	CARBON	47	5%	1/4W	
R745	1-215-455-00	METAL	27K	1%	1/4W	
R746	1-249-405-11	CARBON	100	5%	1/4W	
R747	1-249-403-11	CARBON	68	5%	1/4W	
R748	1-249-412-11	CARBON	390	5%	1/4W	
R749	1-249-410-11	CARBON	270	5%	1/4W	
R750	1-249-405-11	CARBON	100	5%	1/4W	
R751	1-249-409-11	CARBON	220	5%	1/4W	
R752	1-215-423-00	METAL	1.2K	1%	1/4W	
R754	1-215-429-00	METAL	2.2K	1%	1/4W	

<SPARK GAP>

SG731	1-519-422-11	GAP, SPARK	
SG732	1-519-422-11	GAP, SPARK	

****

*A-1331-261-A CB BOARD, COMPLETE
****

4-373-933-01 SHEET (TRANSISTOR), BN
4-382-854-11 SCREW (M3X10), P, SW (+)

<CAPACITOR>

C761	1-162-115-00	CERAMIC	330PF	10%	2KV
C762	1-123-948-00	ELECT	22MF	20%	250V
C763	1-102-050-00	CERAMIC	0.01MF		500V
C764	1-162-115-00	CERAMIC	330PF	10%	2KV
C765	1-130-479-00	MYLAR	0.0047MF	5%	50V
C766	1-101-006-00	CERAMIC	0.047MF		50V
C767	1-101-006-00	CERAMIC	0.047MF		50V
C769	1-124-120-11	ELECT	220MF	20%	16V
C770	1-124-120-11	ELECT	220MF	20%	16V
C771	1-102-114-00	CERAMIC	470PF	10%	50V

<CONNECTOR>

CB1	*1-508-784-00	PIN, CONNECTOR (5MM PITCH) 1P
CB3	*1-508-765-00	PIN, CONNECTOR (5MM PITCH) 3P
CB4	*1-564-511-11	PLUG, CONNECTOR 8P
CB5	*1-564-511-21	PLUG, CONNECTOR 8P
CB17	*1-564-508-11	PLUG, CONNECTOR 5P

<PICTURE TUBE SOCKET>

CRT761⚠	1-251-026-11	SOCKET, PICTURE TUBE

<DIODE>

D761	8-719-911-19	DIODE 1SS119
D762	8-719-911-19	DIODE 1SS119
D763	8-719-911-19	DIODE 1SS119
D764	8-719-911-19	DIODE 1SS119
D765	8-719-911-19	DIODE 1SS119
D766	8-719-911-19	DIODE 1SS119
D768	8-719-911-19	DIODE 1SS119
D769	8-719-109-81	DIODE RD4.7ES-B2

<COIL>

L761	1-408-429-00	INDUCTOR 470UH
L762	1-408-159-00	COIL, SPOOK CHOKE 3.3UH
L763	1-408-159-00	COIL, SPOOK CHOKE 3.3UH
L764	1-408-413-00	INDUCTOR 22UH

<NEON LAMP>

NL761	1-519-108-99	LAMP, NEON
NL762	1-519-108-99	LAMP, NEON

<TRANSISTOR>

Q761	8-729-119-78	TRANSISTOR 2SC2785-HFE
Q762	8-729-119-78	TRANSISTOR 2SC2785-HFE
Q763	8-729-119-80	TRANSISTOR 2SC2688-LK
Q764	8-729-255-12	TRANSISTOR 2SC2551-O
Q765	8-729-200-17	TRANSISTOR 2SA1091-O
Q766	8-729-200-17	TRANSISTOR 2SA1091-O

<RESISTOR>

R761	1-202-847-00	SOLID	560K	20%	1/2W	
R762	1-202-814-11	SOLID	33K	20%	1/2W	
R763	1-202-818-00	SOLID	1K	20%	1/2W	
R764	1-202-842-11	SOLID	220K	20%	1/2W	
R765	1-202-828-11	SOLID	6.8K	20%	1/2W	
R766	1-202-561-00	SOLID	330	20%	1/2W	
R767	1-216-510-11	METAL OXIDE	8.2K	5%	5W	F
R768	1-249-405-11	CARBON	100	5%	1/4W	F
R769	1-249-405-11	CARBON	100	5%	1/4W	F
R770	1-215-927-00	METAL OXIDE	47K	5%	3W	F
R771	1-249-405-11	CARBON	100	5%	1/4W	F
R772	1-249-421-11	CARBON	2.2K	5%	1/4W	F
R773	1-249-413-11	CARBON	470	5%	1/4W	
R774	1-249-401-11	CARBON	47	5%	1/4W	
R776	1-249-405-11	CARBON	100	5%	1/4W	
R777	1-249-403-11	CARBON	68	5%	1/4W	
R778	1-249-412-11	CARBON	390	5%	1/4W	
R779	1-249-415-11	CARBON	680	5%	1/4W	
R780	1-249-405-11	CARBON	100	5%	1/4W	
R781	1-249-409-11	CARBON	220	5%	1/4W	
R782	1-215-423-00	METAL	1.2K	1%	1/4W	
R783	1-215-433-00	METAL	3.3K	1%	1/4W	
R784	1-215-429-00	METAL	2.2K	1%	1/4W	
R785	1-215-418-00	METAL	750	1%	1/4W	

<SPARK GAP>

SG761	1-519-422-11	GAP, SPARK	
SG762	1-519-422-11	GAP, SPARK	

****

*A-1342-214-A V BOARD, COMPLETE
****

*4-395-527-01 HOLDER (B), TR

<CAPACITOR>

C1501	1-102-129-00	CERAMIC	0.01MF	10%	50V
C1502	1-126-101-11	ELECT	100MF	20%	16V
C1504	1-106-383-00	MYLAR	0.047MF		200V
C1505	1-124-907-11	ELECT	10MF	20%	50V
C1506	1-106-359-00	MYLAR	0.0047MF	10%	200V

REF.NO.	PART NO.	DESCRIPTION				REMARK
C1507	1-106-367-00	MYLAR	0.01MF	10%	100V	
C1508	1-162-318-11	CERAMIC	0.001MF	10%	500V	
C1509	1-106-367-00	MYLAR	0.01MF	10%	100V	
C1510	1-126-355-11	ELECT	33MF	20%	160V	
C1511	1-124-668-11	ELECT	2.2MF	20%	200V	
C1512	1-106-391-12	MYLAR	0.1MF	10%	200V	
C1513	1-162-318-11	CERAMIC	0.001MF	10%	500V	
C1514	1-102-951-00	CERAMIC	15PF	5%	50V	
C1515	1-102-959-00	CERAMIC	22PF	5%	50V	
C1516	1-102-963-00	CERAMIC	33PF	5%	50V	
C1517	1-123-875-11	ELECT	10MF	20%	50V	
C1518	1-102-074-00	CERAMIC	0.001MF	10%	50V	
C1519	1-106-359-00	MYLAR	0.0047MF	10%	200V	
C1520	1-126-803-11	ELECT	47MF	20%	16V	
C1521	1-124-907-11	ELECT	10MF	20%	50V	
C1534	1-101-003-00	CERAMIC	0.0047MF		50V	
C1551	1-124-122-11	ELECT	100MF	20%	50V	
C1552	1-124-122-11	ELECT	100MF	20%	50V	
C1553	1-102-824-00	CERAMIC	470PF	5%	50V	
C1554	1-102-824-00	CERAMIC	470PF	5%	50V	
C1555	1-130-483-00	MYLAR	0.01MF	5%	50V	
C1556	1-130-483-00	MYLAR	0.01MF	5%	50V	
C1557	1-102-824-00	CERAMIC	470PF	5%	50V	
C1558	1-102-824-00	CERAMIC	470PF	5%	50V	
C1559	1-102-824-00	CERAMIC	470PF	5%	50V	
C1560	1-102-824-00	CERAMIC	470PF	5%	50V	
C1561	1-130-483-00	MYLAR	0.01MF	5%	50V	
C1562	1-130-483-00	MYLAR	0.01MF	5%	50V	
C1563	1-130-483-00	MYLAR	0.01MF	5%	50V	

<DIODE>

D1501	8-719-911-19	DIODE 1SS119	
D1502	8-719-911-19	DIODE 1SS119	
D1503	8-719-911-19	DIODE 1SS119	
D1504	8-719-911-19	DIODE 1SS119	
D1505	8-719-911-19	DIODE 1SS119	
D1506	8-719-911-19	DIODE 1SS119	
D1507	8-719-110-88	DIODE RD39ES-B2	
D1508	8-719-110-88	DIODE RD39ES-B2	
D1509	8-719-911-19	DIODE 1SS119	

<IC>

IC1551	8-759-145-58	IC UPC4558C	
IC1552	8-759-912-77	IC LM324N	

<COIL>

L1502	1-408-418-00	INDUCTOR	56UH

<TRANSISTOR>

Q1501	8-729-208-39	TRANSISTOR	2SA1306A-Y
Q1502	8-729-017-06	TRANSISTOR	2SC4793
Q1503	8-729-119-78	TRANSISTOR	2SC2785-HFE
Q1504	8-729-119-78	TRANSISTOR	2SC2785-HFE
Q1505	8-729-119-76	TRANSISTOR	2SA1175-HFE
Q1506	8-729-119-78	TRANSISTOR	2SC2785-HFE
Q1507	8-729-119-78	TRANSISTOR	2SC2785-HFE
Q1508	8-729-142-86	TRANSISTOR	2SC3733
Q1551	8-729-231-60	TRANSISTOR	2SD1406-YGR
Q1552	8-729-202-02	TRANSISTOR	2SB1015-Y
Q1553	8-729-231-60	TRANSISTOR	2SD1406-YGR
Q1554	8-729-202-02	TRANSISTOR	2SB1015-Y
Q1555	8-729-231-60	TRANSISTOR	2SD1406-YGR
Q1556	8-729-202-02	TRANSISTOR	2SB1015-Y

<RESISTOR>

REF.NO.	PART NO.	DESCRIPTION				REMARK
R1501	1-249-451-11	CARBON	2.2	5%	1/4W	F
R1502	1-249-414-11	CARBON	560	5%	1/4W	F
R1503	1-247-734-11	CARBON	39	5%	1/2W	F
R1504	1-249-384-11	CARBON	1.8	5%	1/4W	F
R1505	1-249-405-11	CARBON	100	5%	1/4W	
R1506	1-249-419-11	CARBON	1.5K	5%	1/4W	
R1507	1-249-412-11	CARBON	390	5%	1/4W	
R1508	1-249-436-11	CARBON	39K	5%	1/4W	
R1509	1-249-421-11	CARBON	2.2K	5%	1/4W	
R1510	1-249-436-11	CARBON	39K	5%	1/4W	
R1511	1-249-418-11	CARBON	1.2K	5%	1/4W	
R1512	1-249-441-11	CARBON	100K	5%	1/4W	
R1513	1-249-432-11	CARBON	18K	5%	1/4W	
R1514	1-249-405-11	CARBON	100	5%	1/4W	
R1515	1-249-435-11	CARBON	33K	5%	1/4W	
R1517	1-247-713-11	CARBON	1K	5%	1/4W	F
R1519	1-215-916-00	METAL OXIDE	680	5%	3W	F
R1520	1-249-432-11	CARBON	18K	5%	1/4W	
R1521	1-249-414-11	CARBON	560	5%	1/4W	
R1522	1-249-384-11	CARBON	1.8	5%	1/4W	F
R1523	1-249-400-11	CARBON	39	5%	1/4W	F
R1524	1-249-418-11	CARBON	1.2K	5%	1/4W	
R1525	1-249-421-11	CARBON	2.2K	5%	1/4W	
R1526	1-249-426-11	CARBON	5.6K	5%	1/4W	
R1527	1-249-414-11	CARBON	560	5%	1/4W	
R1528	1-249-429-11	CARBON	10K	5%	1/4W	
R1529	1-249-414-11	CARBON	560	5%	1/4W	
R1530	1-216-451-11	METAL OXIDE	120	5%	2W	F
R1531	1-249-429-11	CARBON	10K	5%	1/4W	
R1532	1-249-421-11	CARBON	2.2K	5%	1/4W	
R1533	1-247-903-91	CARBON	1M	5%	1/4W	
R1534	1-249-423-11	CARBON	3.3K	5%	1/4W	
R1535	1-249-392-11	CARBON	8.2	5%	1/4W	F
R1540	1-215-445-00	METAL	10K	1%	1/4W	
R1541	1-215-445-00	METAL	10K	1%	1/4W	
R1542	1-215-445-00	METAL	10K	1%	1/4W	
R1551	1-215-445-00	METAL	10K	1%	1/4W	
R1552	1-215-423-00	METAL	1.2K	1%	1/4W	
R1553	1-249-417-11	CARBON	1K	5%	1/4W	
R1554	1-215-445-00	METAL	10K	1%	1/4W	
R1555	1-215-375-00	METAL	12	1%	1/4W	
R1556	1-215-375-00	METAL	12	1%	1/4W	
R1557	1-215-375-00	METAL	12	1%	1/4W	
R1558	1-215-445-00	METAL	10K	1%	1/4W	
R1559	1-215-445-00	METAL	10K	1%	1/4W	
R1560	1-215-445-00	METAL	10K	1%	1/4W	
R1561	1-215-423-00	METAL	1.2K	1%	1/4W	
R1562	1-215-423-00	METAL	1.2K	1%	1/4W	
R1563	1-215-445-00	METAL	10K	1%	1/4W	
R1564	1-249-417-11	CARBON	1K	5%	1/4W	
R1565	1-215-445-00	METAL	10K	1%	1/4W	
R1566	1-215-375-00	METAL	12	1%	1/4W	
R1567	1-215-375-00	METAL	12	1%	1/4W	
R1568	1-215-375-00	METAL	12	1%	1/4W	
R1569	1-215-445-00	METAL	10K	1%	1/4W	
R1570	1-215-445-00	METAL	10K	1%	1/4W	
R1571	1-249-417-11	CARBON	1K	5%	1/4W	
R1572	1-215-445-00	METAL	10K	1%	1/4W	

V D

REF.NO.	PART NO.	DESCRIPTION				REMARK
R1573	1-215-375-00	METAL	12	1%	1/4W	
R1574	1-215-375-00	METAL	12	1%	1/4W	
R1575	1-215-375-00	METAL	12	1%	1/4W	
R1576	1-215-445-00	METAL	10K	1%	1/4W	
R1577	1-215-445-00	METAL	10K	1%	1/4W	
R1578	1-249-417-11	CARBON	1K	5%	1/4W	
R1579	1-249-417-11	CARBON	1K	5%	1/4W	
R1580	1-249-417-11	CARBON	1K	5%	1/4W	
R1581	1-249-432-11	CARBON	18K	5%	1/4W	
R1582	1-249-432-11	CARBON	18K	5%	1/4W	
		<CONNECTOR>				
V2	*1-564-518-11	PLUG, CONNECTOR 3P				
V22	1-573-300-11	CONNECTOR, BOARD TO BOARD 18P				
**********						
	*A-1346-117-A	D BOARD, COMPLETE				
		**********				
	1-533-223-11	CLIP, FUSE				
	4-382-854-11	SCREW (M3X10), P, SW (+)				
	*4-395-527-01	HOLDER (B), TR				
		<CAPACITOR>				
C901	1-126-320-11	ELECT	10MF	20%	16V	
C902	1-124-477-11	ELECT	47MF	20%	16V	
C903	1-130-471-00	MYLAR	0.001MF	5%	50V	
C904	1-130-471-00	MYLAR	0.001MF	5%	50V	
C905	1-124-477-11	ELECT	47MF	20%	16V	
C906	1-126-233-11	ELECT	22MF	20%	50V	
C907	1-126-101-11	ELECT	100MF	20%	16V	
C908	1-124-907-11	ELECT	10MF	20%	50V	
C910	1-130-483-00	MYLAR	0.01MF	5%	50V	
C911	1-131-341-00	TANTALUM	0.1MF	20%	16V	
C912	1-124-903-11	ELECT	1MF	20%	50V	
C913	1-126-233-11	ELECT	22MF	20%	50V	
C914	1-126-803-11	ELECT	47MF	20%	16V	
C915	1-124-927-11	ELECT	4.7MF	20%	50V	
C916	1-102-074-00	CERAMIC	0.001MF	10%	50V	
C917	1-130-471-00	MYLAR	0.001MF	5%	50V	
C918	1-102-963-00	CERAMIC	33PF	5%	50V	
C919	1-102-963-00	CERAMIC	33PF	5%	50V	
C920	1-102-963-00	CERAMIC	33PF	5%	50V	
C921	1-102-963-00	CERAMIC	33PF	5%	50V	
C922	1-102-963-00	CERAMIC	33PF	5%	50V	
C923	1-102-963-00	CERAMIC	33PF	5%	50V	
C931	1-102-973-00	CERAMIC	100PF	5%	50V	
C932	1-124-903-11	ELECT	1MF	20%	50V	
C933	1-124-234-00	ELECT	22MF	20%	16V	
C934	1-124-234-00	ELECT	22MF	20%	16V	
C935	1-124-234-00	ELECT	22MF	20%	16V	
C936	1-124-234-00	ELECT	22MF	20%	16V	
C937	1-124-234-00	ELECT	22MF	20%	16V	
C938	1-124-234-00	ELECT	22MF	20%	16V	
C939	1-124-234-00	ELECT	22MF	20%	16V	
C940	1-124-916-11	ELECT	22MF	20%	25V	
C941	1-102-123-00	CERAMIC	0.0033MF	10%	50V	
C942	1-102-123-00	CERAMIC	0.0033MF	10%	50V	
C943	1-102-123-00	CERAMIC	0.0033MF	10%	50V	
C1701	1-124-907-11	ELECT	10MF	20%	50V	
C1702	1-124-907-11	ELECT	10MF	20%	50V	
C1703	1-124-907-11	ELECT	10MF	20%	50V	
C1704	1-123-875-11	ELECT	10MF	20%	50V	
C1705	1-102-963-00	CERAMIC	33PF	5%	50V	
C1706	1-102-963-00	CERAMIC	33PF	5%	50V	
C1707	1-102-963-00	CERAMIC	33PF	5%	50V	
C1708	1-102-963-00	CERAMIC	33PF	5%	50V	
C1709	1-102-963-00	CERAMIC	33PF	5%	50V	
C1710	1-102-963-00	CERAMIC	33PF	5%	50V	
C1711	1-126-233-11	ELECT	22MF	20%	50V	
C1712	1-124-916-11	ELECT	22MF	20%	25V	
C1713	1-102-074-00	CERAMIC	0.001MF	10%	50V	
C1714	1-124-478-11	ELECT	100MF	20%	25V	
C1715	1-124-478-11	ELECT	100MF	20%	25V	
C1716	1-126-803-11	ELECT	47MF	20%	25V	
C1717	1-126-803-11	ELECT	47MF	20%	25V	
C1718	1-102-074-00	CERAMIC	0.001MF	10%	50V	
C1719	1-124-234-00	ELECT	22MF	20%	16V	
C1720	1-130-491-00	MYLAR	0.047MF	5%	50V	
C1721	1-130-491-00	MYLAR	0.047MF	5%	50V	
C1722	1-130-491-00	MYLAR	0.047MF	5%	50V	
C1724	1-124-234-00	ELECT	22MF	20%	16V	
C1725	1-102-963-00	CERAMIC	33PF	5%	50V	
C1726	1-124-122-11	ELECT	100MF	20%	35V	
C1727	1-102-963-00	CERAMIC	33PF	5%	50V	
C1728	1-102-963-00	CERAMIC	33PF	5%	50V	
C1729	1-108-426-91	MYLAR	0.027MF		200V	
C1730	1-102-963-00	CERAMIC	33PF	5%	50V	
C1731	1-124-122-11	ELECT	100MF	20%	35V	
C1732	1-108-426-91	MYLAR	0.027MF		200V	
C1733	1-102-963-00	CERAMIC	33PF	5%	50V	
C1734	1-102-963-00	CERAMIC	33PF	5%	50V	
C1735	1-124-122-11	ELECT	100MF	20%	35V	
C1736	1-108-426-91	MYLAR	0.027MF		200V	
C1737	1-124-937-11	ELECT	10MF	20%	16V	
C1738	1-124-122-11	ELECT	100MF	20%	35V	
C1739	1-136-153-00	FILM	0.01MF	5%	50V	
C1740	1-124-122-11	ELECT	100MF	20%	35V	
C1741	1-124-122-11	ELECT	100MF	20%	35V	
C1742	1-126-104-11	ELECT	470MF	20%	35V	
C1744	1-124-478-11	ELECT	100MF	20%	25V	
C1745	1-126-375-11	ELECT	100MF	20%	25V	
C1755	1-106-220-00	MYLAR	0.1MF	10%	100V	
C1756	1-106-220-00	MYLAR	0.1MF	10%	100V	
C1757	1-106-220-00	MYLAR	0.1MF	10%	100V	
C1758	1-106-220-00	MYLAR	0.1MF	10%	100V	
C1759	1-106-220-00	MYLAR	0.1MF	10%	100V	
C1760	1-106-220-00	MYLAR	0.1MF	10%	100V	
C1763	1-126-096-11	ELECT	10MF	20%	25V	
C1764	1-124-477-11	ELECT	47MF	20%	16V	
C1765	1-124-477-11	ELECT	47MF	20%	16V	
C1766	1-126-101-11	ELECT	100MF	20%	16V	
C1769	1-126-157-11	ELECT	10MF	20%	16V	
C1770	1-130-495-00	MYLAR	0.1MF	5%	50V	
C1771	1-126-096-11	ELECT	10MF	20%	25V	
C1772	1-126-096-11	ELECT	10MF	20%	25V	
C1861	1-102-074-00	CERAMIC	0.001MF	10%	50V	
		<CONNECTOR>				
D1	*1-564-510-11	PLUG, CONNECTOR 7P				
D2	*1-564-511-11	PLUG, CONNECTOR 8P				
D3	*1-564-512-11	PLUG, CONNECTOR 9P				
D4	*1-564-508-11	PLUG, CONNECTOR 5P				
D5	*1-564-511-11	PLUG, CONNECTOR 8P				
D6	1-691-169-11	PIN, CONNECTOR 12P				

The components identified by shading and mark ⚠ are critical for safety.
Replace only with part number specified.

Les composants identifies par une trame et une marque ⚠ sont critiques pour la securite.
Ne les remplacer que par une piece portant le numero specifie.

REF.NO.	PART NO.	DESCRIPTION	REMARK
D7	*1-564-507-11	PLUG, CONNECTOR 4P	
D8	*1-564-506-11	PLUG, CONNECTOR 3P	
D9	*1-564-507-11	PLUG, CONNECTOR 4P	
D14	*1-564-513-31	PLUG, CONNECTOR 10P	
		<DIODE>	
D901	8-719-911-19	DIODE 1SS119	
D902	8-719-911-19	DIODE 1SS119	
D1701	8-719-900-95	DIODE V09G	
D1702	8-719-911-19	DIODE 1SS119	
D1703	8-719-900-95	DIODE V09G	
D1704	8-719-900-95	DIODE V09G	
D1705	8-719-900-95	DIODE V09G	
D1706	8-719-900-95	DIODE V09G	
D1707	8-719-911-19	DIODE 1SS119	
D1708	8-719-911-19	DIODE 1SS119	
D1709	8-719-911-19	DIODE 1SS119	
D1710	8-719-911-19	DIODE 1SS119	
D1711	8-719-911-19	DIODE 1SS119	
D1712	8-719-911-19	DIODE 1SS119	
D1713	8-719-911-19	DIODE 1SS119	
D1714	8-719-911-19	DIODE 1SS119	
D1715	8-719-911-19	DIODE 1SS119	
D1716	8-719-911-19	DIODE 1SS119	
D1717	8-719-911-19	DIODE 1SS119	
D1718	8-719-911-19	DIODE 1SS119	
D1720	8-719-109-50	DIODE RD2.0ES-B1	
D1721	8-719-109-50	DIODE RD2.0ES-B1	
D1722	8-719-109-50	DIODE RD2.0ES-B1	
D1723	8-719-109-50	DIODE RD2.0ES-B1	
		<FUSE>	
F901 ⚠	1-532-745-11	FUSE, GLASS TUBE 3.15A/125V	
F902 ⚠	1-532-745-11	FUSE, GLASS TUBE 3.15A/125V	
		<IC>	
IC901	8-759-145-58	IC UPC4558C	
IC902	8-752-033-68	IC CXA1268P	
IC903	8-759-701-56	IC NJM78M05FA	
IC904	8-759-701-65	IC NJM79M05FA	
IC905	8-759-701-89	IC NJM7915FA	
IC906	8-759-148-84	IC UPC2415HF	
IC907	8-759-140-53	IC UPD4053BC	
IC908	8-759-145-58	IC UPC4558C	
IC910	8-759-054-40	IC PA0036	
IC1701	8-759-602-19	IC M5220L	
IC1702	8-759-602-19	IC M5220L	
IC1703	8-759-602-19	IC M5220L	
IC1704	8-749-923-16	IC STK4278-L	
IC1705	8-749-923-16	IC STK4278-L	
IC1706	8-759-113-13	IC UPC1498H	
IC1707	8-759-113-13	IC UPC1498H	
IC1708	8-759-113-13	IC UPC1498H	
IC1709	8-759-145-58	IC UPC4558C	
IC1710	8-759-145-58	IC UPC4558C	
IC1714	8-759-145-58	IC UPC4558C	
IC1715	8-759-145-58	IC UPC4558C	
IC1718	8-759-145-58	IC UPC4558C	

REF.NO.	PART NO.	DESCRIPTION	REMARK
		<COIL>	
L901	1-459-313-00	COIL WITH CORE (HWC)	
L902	1-459-313-00	COIL WITH CORE (HWC)	
L903	1-459-313-00	COIL WITH CORE (HWC)	
L904	1-459-313-00	COIL WITH CORE (HWC)	
		<TRANSISTOR>	
Q902	8-729-900-89	TRANSISTOR DTC144ES	
Q906	8-729-119-78	TRANSISTOR 2SC2785-HFE	
Q907	8-729-119-78	TRANSISTOR 2SC2785-HFE	
Q908	8-729-900-89	TRANSISTOR DTC144ES	
Q909	8-729-119-78	TRANSISTOR 2SC2785-HFE	
Q910	8-729-119-78	TRANSISTOR 2SC2785-HFE	
Q911	8-729-119-76	TRANSISTOR 2SA1175-HFE	
Q912	8-729-119-76	TRANSISTOR 2SA1175-HFE	
		<RESISTOR>	
R901	1-215-463-00	METAL 56K 1% 1/4W	
R902	1-215-463-00	METAL 56K 1% 1/4W	
R903	1-215-449-00	METAL 15K 1% 1/4W	
R904	1-215-455-00	METAL 27K 1% 1/4W	
R905	1-215-449-00	METAL 15K 1% 1/4W	
R906	1-215-469-00	METAL 100K 1% 1/4W	
R907	1-215-469-00	METAL 100K 1% 1/4W	
R908	1-215-469-00	METAL 100K 1% 1/4W	
R909	1-215-473-00	METAL 150K 1% 1/4W	
R910	1-215-437-00	METAL 4.7K 1% 1/4W	
R911	1-215-453-00	METAL 22K 1% 1/4W	
R912	1-215-453-00	METAL 22K 1% 1/4W	
R913	1-215-437-00	METAL 4.7K 1% 1/4W	
R914	1-215-453-00	METAL 22K 1% 1/4W	
R915	1-215-413-00	METAL 470 1% 1/4W	
R916	1-215-457-00	METAL 33K 1% 1/4W	
R917	1-215-453-00	METAL 22K 1% 1/4W	
R919	1-215-399-00	METAL 120 1% 1/4W	
R920	1-215-399-00	METAL 120 1% 1/4W	
R921	1-215-399-00	METAL 120 1% 1/4W	
R922	1-215-399-00	METAL 120 1% 1/4W	
R923	1-215-441-00	METAL 6.8K 1% 1/4W	
R924	1-215-441-00	METAL 6.8K 1% 1/4W	
R925	1-215-441-00	METAL 6.8K 1% 1/4W	
R926	1-215-463-00	METAL 56K 1% 1/4W	
R927	1-215-463-00	METAL 56K 1% 1/4W	
R928	1-215-461-00	METAL 47K 1% 1/4W	
R929	1-215-433-00	METAL 3.3K 1% 1/4W	
R930	1-215-433-00	METAL 3.3K 1% 1/4W	
R931	1-215-433-00	METAL 3.3K 1% 1/4W	
R932	1-215-433-00	METAL 3.3K 1% 1/4W	
R933	1-215-433-00	METAL 3.3K 1% 1/4W	
R934	1-215-433-00	METAL 3.3K 1% 1/4W	
R935	1-215-439-00	METAL 5.6K 1% 1/4W	
R936	1-215-439-00	METAL 5.6K 1% 1/4W	
R937	1-215-439-00	METAL 5.6K 1% 1/4W	
R938	1-215-417-00	METAL 680 1% 1/4W	
R939	1-215-433-00	METAL 3.3K 1% 1/4W	
R940	1-215-429-00	METAL 2.2K 1% 1/4W	
R941	1-215-441-00	METAL 6.8K 1% 1/4W	
R942	1-215-451-00	METAL 18K 1% 1/4W	
R943	1-215-441-00	METAL 6.8K 1% 1/4W	
R944	1-215-439-00	METAL 5.6K 1% 1/4W	
R945	1-215-445-00	METAL 10K 1% 1/4W	
R946	1-215-445-00	METAL 10K 1% 1/4W	
R947	1-215-439-00	METAL 5.6K 1% 1/4W	

D

REF.NO.	PART NO.	DESCRIPTION				REMARK
R948	1-215-447-00	METAL	12K	1%	1/4W	
R949	1-215-439-00	METAL	5.6K	1%	1/4W	
R950	1-215-429-00	METAL	2.2K	1%	1/4W	
R951	1-215-429-00	METAL	2.2K	1%	1/4W	
R952	1-215-429-00	METAL	2.2K	1%	1/4W	
R953	1-215-439-00	METAL	5.6K	1%	1/4W	
R954	1-215-439-00	METAL	5.6K	1%	1/4W	
R955	1-215-435-00	METAL	3.9K	1%	1/4W	
R956	1-215-437-00	METAL	4.7K	1%	1/4W	
R957	1-215-441-00	METAL	6.8K	1%	1/4W	
R958	1-215-437-00	METAL	4.7K	1%	1/4W	
R959	1-215-439-00	METAL	5.6K	1%	1/4W	
R960	1-215-439-00	METAL	5.6K	1%	1/4W	
R961	1-215-439-00	METAL	5.6K	1%	1/4W	
R962	1-215-441-00	METAL	6.8K	1%	1/4W	
R963	1-215-441-00	METAL	6.8K	1%	1/4W	
R964	1-215-441-00	METAL	6.8K	1%	1/4W	
R965	1-215-909-11	METAL OXIDE	47	5%	3W	F
R966	1-215-469-00	METAL	100K	1%	1/4W	
R967	1-215-421-00	METAL	1K	1%	1/4W	
R968	1-215-437-00	METAL	4.7K	1%	1/4W	
R969	1-249-421-11	CARBON	2.2K	5%	1/4W	
R970	1-215-909-11	METAL OXIDE	47	5%	3W	F
R971	1-249-421-11	CARBON	2.2K	5%	1/4W	
R972	1-249-431-11	CARBON	15K	5%	1/4W	
R973	1-249-431-11	CARBON	15K	5%	1/4W	
R974	1-215-399-00	METAL	120	1%	1/4W	
R975	1-215-399-00	METAL	120	1%	1/4W	
R976	1-215-399-00	METAL	120	1%	1/4W	
R977	1-215-399-00	METAL	120	1%	1/4W	
R978	1-215-399-00	METAL	120	1%	1/4W	
R979	1-215-399-00	METAL	120	1%	1/4W	
R980	1-215-399-00	METAL	120	1%	1/4W	
R981	1-215-399-00	METAL	120	1%	1/4W	
R982	1-249-431-11	CARBON	15K	5%	1/4W	
R983	1-249-431-11	CARBON	15K	5%	1/4W	
R984	1-214-804-11	METAL	3.3	1%	1/2W	
R985	1-214-804-11	METAL	3.3	1%	1/2W	
R986	1-214-804-11	METAL	3.3	1%	1/2W	
R987	1-215-421-00	METAL	1K	1%	1/4W	
R988	1-215-421-00	METAL	1K	1%	1/4W	
R989	1-215-421-00	METAL	1K	1%	1/4W	
R990	1-215-421-00	METAL	1K	1%	1/4W	
R991	1-215-421-00	METAL	1K	1%	1/4W	
R992	1-215-421-00	METAL	1K	1%	1/4W	
R993	1-249-429-11	CARBON	10K	5%	1/4W	
R994	1-249-429-11	CARBON	10K	5%	1/4W	
R995	1-215-457-00	METAL	33K	1%	1/4W	
R997	1-215-463-00	METAL	56K	1%	1/4W	
R998	1-215-409-00	METAL	330	1%	1/4W	
R999	1-215-455-00	METAL	27K	1%	1/4W	
R1701	1-249-411-11	CARBON	330	5%	1/4W	
R1702	1-249-427-11	CARBON	6.8K	5%	1/4W	
R1703	1-249-427-11	CARBON	6.8K	5%	1/4W	
R1704	1-249-411-11	CARBON	330	5%	1/4W	
R1705	1-249-411-11	CARBON	330	5%	1/4W	
R1706	1-249-427-11	CARBON	6.8K	5%	1/4W	
R1707	1-249-411-11	CARBON	330	5%	1/4W	
R1708	1-249-427-11	CARBON	6.8K	5%	1/4W	
R1709	1-249-427-11	CARBON	6.8K	5%	1/4W	
R1710	1-249-411-11	CARBON	330	5%	1/4W	
R1711	1-249-411-11	CARBON	330	5%	1/4W	
R1712	1-249-427-11	CARBON	6.8K	5%	1/4W	
R1713	1-215-886-11	METAL OXIDE	100	5%	2W	F

REF.NO.	PART NO.	DESCRIPTION				REMARK
R1714	1-249-411-11	CARBON	330	5%	1/4W	
R1715	1-249-411-11	CARBON	330	5%	1/4W	
R1716	1-215-886-11	METAL OXIDE	100	5%	2W	F
R1717	1-249-411-11	CARBON	330	5%	1/4W	
R1718	1-249-417-11	CARBON	1K	5%	1/4W	
R1719	1-214-792-00	METAL	1	1%	1/2W	
R1720	1-249-411-11	CARBON	330	5%	1/4W	
R1721	1-249-417-11	CARBON	1K	5%	1/4W	
R1722	1-249-411-11	CARBON	330	5%	1/4W	
R1723	1-249-417-11	CARBON	1K	5%	1/4W	
R1724	1-215-886-11	METAL OXIDE	100	5%	2W	F
R1725	1-215-886-11	METAL OXIDE	100	5%	2W	F
R1726	1-215-886-11	METAL OXIDE	100	5%	2W	F
R1727	1-214-792-00	METAL	1	1%	1/2W	
R1728	1-214-792-00	METAL	1	1%	1/2W	
R1729	1-214-792-00	METAL	1	1%	1/2W	
R1730	1-249-405-11	CARBON	100	5%	1/4W	
R1731	1-249-417-11	CARBON	1K	5%	1/4W	
R1732	1-249-405-11	CARBON	100	5%	1/4W	
R1733	1-249-405-11	CARBON	100	5%	1/4W	
R1734	1-249-405-11	CARBON	100	5%	1/4W	
R1735	1-249-405-11	CARBON	100	5%	1/4W	
R1736	1-249-423-11	CARBON	3.3K	5%	1/4W	
R1737	1-249-423-11	CARBON	3.3K	5%	1/4W	
R1738	1-249-423-11	CARBON	3.3K	5%	1/4W	
R1739	1-249-423-11	CARBON	3.3K	5%	1/4W	
R1740	1-249-417-11	CARBON	1K	5%	1/4W	
R1741	1-249-423-11	CARBON	3.3K	5%	1/4W	
R1742	1-249-423-11	CARBON	3.3K	5%	1/4W	
R1743	1-249-417-11	CARBON	1K	5%	1/4W	
R1744	1-249-411-11	CARBON	330	5%	1/4W	
R1745	1-249-405-11	CARBON	100	5%	1/4W	
R1746	1-214-792-00	METAL	1	1%	1/2W	
R1747	1-215-886-11	METAL OXIDE	100	5%	2W	F
R1748	1-215-421-00	METAL	1K	1%	1/4W	
R1749	1-215-421-00	METAL	1K	1%	1/4W	
R1750	1-215-421-00	METAL	1K	1%	1/4W	
R1751	1-215-421-00	METAL	1K	1%	1/4W	
R1752	1-215-421-00	METAL	1K	1%	1/4W	
R1753	1-215-421-00	METAL	1K	1%	1/4W	
R1754	1-214-792-00	METAL	1	1%	1/2W	
R1755	1-215-469-00	METAL	100K	1%	1/4W	
R1756	1-215-437-00	METAL	4.7K	1%	1/4W	
R1757	1-215-437-00	METAL	4.7K	1%	1/4W	
R1758	1-215-437-00	METAL	4.7K	1%	1/4W	
R1759	1-249-405-11	CARBON	100	5%	1/4W	
R1760	1-249-427-11	CARBON	6.8K	5%	1/4W	
R1761	1-249-419-11	CARBON	1.5K	5%	1/4W	
R1762	1-215-445-00	METAL	10K	1%	1/4W	
R1763	1-249-427-11	CARBON	6.8K	5%	1/4W	
R1764	1-249-419-11	CARBON	1.5K	5%	1/4W	
R1765	1-249-419-11	CARBON	1.5K	5%	1/4W	
R1766	1-249-427-11	CARBON	6.8K	5%	1/4W	
R1767	1-249-427-11	CARBON	6.8K	5%	1/4W	
R1768	1-249-439-11	CARBON	68K	5%	1/4W	
R1769	1-215-445-00	METAL	10K	1%	1/4W	
R1770	1-249-405-11	CARBON	100	5%	1/4W	
R1771	1-249-405-11	CARBON	100	5%	1/4W	
R1772	1-215-429-00	METAL	2.2K	1%	1/4W	
R1773	1-215-429-00	METAL	2.2K	1%	1/4W	
R1774	1-215-421-00	METAL	1K	1%	1/4W	
R1775	1-249-429-11	CARBON	10K	5%	1/4W	
R1776	1-215-421-00	METAL	1K	1%	1/4W	

REF.NO.	PART NO.	DESCRIPTION				REMARK
R1777	1-249-423-11	CARBON	3.3K	5%	1/4W	
R1778	1-215-421-00	METAL	1K	1%	1/4W	
R1779	1-215-898-11	METAL OXIDE	10K	5%	2W	F
R1780	1-214-804-11	METAL	3.3	1%	1/2W	
R1781	1-214-804-11	METAL	3.3	1%	1/2W	
R1782	1-215-898-11	METAL OXIDE	10K	5%	2W	F
R1783	1-214-804-11	METAL	3.3	1%	1/2W	
R1784	1-214-804-11	METAL	3.3	1%	1/2W	
R1785	1-215-898-11	METAL OXIDE	10K	5%	2W	F
R1786	1-214-804-11	METAL	3.3	1%	1/2W	
R1787	1-214-804-11	METAL	3.3	1%	1/2W	
R1788	1-249-433-11	CARBON	22K	5%	1/4W	
R1789	1-249-441-11	CARBON	100K	5%	1/4W	
R1790	1-249-433-11	CARBON	22K	5%	1/4W	
R1791	1-249-429-11	CARBON	10K	5%	1/4W	
R1792	1-215-445-00	METAL	10K	1%	1/4W	
R1793	1-249-405-11	CARBON	100	5%	1/4W	
R1794	1-215-429-00	METAL	2.2K	1%	1/4W	
R1795	1-249-433-11	CARBON	22K	5%	1/4W	
R1796	1-249-405-11	CARBON	100	5%	1/4W	
R1797	1-249-429-11	CARBON	10K	5%	1/4W	
R1798	1-249-423-11	CARBON	3.3K	5%	1/4W	
R1800	1-249-405-11	CARBON	100	5%	1/4W	
R1801	1-215-439-00	METAL	5.6K	1%	1/4W	
R1802	1-215-439-00	METAL	5.6K	1%	1/4W	
R1803	1-215-439-00	METAL	5.6K	1%	1/4W	
R1805	1-215-439-00	METAL	5.6K	1%	1/4W	
R1806	1-249-405-11	CARBON	100	5%	1/4W	
R1807	1-249-405-11	CARBON	100	5%	1/4W	
R1808	1-214-792-00	METAL	1	1%	1/2W	
R1809	1-214-792-00	METAL	1	1%	1/2W	
R1810	1-214-792-00	METAL	1	1%	1/2W	
R1811	1-214-792-00	METAL	1	1%	1/2W	
R1812	1-214-792-00	METAL	1	1%	1/2W	
R1813	1-214-792-00	METAL	1	1%	1/2W	
R1814	1-249-431-11	CARBON	15K	5%	1/4W	
R1815	1-247-885-00	CARBON	180K	5%	1/4W	
R1816	1-249-431-11	CARBON	15K	5%	1/4W	
R1817	1-247-885-00	CARBON	180K	5%	1/4W	
R1818	1-249-405-11	CARBON	100	5%	1/4W	
R1819	1-215-437-00	METAL	4.7K	1%	1/4W	
R1820	1-215-437-00	METAL	4.7K	1%	1/4W	
R1821	1-215-437-00	METAL	4.7K	1%	1/4W	
R1822	1-215-445-00	METAL	10K	1%	1/4W	
R1823	1-215-445-00	METAL	10K	1%	1/4W	
R1824	1-215-433-00	METAL	3.3K	1%	1/4W	
R1825	1-215-433-00	METAL	3.3K	1%	1/4W	
R1826	1-215-433-00	METAL	3.3K	1%	1/4W	
R1827	1-215-445-00	METAL	10K	1%	1/4W	
R1828	1-215-445-00	METAL	10K	1%	1/4W	
R1829	1-249-434-11	CARBON	27K	5%	1/4W	
R1830	1-249-434-11	CARBON	27K	5%	1/4W	
R1831	1-249-405-11	CARBON	100	5%	1/4W	
R1832	1-215-471-00	METAL	120K	1%	1/4W	
R1833	1-215-471-00	METAL	120K	1%	1/4W	
R1834	1-215-471-00	METAL	120K	1%	1/4W	
R1835	1-215-437-00	METAL	4.7K	1%	1/4W	
R1836	1-215-437-00	METAL	4.7K	1%	1/4W	
R1837	1-215-421-00	METAL	1K	1%	1/4W	
R1838	1-249-431-11	CARBON	15K	5%	1/4W	
R1839	1-249-431-11	CARBON	15K	5%	1/4W	
R1858	1-215-445-00	METAL	10K	1%	1/4W	
R1859	1-215-445-00	METAL	10K	1%	1/4W	
R1860	1-215-397-00	METAL	100	1%	1/4W	

REF.NO.	PART NO.	DESCRIPTION				REMARK
R1861	1-215-453-00	METAL	22K	1%	1/4W	
R1862	1-215-453-00	METAL	22K	1%	1/4W	
R1863	1-215-397-00	METAL	100	1%	1/4W	
R1864	1-215-437-00	METAL	4.7K	1%	1/4W	
R1865	1-215-453-00	METAL	22K	1%	1/4W	
R1866	1-215-453-00	METAL	22K	1%	1/4W	
R1867	1-215-437-00	METAL	4.7K	1%	1/4W	
R1868	1-215-439-00	METAL	5.6K	1%	1/4W	
R1869	1-215-445-00	METAL	10K	1%	1/4W	
R1870	1-215-445-00	METAL	10K	1%	1/4W	
R1871	1-215-445-00	METAL	10K	1%	1/4W	
R1872	1-215-437-00	METAL	4.7K	1%	1/4W	
R1873	1-215-437-00	METAL	4.7K	1%	1/4W	
R1874	1-215-437-00	METAL	4.7K	1%	1/4W	
R1875	1-215-437-00	METAL	4.7K	1%	1/4W	
R1876	1-215-437-00	METAL	4.7K	1%	1/4W	
R1877	1-215-437-00	METAL	4.7K	1%	1/4W	
R1878	1-215-475-00	METAL	180K	1%	1/4W	
R1879	1-215-475-00	METAL	180K	1%	1/4W	
R1880	1-215-475-00	METAL	180K	1%	1/4W	
R1881	1-215-461-00	METAL	47K	1%	1/4W	
R1882	1-215-445-00	METAL	10K	1%	1/4W	
R1883	1-215-453-00	METAL	22K	1%	1/4W	
R1884	1-215-397-00	METAL	100	1%	1/4W	
R1885	1-215-445-00	METAL	10K	1%	1/4W	
R1886	1-215-445-00	METAL	10K	1%	1/4W	
R1887	1-215-397-00	METAL	100	1%	1/4W	
R1888	1-215-461-00	METAL	47K	1%	1/4W	
R1889	1-215-457-00	METAL	33K	1%	1/4W	
R1890	1-215-457-00	METAL	33K	1%	1/4W	
R1891	1-215-443-00	METAL	8.2K	1%	1/4W	
R1892	1-215-445-00	METAL	10K	1%	1/4W	
R1894	1-215-429-00	METAL	2.2K	1%	1/4W	
R1895	1-215-445-00	METAL	10K	1%	1/4W	
R1896	1-215-445-00	METAL	10K	1%	1/4W	
R1897	1-215-449-00	METAL	15K	1%	1/4W	
R1898	1-215-445-00	METAL	10K	1%	1/4W	
R1899	1-215-421-00	METAL	1K	1%	1/4W	
R1900	1-215-429-00	METAL	2.2K	1%	1/4W	
R1901	1-215-449-00	METAL	15K	1%	1/4W	
R1902	1-215-445-00	METAL	10K	1%	1/4W	
R1903	1-215-445-00	METAL	10K	1%	1/4W	
R1904	1-215-445-00	METAL	10K	1%	1/4W	
R1905	1-215-445-00	METAL	10K	1%	1/4W	
R1906	1-215-429-00	METAL	2.2K	1%	1/4W	
R1907	1-215-445-00	METAL	10K	1%	1/4W	
R1908	1-215-445-00	METAL	10K	1%	1/4W	
R1909	1-215-445-00	METAL	10K	1%	1/4W	
R1910	1-215-445-00	METAL	10K	1%	1/4W	
R1911	1-215-453-00	METAL	22K	1%	1/4W	
R1916	1-215-423-00	METAL	1.2K	1%	1/4W	
R1920	1-215-453-00	METAL	22K	1%	1/4W	
R1921	1-215-445-00	METAL	10K	1%	1/4W	
R1922	1-215-445-00	METAL	10K	1%	1/4W	
R1924	1-215-429-00	METAL	2.2K	1%	1/4W	
R1925	1-215-429-00	METAL	2.2K	1%	1/4W	
R1926	1-215-429-00	METAL	2.2K	1%	1/4W	
R1927	1-215-445-00	METAL	10K	1%	1/4W	
R1928	1-215-421-00	METAL	1K	1%	1/4W	
R1929	1-215-445-00	METAL	10K	1%	1/4W	
R1930	1-215-397-00	METAL	100	1%	1/4W	
R1931	1-215-397-00	METAL	100	1%	1/4W	
R1932	1-215-453-00	METAL	22K	1%	1/4W	

D DS

REF.NO.	PART NO.	DESCRIPTION				REMARK
R1933	1-215-453-00	METAL	22K	1%	1/4W	
R1934	1-215-429-00	METAL	2.2K	1%	1/4W	
R1937	1-215-445-00	METAL	10K	1%	1/4W	
		<VARIABLE RESISTOR>				
RV901	1-241-631-11	RES, ADJ, CARBON 22K				
RV902	1-241-631-11	RES, ADJ, CARBON 22K				
RV903	1-241-631-11	RES, ADJ, CARBON 22K				
RV904	1-241-631-11	RES, ADJ, CARBON 22K				
RV905	1-241-631-11	RES, ADJ, CARBON 22K				
RV906	1-241-631-11	RES, ADJ, CARBON 22K				
RV907	1-241-631-11	RES, ADJ, CARBON 22K				
RV908	1-241-631-11	RES, ADJ, CARBON 22K				
RV909	1-241-631-11	RES, ADJ, CARBON 22K				
RV910	1-241-631-11	RES, ADJ, CARBON 22K				
RV911	1-241-627-11	RES, ADJ, CARBON 1K				
RV912	1-241-631-11	RES, ADJ, CARBON 22K				
RV913	1-238-023-11	RES, ADJ, CARBON 470K				
RV914	1-241-630-11	RES, ADJ, CARBON 10K				
RV915	1-241-630-11	RES, ADJ, CARBON 10K				
RV916	1-241-631-11	RES, ADJ, CARBON 22K				
RV917	1-241-631-11	RES, ADJ, CARBON 22K				
RV918	1-241-631-11	RES, ADJ, CARBON 22K				
RV919	1-241-631-11	RES, ADJ, CARBON 22K				
RV920	1-241-631-11	RES, ADJ, CARBON 22K				
RV921	1-241-631-11	RES, ADJ, CARBON 22K				
RV922	1-241-631-11	RES, ADJ, CARBON 22K				
RV923	1-241-631-11	RES, ADJ, CARBON 22K				
RV924	1-241-631-11	RES, ADJ, CARBON 22K				
RV925	1-241-631-11	RES, ADJ, CARBON 22K				
RV926	1-241-631-11	RES, ADJ, CARBON 22K				
RV927	1-241-631-11	RES, ADJ, CARBON 22K				
RV928	1-241-630-11	RES, ADJ, CARBON 10K				
RV929	1-241-631-11	RES, ADJ, CARBON 22K				
RV930	1-241-630-11	RES, ADJ, CARBON 10K				
RV931	1-241-631-11	RES, ADJ, CARBON 22K				
RV932	1-241-631-11	RES, ADJ, CARBON 22K				
RV933	1-241-631-11	RES, ADJ, CARBON 22K				
RV934	1-241-631-11	RES, ADJ, CARBON 22K				
RV935	1-241-631-11	RES, ADJ, CARBON 22K				
RV936	1-241-631-11	RES, ADJ, CARBON 22K				
RV937	1-241-630-11	RES, ADJ, CARBON 10K				
RV938	1-241-630-11	RES, ADJ, CARBON 10K				
RV939	1-241-630-11	RES, ADJ, CARBON 10K				
RV940	1-241-631-11	RES, ADJ, CARBON 22K				
RV941	1-241-631-11	RES, ADJ, CARBON 22K				
RV942	1-241-631-11	RES, ADJ, CARBON 22K				
RV943	1-241-631-11	RES, ADJ, CARBON 22K				
RV944	1-241-631-11	RES, ADJ, CARBON 22K				
RV945	1-241-631-11	RES, ADJ, CARBON 22K				
RV946	1-241-631-11	RES, ADJ, CARBON 22K				
RV947	1-241-631-11	RES, ADJ, CARBON 22K				
RV948	1-241-631-11	RES, ADJ, CARBON 22K				
RV949	1-241-631-11	RES, ADJ, CARBON 22K				
RV950	1-241-631-11	RES, ADJ, CARBON 22K				
RV951	1-241-631-11	RES, ADJ, CARBON 22K				
RV952	1-241-631-11	RES, ADJ, CARBON 22K				
RV953	1-241-631-11	RES, ADJ, CARBON 22K				
RV954	1-241-631-11	RES, ADJ, CARBON 22K				
RV956	1-241-631-11	RES, ADJ, CARBON 22K				
RV957	1-241-631-11	RES, ADJ, CARBON 22K				
RV958	1-241-631-11	RES, ADJ, CARBON 22K				
RV959	1-241-631-11	RES, ADJ, CARBON 22K				
RV960	1-241-630-11	RES, ADJ, CARBON 10K				
RV961	1-241-631-11	RES, ADJ, CARBON 22K				
RV962	1-241-631-11	RES, ADJ, CARBON 22K				
RV963	1-241-631-11	RES, ADJ, CARBON 22K				
RV964	1-241-631-11	RES, ADJ, CARBON 22K				
RV965	1-241-631-11	RES, ADJ, CARBON 22K				
RV966	1-241-631-11	RES, ADJ, CARBON 22K				
RV967	1-241-631-11	RES, ADJ, CARBON 22K				
RV968	1-241-631-11	RES, ADJ, CARBON 22K				
RV969	1-241-631-11	RES, ADJ, CARBON 22K				
RV970	1-241-631-11	RES, ADJ, CARBON 22K				
RV971	1-241-631-11	RES, ADJ, CARBON 22K				
RV972	1-241-631-11	RES, ADJ, CARBON 22K				
RV973	1-241-631-11	RES, ADJ, CARBON 22K				
RV974	1-241-631-11	RES, ADJ, CARBON 22K				
RV975	1-241-631-11	RES, ADJ, CARBON 22K				
RV976	1-241-631-11	RES, ADJ, CARBON 22K				
RV977	1-241-631-11	RES, ADJ, CARBON 22K				
RV978	1-241-631-11	RES, ADJ, CARBON 22K				
RV979	1-241-631-11	RES, ADJ, CARBON 22K				
RV980	1-238-019-11	RES, ADJ, CARBON 47K				
RV981	1-241-631-11	RES, ADJ, CARBON 22K				
RV982	1-241-631-11	RES, ADJ, CARBON 22K				
**********						
*1-644-278-11		DS BOARD				
		********				
		<CAPACITOR>				
C1745	1-126-101-11	ELECT	100MF	20%	16V	
C1746	1-126-101-11	ELECT	100MF	20%	16V	
C1747	1-126-101-11	ELECT	100MF	20%	16V	
C1748	1-126-101-11	ELECT	100MF	20%	16V	
C1750	1-124-916-11	ELECT	22MF	20%	25V	
C1751	1-126-101-11	ELECT	100MF	20%	16V	
C1752	1-124-916-11	ELECT	22MF	20%	25V	
C1753	1-124-916-11	ELECT	22MF	20%	25V	
C1851	1-102-074-00	CERAMIC	0.001MF	10%	50V	
		<CONNECTOR>				
DS6	1-691-182-11	CONNECTOR (BOARD TO BOARD) 12P				
		<IC>				
IC1711	8-759-111-69	IC UPC1037HA				
IC1712	8-759-602-19	IC M5220L				
IC1713	8-759-111-69	IC UPC1037HA				
		<RESISTOR>				
R1840	1-215-445-00	METAL	10K	1%	1/4W	
R1841	1-215-433-00	METAL	3.3K	1%	1/4W	
R1842	1-215-465-00	METAL	68K	1%	1/4W	
R1843	1-215-421-00	METAL	1K	1%	1/4W	
R1844	1-215-455-00	METAL	27K	1%	1/4W	
R1845	1-215-455-00	METAL	27K	1%	1/4W	
R1846	1-215-421-00	METAL	1K	1%	1/4W	
R1850	1-215-461-00	METAL	47K	1%	1/4W	
R1851	1-215-461-00	METAL	47K	1%	1/4W	
R1852	1-215-429-00	METAL	2.2K	1%	1/4W	
R1853	1-215-397-00	METAL	100	1%	1/4W	

DS H1 H2

The components identified by shading and mark ⚠ are critical for safety.
Replace only with part number specified.

Les composants identifies par une trame et une marque ⚠ sont critiques pour la securite.
Ne les remplacer que par une piece portant le numero specifie.

REF.NO.	PART NO.	DESCRIPTION				REMARK
R1854	1-215-429-00	METAL	2.2K	1%	1/4W	
R1855	1-215-397-00	METAL	100	1%	1/4W	
R1940	1-215-445-00	METAL	10K	1%	1/4W	
R1941	1-215-433-00	METAL	3.3K	1%	1/4W	
R1942	1-215-421-00	METAL	1K	1%	1/4W	
R1943	1-215-465-00	METAL	68K	1%	1/4W	
R1944	1-215-421-00	METAL	1K	1%	1/4W	
R1945	1-215-455-00	METAL	27K	1%	1/4W	
R1946	1-215-455-00	METAL	27K	1%	1/4W	
		<VARIABLE RESISTOR>				
RV983	1-241-630-11	RES, ADJ, CARBON 10K				
RV984	1-241-630-11	RES, ADJ, CARBON 10K				

****

	*1-643-591-11	H1 BOARD	
		********	
	4-033-777-01	HOLDER, LED	
	*4-374-987-01	GUIDE, LIGHT	
	4-381-686-01	BRACKET (B), LIGHT GUIDE	
		<CAPACITOR>	
C1601	1-124-907-11	ELECT 10MF	20% 50V
C1602	1-124-907-11	ELECT 10MF	20% 50V
C1603	1-124-907-11	ELECT 10MF	20% 50V
C1604	1-124-261-00	ELECT 10MF	20% 50V
		<DIODE>	
D1601	8-719-812-41	DIODE TLR124	
D1602	8-719-812-41	DIODE TLR124	
		<CONNECTOR>	
H11	*1-564-526-11	PLUG, CONNECTOR 11P	
H15	*1-564-517-41	PLUG, CONNECTOR 2P	
		<IC>	
IC1601	8-741-148-33	IC SBX1483-59	
		<RESISTOR>	
R1601	1-249-430-11	CARBON 12K	5% 1/4W
R1602	1-249-425-11	CARBON 4.7K	5% 1/4W
R1603	1-249-421-11	CARBON 2.2K	5% 1/4W
R1604	1-249-419-11	CARBON 1.5K	5% 1/4W
R1606	1-249-405-11	CARBON 100	5% 1/4W
R1607	1-249-405-11	CARBON 100	5% 1/4W
R1608	1-249-411-11	CARBON 330	5% 1/4W
R1609	1-249-411-11	CARBON 330	5% 1/4W
		<SWITCH>	
S1601	1-554-303-21	SWITCH, TACTIL	
S1602	1-554-303-21	SWITCH, TACTIL	
S1603	1-554-303-21	SWITCH, TACTIL	
S1604	1-554-303-21	SWITCH, TACTIL	
S1605	1-554-303-21	SWITCH, TACTIL	
S1606⚠	1-571-731-21	SWITCH, TACTIL (POWER)	

****

	*1-643-592-11	H2 BOARD	
		********	
		<CAPACITOR>	
C1651	1-124-477-11	ELECT 47MF	20% 16V
C1655	1-124-927-11	ELECT 4.7MF	20% 50V
		<DIODE>	
D1651	8-719-908-03	DIODE GP08D	
D1652	8-719-908-03	DIODE GP08D	
D1653	8-719-108-12	DIODE RD9.1E-W	
D1654	8-719-108-12	DIODE RD9.1E-W	
D1655	8-719-108-12	DIODE RD9.1E-W	
D1659	8-719-911-19	DIODE 1SS119	
D1660	8-719-110-88	DIODE RD39ES-B2	
D1661	8-719-110-88	DIODE RD39ES-B2	
D1662	8-719-110-88	DIODE RD39ES-B2	
D1663	8-719-110-88	DIODE RD39ES-B2	
		<CONNECTOR>	
H22	*1-564-519-41	PLUG, CONNECTOR 4P	
H25	*1-564-517-41	PLUG, CONNECTOR 2P	
H26	*1-564-519-11	PLUG, CONNECTOR 4P	
H28	*1-564-518-11	PLUG, CONNECTOR 3P	
H211	*1-564-517-11	PLUG, CONNECTOR 2P	
H216	*1-564-525-11	PLUG, CONNECTOR 10P	
H225	*1-564-518-11	PLUG, CONNECTOR 3P	
		<JACK>	
J1651	1-695-817-11	JACK BLOCK, PIN 3P	
		<TRANSISTOR>	
Q1651	8-729-119-78	TRANSISTOR 2SC2785-HFE	
Q1652	8-729-119-78	TRANSISTOR 2SC2785-HFE	
Q1653	8-729-119-78	TRANSISTOR 2SC2785-HFE	
		<RESISTOR>	
R1651	1-249-419-11	CARBON 1.5K	5% 1/4W
R1652	1-249-421-11	CARBON 2.2K	5% 1/4W
R1653	1-249-425-11	CARBON 4.7K	5% 1/4W
R1654	1-249-430-11	CARBON 12K	5% 1/4W
R1655	1-249-417-11	CARBON 1K	5% 1/4W
R1656	1-249-417-11	CARBON 1K	5% 1/4W
R1657	1-249-436-11	CARBON 39K	5% 1/4W
R1658	1-249-437-11	CARBON 47K	5% 1/4W
R1659	1-249-437-11	CARBON 47K	5% 1/4W
		<RELAY>	
RY1651	1-515-586-11	RELAY (DS-2)	
RY1652	1-515-586-11	RELAY (DS-2)	
		<SWITCH>	
S1651	1-554-303-21	SWITCH, TACTIL	
S1652	1-554-303-21	SWITCH, TACTIL	
S1653	1-554-303-21	SWITCH, TACTIL	
S1654	1-554-303-21	SWITCH, TACTIL	

H2 ZR ZG ZB N

Les composants identifies par une trame et une marque ⚠ sont critiques pour la securite. Ne les remplacer que par une piece portant le numero specifie.

The components identified by shading and mark ⚠ are critical for safety. Replace only with part number specified.

REF.NO.	PART NO.	DESCRIPTION				REMARK
S1655	1-554-303-21	SWITCH, TACTIL				
**********						
	*A-1390-340-A	ZR BOARD, COMPLETE				
		**********				
		<CAPACITOR>				
C1901	1-162-115-00	CERAMIC	330PF	10%	2KV	
C1902	1-162-115-00	CERAMIC	330PF	10%	2KV	
		<RESISTOR>				
R1901	1-202-818-00	SOLID	1K	20%	1/2W	
R1902	1-202-818-00	SOLID	1K	20%	1/2W	
R1903	1-249-414-11	CARBON	560	5%	1/4W	
R1904	1-249-414-11	CARBON	560	5%	1/4W	
		<CONNECTOR>				
ZR1	*1-564-522-11	PLUG, CONNECTOR 7P				
ZR2	*1-564-518-11	PLUG, CONNECTOR 3P				
ZR18	*1-691-292-11	PIN, CONNECTOR (PC BOARD) 3P				
**********						
	*A-1390-346-A	ZG BOARD, COMPLETE				
		**********				
		<CAPACITOR>				
C1911	1-162-115-00	CERAMIC	330PF	10%	2KV	
C1912	1-162-115-00	CERAMIC	330PF	10%	2KV	
		<RESISTOR>				
R1911	1-202-818-00	SOLID	1K	20%	1/2W	
R1912	1-202-818-00	SOLID	1K	20%	1/2W	
R1913	1-249-414-11	CARBON	560	5%	1/4W	
R1914	1-249-414-11	CARBON	560	5%	1/4W	
		<CONNECTOR>				
ZG2	*1-564-523-11	PLUG, CONNECTOR 8P				
ZG19	*1-691-292-11	PIN, CONNECTOR (PC BOARD) 3P				
**********						
	*A-1390-347-A	ZB BOARD, COMPLETE				
		**********				
		<CAPACITOR>				
C1921	1-162-115-00	CERAMIC	330PF	10%	2KV	
C1922	1-162-115-00	CERAMIC	330PF	10%	2KV	
		<RESISTOR>				
R1921	1-202-818-00	SOLID	1K	20%	1/2W	
R1922	1-202-818-00	SOLID	1K	20%	1/2W	
R1923	1-249-414-11	CARBON	560	5%	1/4W	
R1924	1-249-414-11	CARBON	560	5%	1/4W	
		<CONNECTOR>				
ZB3	*1-564-524-11	PLUG, CONNECTOR 9P				
ZB20	*1-691-292-11	PIN, CONNECTOR (PC BOARD) 3P				
**********						
	*A-1390-351-A	N BOARD, COMPLETE				
		**********				
	4-039-042-01	SPACER, INSULATING				
	4-382-854-11	SCREW (M3X10), P, SW (+)				
	4-383-023-01	SPACER, MICA				
		<CAPACITOR>				
C801	1-125-489-00	ELECT(BLOCK)	560MF	20%	200V	
C802	1-123-024-21	ELECT	33MF		160V	
C803	1-136-729-11	FILM	1.5MF	5%	400V	
C804	1-106-383-00	MYLAR	0.047MF		200V	
C805	1-102-030-00	CERAMIC	330PF	10%	500V	
C806	1-130-495-00	MYLAR	0.1MF	5%	50V	
C807	1-123-875-11	ELECT	10MF	20%	50V	
C808	1-126-183-11	ELECT	1000MF	20%	16V	
C809	1-124-903-11	ELECT	1MF	20%	50V	
C810	1-124-903-11	ELECT	1MF	20%	50V	
C811	1-124-902-00	ELECT	0.47MF	20%	50V	
C812	1-102-973-00	CERAMIC	100PF	5%	50V	
C813	1-102-244-00	CERAMIC	220PF	10%	500V	
C814	1-106-391-12	MYLAR	0.1MF	10%	200V	
C815	1-106-367-00	MYLAR	0.01MF	10%	200V	
C816	1-124-907-11	ELECT	10MF	20%	50V	
C817	1-124-119-00	ELECT	330MF	20%	16V	
C818	1-102-824-00	CERAMIC	470PF	5%	50V	
C819	1-124-907-11	ELECT	10MF	20%	50V	
C820	1-124-907-11	ELECT	10MF	20%	50V	
C821	1-124-907-11	ELECT	10MF	20%	50V	
C822	1-124-034-51	ELECT	33MF	20%	16V	
C823	1-124-907-11	ELECT	10MF	20%	50V	
C824	1-124-034-51	ELECT	33MF	20%	16V	
C825	1-124-034-51	ELECT	33MF	20%	16V	
C826	1-124-907-11	ELECT	10MF	20%	50V	
C827	1-124-907-11	ELECT	10MF	20%	50V	
C828	1-124-907-11	ELECT	10MF	20%	50V	
C829	1-124-034-51	ELECT	33MF	20%	16V	
C830	1-124-907-11	ELECT	10MF	20%	50V	
C831	1-106-220-00	MYLAR	0.1MF	10%	100V	
C832	1-124-907-11	ELECT	10MF	20%	50V	
C833	1-124-916-11	ELECT	22MF	20%	50V	
C834	1-102-121-00	CERAMIC	0.0022MF	10%	50V	
C835	1-124-927-11	ELECT	4.7MF	20%	50V	
C836	1-130-475-00	MYLAR	0.0022MF	5%	50V	
C837	1-136-169-00	FILM	0.22MF	5%	50V	
C838	1-130-475-00	MYLAR	0.0022MF	5%	50V	
C839	1-102-106-00	CERAMIC	100PF	10%	50V	
C840	⚠ 1-136-807-11	FILM	0.018MF	3%	1.6KV	
C841	1-136-729-11	FILM	1.5MF	5%	400V	
C842	1-130-471-00	MYLAR	0.001MF	5%	50V	
C844	1-106-391-12	MYLAR	0.1MF	10%	200V	
C850	1-136-169-00	FILM	0.22MF	5%	50V	
C851	1-124-907-11	ELECT	10MF	20%	50V	
C852	1-124-907-11	ELECT	10MF	20%	50V	
C853	1-106-220-00	MYLAR	0.1MF	10%	100V	
C854	1-126-329-11	ELECT	470MF	20%	50V	
C855	1-124-514-11	ELECT	100MF	20%	50V	
C856	1-162-114-00	CERAMIC	0.0047MF		2KV	
C858	1-124-119-00	ELECT	330MF	20%	16V	
C888	1-124-903-11	ELECT	1MF	20%	50V	

The components identified by shading and mark ⚠ are critical for safety.
Replace only with part number specified.

Les composants identifies par une trame et une marque ⚠ sont critiques pour la securite.
Ne les remplacer que par une piece portant le numero specifie.

REF.NO.	PART NO.	DESCRIPTION	REMARK
		<DIODE>	
D801	8-719-928-08	DIODE ERD28-08S	
D802	8-719-300-80	DIODE RU-1C	
D803	8-719-109-85	DIODE RD5.1ES-B2	
D804	8-719-911-19	DIODE 1SS119	
D805	8-719-911-19	DIODE 1SS119	
D806	8-719-109-85	DIODE RD5.1ES-B2	
D807	8-719-109-85	DIODE RD5.1ES-B2	
D808	8-719-911-19	DIODE 1SS119	
D809	8-719-911-19	DIODE 1SS119	
D810	8-719-911-19	DIODE 1SS119	
D811	8-719-109-85	DIODE RD5.1ES-B2	
D812	8-719-911-19	DIODE 1SS119	
D813	8-719-911-19	DIODE 1SS119	
D814	8-719-911-19	DIODE 1SS119	
D815	8-719-110-36	DIODE RD13ES-B2	
D817	8-719-945-80	DIODE ERC06-15S	
D818	8-719-911-19	DIODE 1SS119	
D820	8-719-911-19	DIODE 1SS119	
D850	8-719-109-71	DIODE RD3.9ES-B1	
D851 ⚠	8-719-903-09	DIODE V30N	
D852	8-719-911-19	DIODE 1SS119	
D853 ⚠	8-719-903-09	DIODE V30N	
D891	8-719-110-49	DIODE RD18ES-B2	
D892	8-719-110-49	DIODE RD18ES-B2	
		<IC>	
IC801	8-759-231-58	IC TA7812S	
IC802	8-759-103-93	IC UPC393C	
IC803	8-759-990-82	IC TL082CP	
IC804	8-759-103-93	IC UPC393C	
IC805	8-759-100-75	IC UPC1394C	
		<COIL>	
L801	1-459-862-11	COIL, CHOKE 90UH	
L802	1-424-603-11	COIL, CHOKE 1.05MMH	
L803	1-459-313-00	COIL WITH CORE (HWC)	
L804	1-410-482-31	INDUCTOR 100UH	
L805 ⚠	1-424-603-11	COIL, CHOKE 1.05MMH	
		<CONNECTOR>	
N1	1-506-348-99	PIN, CONNECTOR 3P	
N2	*1-564-508-11	PLUG, CONNECTOR 5P	
N3	*1-508-766-00	PIN, CONNECTOR (5MM PITCH) 4P	
N4	*1-564-507-11	PLUG, CONNECTOR 4P	
N5	*1-564-508-11	PLUG, CONNECTOR 5P	
N6	*1-508-786-00	PIN, CONNECTOR (5MM PITCH) 2P	
N7	*1-508-765-00	PIN, CONNECTOR (5MM PITCH) 3P	
N8	*1-508-766-00	PIN, CONNECTOR (5MM PITCH) 4P	
N9	1-506-348-99	PIN, CONNECTOR 3P	
N10	*1-564-511-41	PLUG, CONNECTOR 8P	
N20	*1-560-126-00	PLUG, CONNECTOR (2.5MM) 6P	
N21	*1-560-123-00	PLUG, CONNECTOR (2.5MM) 3P	
N30	*1-508-784-00	PIN, CONNECTOR (5MM PITCH) 1P	
N851	*1-506-371-00	PIN, CONNECTOR 2P	
N853	*1-506-371-00	PIN, CONNECTOR 2P	
		<NEON LAMP>	
NL801	1-519-108-99	LAMP, NEON	

REF.NO.	PART NO.	DESCRIPTION	REMARK
		<TRANSISTOR>	
Q801 ⚠	8-729-201-61	TRANSISTOR 2SC2555-1	
Q802	8-729-119-80	TRANSISTOR 2SC2688-LK	
Q803	8-729-119-76	TRANSISTOR 2SA1175-HFE	
Q804	8-729-119-78	TRANSISTOR 2SC2785-HFE	
Q805	8-729-119-78	TRANSISTOR 2SC2785-HFE	
Q806	8-729-119-80	TRANSISTOR 2SC2688-LK	
Q807	8-729-119-78	TRANSISTOR 2SC2785-HFE	
Q808	8-729-119-78	TRANSISTOR 2SC2785-HFE	
Q809	8-729-119-76	TRANSISTOR 2SA1175-HFE	
Q811 ⚠	8-729-805-07	TRANSISTOR 2SD1887-CA	
Q812	8-729-019-88	TRANSISTOR 2SC3675-CB	
Q820	8-729-119-76	TRANSISTOR 2SA1175-HFE	
Q851	8-729-119-78	TRANSISTOR 2SC2785-HFE	
Q852	8-729-119-78	TRANSISTOR 2SC2785-HFE	
Q853	8-729-820-98	TRANSISTOR 2SC4256CB	
		<RESISTOR>	
R801	1-216-378-11	METAL OXIDE 5.6 5% 2W F	
R802	1-215-926-00	METAL OXIDE 33K 5% 3W F	
R803	1-215-926-00	METAL OXIDE 33K 5% 3W F	
R804	1-249-429-11	CARBON 10K 5% 1/4W	
R805	1-249-423-11	CARBON 3.3K 5% 1/4W	
R806	1-249-425-11	CARBON 4.7K 5% 1/4W	
R807	1-249-441-11	CARBON 100K 5% 1/4W	
R808	1-249-417-11	CARBON 1K 5% 1/4W	
R809	1-249-417-11	CARBON 1K 5% 1/4W	
R810	1-249-441-11	CARBON 100K 5% 1/4W	
R811	1-249-421-11	CARBON 2.2K 5% 1/4W	
R812	1-249-420-11	CARBON 1.8K 5% 1/4W F	
R813	1-215-921-11	METAL OXIDE 4.7K 5% 3W F	
R814	1-249-409-11	CARBON 220 5% 1/4W	
R815	1-249-415-11	CARBON 680 5% 1/4W	
R816	1-214-777-00	METAL 100K 1% 1/4W	
R817	1-215-471-00	METAL 120K 1% 1/4W	
R818	1-215-471-00	METAL 120K 1% 1/4W	
R819	1-215-450-00	METAL 16K 1% 1/4W	
R820	1-215-451-00	METAL 18K 1% 1/4W	
R821	1-249-423-11	CARBON 3.3K 5% 1/4W	
R822	1-249-433-11	CARBON 22K 5% 1/4W	
R823	1-249-429-11	CARBON 10K 5% 1/4W	
R824	1-215-469-00	METAL 100K 1% 1/4W	
R825	1-215-453-00	METAL 22K 1% 1/4W	
R826	1-214-962-00	METAL 820K 1% 1/4W	
R827	1-214-764-00	METAL 30K 1% 1/4W	
R828	1-215-455-00	METAL 27K 1% 1/4W	
R829	1-215-455-00	METAL 27K 1% 1/4W	
R830	1-215-928-11	METAL OXIDE 68K 5% 3W F	
R831	1-215-928-11	METAL OXIDE 68K 5% 3W F	
R832	1-249-417-11	CARBON 1K 5% 1/4W	
R833	1-249-419-11	CARBON 1.5K 5% 1/4W	
R834	1-249-419-11	CARBON 1.5K 5% 1/4W	
R835	1-215-429-00	METAL 2.2K 1% 1/4W	
R836	1-215-435-00	METAL 3.9K 1% 1/4W	
R837	1-249-433-11	CARBON 22K 5% 1/4W	
R838	1-249-435-11	CARBON 33K 5% 1/4W	
R839	1-249-438-11	CARBON 56K 5% 1/4W	
R840	1-249-434-11	CARBON 27K 5% 1/4W	
R841	1-249-429-11	CARBON 10K 5% 1/4W	
R842	1-249-435-11	CARBON 33K 5% 1/4W	
R843	1-249-423-11	CARBON 3.3K 5% 1/4W	

N **S**

• The components identified by ⊠ in this manual have been carefully factory-selected for each set in order to satisfy regulations regarding X-ray radiation. Should replacement be required, replace only with the value originally used.

Les composants identifies par une trame et une marque ⚠ sont critiques pour la securite. Ne les remplacer que par une piece portant le numero specifie.

The components identified by shading and mark ⚠ are critical for safety. Replace only with part number specified.

REF.NO.	PART NO.	DESCRIPTION				REMARK
R844	1-249-433-11	CARBON	22K	5%	1/4W	
R845	1-249-435-11	CARBON	33K	5%	1/4W	
R846	1-249-429-11	CARBON	10K	5%	1/4W	
R847	1-214-761-00	METAL	22K	1%	1/4W	
R848	1-215-429-00	METAL	2.2K	1%	1/4W	
R849	1-215-421-00	METAL	1K	1%	1/4W	
R850	1-215-429-00	METAL	2.2K	1%	1/4W	
R851	1-215-404-00	METAL	200	1%	1/4W	
⊠R852 ⚠		METAL			1/4W	
R853	1-215-469-00	METAL	100K	1%	1/4W	
R854	1-249-430-11	CARBON	12K	5%	1/4W	
R855	1-215-469-00	METAL	100K	1%	1/4W	
R856	1-249-430-11	CARBON	12K	5%	1/4W	
R857	1-249-433-11	CARBON	22K	5%	1/4W	
R858	1-249-413-11	CARBON	470	5%	1/4W	
R859	1-249-435-11	CARBON	33K	5%	1/4W	
R860	1-249-441-11	CARBON	100K	5%	1/4W	
R861	1-249-421-11	CARBON	2.2K	5%	1/4W	
R862	1-249-434-11	CARBON	27K	5%	1/4W	
R863	1-249-431-11	CARBON	15K	5%	1/4W	
R864	1-249-423-11	CARBON	3.3K	5%	1/4W	
R865	1-249-440-11	CARBON	82K	5%	1/4W	
R866	1-249-436-11	CARBON	39K	5%	1/4W	
R867	1-249-437-11	CARBON	47K	5%	1/4W	
R868	1-249-428-11	CARBON	8.2K	5%	1/4W	
R869	1-249-429-11	CARBON	10K	5%	1/4W	
R870	1-249-417-11	CARBON	1K	5%	1/4W	
R871	1-249-440-11	CARBON	82K	5%	1/4W	
R872	1-249-423-11	CARBON	3.3K	5%	1/4W	
R873	1-249-441-11	CARBON	100K	5%	1/4W	
R874	1-249-435-11	CARBON	33K	5%	1/4W	
R875	1-249-421-11	CARBON	2.2K	5%	1/4W	
R876	1-215-426-00	METAL	1.6K	1%	1/4W	
R877	1-249-435-11	CARBON	33K	5%	1/4W	
R878	1-249-441-11	CARBON	100K	5%	1/4W	
R879	1-216-489-11	METAL OXIDE	27K	5%	3W	F
R880	1-249-429-11	CARBON	10K	5%	1/4W	
R881	1-214-761-00	METAL	22K	1%	1/4W	
R882	1-249-433-11	CARBON	22K	5%	1/4W	
R883	1-249-417-11	CARBON	1K	5%	1/4W	
R884	1-215-894-11	METAL OXIDE	2.2K	5%	2W	F
R885	1-249-438-11	CARBON	56K	5%	1/4W	
R886	1-249-414-11	CARBON	560	5%	1/4W	
R887	1-215-397-00	METAL	100	1%	1/4W	
R888	1-249-410-11	CARBON	270	5%	1/4W	
R889	1-249-417-11	CARBON	1K	5%	1/4W	
R890	1-249-417-11	CARBON	1K	5%	1/4W	
R891	1-216-489-11	METAL OXIDE	27K	5%	3W	F
R892	1-249-417-11	CARBON	1K	5%	1/4W	F
R893	1-215-453-00	METAL	22K	1%	1/4W	
R894	1-249-401-11	CARBON	47	5%	1/4W	
R895	1-202-731-00	SOLID	10M	20%	1/2W	
R896	1-260-111-11	CARBON	10K	5%	1/2W	
R897	1-247-881-00	CARBON	120K	5%	1/4W	
R898	1-202-730-00	SOLID	8.2M	20%	1/2W	
R899	1-249-429-11	CARBON	10K	5%	1/4W	
R903	1-247-735-11	SOLID	47	20%	1/2W	
R904	1-215-928-11	METAL OXIDE	68K	5%	3W	F
R905	1-215-911-11	METAL OXIDE	100	5%	3W	F

<SPARK GAP>

SG801	1-519-422-11	GAP, SPARK	

REF.NO.	PART NO.	DESCRIPTION	REMARK
T801 ⚠	1-437-078-11	TRANSFORMER, HORIZONTAL DRIVE	
T802	1-437-090-00	HDT	
T803 ⚠	1-453-121-11	TRANSFORMER ASSY, FLYBACK (NX-2630B4)	

****

	*A-1394-421-A	S BOARD, COMPLETE	
		**********	
	*1-565-514-11	SOCKET, CONNECTOR 2P	

<CAPACITOR>

C3403	1-164-161-11	CERAMIC CHIP	0.0022MF	10%	50V
C3408	1-164-232-11	CERAMIC CHIP	0.01MF	10%	50V
C3409	1-124-477-11	ELECT	47MF	20%	16V
C3411	1-124-034-51	ELECT	33MF	20%	16V
C3442	1-164-161-11	CERAMIC CHIP	0.0022MF	10%	50V
C3446	1-163-129-00	CERAMIC CHIP	330PF	5%	50V
C3447	1-163-117-00	CERAMIC CHIP	100PF	5%	50V
C3448	1-163-023-00	CERAMIC CHIP	0.015MF	10%	50V
C3449	1-164-182-11	CERAMIC CHIP	0.0033MF	10%	50V
C3450	1-163-109-00	CERAMIC CHIP	47PF	5%	50V
C3451	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C3452	1-163-989-11	CERAMIC CHIP	0.033MF	10%	25V
C3453	1-124-477-11	ELECT	47MF	20%	16V
C3454	1-126-162-11	ELECT	3.3MF	20%	50V
C3455	1-126-163-11	ELECT	4.7MF	20%	16V
C3456	1-163-129-00	CERAMIC CHIP	330PF	5%	50V
C3457	1-163-117-00	CERAMIC CHIP	100PF	5%	50V
C3459	1-124-477-11	ELECT	47MF	20%	16V
C3460	1-163-099-00	CERAMIC CHIP	18PF	5%	50V
C3461	1-163-099-00	CERAMIC CHIP	18PF	5%	50V
C3507	1-164-232-11	CERAMIC CHIP	0.01MF	10%	50V
C3508	1-164-005-11	CERAMIC CHIP	0.47MF		25V
C3509	1-163-139-00	CERAMIC CHIP	820PF	5%	50V
C3515	1-163-121-00	CERAMIC CHIP	150PF	5%	50V
C3540	1-126-157-11	ELECT	10MF	20%	16V

<DIODE>

D3444	8-719-404-46	DIODE MA110

<IC>

IC3401	8-759-403-44	IC MN1280-S
IC3402	8-759-070-42	IC M37201M6-A18FP
IC3441	8-759-982-21	IC RC78L05A
IC3442	8-759-084-12	IC LA7945
IC3443	8-759-158-03	IC LC7458A-02
IC3444	8-759-403-44	IC MN1280-S

<COIL>

L3401	1-408-421-00	INDUCTOR	100UH
L3461	1-408-409-00	INDUCTOR	10UH
L3462	1-408-421-00	INDUCTOR	100UH

<TRANSISTOR>

Q3441	8-729-422-27	TRANSISTOR 2SD601A-Q
Q3444	8-729-903-10	TRANSISTOR FMW1

REF.NO.	PART NO.	DESCRIPTION				REMARK
		<RESISTOR>				
R3401	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R3402	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R3403	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R3404	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R3405	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	
R3406	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R3407	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R3408	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R3409	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R3441	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R3442	1-216-041-00	METAL GLAZE	470	5%	1/10W	
R3443	1-216-041-00	METAL GLAZE	470	5%	1/10W	
R3444	1-216-077-00	METAL GLAZE	15K	5%	1/10W	
R3445	1-216-689-11	METAL GLAZE	39K	5%	1/10W	
R3446	1-216-085-00	METAL GLAZE	33K	5%	1/10W	
R3449	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R3450	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	
R3451	1-216-093-00	METAL GLAZE	68K	5%	1/10W	
R3452	1-216-079-00	METAL GLAZE	18K	5%	1/10W	
R3453	1-216-679-11	METAL CHIP	15K	0.50%	1/10W	
R3454	1-216-037-00	METAL GLAZE	330	5%	1/10W	
R3455	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	
R3456	1-216-077-00	METAL GLAZE	15K	5%	1/10W	
R3463	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R3464	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R3465	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R3472	1-216-091-00	METAL GLAZE	56K	5%	1/10W	
R3473	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R3474	1-216-295-00	METAL GLAZE	0	5%	1/10W	
R3504	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	
R3509	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R3511	1-216-025-00	METAL GLAZE	100	5%	1/10W	
R3512	1-216-059-00	METAL GLAZE	2.7K	5%	1/10W	
R3513	1-216-059-00	METAL GLAZE	2.7K	5%	1/10W	
R3514	1-216-059-00	METAL GLAZE	2.7K	5%	1/10W	
R3519	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R3520	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R3521	1-216-049-00	METAL GLAZE	1K	5%	1/10W	
R3525	1-216-295-00	METAL GLAZE	0	5%	1/10W	
R3526	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R3528	1-216-295-00	METAL GLAZE	0	5%	1/10W	
R3529	1-216-295-00	METAL GLAZE	0	5%	1/10W	
R3530	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R3531	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R3532	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R3535	1-216-033-00	METAL GLAZE	220	5%	1/10W	
R3537	1-216-295-00	METAL GLAZE	0	5%	1/10W	
R3540	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
		<CONNECTOR>				
S42	*1-568-378-21	PIN, CONNECTOR 3P				
S43	*1-564-508-11	PLUG, CONNECTOR 5P				
S45	*1-564-511-71	PLUG, CONNECTOR 8P				
S46	*1-564-506-11	PLUG, CONNECTOR 3P				
S47	*1-564-506-11	PLUG, CONNECTOR 3P				
		<CRYSTAL>				
X3401	1-577-082-11	VIBRATOR, CERAMIC				
X3441	1-577-364-11	VIBRATOR, CERAMIC				

REF.NO.	PART NO.	DESCRIPTION				REMARK
**********						
	*A-1394-422-A	U BOARD, COMPLETE				
		**********				
		<CAPACITOR>				
C1004	1-102-125-00	CERAMIC	0.0047MF	10%	50V	
C1005	1-126-301-11	ELECT	1MF	20%	50V	
C1006	1-164-096-11	CERAMIC	0.01MF		50V	
C1007	1-124-598-11	ELECT	22MF	20%	25V	
C1008	1-124-598-11	ELECT	22MF	20%	25V	
C1010	1-124-465-00	ELECT	0.47MF	20%	50V	
C1011	1-124-465-00	ELECT	0.47MF	20%	50V	
C1012	1-124-465-00	ELECT	0.47MF	20%	50V	
C1013	1-102-125-00	CERAMIC	0.0047MF	10%	50V	
C1014	1-126-163-11	ELECT	4.7MF	20%	50V	
C1016	1-126-163-11	ELECT	4.7MF	20%	50V	
C1018	1-126-301-11	ELECT	1MF	20%	50V	
C1020	1-124-242-00	ELECT	33MF	20%	25V	
C1021	1-124-465-00	ELECT	0.47MF	20%	50V	
C1022	1-124-242-00	ELECT	33MF	20%	25V	
C1026	1-102-949-00	CERAMIC	12PF	5%	50V	
C1027	1-102-949-00	CERAMIC	12PF	5%	50V	
C1028	1-124-242-00	ELECT	33MF	20%	25V	
C1029	1-124-282-00	ELECT	22MF	20%	16V	
C1030	1-124-478-11	ELECT	100MF	20%	25V	
C1031	1-102-963-00	CERAMIC	33PF	5%	50V	
C1033	1-124-598-11	ELECT	22MF	20%	25V	
C1034	1-124-282-00	ELECT	22MF	20%	16V	
C1036	1-124-282-00	ELECT	22MF	20%	16V	
C1037	1-124-282-00	ELECT	22MF	20%	16V	
C1039	1-124-478-11	ELECT	100MF	20%	25V	
C1047	1-124-465-00	ELECT	0.47MF	20%	50V	
C1048	1-126-301-11	ELECT	1MF	20%	50V	
C1049	1-124-598-11	ELECT	22MF	20%	25V	
C1051	1-124-465-00	ELECT	0.47MF	20%	50V	
C1055	1-124-589-11	ELECT	47MF	20%	16V	
C1056	1-124-499-11	ELECT	1MF	20%	50V	
C1057	1-124-768-11	ELECT	4.7MF	20%	50V	
C1059	1-124-499-11	ELECT	1MF	20%	50V	
C1060	1-124-499-11	ELECT	1MF	20%	50V	
C1061	1-124-499-11	ELECT	1MF	20%	50V	
C1062	1-102-129-00	CERAMIC	0.01MF	10%	50V	
C1063	1-124-768-11	ELECT	4.7MF	20%	50V	
C1066	1-126-101-11	ELECT	100MF	20%	16V	
		<BLOCK>				
CM1002	1-466-162-31	BLOCK, COM FILTER (CFB-4)				
		<DIODE>				
D1005	8-719-110-36	DIODE RD13ES-B2				
D1009	8-719-110-36	DIODE RD13ES-B2				
D1010	8-719-110-36	DIODE RD13ES-B2				
D1011	8-719-110-36	DIODE RD13ES-B2				
D1012	8-719-110-36	DIODE RD13ES-B2				
D1013	8-719-110-36	DIODE RD13ES-B2				
D1017	8-719-110-36	DIODE RD13ES-B2				
D1018	8-719-110-36	DIODE RD13ES-B2				
D1019	8-719-110-36	DIODE RD13ES-B2				
D1020	8-719-109-66	DIODE RD3.3ES-B2				
D1021	8-719-109-66	DIODE RD3.3ES-B2				

U UT

REF.NO.	PART NO.	DESCRIPTION				REMARK
D1022	8-719-109-66	DIODE RD3.3ES-B2				
		<IC>				
IC1002	8-752-056-50	IC CXA1545S				
IC1011	8-759-145-57	IC UPC4557C				
		<COIL>				
L1001	1-408-422-00	INDUCTOR	120UH			
L1002	1-408-422-00	INDUCTOR	120UH			
		<TRANSISTOR>				
Q1009	8-729-119-78	TRANSISTOR 2SC2785-HFE				
Q1010	8-729-119-78	TRANSISTOR 2SC2785-HFE				
Q1016	8-729-119-76	TRANSISTOR 2SA1175-HFE				
Q1017	8-729-119-76	TRANSISTOR 2SA1175-HFE				
Q1018	8-729-141-26	TRANSISTOR 2SC3622A-LK				
Q1019	8-729-119-76	TRANSISTOR 2SA1175-HFE				
Q1020	8-729-119-76	TRANSISTOR 2SA1175-HFE				
Q1021	8-729-119-76	TRANSISTOR 2SA1175-HFE				
Q1022	8-729-141-26	TRANSISTOR 2SC3622A-LK				
Q1023	8-729-119-78	TRANSISTOR 2SC2785-HFE				
Q1029	8-729-119-76	TRANSISTOR 2SA1175-HFE				
Q1030	8-729-119-78	TRANSISTOR 2SC2785-HFE				
Q1031	8-729-119-78	TRANSISTOR 2SC2785-HFE				
Q1032	8-729-119-76	TRANSISTOR 2SA1175-HFE				
Q1033	8-729-119-76	TRANSISTOR 2SA1175-HFE				
Q1034	8-729-119-76	TRANSISTOR 2SA1175-HFE				
		<RESISTOR>				
R1011	1-249-435-11	CARBON	33K	5%	1/4W	
R1012	1-249-434-11	CARBON	27K	5%	1/4W	
R1013	1-249-417-11	CARBON	1K	5%	1/4W	
R1014	1-249-441-11	CARBON	100K	5%	1/4W	
R1015	1-249-425-11	CARBON	4.7K	5%	1/4W	
R1016	1-249-441-11	CARBON	100K	5%	1/4W	
R1017	1-249-405-11	CARBON	100	5%	1/4W	
R1018	1-249-427-11	CARBON	6.8K	5%	1/4W	
R1019	1-249-427-11	CARBON	6.8K	5%	1/4W	
R1023	1-249-405-11	CARBON	100	5%	1/4W	
R1026	1-249-425-11	CARBON	4.7K	5%	1/4W	
R1028	1-249-434-11	CARBON	27K	5%	1/4W	
R1029	1-249-435-11	CARBON	33K	5%	1/4W	
R1030	1-249-417-11	CARBON	1K	5%	1/4W	
R1032	1-249-417-11	CARBON	1K	5%	1/4W	
R1033	1-249-393-11	CARBON	10	5%	1/4W	F
R1034	1-249-417-11	CARBON	1K	5%	1/4W	
R1036	1-249-440-11	CARBON	82K	5%	1/4W	
R1037	1-249-440-11	CARBON	82K	5%	1/4W	
R1038	1-249-440-11	CARBON	82K	5%	1/4W	
R1043	1-249-417-11	CARBON	1K	5%	1/4W	
R1046	1-249-413-11	CARBON	470	5%	1/4W	
R1048	1-249-405-11	CARBON	100	5%	1/4W	
R1050	1-249-405-11	CARBON	100	5%	1/4W	
R1051	1-249-417-11	CARBON	1K	5%	1/4W	
R1052	1-249-413-11	CARBON	470	5%	1/4W	
R1054	1-249-405-11	CARBON	100	5%	1/4W	
R1055	1-249-413-11	CARBON	470	5%	1/4W	
R1056	1-249-405-11	CARBON	100	5%	1/4W	
R1057	1-249-441-11	CARBON	100K	5%	1/4W	
R1059	1-249-405-11	CARBON	100	5%	1/4W	
R1061	1-249-409-11	CARBON	220	5%	1/4W	
R1062	1-249-441-11	CARBON	100K	5%	1/4W	
R1063	1-249-409-11	CARBON	220	5%	1/4W	
R1066	1-215-437-00	METAL	4.7K	1%	1/4W	
R1067	1-215-437-00	METAL	4.7K	1%	1/4W	
R1068	1-215-437-00	METAL	4.7K	1%	1/4W	
R1069	1-215-437-00	METAL	4.7K	1%	1/4W	
R1070	1-249-411-11	CARBON	330	5%	1/4W	
R1071	1-249-431-11	CARBON	15K	5%	1/4W	
R1073	1-249-431-11	CARBON	15K	5%	1/4W	
R1077	1-249-418-11	CARBON	1.2K	5%	1/4W	
R1078	1-249-418-11	CARBON	1.2K	5%	1/4W	
R1079	1-249-405-11	CARBON	100	5%	1/4W	
R1080	1-215-423-00	METAL	1.2K	1%	1/4W	
R1081	1-215-421-00	METAL	1K	1%	1/4W	
R1089	1-249-405-11	CARBON	100	5%	1/4W	
R1094	1-249-405-11	CARBON	100	5%	1/4W	
R1096	1-249-405-11	CARBON	100	5%	1/4W	
R1099	1-249-413-11	CARBON	470	5%	1/4W	
R1110	1-249-405-11	CARBON	100	5%	1/4W	
R1116	1-249-441-11	CARBON	100K	5%	1/4W	
R1118	1-249-413-11	CARBON	470	5%	1/4W	
R1121	1-249-441-11	CARBON	100K	5%	1/4W	
R1133	1-249-405-11	CARBON	100	5%	1/4W	
R1134	1-249-405-11	CARBON	100	5%	1/4W	
R1137	1-249-411-11	CARBON	330	5%	1/4W	
R1138	1-249-415-11	CARBON	680	5%	1/4W	
R1139	1-249-413-11	CARBON	470	5%	1/4W	
R1140	1-249-413-11	CARBON	470	5%	1/4W	
R1141	1-249-413-11	CARBON	470	5%	1/4W	
R1142	1-249-415-11	CARBON	680	5%	1/4W	
R1147	1-249-405-11	CARBON	100	5%	1/4W	
R1148	1-249-405-11	CARBON	100	5%	1/4W	
R1149	1-249-417-11	CARBON	1K	5%	1/4W	
R1150	1-249-405-11	CARBON	100	5%	1/4W	
R1151	1-249-405-11	CARBON	100	5%	1/4W	
R1152	1-249-417-11	CARBON	1K	5%	1/4W	
		<CONNECTOR>				
U12	1-573-300-11	CONNECTOR, BOARD TO BOARD 18P				
U13	1-573-300-11	CONNECTOR, BOARD TO BOARD 18P				
U16	*1-564-513-11	PLUG, CONNECTOR 10P				
U22	1-566-942-11	CONNECTOR,HINGE(RECEPTACLE)30P				
U23	*1-566-367-11	CONNECTOR, HINGE (RECEPTACLE)				
U47	*1-564-506-11	PLUG, CONNECTOR 3P				
**********						
	*A-1394-432-A	UT BOARD, COMPLETE				
		**********				
		<CAPACITOR>				
C1152	1-102-074-00	CERAMIC	0.001MF	10%	50V	
C1154	1-164-096-11	CERAMIC	0.01MF		50V	
C1155	1-126-103-11	ELECT	470MF	20%	16V	
C1158	1-124-598-11	ELECT	22MF	20%	25V	
C1160	1-124-598-11	ELECT	22MF	20%	25V	
C1161	1-124-598-11	ELECT	22MF	20%	25V	
C1164	1-126-103-11	ELECT	470MF	20%	16V	
C1165	1-126-301-11	ELECT	1MF	20%	50V	
C1166	1-126-301-11	ELECT	1MF	20%	50V	
C1167	1-126-301-11	ELECT	1MF	20%	50V	

The components identified by shading and mark ⚠ are critical for safety.
Replace only with part number specified.

Les composants identifies par une trame et une marque ⚠ sont critiques pour la securite.
Ne les remplacer que par une piece portant le numero specifie.

• The components identified by ⊠ in this manual have been carefully factory-selected for each set in order to satisfy regulations regarding X-ray radiation. Should replacement be required, replace only with the value originally used.

REF.NO.	PART NO.	DESCRIPTION				REMARK
C1168	1-126-301-11	ELECT	1MF	20%	50V	
C1199	1-102-129-00	CERAMIC	0.01MF	10%	50V	
C1200	1-102-129-00	CERAMIC	0.01MF	10%	50V	
		<DIODE>				
D1152	8-719-110-36	DIODE RD13ES-B2				
D1158	8-719-110-36	DIODE RD13ES-B2				
D1159	8-719-110-36	DIODE RD13ES-B2				
D1160	8-719-110-36	DIODE RD13ES-B2				
D1163	8-719-110-36	DIODE RD13ES-B2				
D1164	8-719-110-36	DIODE RD13ES-B2				
D1165	8-719-110-36	DIODE RD13ES-B2				
D1166	8-719-110-36	DIODE RD13ES-B2				
D1167	8-719-110-36	DIODE RD13ES-B2				
D1168	8-719-110-36	DIODE RD13ES-B2				
D1169	8-719-110-36	DIODE RD13ES-B2				
D1170	8-719-110-36	DIODE RD13ES-B2				
		<JACK>				
J1001	1-537-187-11	TERMINAL, PUSH (4P)				
J1003	1-573-970-11	BLOCK, (S) TERMINAL				
J1004	1-695-049-11	BLOCK, (S) TERMINAL				
J1005	1-695-054-11	JACK BLOCK, PIN				
J1006	1-573-970-11	BLOCK, (S) TERMINAL				
J1007	1-573-969-11	JACK BLOCK, PIN				
J1008	1-573-969-11	JACK BLOCK, PIN				
		<RESISTOR>				
R1153	1-249-403-11	CARBON	68	5%	1/4W	
R1164	1-247-895-00	CARBON	470K	5%	1/4W	
R1165	1-247-895-00	CARBON	470K	5%	1/4W	
R1166	1-247-895-00	CARBON	470K	5%	1/4W	
R1167	1-247-895-00	CARBON	470K	5%	1/4W	
R1168	1-247-895-00	CARBON	470K	5%	1/4W	
R1169	1-249-403-11	CARBON	68	5%	1/4W	
R1170	1-249-403-11	CARBON	68	5%	1/4W	
R1171	1-247-895-00	CARBON	470K	5%	1/4W	
R1172	1-247-895-00	CARBON	470K	5%	1/4W	
R1173	1-247-804-11	CARBON	75	5%	1/4W	
R1174	1-247-895-00	CARBON	470K	5%	1/4W	
R1175	1-247-895-00	CARBON	470K	5%	1/4W	
R1176	1-247-804-11	CARBON	75	5%	1/4W	
R1178	1-247-895-00	CARBON	470K	5%	1/4W	
R1179	1-247-895-00	CARBON	470K	5%	1/4W	
R1180	1-247-804-11	CARBON	75	5%	1/4W	
R1181	1-247-804-11	CARBON	75	5%	1/4W	
R1183	1-247-895-00	CARBON	470K	5%	1/4W	
R1184	1-247-895-00	CARBON	470K	5%	1/4W	
R1185	1-247-895-00	CARBON	470K	5%	1/4W	
R1186	1-247-895-00	CARBON	470K	5%	1/4W	
R1188	1-247-804-11	CARBON	75	5%	1/4W	
R1191	1-249-425-11	CARBON	4.7K	5%	1/4W	
R1192	1-249-425-11	CARBON	4.7K	5%	1/4W	
R1193	1-249-425-11	CARBON	4.7K	5%	1/4W	
R1194	1-249-425-11	CARBON	4.7K	5%	1/4W	
R1196	1-249-426-11	CARBON	5.6K	5%	1/4W	
		<SWITCH>				
S1150	1-572-198-11	SWITCH, KEYBOARD				

REF.NO.	PART NO.	DESCRIPTION	REMARK
		<CONNECTOR>	
UT11	*1-564-519-11	PLUG, CONNECTOR 4P	
UT22	*1-566-941-11	CONNECTOR, HINGE (TAB) 30P	
UT23	*1-566-641-11	CONNECTOR, HINGE (TAB) 18P	
UT35	*1-564-518-11	PLUG, CONNECTOR 3P	
		**********	
		MISCELLANEOUS	
		**********	
	⚠ 1-241-744-11	RESISTOR ASSY (HIGH-VOLTAGE)	
	⚠ 1-451-396-21	DEFLECTION YOKE (Y936PA)	
	⚠ 1-452-443-13	NECK ASSY, PICTURE TUBE(NA367)	
	⚠ 1-453-108-11	DC BLOCK, HIGH-VOLTAGE	
	1-544-768-11	SPEAKER (13CM) (COAXIAL)	
	*1-555-110-00	CABLE, PIN	
	1-561-306-00	JACK, PIN (F)	
	1-574-590-31	LEAD ASSY, HIGH-VOLTAGE	
	⚠ 1-696-002-12	CORD, POWER (WITH NOISE FILTER)	
V902	⚠ 8-736-631-05	PICTURE TUBE (SD-249 (G))	
V903	⚠ 8-736-632-05	PICTURE TUBE (SD-249 (B))	
V901	⚠ 8-736-633-05	PICTURE TUBE (SD-249 (R))	
⊠R900	⚠	METAL FILM 1/4W	
⊠R901	⚠	METAL FILM 1/4W	
⊠R902	⚠	METAL FILM 1/4W	
		**********	
		ACCESSORIES AND PACKING MATERIALS	
		**********	
	*3-704-356-01	SHEET (STANDARD), PROTECTION	
	3-756-987-21	MANUAL, INSTRUCTION	
	3-756-987-31	MANUAL, INSTRUCTION (KP-41EXR96(C))	
	3-756-987-41	MANUAL, INSTRUCTION (KP-41EXR96(U))	
	*4-030-895-01	JOINT	
	*4-036-102-01	CUSHION (UPPER) (ASSY)	
	*4-036-106-01	INDIVIDUAL CARTON	
	*4-036-107-01	TRAY	
	*4-036-108-01	CUSHION (LOWER) (ASSY)	
	*4-381-155-01	BAG, PROTECTION	
		REMOTE COMMANDER	
	1-693-114-21	REMOTE COMMANDER (RM-Y112A)	
	9-902 719-01	COVER (FOR RM-Y112A)	
	9-998-214-01	COVER, BATTERY (FOR RM-Y112A)	

9-964-938-01

Sony Corporation
TV Group

English
93DJ0247-1
Printed in USA